

LIGHT FIXTURE SCHEDULE

ALL FIXTURES, LAMPS, TRACK, TRACK FITTINGS AND SUPPORT CABLE SHALL BE FURNISHED BY LUCKY'S MARKET AND INSTALLED BY THE CONTRACTOR. QUANTITIES SHALL BE VERIFIED BY LUCKY'S MARKET'S SUPPLIER.

TYPICAL LIGHTING PACKAGE

TYPE	DESCRIPTION	MANUFACTURER AND MODEL #	MOUNTING	VOLTAGE	LAMPS/ FIXTURE	INPUT WATTS/ FIXTURE	NOTES
A	LINEAR LED FIXTURE W/ DIMMING DRIVER	COLUMBIA LCL-35V-LEDU	PENDANT MOUNT 12" AFF	120/277	INCLUDED	96	-
AE	LINEAR LED FIXTURE W/ DIMMING DRIVER	COLUMBIA LCL-35V-LEDU-ELL14	PENDANT MOUNT 12" AFF	120/277	INCLUDED	96	1
B2	1-CIRCUIT WHITE TRACK (2'-0" NOMINAL LENGTH)	CONTECH LIGHTING LT-2-P	PENDANT MOUNT 12" AFF	120	-	-	2
B4	1-CIRCUIT WHITE TRACK (4'-0" NOMINAL LENGTH)	CONTECH LIGHTING LT-4-P	PENDANT MOUNT 12" AFF	120	-	-	2
B6	1-CIRCUIT WHITE TRACK (6'-0" NOMINAL LENGTH)	CONTECH LIGHTING LT-6-P	PENDANT MOUNT 12" AFF	120	-	-	2
B8	1-CIRCUIT WHITE TRACK (8'-0" NOMINAL LENGTH)	CONTECH LIGHTING LT-8-P	PENDANT MOUNT 12" AFF	120	-	-	2
B12	1-CIRCUIT WHITE TRACK (12'-0" NOMINAL LENGTH)	CONTECH LIGHTING LT-12-P	PENDANT MOUNT 12" AFF	120	-	-	2
B0	1-CIRCUIT TRACK (CUT TO LENGTH)	CONTECH LIGHTING LT-4-P	PENDANT MOUNT 12" AFF	120	-	-	2
BH	TRACK HEAD	CONTECH LT25-P WITH BATIOC 80412 13 WATT 28 DEGREE LAMP	TRACK MOUNT	120	(3) PAR 30 LED	12	-
D	4" RECESSED DOWNLIGHT	HALO HSD0CAT4.6.5016MS-890W	RECESSED	120/277	INCLUDED	17.5	-
DL	LED DOCK LIGHT WITH MOUNTING ARM ON/OFF SWITCH AND WET LOCATION LABEL	PHOSGEN DL4-18-LED-404RM	WALL BRACKET AT 4'-6" AFF	120V	(1) 18W LED	16	-
E	8" STRIP LIGHTS- CHAIN HUNG AND WIRE GUARDS	ORACLE 8-DC-4-32-78-80C/10-00G89	PENDANT MOUNT 12" AFF	120/277	(4) 12W LED T8	48	-
E2	8" STRIP LIGHTS- CHAIN HUNG AND WIRE GUARDS	ORACLE 8-DC-4-32-78-80C/10-00G89-5MG-78-EX-1400	PENDANT MOUNT 12" AFF	120/277	(4) 12W LED T8	48	1
F	4" VAPOR LIGHT LED	COLUMBIA L3EM-40W-RFA-8DU	SURFACE	120/277	INCLUDED	47	-
FE	4" VAPOR LIGHT LED W/ EMERGENCY POWER PACK	COLUMBIA L3EM-40W-RFA-8DU-ELL14	SURFACE	120/277	INCLUDED	47	-
FI	4" WRAP AROUND	ORACLE 4-0W-LED-4000L-DV10-MVOLT-39K-80	SURFACE	120/277	INCLUDED	46	-
FI2	4" WRAP AROUND	ORACLE 4-0W-LED-4000L-DV10-MVOLT-39K-80-ENGLED	SURFACE	120/277	INCLUDED	46	1
G	RAMEN BAR PENDANT	GLORIE ELECTRIC S4835	PENDANT MOUNT 8" AFF TO BOTTOM OF FIXTURE	120	-	60	-
H	3X3 TROFFER LUMINAIRE	ORACLE 22-0VHP-LED-4000L-DV10-MVOLT-39K-80	RECESSED	120/277	INCLUDED	44	-
H2	3X3 TROFFER LUMINAIRE	ORACLE 22-0VHP-LED-4000L-DV10-MVOLT-39K-80-EMF-LED	RECESSED	120/277	INCLUDED	44	1
H3	HEAT LAMP	HATCO DL-500-R-10-GLOSSY GRAY/BLACK GORD	SURFACE	120	1150W	250	-
HL	WHSK LIGHT	BENCLIF DESIGNER INDUSTRIAL WHSK LIGHTING PENDANT WITH BRASS STEEL CHAIN/FRY AND BLACK GORD	PENDANT	120	100W	60	-
X1	EXTERIOR WALL PASH	ORER KSPS-4-037-0102	SPRINGER MOUNT AT 3' AFF	-	INCLUDED	46	-
EP1	EMERGENCY BATTERY PACK	MULLE 80-LED-W	SURFACE	120/277	INCLUDED	1.5	-
EP2	EXTERIOR EMERGENCY BATTERY PACK	LITHONIA APN06-08-001	SURFACE	120/277	INCLUDED	1.5	-
EX1	EDGE OUT EXIT SIGN- SINGLE SIDED	MULLE 02-08-001	-	120/277	INCLUDED	3.1	-
EX2	EDGE OUT EXIT SIGN- DOUBLE SIDED	MULLE 02-08-RM-U	PENDANT	120/277	INCLUDED	3.1	-

- NOTES:  
 1. CONNECT BRANCH CIRCUIT TO BREAKER LAST AHEAD OF ALL OTHERS AND LOCAL SWITCHING.  
 2. ATTACH SUPPORT CABLE TO TRACK PER MANUFACTURER'S INSTRUCTIONS. PROVIDE POWER FEEDS SECTIONS (A-1 TO P), MINI CONNECTORS (LUG-2-P) AND CORNER SECTIONS (A-1 TO P) AS NEEDED.

SHEET INDEX

- E001 ELECTRICAL NOTES, SYMBOLS, AND SCHEDULES
- E101 POWER PLAN
- E102 ENLARGED POWER PLANS
- E103 CASE POWER AND LIGHTING PLAN
- E104 ROOF POWER PLAN
- E201 LIGHTING PLAN
- E301 SPECIAL SYSTEMS PLAN
- E401 ELECTRICAL RISER PLAN
- E501 PANEL SCHEDULES
- E502 PANEL SCHEDULES
- E601 ELECTRICAL DETAILS

GENERAL NOTES

1. PROVIDE SEAL FITTINGS AT CONDUIT ENTRIES TO FREEZERS, COOLERS, AND PREP AREAS TO PREVENT MOISTURE. CAULK FOUND CONDUIT PENETRATIONS THROUGH WALLS AND CEILING. DETAIL TO RC401.
2. IN BOX COOLERS/FREEZERS, COORDINATE LIGHTING FIXTURES WITH BLOWER COIL UNITS.
3. LEVEL LIGHTING TRACKS AFTER INSTALLATION. POSITIONING AND AIMING LAMP HEADS.
4. COORDINATE LIGHTING FIXTURE LOCATIONS WITH REFLECTED CEILING PLAN ON ARCHITECTURAL DRAWINGS.
5. DO NOT ATTACH SUPPORTS TO THE ROOF DECK. INSTEAD, ATTACH SUPPORTS TO THE ROOF STRUCTURAL FRAMING.
6. CONDUIT FOR LIGHTING FIXTURES AND BLOWER COIL UNITS INSIDE BOX COOLERS/FREEZERS SHALL BE RUN OUTSIDE ON TOP OF BOXES. CONDUIT NOT BE RUN INSIDE BOXES.
7. TYPE SO CORD (BLACK IF THERE IS AN EXPOSED OR GREEN CEILING AND WHITE IF THERE IS A WHITE CEILING), OR MC CABLE IF TYPE SO CORD IS PROHIBITED, SHALL BE USED FOR DROPS DOWN TO LIGHTING TRACK.
8. LIQUIDTIGHT FLEXIBLE METAL CONDUIT SHALL BE USED UNDER REFRIGERATED CASES.

ELECTRICAL DEVICE REQUIREMENTS

1. ALL DUPLEX OUTLETS SHALL BE 5-20R UNLESS NOTED OTHERWISE.
2. ALL OUTLETS SHALL BE MOUNTED AT 18" ABOVE FINISHED FLOOR UNLESS NOTED OTHERWISE.
3. ALL DEVICES (OUTLETS, SWITCHES, DATA OUTLETS, ETC) SHALL BE WHITE UNLESS NOTED OTHERWISE. DEVICES INSTALLED IN AREAS WHERE THE WALL FINISH IS METAL SHALL HAVE STAINLESS STEEL COVER PLATES. DEVICES INSTALLED IN AREAS WITH OTHER WALL FINISHES (E. PAINT, WOOD, RFP) SHALL HAVE WHITE, NYLON COVER PLATES.
4. IG OUTLETS SHALL BE ORANGE AND SHALL HAVE A DEDICATED, INSULATED GROUND WIRE RUN FROM THE ISOLATED GROUND TERMINAL OF THE OUTLET BACK TO THE GROUND BAR IN THE PANEL FEEDING IT. A SEPARATE GROUND WIRE SHALL BE RUN TO THE PANEL GROUND BAR TO SERVE THE GROUNDING OF THE OUTLET YOKE, OUTLET BOX, ETC.


ABBREVIATIONS

- AF ABOVE FINISHED FLOOR
- G GROUND
- C CONDUIT
- IG ISOLATED GROUND
- GF GROUND FAULT CIRCUIT INTERRUPTER
- WG WEATHERPROOF(WHILE-IN-USE)/GFCI TYPE
- WP WEATHERPROOF(WHILE-IN-USE)
- RTU ROOF TOP UNIT
- TFM THE FRESH MARKET
- UJN UNLESS OTHERWISE NOTED
- LFMC LIQUIDTIGHT FLEXIBLE METAL CONDUIT
- (P) PARTIAL CIRCUIT
- ETR EXISTING TO REMAIN


ELECTRICAL SYMBOL LIST

	TYPICAL LIGHTING FIXTURES - LETTER INDICATES TYPE.		FUSIBLE DISCONNECT, AMP RATING/# POLES/FUSE RATING INDICATED. IF NO FUSE RATING IS INDICATED, FUSE PER EQUIPMENT MANUFACTURER'S RECOMMENDED MOOP. PROVIDE TYPE NEMA 3R FOR OUTDOOR LOCATIONS.		MOTION SENSOR - SENSOR SWITCH #CMR-PDT-2P, OR EQUAL. CONTRACTOR SHALL ADJUST THE DEFAULT SETTINGS AFTER INSTALLATION TO PROVIDE PROPER OPERATION OF THE DEVICE.		SPRINKLER VALVE TAMPER SWITCH.
	ELECTRICAL CONNECTION TO EQUIPMENT. COORDINATE LOCATION AND CONNECTION DETAILS WITH EQUIPMENT PROVIDER.		WEATHERPROOF PUSH BUTTON FOR DOOR BELL - EDWARDS #1785 OR EQUAL.		DOOR BELL AND TRANSFORMER. EDWARDS #540-40S BELL (24v, 4") AND #599 TRANSFORMER (120V PR. - 24V SEC.) OR EQUAL.		SPRINKLER FLOW SWITCH.
	JUNCTION BOX.		BRANCH CIRCUIT CONCEALED, UNLESS OTHERWISE NOTED.		FIRE ALARM CONTROL PANEL.		FIRE ALARM MONITOR MODULE.
	SINGLE POLE SWITCH.		HOME RUN CIRCUIT - PANEL AND CIRCUIT NUMBER INDICATED.		FIRE ALARM CONTROL RELAY.		FIRE ALARM CONTROL RELAY.
	THREE-WAY SWITCH.		FIRE ALARM CONTROL PANEL.		FIRE ALARM SYSTEM ANNUNCIATOR.		FIRE ALARM PULL STATION.
	2-POLE MOTOR-RATED TOGGLE DISCONNECT WITH PADLOCKABLE HANDLE.		FIRE ALARM CONTROL PANEL.		HORN/STROBE - MOUNT 80" AFF TO CENTER - 75 CD RATING, UON.		FIRE ALARM PULL STATION.
	DOOR LIMIT SWITCH.		FIRE ALARM CONTROL PANEL.		STROBE - MOUNT 80" AFF TO CENTER - 75 CD RATING, UON.		FIRE ALARM PULL STATION.
	PIR OCCUPANCY SENSING WALL SWITCH - SENSOR SWITCH #MSD-10X OR EQUAL. CONTRACTOR SHALL ADJUST THE DEFAULT SETTINGS AFTER INSTALLATION TO PROVIDE PROPER OPERATION OF THE DEVICE. SWITCH TO BE SET FOR MANUAL 'ON' AND AUTO 'OFF'.		FIRE ALARM CONTROL PANEL.		SMOKE DETECTOR.		FIRE ALARM PULL STATION.
	2-BUTTON OCCUPANT SENSING WALL SWITCH. SENSOR SWITCH #SD OR EQUAL. CONTRACTOR SHALL ADJUST THE DEFAULT SETTINGS AFTER INSTALLATION TO PROVIDE PROPER OPERATION. REFER TO NOTE ON LIGHTING PLAN FOR SWITCH SPECIFIC OPERATION REQUIREMENTS.		FIRE ALARM CONTROL PANEL.		DUCT SMOKE DETECTOR - FURNISHED AND WIRED BY ELECTRICAL CONTRACTOR, MOUNTED BY MECHANICAL CONTRACTOR.		FIRE ALARM PULL STATION.
	OCCUPANT SENSING WALL SWITCH WITH HIGH HUMIDITY/LOW TEMP OPTION. SENSOR SWITCH WSD-LT OR EQUAL.		FIRE ALARM CONTROL PANEL.		CEILING PENDANT MOUNTED 177 CD HORN/STROBE, UON.		FIRE ALARM PULL STATION.
	OCCUPANT SENSING WALL SWITCH WITH 0-10 VOLT DIMMING. SENSOR SWITCH WSD-D OR EQUAL.		FIRE ALARM CONTROL PANEL.		CEILING PENDANT MOUNTED 177 CD STROBE, UON.		FIRE ALARM PULL STATION.
	FLUSH MOUNTED PANEL BOARD.		FIRE ALARM CONTROL PANEL.		TEMPERATURE (HEAT) DETECTOR.		FIRE ALARM PULL STATION.
	SURFACE MOUNTED PANEL BOARD.		FIRE ALARM CONTROL PANEL.		SPRINKLER ALARM BELL.		FIRE ALARM PULL STATION.
	MOTION SENSOR - SENSOR SWITCH #CMR-9-LT-P, OR EQUAL. CONTRACTOR SHALL ADJUST THE DEFAULT SETTINGS AFTER INSTALLATION TO PROVIDE PROPER OPERATION OF THE DEVICE.		FIRE ALARM CONTROL PANEL.		FIRE ALARM CONTROL PANEL.		FIRE ALARM PULL STATION.

Order Plans @



LUCKY'S MARKET  
 6420 NAPLES BLVD.  
 NAPLES, FLA. 34109



REVISIONS

PERMIT ISSUE  
 APRIL 27, 2019  
 BID ISSUE 04/27/19  
 STORE NUMBER  
 57  
 WD PROJECT NUMBER  
 LKYUP001