

NOTES:

1. The Fixture Electrical Installer shall install each motion sensoto control 2 cases maximum. When an odd number of cases are in a row one motion sensor will control only one case. See Typical - B.
2. Motion sensors shall only be used on cases in an aisle. No motion sensors are to be placed on end caps, dairy doors, nutrition cases, etc.
3. Motion sensors shall be mounted to one side or the other of the case joint.
4. Owner Supplied Items: Watt Stopper motion sensor kit #PRO number K-001767. Kit includes (1) power supply,(1) motion sensor, (1) 10' shielded cable, (1) connector and (1) splitter.
5. Refer to Kroger Installation Specifications for Watt Stopper Motion Sensor for additional information.

Based on Watt Stopper Motion Sensor Model No. PS-100

GLASS DOOR CASE MOTION SENSOR	DATE: 3/13/12
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	EISD-1

ORIGINAL ISSUE DATE 1/02/09



NOTES:

1. DASHED LINES INDICATE HIDDEN CONDUIT IN SHELF BACK AND BASE.

SHELVING ELECTRIC FROM OVERHEAD	DATE: 11/10/16
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	EISD-2

ORIGINAL ISSUE DATE 7/23/12



PENDENT RECEPTACLE FOR SUSPENDED CEILING	DATE: 1/31/17
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-16

ORIGINAL ISSUE DATE 2/20/08



NOTE - FADED "TS" MARKS SHOWN WITHIN THE ROOTPRINT OF A REFRIGERATED CASE INDICATE. POWER INSTEAD OF LOCATIONS WHEN LOOKING AT THE CASE FROM THE FRONT. MARKED TO THE LEFT WITHIN THE CASE INDICATES ELECTRIC LOCATIONS. PROVIDE WIRING BETWEEN COMMON POINTS AS SHOWN. PROVIDE 1 1/2" CONDUIT AND WIRE FROM TO CASE FANS, LIGHTS, AND ANTI-SWEAT SOURCE PANELBOARD/POWER FEEMAT FROM JUNCTION BOX OF CASES WITH ROWN ARROWS TO INDICATES CIRCUIT.

CASE CONDUIT AND WIRING DETAIL	DATE: 08-20-07
	SCALE: NONE
	DETAIL 'F'

ORIGINAL ISSUE DATE 8/20/08



NOTE:
NO TRACK LIGHT AT CEILINGS BELOW

LIGHTING DETAILS - DECO	DATE: 4/5/18
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-48

ORIGINAL ISSUE DATE 1/09/13



NOTES:

1. FOLLOW INSTRUCTIONS FROM CHECKSTAND MANUFACTURER SUPPLIED WITH POWER POLES FOR ASSEMBLY & INITIAL INSTALLATION.
2. POWER POLE WEIGHT IS SUPPORTED BY CHECKSTAND. CUT TOP OF POWER POLE AS NECESSARY AND ATTACH TOP OF POWER POLE TO CHECKSTAND.
3. WHEN TOP OF POWER POLE MISSES EXISTING STRUCTURAL STEEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT, SUCH AS UNISTRUT CHANNEL, ACROSS NEAREST JOISTS.
4. SECURELY ATTACH POWER POLE TO EXISTING STRUCTURE OR NEW METAL SUPPORT. DO NOT DRILL THRU, RUN BOLTS THRU, OR SCREW INTO POLE, TO PREVENT SHARP EDGES WHICH COULD DAMAGE COMMUNICATION CABLES.
5. 3/8" x 3" INSIDE LENGTH x 4" INSIDE WIDTH SQUARE U-BOLT, TO CONNECT TO SLOTTED METAL SUPPORT (UNISTRUT) CHANNEL, WITHOUT DRILLING. IF POWER POLE IS TO BE INSTALLED IN A LOCATION WHERE THERE IS NO METAL SUPPORT (UNISTRUT) CHANNEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT (UNISTRUT) CHANNEL, WITHOUT DRILLING, TO PERMIT VERTICAL MOVEMENT OF ROOF STRUCTURE. SIMILAR UNISTRUT HARDWARE MAY BE USED IN LIEU OF U-BOLTS, TO SECURELY ATTACH POWER POLES.
6. HEIGHTS INDICATED RESULT IN POSITIONING BRACKETS TO PARTIALLY COVER SOME ACCESS HOLES.
7. METAL SUPPORT (UNISTRUT), SQUARE U-BOLT AND ATTACHMENT HARDWARE, MC CABLE, SUPPLIED AND INSTALLED BY CONTRACTOR. ALL OTHER COMPONENTS SUPPLIED BY OWNER.
8. LANE LIGHT IS SUPPLIED WITH 10'-0" LONG CORD AND STANDARD GROUNDED PLUG. CONTRACTOR TO RUN LANE LIGHT CORD THROUGH POWER POLE AND BETWEEN CHECKSTAND, INSTALL PREDRILLED HOLE IN POWER POLE AND CUT BOTTOM OF POWER POLE TO FACTORY INSTALLED RECEPTACLE IN CHECKSTAND BASE DESIGNATED FOR LANE LIGHT. RECEPTACLE IS CONTROLLED BY FACTORY INSTALLED SWITCH IN CHECKSTAND BASE.
9. REMOVE COVER FROM SECOND HOLE FROM BACK TO BACK LIGHTING SYMCRET INSTALLATION.
10. LANE LIGHT IS SUPPLIED WITH 36"OF LONG) CORD AND STANDARD GROUNDED PLUG. CONTRACTOR TO RUN LANE LIGHT CORD THROUGH POWER POLE AND BETWEEN CHECKSTAND, INSTALL PREDRILLED HOLE IN POWER POLE AND CUT BOTTOM OF POWER POLE TO FACTORY INSTALLED RECEPTACLE IN CHECKSTAND BASE DESIGNATED FOR LANE LIGHT. RECEPTACLE IS CONTROLLED BY FACTORY INSTALLED SWITCH IN CHECKSTAND BASE. LANE LIGHT TO BE POWERED FROM REQUIRED CIRCUIT INSIDE BELT SCAN UNIT. BTYDER CORD TO BE COILED IN BOTTOM OF SELF SCAN UNIT.
11. ONE COMPARTMENT POWER POLES, LIGHTS, SWITCHES AND RECEPTACLES SUPPLIED AND INSTALLED BY CONTRACTOR.
12. ALL HIGH VOLTAGE CONDUCTORS MUST BE WRAPPED WITH STEEL JACKETING (MC CABLE).
13. ALL HIGH VOLTAGE CONDUCTORS MUST BE WRAPPED WITH STEEL JACKETING (MC CABLE).
14. MONITOR MOUNTED TO THE TOP STEEL TUBE OF THE MERCHANDISING RACK, CENTERED ON THE CENTER LINE OF CHECKSTAND SCALE. NOTIFY STORES. CONFIRM LOCATION WITH LOCAL LP MANAGER.

CHECKOUT POWER POLE AND LANE LIGHT INSTALLATION	DATE: 6/5/15
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-62

ORIGINAL ISSUE DATE 12/19/07



NOTES:

1. FOLLOW INSTRUCTIONS FROM CHECKSTAND MANUFACTURER SUPPLIED WITH POWER POLES FOR ASSEMBLY & INITIAL INSTALLATION. POWER POLES AS FOLLOWS:
   - PRE-CUT ACCESS HOLE ON 3" SIDE OF POLE AT LIGHT BRACKET MOUNTING HEIGHT.
   - PRE-CUT ACCESS HOLE ON 3" SIDE OF POLE AT POWER RECEPTACLE MOUNTING ABOVE ELEVATION, FOR DUPLEX RECEPTACLE.
2. POSITION POWER POLE AGAINST BACK OF SELF-SCAN SHELF THEN BOLT POLE BASE FLANGE TO FLOOR. CUT TOP OF POWER POLE AS NECESSARY AND ATTACH TOP OF POWER POLE TO BUILDING STRUCTURE.
3. WHEN TOP OF POWER POLE MISSES EXISTING STRUCTURAL STEEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT, SUCH AS UNISTRUT CHANNEL, ACROSS NEAREST JOISTS.
4. SECURELY ATTACH POWER POLE TO EXISTING STRUCTURE OR NEW METAL SUPPORT (UNISTRUT). DO NOT DRILL THRU, RUN BOLTS THRU, OR SCREW INTO POLE, TO PREVENT SHARP EDGES WHICH COULD DAMAGE COMMUNICATION CABLES.
5. 3/8" x 3" INSIDE LENGTH x 4" INSIDE WIDTH SQUARE U-BOLT, TO CONNECT TO SLOTTED METAL SUPPORT (UNISTRUT) CHANNEL, WITHOUT DRILLING. IF POWER POLE IS TO BE INSTALLED IN A LOCATION WHERE THERE IS NO METAL SUPPORT (UNISTRUT) CHANNEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT (UNISTRUT) CHANNEL, WITHOUT DRILLING, TO PERMIT VERTICAL MOVEMENT OF ROOF STRUCTURE. SIMILAR UNISTRUT HARDWARE MAY BE USED IN LIEU OF U-BOLTS, TO SECURELY ATTACH POWER POLES.
6. HEIGHTS INDICATED RESULT IN POSITIONING BRACKETS TO PARTIALLY COVER SOME ACCESS HOLES.
7. METAL SUPPORT (UNISTRUT), SQUARE U-BOLT AND ATTACHMENT HARDWARE, MC CABLE, SUPPLIED AND INSTALLED BY CONTRACTOR. ALL OTHER COMPONENTS SUPPLIED BY OWNER.
8. LANE LIGHT IS SUPPLIED WITH 10'-0" LONG CORD AND STANDARD GROUNDED PLUG. CONTRACTOR TO RUN LANE LIGHT CORD THROUGH POWER POLE AND BETWEEN CHECKSTAND, INSTALL PREDRILLED HOLE IN POWER POLE AND CUT BOTTOM OF POWER POLE TO FACTORY INSTALLED RECEPTACLE IN CHECKSTAND BASE DESIGNATED FOR LANE LIGHT. RECEPTACLE IS CONTROLLED BY FACTORY INSTALLED SWITCH IN CHECKSTAND BASE.
9. ALL HIGH VOLTAGE CONDUCTORS MUST BE WRAPPED WITH STEEL JACKETING (MC CABLE).

SELF-SCAN CHECKOUT POWER POLE AND LANE LIGHT INSTALLATION	DATE: 5/7/10
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-62A

ORIGINAL ISSUE DATE 5/7/10



NOTES:

1. THIS DETAIL IS ASSOCIATED WITH [illegible] TRACK LIGHTING FIXTURES. HANG ELECTRIFIED TRACK FOR MULTIPLE FIXTURES WITH APOPHIFT CABLE, THREADED ROD, COUPLING, AND SQUARE WASHER. THREADED ROD SHOULD BE USED TO SUPPORT ELECTRIFIED TRACK WITH MIN. 3/16" DIAMETER STEEL APOPHIFT CABLE. APOPHIFT CABLE WITH CABLE LOCKS ARE NOT ACCEPTABLE AS THE SOLE MEANS OF SUPPORT.
2. FIXTURE SUPPORT AND POWER CONNECTION METHODS SHALL COMPLY WITH ALL APPLICABLE CODES AND STANDARDS AS REQUIRED BY GOVERNING CODES.
3. INSTALL ELECTRIFIED TRACK WITH MIN. 3/16" DIAMETER STEEL APOPHIFT CABLE WITH CABLE LOCKS AT EACH END AND AT INTERVALS NOT EXCEEDING 4'-0" ON CENTER. SECURE CABLE TO STRUCTURE AS REQUIRED BY GOVERNING CODES.
4. MONOPOINT FIXTURE TO BE HUNG BY 1/4" THREADED ROD, COUPLING, AND JUNCTION BOX. USE LONGER DROPS INSTALL THREADED COUPLING AS HIGH AS POSSIBLE. ATTACH TO BOTTOM OF JUNCTION BOX WITH 1/4" DIAMETER STEEL JAMB NUTS AND WASHER. ON BOTTOM OF JUNCTION BOX BY ATTACHING WITH LOCK NUT WITH NYLON INSERT. USE STANDARD JAMB NUT ON TOP OF THE TRACK. 4" TRACK TO BE INSTALLED BY [illegible] TRACK CONDUIT. ATTACH MONOPOINT FIXTURE TO TRACK WITH MONOPOINT ATTACHMENT METAL SUPPORT
5. [illegible] LENGTH AND HEIGHT ABOVE FLOOR VARIES PER LOCATION. REFER TO LIGHTING PLAN FOR MOUNTING HEIGHT AND LOCATIONS.

LED TRACK LIGHT & MONOPOINT DETAIL	DATE: 11/15/13
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-50

ORIGINAL ISSUE DATE 11/07/13



NOTES:

1. THIS DETAIL SHALL BE USED FOR TRACK LIGHTING CIRCUITS WHERE A SINGLE CURRENT LIMITER IS USED TO CONTROL MULTIPLE SECTIONS OF TRACK.
2. THE CURRENT LIMITER SHALL PROTECT ALL TRACK SECTIONS DOWNSTREAM. POWER SHALL RUN FROM THE CIRCUIT BREAKER TO THE FIRST JUNCTION BOX ABOVE THE TRACK WITH THE CURRENT LIMITER. THE TRACK WITH THE CURRENT LIMITER SHALL BE PROVIDED WITH A TRACK END FEED SUCH THAT THE DOWNSTREAM POWER IS ALSO PROTECTED FROM THE CURRENT LIMITER. THE END FEED SHALL ROUTE TO A JUNCTION BOX ABOVE THE CEILING. THIS JUNCTION BOX MAY FEED ALL OTHER TRACK LIGHTS ON THE CIRCUIT AS IT IS PROTECTED BY THE CURRENT LIMITER.

CURRENT LIMITER FEEDING DOWNSTREAM TRACK LIGHTING	DATE: 05/15/14
	SCALE: NONE
	DRAWN: CSB
	DETAIL '50B'

ORIGINAL ISSUE DATE 05/15/14



NOTE:
CORD DROP SHALL BE FIELD COORDINATED TO OPERATE 1 TO 3 CIRCUITS. PROVIDE HANDLE TIES AS NECESSARY FOR SIMULTANEOUS BREAKER DISCONNECT. REFER TO CHART BELOW FOR SO TYPE.

1 CIRCUIT, 1 TO 2 DEVICES:
3 WIRE SO., (1) DUPLEX.

1 CIRCUIT 3-4 DEVICES:
3 WIRE SO., (2) DUPLEX.

2 CIRCUIT, 1 TO 2 DEVICES:
4 WIRE SO., (1) DUPLEX WITH TABS CUT.

2 CIRCUIT 3-4 DEVICES:
4 WIRE SO., (2) DUPLEX, EACH TO ONE CIRCUIT.

3 CIRCUIT 3-4 DEVICES:
5 WIRE SO., (2) DUPLEX, (1) WITH TABS CUT.

PENDENT MULTI RECEPTACLE FOR CEILING	DATE: 1/31/17
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-16A

ORIGINAL ISSUE DATE 10/09/13



NOTES:

1. ALARM SYSTEM WITH DELAY EGRESS FINISH HARDWARE. DELAY EGRESS FEATURE MAY BE DEACTIVATED IF NOT NEEDED.
2. POWER SUPPLY/CHARGER, SET FOR 5 SECOND DELAY.
3. WIRING INSTALLED IN WALLS, [illegible] PAINTED AREAS OR PAINTED TO MATCH DOOR WHERE EXPOSED.
4. CONTRACTOR SUPPLIED ITEMS: [illegible] ARMORED CABLE, 7/8" x 7/16" WIREMOLD v5SB/AC or EQUAL, AND MISC. INSTALLATION HARDWARE.
5. CONTRACTOR PROVIDED HARDWARE INCLUDES DOOR/FRAME, CONTROL PANEL, BIO READER AND MAGNETIC CONTACTS SUPPLIED AND INSTALLED BY SECURITY SYSTEM CONTRACTOR.

EMPLOYEE ENTRY, EXIT WITH DELAYED EGRESS	DATE: 11/9/17
	DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-22B

ORIGINAL ISSUE DATE 3/13/12

OWNERSHIP OF INSTRUMENTS OF SERVICE
All reports, plans, specifications, computer files, field data, notes and other documents and instruments prepared by the Consultant as instruments of service shall remain the property of the Consultant. The Consultant shall retain all common law, statutory and other reserved rights, including the copyright thereto.

Order Plans @ WWW.DLine.com

STUDIO A architecture
1975 RAMSEY TOWN PLACE
LEXINGTON, KENTUCKY 40514
(859) 977-0888 FAX 977-0889
WWW.STUDIOA-ARCH.COM

CONSULTANTS

KLH ENGINEERS
MECHANICAL/ELECTRICAL/PLUMBING
WWW.KLHENGINEERS.COM
LEXINGTON, KENTUCKY
1728 ALEXANDRIA PIKE, SUITE 11
LEXINGTON, KENTUCKY 40504
859-254-6193 859-442-6500
COLUMBUS, OHIO
614-754-4100 FAX

KROGER L758

234 EASTBROOKE PKWY,
MT WASHINGTON, KY

CLIENT

KROGER COMPANY
1600 Ormsby Station Court
Louisville, Kentucky 40223

ELECTRICAL STANDARD DETAILS

No.	Description	Date

BID ISSUE

© 2017 STUDIO A ARCHITECTURE
THESE PLANS AND DRAWINGS ARE COPYRIGHT. USE OF THE WORK IN WHOLE OR IN PART IS FORBIDDEN WITHOUT THE EXPRESSED WRITTEN CONSENT OF STUDIO A ARCHITECTURE.

E5.1.1

Project number 20166
Date 08/17/2018

2" REFERENCE LINE
JAD JAT