SCALE DOWN 1/64



Notice:
Installing Contractor to adapt Control System as required for Controls Installed --- CPC or Danfoss.

Notes:
1. ALL ELECTRICAL APPARATUS SHOWN, SHALL BE FURNISHED BY KROGER, ALL EQUIPMENT TO BE INSTALLED BY THE ELECTRICAL CONTRACTOR.
2. ALL CONDUIT AND 120 VOLT WIRING IS FURNISHED AND INSTALLED BY THE ELECTRICAL CONTRACTOR.
3. ALL LOW VOLTAGE HVAC CONTROL AND TELEPHONE WIRING IS BY OTHERS.
4. EACH LIGHTING CONTACTOR FURNISHED BY KROGER SHALL CONTAIN A 2ND--NPC CONTROL MODULE FOR 24 VOLT AC CONNECTION. THE ELECTRICAL CONTRACTOR SHALL PROVIDE THE 24 VOLT CONTROL WIRING TO EACH LIGHTING CONTACTOR COIL.

CONTROL PANEL DIAGRAM	DATE: 1/1/11 SCALE: NONE DRAWN: JFQ
MASTER SPECIFICATION DETAIL	ESD-53

ORIGINAL ISSUE DATE 2/20/08



COLUMN MOUNTED CONVENIENCE OUTLET SECTIONS	DATE: 11/10/11 SCALE: NONE DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-54

ORIGINAL ISSUE DATE 1/30/09



COLUMN MOUNTED PRICE CHECKER SECTIONS	DATE: 1/30/09 SCALE: NONE DRAWN: JFQ
MASTER SPECIFICATION DETAIL	ESD-55

ORIGINAL ISSUE DATE 1/30/09



Notice:
PROVIDE SCALOFFS INSIDE STORE WHEN REQUIRED BY LOCAL AUTHORITY HAVING JURISDICTION.

ELECTRIC AND COMMUNICATION CONDUITS FOR FUEL CENTER	DATE: 9-24-07 SCALE: NONE DRAWN: JFQ
MASTER SPECIFICATION DETAIL	ESD-61

ORIGINAL ISSUE DATE 4/11/07



Notes:
1. FOLLOW INSTRUCTIONS FROM CHECKSTAND MANUFACTURER SUPPLIED WITH POWER POLES FOR ASSEMBLY & INSTALLATION.
2. POWER POLE WEIGHT IS SUPPORTED BY CHECKSTAND. CUT TOP OF POWER POLE AS NECESSARY AND ATTACH TO BUILDING STRUCTURE.
3. WITH TOP OF POWER POLE NEXT TO EXISTING STRUCTURAL STEEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT, SUCH AS UNISTRUT CHANNEL, ACROSS NEAREST JOISTS.
4. SECURELY ATTACH POWER POLE TO EXISTING STRUCTURE OR NEW METAL SUPPORT AS REQUIRED. DRILL HOLES AND USE BOLTS OR SCREWS W/SS POLE, PREVENT MARRING FINISH WHEN CONTRACTOR COMMENCES.
5. 3/8" x 8" INSERT LENGTH x 4" INSERT WIDTH SQUARE U-BOLT TO CONNECT TO ATTACHED METAL SUPPORT. ORIENT U-BOLT WITH CHECKSTAND. POWER POLE IS CENTERED ON A BUILT-IN METAL SUPPORT (UNISTRUT) CHANNEL. ATTACH POWER POLE TO CHECKSTAND WITH (2) 3/8" x 1" HEX HEAD BOLTS. ATTACH POWER POLE TO ROOF STRUCTURE WITH (2) 3/8" x 1" HEX HEAD BOLTS. HARDWARE MAY BE USED IN LIEU OF U-BOLTS, TO SECURELY ATTACH POWER POLE.
6. HEIGHTS INDICATED INSTALL IN POSITIONING BRACKETS TO PARTIALLY CONFORM SCALOFFS TO HOLES.
7. METAL SUPPORT (UNISTRUT), SQUARE U-BOLT AND ATTACHMENT HARDWARE, MC CABLE, ARE SUPPLIED & INSTALLED BY CONTRACTOR. ALL OTHER COMPONENTS SUPPLIED BY OTHERS.
8. LANE LIGHT IS SUPPLIED WITH 10' OF LONG CABLE WITH PLUG. CONTRACTOR TO RUN LANE LIGHT CABLE FROM CHECKSTAND TO POWER POLE. CUT CABLE TO LENGTH AS REQUIRED. INSTALL PLUG ONTO CABLE ESSENTIALLY IN CHECKSTAND BASE COMPARTMENT TO FACILITATE FUTURE SERVICE. CONTRACTOR TO RUN POWER CABLE FROM PREINSTALLED HOLES IN POWER POLE TO BE PLUGGED INTO SERVICEABLE PLUG.
9. ONE COMPARTMENT FROM CHECKSTAND MANUFACTURER SUPPLIED BY OTHERS. LIGHT BULBS FOR LANE LIGHTS ARE SUPPLIED BY OTHERS.
10. ALL LIGHTS AND WIRES COME FROM CHECKSTAND MANUFACTURER SUPPLIED BY OTHERS INSTALLED BY CONTRACTOR.
11. ALL HIGH VOLTAGE CONDUCTORS WRAPPED WITH GROUNDING (MC CABLE).

CHECKOUT POWER POLE AND LANE LIGHT INSTALLATION	DATE: 6/5/15 SCALE: NONE DRAWN: ZAW
MASTER SPECIFICATION DETAIL	ESD-62

ORIGINAL ISSUE DATE 12/19/07



NOTES:
1. FOLLOW INSTRUCTIONS FROM CHECKSTAND MANUFACTURER SUPPLIED WITH POWER POLES FOR ASSEMBLY & INSTALLATION. POWER POLES AS FOLLOWS:
   - PRE-1921 ASSEMBLY FIELD SET OF 8 POLE AT LIGHT BRACKET MOUNTING OPENING.
   - PRE-1921 ASSEMBLY FIELD SET OF 8 POLE AT VERIFY INDICATED ON GROUP ELEVATIONS, FOR DISPLAY MOUNTINGS.
2. POWER POLE WILL ALWAYS BASE OF 8FT FROM 8FT2 SITE BELT POLE SAME FLANGE TO FLOOR. SET TOP OF POWER POLE AS NECESSARY AND ATTACH TOP OF POWER POLE TO BUILDING STRUCTURE.
3. WITH TOP OF POWER POLE NEXT TO EXISTING STRUCTURAL STEEL, PROVIDE & SECURELY ATTACH A METAL SUPPORT, SUCH AS UNISTRUT CHANNEL, ACROSS NEAREST JOISTS.
4. SECURELY ATTACH POWER POLE TO EXISTING STRUCTURE OR NEW METAL SUPPORT AS REQUIRED. DRILL HOLES AND USE BOLTS OR SCREWS W/SS POLE, PREVENT MARRING FINISH WHEN CONTRACTOR COMMENCES.
5. METAL SUPPORT, SQUARE U-BOLT AND ATTACHMENT HARDWARE, MC CABLE, ARE SUPPLIED & INSTALLED BY CONTRACTOR. ALL OTHER COMPONENTS SUPPLIED BY OWNER.
6. CONTRACTOR TO SUPPLY AND INSTALL DUPLEX RECEPTACLE & COVER PLATES. CONTRACTOR TO COMPLETE WIRING INSTALLATION WITHIN ELECTRIC CIRCUIT & RECEPTACLES.
7. CONTRACTOR TO FIELD FURNISHOUT AND INSTALL STAINLESS STEEL PROTECTOR TRIM WIRING FROM POWER POLE AND BETWEEN OVERHEAD, FASTEN TO FLOOR AS NEEDED.
8. MONITOR COMES FROM MOUNTING HOLE FOR BACK TO BACK LIGHTING BRACKET INSTALLATION.
9. LANE LIGHT IS SUPPLIED WITH 10' OF LONG CORD AND STANDARD GROUNDED PLUG. CONTRACTOR TO RUN LANE LIGHT CORD FROM CHECKSTAND TO POWER POLE, AND OUT OF POWER POLE NEXT TO PREINSTALLED HOLE. CUT CORD TO LENGTH AS REQUIRED. INSTALL PLUG ONTO CORD. PUTTING CORD IN BASE