PANELBOARD SCHEDULE - 'LA'

MAIN: 225A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1													4.0										1.0						2
3	60	3	6	1"	WASHER								4.0										1.0	DRYER	1/2"	12	3	30	4
5													4.0										1.0						6
7													4.0										1.0						8
9	60	3	6	1"	WASHER								4.0										1.0	DRYER	1/2"	12	3	30	10
11													4.0										1.0						12
13												0.2												DRYER SERVICE REC	1/2"	12	1	20	14
15	20	1	12	1/2"	ICO LAB							0.6	1.2											MOTORIZED DAMPER	1/2"	12	1	20	16
17	20	1	12	1/2"	LAUNDRY RECEPTS		0.5														0.5			OFFICE RECEPTS	1/2"	12	1	20	18
19	20	1	12	1/2"	LAUNDRY CHUTE																			SPACE ONLY					20
21	20	1			SPARE																			SPACE ONLY					22
23	20	1			SPARE																			SPACE ONLY					24
25	20	1			SPARE																			SPACE ONLY					26
27	20	1			SPARE																			SPACE ONLY					28
29	20	1			SPARE																			SPACE ONLY					30
31					SPACE ONLY																			SPACE ONLY					32
33					SPACE ONLY																			SPACE ONLY					34
35					SPACE ONLY																			SPACE ONLY					36
37					SPACE ONLY																			SPACE ONLY					38
39					SPACE ONLY																			SPACE ONLY					40
41					SPACE ONLY																			SPACE ONLY					42
LIGHTING (KVA):						0.0	0.0	0.0	0.0	0.0	0.0	25.2				0.0	0.7	0.0	0.0	0.0	0.0	6.0		CONNECTED LOAD (KVA):					33.0
RECEPTACLES (KVA):						1.3																		DEMAND LOAD (KVA):					33.0
MOTORS (KVA):						0.5							PHASE A	93	84.8														
A/C (KVA):						0.0							PHASE B	72	97.5									CONNECTED LOAD (AMPS):					91.5
HEATING (KVA):						0.0							PHASE C	71	92.3									DEMAND LOAD (AMPS):					91.6
KITCHEN (KVA):						0.0										KVA	AMPS												
MISCELLANEOUS (KVA):						31.2																							

NOTES: ** VERIFY REQUIRMENTS WITH EQUIPMENT VENDOR PRIOR TO ORDERING ANY BREAKERS AND ADJUST AS REQUIRED.

PNL 'LA' DEMAND CALCS

LIGHTING	0.00	KVA X	125 %	=	0.0 KVA
RECEPTAC TOTAL	1.26	KVA			
1ST	10.00	KVA X	100 %	=	1.3 KVA
REMAIN	0.00	KVA X	50 %	=	0.0 KVA
MOTORS	0.50	KVA X	100 %	=	0.5 KVA
A/C	0.00	KVA X	100 %	=	0.0 KVA
HEATING	0.00	KVA X	100 %	=	0.0 KVA
LOCKED-OUT LOAD		KVA X	100 %	=	0.0 KVA
KITCHEN	0.00	KVA X	65 %	=	0.0 KVA
MISCELLANEOUS	31.20	KVA X	100 %	=	31.2 KVA
TOTAL	=	91.8 amps		=	33.0 KVA

'DIM' LUTRON GP 24 DIMMING PANEL

MAIN: 125A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1	20	1	12	1/2"	GATHERING PENDANT	0.3							2.2											BUS, PENDANTS	1/2"	12	1	20	2
3	20	1	12	1/2"	GATHERING DOWN	0.2							0.1											BREAKFAST DOWN	1/2"	12	1	20	4
5	20	1	12	1/2"	GATHERING WASHER	0.2								0.5										CORRIDOR	1/2"	12	1	20	6
7	20	1	12	1/2"	SERVERY DOWN	0.3								0.5										ENTRY/CORRIDOR	1/2"	12	1	20	8
9	20	1	12	1/2"	REGISTRATION WASH	0.1								0.3										COVE LIGHT (ON/OFF)	1/2"	12	1	20	10
11	20		12	1/2"	SPARE																			SPACE ONLY					12
13	20		12	1/2"	SPARE																			SPACE ONLY					14
15	20		12	1/2"	SPARE																			SPACE ONLY					16
17	20		12	1/2"	SPARE																			SPACE ONLY					18
19	20		12	1/2"	SPACE ONLY																			SPACE ONLY					20
21	20		12	1/2"	SPACE ONLY																			SPACE ONLY					22
23	20		12	1/2"	SPACE ONLY																			SPACE ONLY					24
LIGHTING (KVA):						2.6	1.1	0.0	0.0	0.0	0.0	0.0	2.2			1.3	0.9	0.0	0.0	0.0	0.0	0.0		CONNECTED LOAD (KVA):					2.6
RECEPTACLES (KVA):						0.0																		DEMAND LOAD (KVA):					3.3
MOTORS (KVA):						0.0							PHASE A	1	10.6														
A/C (KVA):						0.0							PHASE B	1	5.6									CONNECTED LOAD (AMPS):					7.3
HEATING (KVA):						0.0							PHASE C	2	5.5									DEMAND LOAD (AMPS):					9.1
KITCHEN (KVA):						0.0										KVA	AMPS												
MISCELLANEOUS (KVA):						0.0																							

NOTES: VENDOR SHALL PROVIDE FACTORY DRAWINGS AFTER BID FOR INSTALLATION.

PNL 'DIM' DEMAND CALCS

LIGHTING	2.64	KVA X	125 %	=	3.3 KVA
RECEPTAC TOTAL	0.00	KVA			
1ST	10.00	KVA X	100 %	=	0.0 KVA
REMAIN	0.00	KVA X	50 %	=	0.0 KVA
MOTORS	0.00	KVA X	100 %	=	0.0 KVA
A/C	0.00	KVA X	100 %	=	0.0 KVA
HEATING	0.00	KVA X	100 %	=	0.0 KVA
LOCKED-OUT LOAD		KVA X	100 %	=	0.0 KVA
KITCHEN	0.00	KVA X	65 %	=	0.0 KVA
MISCELLANEOUS	0.00	KVA X	100 %	=	0.0 KVA
TOTAL	=	9.1 amps		=	3.3 KVA

PANELBOARD SCHEDULE - '1L'

MAIN: 125A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1	20	1	12	1/2"	LIGHTING CONTROL								0.1											LIGHTS-PATIO	1/2"	12	1	20	2
3	20	1	12	1/2"	LIGHTS-SIGNAGE	0.2								0.9										LIGHTS BEACON	1/2"	12	1	20	4
5	20	1	12	1/2"	LIGHTS-OUTDR LOUNGE	0.3								0.9										LIGHTS-POLE	1/2"	12	1	20	6
7	20	1	12	1/2"	LIGHTS-FLAG	0.6								0.9										LIGHTS-POLE	1/2"	12	1	20	8
9	20	1	12	1/2"	LIGHTS-PYLON	0.2								0.7										LIGHTS-POLE	1/2"	12	1	20	10
11	20	1	12	1/2"	LIGHTS-ENTRY/EXT SIGN	1.2								0.7										LIGHTS-POLE	1/2"	12	1	20	12
13	20	1	12	1/2"	LIGHTS-ENTRY/EXT SIGN	1.2								0.7										LIGHTS-POOL	1/2"	12	1	20	14
15	20	1	12	1/2"	LIGHTS-ENTRY/EXT SIGN	1.2								0.2										LIGHTS-BUILDING	1/2"	12	1	20	16
17	20	1			SPARE																			SPARE			1	20	18
19	20	1	12	1/2"	LTS-ENTRY	0.2																		SPARE			1	20	20
21	20	1	12	1/2"	LTG SIGNAGE	0.2																		SPARE			1	20	22
23	20	1	12	1/2"	LTG EXIT SIGNAGE	1.2																		SPACE ONLY					24
25	20	1	12	1/2"	LTG SIGNAGE	1.2																		SPACE ONLY					26
27	20	1	12	1/2"	SPRINKLER POWER							1.0												SPACE ONLY					28
29	20	1	12	1/2"	SPRINKLER POWER							1.0												SPACE ONLY					30
31					SPACE ONLY																			SPACE ONLY					32
33					SPACE ONLY																			SPACE ONLY					34
35					SPACE ONLY																			SPACE ONLY					36
37					SPACE ONLY																			SPACE ONLY					38
39					SPARE																			SPACE ONLY					40
41					SPARE																			SPACE ONLY					42
LIGHTING (KVA):						14.5	9.6	0.0	0.0	0.0	0.0	0.0	2.2			4.9	0.0	0.0	0.0	0.0	0.0	0.0		CONNECTED LOAD (KVA):					16.7
RECEPTACLES (KVA):						0.0																		DEMAND LOAD (KVA):					20.3
MOTORS (KVA):						0.0							PHASE A	6	50.3														
A/C (KVA):						0.0							PHASE B	5	34.4									CONNECTED LOAD (AMPS):					49.4
HEATING (KVA):						0.0							PHASE C	5	44.5									DEMAND LOAD (AMPS):					56.4
KITCHEN (KVA):						0.0										KVA	AMPS												
MISCELLANEOUS (KVA):						2.2																							

NOTES: ** COORDINATE ALL REQUIREMENTS WITH VENDOR PRIOR TO ANY WORK OR START-UP

PNL '1L' DEMAND CALCS

LIGHTING	6.69	KVA X	125 %	=	8.3 KVA
RECEPTAC TOTAL	0.00	KVA			
1ST	10.00	KVA X	100 %	=	0.0 KVA
REMAIN	0.00	KVA X	50 %	=	0.0 KVA
MOTORS	0.00	KVA X	100 %	=	0.0 KVA
A/C	0.00	KVA X	100 %	=	0.0 KVA
HEATING	0.00	KVA X	100 %	=	0.0 KVA
LOCKED-OUT LOAD		KVA X	100 %	=	0.0 KVA
KITCHEN	0.00	KVA X	65 %	=	0.0 KVA
MISCELLANEOUS	0.00	KVA X	100 %	=	0.0 KVA
TOTAL	=	22.9 amps		=	8.3 KVA

PANELBOARD SCHEDULE - '1P'

MAIN: 200A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES: NEMA 4X

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1													0.8										0.8	PATIO RECEPTS	1/2"	12	1	20	2
3													0.9										0.9	POOL RECEPTS - GFI	1/2"	12	1	20	4
5													0.3										0.3	GAS GRILLES **	1/2"	12	1	20	6
7	20	1	12	1/2"	POOL EQUIP. REC.							0.5												TRSP					8
9	20	1	12	1/2"	POOL EQUIP. FAN		0.3						1.0										1.0	LIGHTS - GFI	1/2"	12	1	20	10
11	20	1	12	1/2"	POOL HEATER								15.0										0.2	LIGHTS - GFI	1/2"	12	1	20	12
13	20	1	12	1/2"	POOL EQUIPMENT							0.5												POOL EQUIPMENT GENERATOR	1/2"	12	1	20	14
15	20	1			SPARE							0.5												TRSP					16
17	20	1			SPARE							0.5											0.7	EP-9	1/2"	12	1	15	16
18														1.3									1.0	EP-2	1/2"	12	2	20	20
21	20	3	12	1/2"	POOL PUMP **									1.3									1.0						22
23														1.3									1.0	SPARE	1/2"	12	1	20	24
25					SHUNT TRIP SPACE																			SPACE					26
27					SPACE																			SPACE					28
29					SPACE																			SPACE					30
31					SPACE																			SPACE					32
33					SPACE																			SPACE					34
35					SPACE																			SPACE					36
37					SPACE																			SPACE					38
39					SPACE																			SPACE					40
41					SPACE																			SPACE					42
LIGHTING (KVA):						2.0	0.9	0.0	4.2	0.0	0.0	2.0				2.2	0.0	0.0	2.0	0.0	0.7			CONNECTED LOAD (KVA):					14.1
RECEPTACLES (KVA):						2.2																		DEMAND LOAD (KVA):					14.8
MOTORS (KVA):						0.0							PHASE A	6	33.7														
A/C (KVA):						4.0							PHASE B	6	41.7									CONNECTED LOAD (AMPS):					39.1
HEATING (KVA):						0.0							PHASE C	5	42.8									DEMAND LOAD (AMPS):					40.5
KITCHEN (KVA):						0.0										KVA	AMPS												
MISCELLANEOUS (KVA):						3.7																							

NOTES: ** INDICATES SHUNT TRIP BREAKER

PNL '1P' DEMAND CALCS

LIGHTING	2.00	KVA X	125 %	=	2.5 KVA
RECEPTAC TOTAL	2.18	KVA			
1ST	10.00	KVA X	100 %	=	2.2 KVA
REMAIN	0.00	KVA X	50 %	=	0.0 KVA
MOTORS	4.20	KVA X	100 %	=	4.2 KVA
A/C	0.00	KVA X	100 %	=	0.0 KVA
HEATING	3.00	KVA X	100 %	=	3.0 KVA
LOCKED-OUT LOAD		KVA X	100 %	=	0.0 KVA
KITCHEN	0.00	KVA X	65 %	=	0.0 KVA
MISCELLANEOUS	3.70	KVA X	100 %	=	3.7 KVA
TOTAL	=	40.5 amps		=	14.8 KVA

PANELBOARD SCHEDULE - "KP"

MAIN: 200A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1	20	1	12	1/2"	DISPLAY FISH (2) *								1.1											TURBO CHEF (3)	1"	6	2	60	2
3	20	1	12	1/2"	DISPLAY FREEZ (1) *									1.1									2.9						4
5	20	1	12	1/2"	WARM KETTLE (2) *								0.2											SPACE ONLY					6
7					SPARE									0.5									0.5	REACH IN REF. (2) *	1/2"	12	1	20	8
9	20	1	10	1/2"	VENTLESS EXHAUST	0.8									0.7								1.3	REACH IN FREEZ (2) *	1/2"	12	1	20	10
11	20	1	12	1/2"	CON. TOASTER (10) *										1.7								0.6	DC REF. (4) *	1/2"	12	1	20	12
13	20	1	10	1/2"	JUICE DISP. (5) *									1.2										RECEPTACLE (*)	1/2"	12	1	20	14
15	20	1	10	1/2"	WARMING OVEN (6) *								2.0										0.2	RECEPTACLE (*)	1/2"	12	1	20	16
17	50	2	6	1"	COFFEE MAKER (14) *								3.8										0.4	RECEPTACLE (*)	1/2"	12	1	20	18
19													3.6																20
21	20	1			SPARE									3.6									4.2	DISHMACHINE (30)	3/4"	8	3	45	22
23	20	1			SPARE										3.6								4.2						24
25	30	1	12	1/2"	WAFFLE IRON (12) *								1.4											SPARE			1	20	26
27	20	1	12	1/2"	EP-2									0.2										SPARE			1	20	28
29	20	1	12	1/2"	SPARE										0.2									SPARE			1	20	30
31	20	1	12	1/2"	SPARE																			SPACE					32
33	20	1	12	1/2"	SPARE																			SPACE					34
35					SPACE																			SPACE					36
37					SPACE																			SPACE					38
39					SPACE																			SPACE					40
41					SPACE																			SPACE					42
LIGHTING (KVA):						0.8	0.0	1.1	0.0	0.0	0.0	0.0	3.7	3.7	0.0	0.0	0.0	0.0	0.0	0.7	0.0	0.0	2.1	CONNECTED LOAD (KVA):					42.0
RECEPTACLES (KVA):						0.7																		DEMAND LOAD (KVA):					31.8
MOTORS (KVA):						0.0							PHASE A	16	133.3														
A/C (KVA):						0.0							PHASE B	15	122.3									CONNECTED LOAD (AMPS):					116.5
HEATING (KVA):						0.0							PHASE C	11	94.1									DEMAND LOAD (AMPS):					87.7
KITCHEN (KVA):						30.4										KVA	AMPS												
MISCELLANEOUS (KVA):						1.1																							

NOTES 1. BASIS OF DESIGN IS SQUARE D. 2. * DENOTES BREAKER SHALL BE GFCI TYPE

PNL 'KP' DEMAND CALCS

LIGHTING	3.69	KVA X	125 %	=	4.6 KVA
RECEPTAC TOTAL	0.72	KVA			
1ST	10.00	KVA X	100 %	=	0.7 KVA
REMAIN	0.00	KVA X	50 %	=	0.0 KVA
MOTORS	0.00	KVA X	100 %	=	0.0 KVA
A/C	0.00	KVA X	100 %	=	0.0 KVA
HEATING	0.00	KVA X	100 %	=	0.0 KVA
LOCKED-OUT LOAD		KVA X	100 %	=	0.0 KVA
KITCHEN	32.47	KVA X	65 %	=	21.0 KVA
MISCELLANEOUS	5.76	KVA X	100 %	=	5.2 KVA
TOTAL	=	87.7 amps		=	31.6 KVA

PANELBOARD SCHEDULE - "IG"

MAIN: 125A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | A/C: | SEE RISER | NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTR	KIT	MISC	A	B	C	MISC	KIT	HTR	A/C	MTR	REC	LTG	LOAD (KVA)	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1	20	1	12	1/2"	SPARE								0.4											REGISTRATION RECEP	1/2"	12	1	20	2
3	20	1	12	1/2"	TELE RECEP	0.4								0.4										REGISTRATION RECEP	1/2"	12	1	20	4
5	20	1	12	1/2"	SATV RECEP								0.4											REGISTRATION RECEP	1/2"	12	1	20	6
7	20	1	12	1/2"	CWC RECEP									0.4										REGISTRATION RECEP	1/2"	12	1	20	8
9	20	1	12	1/2"	CWG RECEP								0.4											REGISTRATION RECEP	1/2"	12	1	20	10
11	20	1	12	1/2"	MATV RECEP									0.7										OFFICE RECEPS	1/2"	12	1	20	12
13	20	1	12	1/2"	MATV RECEP								0.4											OFFICE RECEPS	1/2"	12	1	20	14
15	20	1	12	1/2"	PHONE RACK RECEP									0.2										TV RECEPT	1/2"	12	1	20	16
17	20	1	12	1/2"	PHONE RACK RECEP								0.5										0.7	WX STATIONS	1/2"	12	1	20	18
19	20	1	12	1/2"	PACP **									1.1										SPARE	1/2"	12	1	20	20
21	20	1	12	1/2"	ACCESS CLTG **								0.5										1.0	SADO REC	1/2"	12	1	20	22
23	20	1	12	1/2"	SPARE								0.5										1.0	SADO REC	1/2"	12	1	20	24
25	20	1	12	1/2"	REC. WORK	0.7								0.2									0.1						26
27	20	1	12	1/2"	RECK WORK	0.2									0.1								0.1	SPD	3/4"	16	3	35	28
29	20	1			SPARE																		0.1						30
31	20	1			SPARE																			SPACE ONLY					32
33	20	1			SPARE																			SPACE ONLY					34
35	20	1			SPARE																			SPACE ONLY					36
37					SPACE ONLY																			SPACE ONLY					38
39					SPACE ONLY																			SPACE ONLY					40
41					SPACE ONLY																			SPACE ONLY					42
LIGHTING (KVA):						0.0	0.0	1.3	0.0	0.0	3.2	0.0	4.8			0.0	4.7	0.0	0.0	0.0	0.0	2.3		CONNECTED LOAD (KVA):					12.8
RECEPTACLES (KVA):						0.9																		DEMAND LOAD (KVA):					12.8
MOTORS (KVA):						0.0							PHASE A	4	31.0														
A/C (KVA):						0.0							PHASE B	4	34.7									CONNECTED LOAD (AMPS):					35.6
HEATING (KVA):						0.0							PHASE C	5	41.2									DEMAND LOAD (AMPS):					35.6
KITCHEN (KVA):						0.0										KVA	AMPS												
MISCELLANEOUS (KVA):						6.8																							

NOTES 1. BASIS OF DESIGN IS SQUARE D. 2. ** INDICATES RED BREAKER WITH LOCK OFF DEVICE.

PNL 'IG' DEMAND CALCS

LIGHTING	0.00	KVA X	125 %	=	0.0 KVA
RECEPTAC TOT