1 E-301 COMPUTER/DATA/TEL. OUTLET BOX DETAIL
NO SCALE



2 E-301 WORKING CLEARANCE FOR ELECTRICAL EQUIPMENT
NEC ARTICLE 110-26



3 E-301 COMPUTER/DATA/TEL. OUTLET DETAIL
NO SCALE

VOLTAGE DROP SCHEDULE

120 VOLT BRANCH CIRCUITS UP TO 8 AMPS

RUN DISTANCE IN FEET			WIRE SIZE AWG
1'	-	120'	#12
121'	-	190'	#10
191'	-	300'	#8
301'	-	480'	#6

120 VOLT BRANCH CIRCUITS 9 AMPS TO 14 AMPS

RUN DISTANCE IN FEET			WIRE SIZE AWG
1'	-	65'	#12
66'	-	110'	#10
111'	-	170'	#8
171'	-	270'	#6

277 VOLT BRANCH CIRCUITS UP TO 14 AMPS

RUN DISTANCE IN FEET			WIRE SIZE AWG
1'	-	160'	#12
161'	-	250'	#10
251'	-	390'	#8
391'	-	620'	#6

WIRE SIZES INDICATED IN PANEL SCHEDULES ARE MINIMUM WIRE SIZES. CONTRACTOR SHALL UPSIZE WIRES BASED ON LOAD AND LENGTH OF RUN AS INDICATED IN SCHEDULE ABOVE.



FIRE ALARM RISER NOTES:
1. FACP HAS A MINIMUM 24HR. BATTERY BACK-UP.
2. ALL ITEMS INDICATED DASHED ARE EXISTING TO REMAIN.
3. FACP IS CONNECTED TO A UL APPROVED CENTRAL STATION.
4. ZONE PER NFPA 72 AND MANUFACTURER'S RECOMMENDATIONS.
5. SEE PLANS FOR EXACT DEVICE QUANTITY AND LOCATIONS.
6. CONTRACTOR SHALL MODIFY EXISTING SIMPLEX SYSTEM AS REQUIRED TO HANDLE THE NEW FIRE ALARM DEVICES.
7. SEE SPECIFICATIONS FOR ADDITIONAL REQUIREMENTS.

4 E-301 FIRE ALARM RISER DIAGRAM
NO SCALE



5 E-301 POWER RISER DIAGRAM
NO SCALE

NOTES:
1. ITEMS INDICATED AS DASHED ARE EXISTING TO REMAIN UNDER SHELL BUILDING PLANS. FIELD COORDINATE PLACMENT OF PANEL 'R3' WITH LOCATION INDICATED IN TENANT UPFIT PLAN SET.

FIRE ALARM SEQUENCE

SEQUENCE OF OPERATIONS

ALARM SOURCE AND TYPE	BUILDING SYSTEM OUTPUTS: ACTUATE COMMON ALARM SIGNAL INDICATOR	ACTUATE AUDIBLE ALARM SIGNAL	ACTUATE COMMON SUPERVISORY SIGNAL INDICATOR	ACTUATE AUDIBLE SUPERVISORY SIGNAL	ACTUATE COMMON TROUBLE SIGNAL INDICATOR	ACTUATE AUDIBLE TROUBLE SIGNAL	ACTUATE CENTRAL EXACTION SIGNAL	ACTUATE EXTERNAL HORN / STROBE	TRANSMIT F.A. SIGNAL TO CENTRAL COMMUNICATOR	TRANSMIT SUPERVISORY SIGNAL TO CENTRAL COMM.	TRANSMIT TROUBLE SIGNAL TO CENTRAL COMM.	SHOW CHANGE OF STATUS ON ANNUNCIATOR	TRANSMIT ALARM SIGNAL TO CENTRAL STATION	TRANSMIT SUPERVISORY SIGNAL TO CENTRAL STATION	TRANSMIT TROUBLE SIGNAL TO CENTRAL STATION
1. MANUAL PULL STATION ALARM	■	■					■	■	■			■	■		
2. BUILDING SMOKE DETECTOR	■	■					■	■	■			■	■		
3. DUCT DETECTOR ALARM			■	■			■	■	■			■	■		
4. SMOKE DETECTOR DIRTY/MALFUNCTION - ALL					■	■	■	■	■			■	■		
5. SPRINKLER WATERFLOW	■	■					■	■	■			■	■		
6. SPRINKLER TAMPER			■	■			■	■	■			■	■		
7. FIRE ALARM AC POWER FAILURE					■	■				■		■			
8. FIRE ALARM SYSTEM LOW BATTERY					■	■				■		■			
9. OPEN CIRCUIT					■	■				■		■			
10. GROUND FAULT					■	■				■		■			
11. NOTIFICATION APPLIANCE CIRCUIT SHORT					■	■				■		■			
12. SYSTEM RESET	(SEE NOTES 1 AND 2 BELOW FOR ACTIONS)											■			

NOTES:
1. "SYSTEM RESET" SHALL CLEAR ALL DETECTOR AND MANUAL ALARM SIGNALS, STOP AND RESET THE PRE-DISCHARGE COUNTDOWN, AND STOP TRANSMISSION OF ALL ALARM SIGNALS TO THE MAIN PANEL.
2. SYSTEM SHALL BE PROGRAMMED SUCH THAT THE SYSTEM CAN BE RESET WHILE THE MANUAL ABORT BUTTON IS ACTIVATED.
3. SYSTEM SHALL HAVE A 3 BEAT TEMPORAL SOUND PATTERN.

PANELBOARD SCHEDULE - 'R3'

MAIN: 225A M.L.O. VOLTAGE: 208/120 PHASE: 3 WIRE: 4 MOUNTING: SURFACE AIC: 10,000 NOTES:

CKT #	BKR TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	PHASE	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT #
1	20	1	12	1/2"	RECEPTACLES		1.1						A				1.5				AH-1	1/2"	12	1	20	2
3	20	1	12	1/2"	RECEPTACLES		0.7						B				1.5				AH-2	1/2"	12	1	20	4
5	20	1	12	1/2"	EWC *						0.9		C								SPARE			1	20	6
7	20	1	12	1/2"	RECEPTS. SMOOTH *		0.4						A								SPARE			1	20	8
9	20	1	12	1/2"	H.C. REFRIGE. *						0.8		B				2.7				HP-1	1"	6	2	50	10
11	20	1	12	1/2"	ICE MACHINE *						1.2		C				2.7									12
13	20	1	12	1/2"	RECEPTS.		0.5						A				2.7				HP-2	1"	6	2	50	14
15	20	1	12	1/2"	DRINK REC *						0.8		B				2.7									16
17	20	1	12	1/2"	RECEPTACLES		0.2						C								SPACE					18
19	20	1	12	1/2"	RECEPTACLES		0.2						A							1.0	WASHING MACHINE *	1/2"	12	1	20	20
21	20	1	12	1/2"	STEREO (SHUNT)						0.4		B					2.3			DRYER	3/4"	10	2	30	22
23					SHUNT TRIP SPACE								C					2.3								24
25	20	1	12	1/2"	RECEPTACLES		0.4						A								SPARE			1	20	26
27	20	1	12	1/2"	RECEPTACLES		0.9						B							0.3	DWH	1/2"	12	1	20	28
29	20	1	12	1/2"	SHOW WINDOWS						1.9		C								SPARE			1	20	30
31	20	1	12	1/2"	SHOW WINDOWS						1.9		A	1.2							LIGHTING	1/2"	12	1	20	32
33	20	1	12	1/2"	SHOW WINDOWS						1.9		B	1.2							LIGHTING	1/2"	12	1	20	34
35	20	1	12	1/2"	SHOW WINDOWS						1.9		C	0.5							LIGHTING TRACK	1/2"	12	1	20	36
37	20	1			SPARE								A				1.2				FANS	1/2"	12	1	20	38
39	20	1			SPARE								B				1.2				FANS	1/2"	12	1	20	40
41	20	1			SPARE								C				1.2				SIGN	1/2"	12	1	20	42
LIGHTING (KVA):						4.1	0.0	3.1	1.3	0.0	0.0	0.0	10.9	4.1	0.0	2.4	13.7	4.5	0.0	1.3	CONNECTED LOAD (KVA):					41.2
RECEPTACLES (KVA):						3.1															DEMAND LOAD (KVA):					42.2
MOTORS (KVA):						3.7							PHASE A	12	100.0											
A/C (KVA):						13.7							PHASE B	17	144.1						CONNECTED LOAD (AMPS):					114.4
HEATING (KVA):						4.5							PHASE C	12	99.5						DEMAND LOAD (AMPS):					117.3
KITCHEN (KVA):						0.0								KVA	AMPS											
MISCELLANEOUS (KVA):						12.2																				

NOTES: 1. EXISTING PER SHELL DRAWINGS 2. * INDICATES NEW GFCI RATED BREAKER 3. ** INDICATES BREAKE WITH LOCK OFF DEVICE

MECH/ELEC SCHEDULE

ITEM	(WATTS) MCA	MOCP	VOLTAGE	DISCONNECT
DWH	(19.4)	-	120V-1Ø	S_W
EF-1,2,3,4	(19.4)	-	120V-1Ø	S_W SWITCH W/LIGHTS
AH-1/2	12.9	20	120V-1Ø	S_W
CU-1/2	31.9	50	208V-1Ø	60/50 P-3R

NOTE:
1. EC TO COORDINATE WITH MC AND PROVIDE ELECTRICAL CONNECTIONS AS REQUIRED FOR PER MANUFACTURES STAMPED DATA PLATES FOR A COMPLETE AND OPERATIONAL MECHANICAL/ELECTRICAL SYSTEM.

PNL 'R3' DEMAND CALCS

LIGHTING	4.05	KVA	X	125 %	=	**5.1 KVA**
RECEPTACTOTAL	3.08	KVA				
1ST	10.00	KVA	X	100 %	=	**3.1 KVA**
REMAIN	0.00	KVA	X	50 %	=	**0.0 KVA**
MOTORS	3.66	KVA	X	100 %	=	**3.7 KVA**
A/C	13.75	KVA	X	100 %	=	**13.7 KVA**
HEATING	4.50	KVA	X	100 %	=	**4.5 KVA**
LOCKED-OUT LOAD		KVA	X	100 %	=	**0.0 KVA**
KITCHEN	0.00	KVA	X	65 %	=	**0.0 KVA**
MISCELLANEOUS	12.20	KVA	X	100 %	=	**12.2 KVA**
TOTAL	=	**117.3 amps**			=	**42.2 KVA**

Order Plans @ WWW.LDLine.com

ODa
overcash demmitt
2010 south tryon st. suite 1a
charlotte north carolina 28203
office.704.332.1615
web.www.odarch.com

NORTH CAROLINA REGISTERED PROFESSIONAL ENGINEER 037734 MICHAEL J SMITH 12/6/2019

WAVE ENGINEERING
1520 S. MINT ST., SUITE 110
CHARLOTTE NC 28203
704.910.2677
INFO@WAVE-ENGINEERING.COM
NC CORP. LICENSE #P-1627
WAVE PROJECT #19-1128

Hustle House

ODA Project No. 183324

Charlotte, NC

FOR CONSTRUCTION

06.28.2019

REVISIONS

No.	Description	Date

ELECTRICAL RISERS & SCHEDULES

E-301

Copyright 2017 Overcash Demmitt Architects