ELECTRICAL SYMBOLS

LIGHTING SYMBOLS

SYMBOL	DESCRIPTION	MH (UON)
$	SINGLE POLE TOGGLE SWITCH	48" TOD
$a	SWITCH: SUB LETTER INDICATES FIXTURES CONTROLLED (a)	48" TOD
$2	DOUBLE POLE TOGGLE SWITCH	48" TOD
$3	THREE WAY TOGGLE SWITCH (SPDT)	48" TOD
$4	FOUR WAY TOGGLE SWITCH (DPDT)	48" TOD
$K	KEY OPERATED SWITCH	48" TOD
$3D a	THREE WAY DIMMER SWITCH: SUBLETTER INDICATES FIXTURES CONTROLLED (a)	48" TOD
$M	MANUAL STARTER W/ OVERLOADS	48" TOD
$P	SWITCH W/ PILOT LIGHT	48" TOD
$D	DIMMER SWITCH	48" TOD
$4D	4 BUTTON DIMMER SWITCH	48" TOD
$LV	LOW VOLTAGE CONTROL SWITCH	48" TOD
$T	MANUAL TIME SWITCH	48" TOD
$C	MOMENTARY CONTACT SWITCH	48" TOD
$WP	SWITCH WITH WEATHERPROOF ENCLOSURE	48" TOD
OS OS	OCCUPANCY SENSOR (CEILING & WALL MOUNTED)	
VS	VACANCY SENSOR	
T	TIME CLOCK	
R	RELAY	
L	LIGHTING CONTACTOR	
P	PHOTOCELL OR PUSHPLATE SWITCH	
ADP2	EMERGENCY SHUNT RELAY, UL 924 LISTED (CEILING MOUNTED)	
	LIGHTING FIXTURE: RECESSED, SURFACE, OR PENDANT MOUNTED - TYPE AS SPECIFIED	
	LIGHTING FIXTURE: 2 BALLAST	
	LIGHTING FIXTURE: INDUSTRIAL	
	LIGHTING FIXTURE: WALL MOUNTED - TYPE AS SPECIFIED	
	LIGHTING FIXTURE: RECESSED, SURFACE, OR PENDANT MOUNTED	
	LIGHTING FIXTURE: WALL MOUNTED - TYPE AS SPECIFIED	
	WALL WASHER	
	ADJUSTABLE WALL WASHER	
	LIGHTING FIXTURE ON EMERGENCY OR NIGHT LIGHT CIRCUIT (NL)	
	EMERGENCY BATTERY PACK: W/ NUMBER OF HEADS INDICATED	
	EMERGENCY BATTERY PACK: W/ REMOTE HEADS	
	REMOTE EMERGENCY HEAD	
	EMERGENCY BATTERY PACK: SEMI RECESSED, CEILING MOUNT	
	EXIT SIGN: CEILING OR PENDANT MOUNTED (SHADED PORTION INDICATES FACE)	
	EXIT SIGN: WALL MOUNTED - END, BACK	
	EXIT SIGN: W/ DIRECTIONAL ARROWS	
	POLE MOUNTED LIGHTING FIXTURE: SINGLE HEAD, DOUBLE HEAD	
	POLE MOUNTED LIGHTING FIXTURE: SINGLE, POLE TOP	
	LIGHTING POLE (SPORTS)	

SPECIAL SYSTEMS SYMBOLS

SYMBOL	DESCRIPTION	MH (UON)
FH	FIRE ALARM HORN TYPE SPEAKER	NOTE 5
FH	FIRE ALARM FLASHING STROBE LIGHT - WALL MOUNTED	NOTE 5
FH	FIRE ALARM HORN	NOTE 5
FH	COMBINATION FIRE ALARM HORN AND FLASHING STROBE LIGHT	NOTE 5
S F	S - CEILING SPEAKER, F - FIRE ALARM SPEAKER	
	FIRE ALARM SPEAKER W/ STROBE	
HS	HORN TYPE SPEAKER	
H	MAGNETIC DOOR HOLDER	
DACT	DIGITAL ALARM COMMUNICATOR TRANSMITTER	
FAAP	FIRE ALARM ANNUNCIATOR PANEL	
FACP	FIRE ALARM CONTROL PANEL	
RAM	RESCUE ASSISTANCE MASTER CONTROL PANEL	48" TOD
RAR	RESCUE ASSISTANCE REMOTE STATION	48" TOD
TP	FIRE ALARM TRANSPONDER	
DS DS	DOOR SOLENOID, ELECTRIC STRIKE - LOCKING DEVICE CONNECTION POINT	
	FIRE ALARM PULL STATION	48" TOD
	HEAT DETECTOR: E = ELEVATOR CONTROLS	
AUDIBLE	SMOKE DETECTOR (PHOTOELECTRIC): AB = AUDIBLE BASE, E = ELEVATOR CONTROLS	
	SMOKE DETECTOR (IONIZATION)	
	FIRE ALARM DUCT DETECTOR WITH RELAY	
	CARBON MONOXIDE DETECTOR	
ARC	FIRE ALARM SYSTEM ADDRESSABLE RELAY - CONTROL	
AMX	FIRE ALARM SYSTEM ADDRESSABLE RELAY - MONITOR	
RAL	FIRE ALARM SYSTEM REMOTE ALARM LIGHT	
FS	FLOW SWITCH CONNECTION	
TS	TAMPER SWITCH CONNECTION	
TRASMITTER LBT / LIGHT BEAM RECEIVER LBR	FIRE ALARM LINEAR BEAM SMOKE DETECTOR: TRANSMITTER (LBT) AND RECEIVER (LBR)	
F	FIRE FIGHTER'S TELEPHONE JACK	48" TOD
M	MONITOR SYSTEM JUNCTION BOX	36" CTR
A	AMPLIFIER	
K	KEYPAD	48" TOD
CR	CARD READER	48" TOD
DM	DOOR ALARM CONTACT	
	ROUGH-IN JUNCTION BOX FOR CCTV CAMERA	
PP	PUSH BUTTON PLATE	
	TELEVISION ANTENNA OUTLET	18" CTR
	CABLE TV OUTLET	
CB	TELEVISION SYSTEM SPLITTER - 2 WAY, 4 WAY	
AR	A/V CREDENZA LOCATION	
IP	A/V INPUT PLATE	
R	A/V IN-WALL RACK	
MT	A/V MONITOR TV	
SC	A/V SCREEN CONTROL	
SP	A/V SCHEDULER PANEL	
ST	A/V SIGNAGE TV	
TP	A/V TOUCH PANEL	
	DATA/TELEPHONE OUTLET, CEILING MOUNTED	
	TELEPHONE OUTLET	18" CTR
	DATA OUTLET	18" CTR
	TELEPHONE OUTLET, WALL MOUNTED	54" CTR
E	TELEPHONE OUTLET, EMERGENCY	54" TOD
	DATA/TELEPHONE OUTLET: UNSHADED AREA = DATA, SHADED AREA = VOICE NUMERALS INDICATE QUANTITY OF WIRED JACKS	18" CTR
	TELEPHONE OUTLET, FLOOR MOUNTED	
	DATA OUTLET, FLOOR MOUNTED	
	DATA/TELEPHONE OUTLET, FLOOR MOUNTED: UNSHADED AREA = DATA, SHADED AREA = VOICE NUMERALS INDICATE QUANTITY OF WIRED JACKS	
	COMBINATION POWER & TELEPHONE OUTLET, FLOOR MOUNTED	
	COMBINATION POWER & DATA OUTLET, FLOOR MOUNTED	
	COMBINATION POWER & DATA/TELEPHONE OUTLET, FLOOR MOUNTED	
WAP	WIRELESS ACCESS POINT	

POWER SYMBOLS

SYMBOL	DESCRIPTION	MH (UON)
$	COMBINATION SWITCH AND SIMPLEX RECEPTACLE	48" TOD
$	COMBINATION SWITCH AND DUPLEX RECEPTACLE	48" TOD
	SIMPLEX RECEPTACLE	18" CTR
E	DUPLEX RECEPTACLE: "E" (IF SHOWN) INDICATES CONNECTED TO EMERGENCY CIRCUIT	18" CTR
	DUPLEX RECEPTACLE: FLOOR MOUNTED	
	DUPLEX RECEPTACLE: SPLIT WIRED, BOTTOM HALF SWITCHED	18" CTR
	DUPLEX RECEPTACLE: CEILING MOUNTED	
	DUPLEX RECEPTACLE: PEDESTAL TYPE	
	DUPLEX RECEPTACLE: MOUNTED 6" ABOVE BACKSPLASH OR COUNTER	
GFI	DUPLEX RECEPTACLE: GROUND FAULT INTERRUPTER TYPE	18" CTR
GFI	DUPLEX RECEPTACLE: GFI MOUNTED 6" ABOVE BACKSPLASH OR COUNTER	
H	DUPLEX RECEPTACLE: MOUNTED HIGH	84" CTR
IG	DUPLEX RECEPTACLE: ISOLATED GROUND	18" CTR
	DUPLEX RECEPTACLE: AT 54" A.F.F.	54" CTR
	DOUBLE DUPLEX RECEPTACLE	18" CTR
IG	DOUBLE DUPLEX RECEPTACLE ISOLATED GROUND	18" CTR
C	SIMPLEX RECEPTACLE: CART RECHARGE	36" CTR
C	DUPLEX RECEPTACLE: CART RECHARGE	36" CTR
P	DUPLEX RECEPTACLE: PAY PHONE	54" CTR
A	SPECIAL RECEPTACLE: NEMA 6-20R (20A, 2P, 3W, 206V)	18" CTR
B	SPECIAL RECEPTACLE: NEMA 6-30R (30A, 2P, 3W, 206V)	18" CTR
C	SPECIAL RECEPTACLE: NEMA 14-20R (20A, 3P, 4W, 208/120V)	18" CTR
D	SPECIAL RECEPTACLE: NEMA 15-30R (30A, 3P, 4W, 208V)	18" CTR
A	SPECIAL RECEPTACLE: FLOOR MOUNTED, NEMA 6-20R	
A	SPECIAL RECEPTACLE: PEDESTAL TYPE, NEMA 6-20R	
	TELEVISION RECEPTACLE	72" CTR
H	TELEVISION RECEPTACLE	18" BFC
	CLOCK HANGER OUTLET	84" CTR
	PROGRAM CLOCK OUTLET: SINGLE FACE, DOUBLE FACE	84"
EPO	EMERGENCY POWER OFF SWITCH	48" TOD
	JUNCTION BOX	
	JUNCTION BOX - WALL MOUNTED	48" TOD
	EQUIPMENT CONNECTION AS NOTED	
	EQUIPMENT CONNECTION AS NOTED - WALL MOUNTED	48" TOD
3	HEATER CONNECTION - NUMBER INDICATES KILOWATTS (KW)	
	HEATER CONNECTION - CEILING MOUNTED	
CB	3 POLE CIRCUIT BREAKER	
	NON-FUSED DISCONNECT SWITCH: 30A, 3P (UON)	
	FUSED DISCONNECT SWITCH: FUSE SIZE AS INDICATED (40A)	
MS	MAGNETIC MOTOR STARTER	
FVNR	COMBINATION MAGNETIC MOTOR STARTER: ABBREVIATION INDICATES TYPE - FVNR, FVR, RVAT, 2S1W, 2S2W, SST	
VFC	VARIABLE FREQUENCY CONTROLLER W/ FUSED DISCONNECT SWITCH	
VFD	VARIABLE FREQUENCY DRIVE W/ DISCONNECT SWITCH	
HP	MOTOR: NUMERALS (IF SHOWN) INDICATE HP	
KW	GENERATOR: NUMERALS (IF SHOWN) INDICATE KW	
M	MANUAL MOTOR STARTER W/ THERMAL OVERLOADS	
M	MOTOR SWITCH	
M	MECHANICAL EQUIPMENT CONNECTION - WITH MOTOR	
	MECHANICAL EQUIPMENT CONNECTION - NO MOTOR	
CP	CONTROL PANEL: TYPE AS INDICATED	
PB	MOMENTARY CONTACT START-STOP PUSHBUTTON STATION	48" TOD
PBM	MAINTAINED CONTACT START-STOP PUSHBUTTON STATION	48" TOD
ES	MAINTAINED CONTACT EMERGENCY STOP PUSHBUTTON STATION	48" TOD
	BRANCH PANELBOARD	90" TOC
	DISTRIBUTION PANELBOARD	
T	TRANSFORMER, CONCRETE PAD MOUNTED	

SYMBOL	DESCRIPTION
	RACEWAY "UP" OR "TOWARDS"
	RACEWAY "DOWN" OR "AWAY"
	CIRCUIT CONCEALED IN WALLS OR CEILING SPACE: CONDUCTORS SHALL BE MINIMUM 2#12 AWG AND 1#12 AWG GROUND IN 3/4" CONDUIT (UON)
	RACEWAY CONCEALED IN SLAB OR BELOW GRADE
	BRANCH CIRCUIT HOMERUN TO PANELBOARD: QUANTITY OF CIRCUITS INDICATED BY ARROWS NUMBER OF CONDUCTORS SHALL BE MINIMUM 4#12 AWG AND 1#12 AWG GROUND IN 3/4" CONDUIT (UON)
	RACEWAY RUN EXPOSED: CONDUCTORS SHALL BE MINIMUM 2#12 AWG AND 1#12 AWG GROUND IN 3/4" CONDUIT (UON)
	BUS DUCT OR CABLE TRAY "UP" OR "TOWARDS"
	BUS DUCT OR CABLE TRAY "DOWN" OR "AWAY"
	BUS DUCT: TYPE AND SIZE AS INDICATED
	TELEPHONE AND POWER POLE ASSEMBLY
	CONCRETE ENCASED DUCTBANK BELOW GRADE
W	SURFACE MOUNTED RACEWAY ASSEMBLY WITH REMOVABLE COVER
	MULTI OUTLET ASSEMBLY: DARK SQUARES INDICATE PREWIRED RECEPTACLE LOCATIONS SIZE AS INDICATED
	MULTI OUTLET ASSEMBLY: WITH RECEPTACLES LOCATED WHERE INDICATED
	2 CELL MULTI OUTLET ASSEMBLY: WITH COMMUNICATION DEVICES AND RECEPTACLES LOCATED WHERE INDICATED
	MULTI OUTLET ASSEMBLY: WITH COMMUNICATION DEVICES LOCATED WHERE INDICATED
	FLEXIBLE CONDUIT
	CABLE TRAY
	GROUND ROD
	LIGHTNING PROTECTION AIR TERMINAL
G	GROUND WIRE CONNECTION
G	GROUND WIRE
	LIGHTNING PROTECTION DOWN LEAD
	UTILITY POLE

ELECTRICAL DIAGRAMS AND SYMBOLS

SYMBOL	DESCRIPTION
NOTE	AUTOMATIC TRANSFER DEVICE
	METERING DEVICES: A - AMMETER, V - VOLTMETER, PF - POWER FACTOR, HZ - FREQUENCY METER
	DIGITAL METER
(50)	FUSE: FUSE SIZE AS INDICATED (50A)
	GROUND CONNECTION
	TRANSFORMER (DELTA - RESISTANCE GROUNDED WYE SHOWN)
	CURRENT TRANSFORMER
	POTENTIAL TRANSFORMER
LA	LIGHTNING ARRESTOR
	MOTOR STARTER CONTACTOR AND THERMAL OVERLOAD
K	KIRK KEY INTERLOCK SYSTEM
TRIP FRAME	MOLDED CASE CIRCUIT BREAKER WITH RATINGS AS INDICATED
	SWITCH
	DRAW OUT DEVICE
52	DRAW OUT POWER CIRCUIT BREAKER
CB	ENCLOSED CIRCUIT BREAKER
FVNR	COMBINATION MAGNETIC MOTOR STARTER - ABBREVIATION INDICATES TYPE: FVNR, FVR, RVAT, 2S1W, 2S2W, SST
SPD	SURGE PROTECTION DEVICE
VFC	VARIABLE FREQUENCY CONTROLLER W/ FUSED DISCONNECT SWITCH
VFC	VARIABLE FREQUENCY CONTROLLER
2S2W	MOTOR - SINGLE WINDING UNLESS OTHERWISE NOTED: 2S2W = 2 SPEED, 2 WINDING 2S1W = 2 SPEED, 1 WINDING NUMERALS (IF SHOWN) INDICATE HP

CIRCUIT DESIGNATIONS

LIGHTING A # a
- A: FIXTURE TYPE
- #: CIRCUIT DESIGNATION (#12AWG MINIMUM)
- a: SWITCH DESIGNATION

POWER #
- #: CIRCUIT DESIGNATION (#12AWG MINIMUM)

ELECTRICAL SYMBOLS NOTES

1. THIS IS A STANDARD SYMBOL LIST. SOME SYMBOLS MAY NOT APPEAR ON THE ACCOMPANYING DRAWINGS.
2. REFER TO SPECIFICATIONS FOR DETAILED REQUIREMENTS.
3. PLAN AND SECTION SYMBOLS MAY ALSO BE USED ON RISER DIAGRAMS.
4. ON SINGLE LINE DIAGRAMS FOR 3 PHASE SYSTEMS, DEVICE QUANTITY = 3, UNLESS OTHERWISE NOTED.
5. DEVICE SHALL BE MOUNTED A MINIMUM OF 90" AFF TO BOTTOM OF DEVICE OR BELOW THE FINISHED CEILING OF NOT LESS THAN 6" TO TOP OF DEVICE, WHICHEVER IS LOWER.
6. UNLESS OTHERWISE NOTED, ALL INTERIOR CONDUITS AND BOXES SHALL BE CONCEALED.

ELECTRICAL ABBREVIATIONS

NOTE: THIS IS A STANDARD ABBREVIATION LIST. SOME ABBREVIATIONS MAY NOT APPEAR ON THE ACCOMPANYING DRAWINGS.

2S1W	2 SPEED SINGLE WINDING	KWH	KILOWATT HOUR
2S2W	2 SPEED DOUBLE WINDING		
		LA	LIGHTNING ARRESTOR
A, AMP	AMPERE	LC	LIGHTING CONTACTOR
A/C	AIR CONDITIONING	LP	LIGHTING PANEL
AC	ALTERNATING CURRENT	LRA	LOCKED ROTOR AMPERES
AFCI	ARC FAULT CIRCUIT INTERRUPTER	LTG	LIGHTING
AFF	ABOVE FINISHED FLOOR	LTNG	LIGHTNING
AFG	ABOVE FINAL GRADE		
AHU	AIR HANDLING UNIT	MATV	MASTER ANTENNA TELEVISION
AIC	AMPS INTERRUPTING CAPACITY	MCB	MAIN CIRCUIT BREAKER
ALT	ALTERNATE	MCC	MOTOR CONTROL CENTER
ANN	ANNUNCIATOR	MEH	METAL HALIDE
APPROX	APPROXIMATELY	MH	MANHOLE, MOUNTING HEIGHT
ARCH	ARCHITECT	MLO	MAIN LUGS ONLY
ATC	AUTOMATIC TEMPERATURE CONTROL	MSP	MOTOR STARTER PANEL
ATS	AUTOMATIC TRANSFER SWITCH	MTD	MOUNTED
AV	AUDIOVISUAL	MV	MERCURY VAPOR
AWG	AMERICAN WIRE GAUGE		
		NC	NORMALLY CLOSED
BAS	BUILDING AUTOMATION SYSTEM	NEC	NATIONAL ELECTRIC CODE
BFC	BELOW FINISHED CEILING	NFSS	NON-FUSED SAFETY SWITCH
BFG	BELOW FINISHED GRADE	NO	NUMBER, NORMALLY OPEN
BLDG	BUILDING		
BOD	BOTTOM OF DEVICE	OC	ON CENTER
		OFCI	OWNER FURNISHED CONTRACTOR INSTALLED
C, CND	CONDUIT		
CATV	CABLE TELEVISION	OFOI	OWNER FURNISHED OWNER INSTALLED
CB	CIRCUIT BREAKER		
CCTV	CLOSED CIRCUIT TELEVISION	OH	OVERHEAD
CKT, CCT	CIRCUIT		
CL	CURRENT LIMITING	P	POLE
CLG	CEILING	PB	PUSHBUTTON
CONN	CONNECT	PF	POWER FACTOR
CPT	CONTROL POWER TRANSFORMER	PFCC	POWER FACTOR CORRECTION CAPACITOR
CT	CURRENT TRANSFORMER	PL	PILOT LIGHT
CTR	CENTER	PLC	PROGRAMMABLE LIGHTING CONTROL
CU, CO	COPPER	PNL	PANEL
CX	CONNECT TO EXISTING	PP	POWER PANEL
		PU	PUMP
DC	DIRECT CURRENT	PR	PAIR
DISC	DISCONNECT	PRN	PRINTER
DN	DOWN	PT	POTENTIAL TRANSFORMER
DP	DISTRIBUTION PANEL	PVC	POLYVINYL CHLORIDE
DPDT	DOUBLE POLE DOUBLE THROW	Ø, PH	PHASE
DPST	DOUBLE POLE SINGLE THROW		
DT	DOUBLE THROW	QTY	QUANTITY
DTL	DETAIL		
E, EMERG	EMERGENCY	RCS	REMOTE CONTROL SWITCH
EA	EACH	REC, RECPT	RECEPTACLE
EC	EMPTY CONDUIT	REQ'D	REQUIRED
EF	EXHAUST FAN	RFI	RADIO FREQUENCY INTERFERENCE
EH	ELECTRIC HEATER	RGS	RIGID GALVANIZED STEEL
ELEC	ELECTRIC	RLA	RUNNING LOAD AMPERES
ELEV	ELEVATION, ELEVATOR	RM	ROOM
ETR	EXISTING TO REMAIN	RVAT	REDUCED VOLTAGE AUTO TRANSFORMER
EWC	ELECTRIC WATER COOLER		
EX	EXISTING	RX	REMOVE EXISTING
EXP	EXPOSED		
		SC	SURGE CAPACITOR
FA	FIRE ALARM	SEC	SECONDARY
FAAP	FIRE ALARM ANNUNCIATOR PANEL	SN, S:N	SOLID NEUTRAL
FACP	FIRE ALARM CONTROL PANEL	SP	SURGE PROTECTION
FBO	FURNISHED BY OTHERS	SPD	SURGE PROTECTION DEVICE
FC	FAN COIL	SPDT	SINGLE POLE DOUBLE THROW
FDR	FEEDER	SS	SAFETY SWITCH
FLA	FULL LOAD AMPERES	SST	SOLID STATE
FLR	FLOOR	ST	SINGLE THROW
FR	FRAME	SW	SWITCH
FU	FUSED, FUSIBLE	SWBD	SWITCHBOARD
FUSS	FUSED SAFETY SWITCH		
FVNR	FULL VOLTAGE NON-REVERSING	TBR	TO BE REMOVED
FVR	FULL VOLTAGE REVERSING	TC	TIME CLOCK
		TEL, TELE	TELEPHONE
GEN	GENERATOR, GENERAL	TH	TUNGSTEN HALOGEN
GFCI	GROUND FAULT CIRCUIT INTERRUPTER	TOC	TOP OF CABINET
		TOD	TOP OF DEVICE
GFI	GROUND FAULT INTERRUPTER	TRANS, XFMR	TRANSFORMER
GFP	GROUND FAULT PROTECTED		
GFR	GROUND FAULT RELAY	TTB	TELEPHONE TERMINAL BOARD
GRD	GROUND	TW	TWISTED
GRS	GALVANIZED RIGID STEEL	TYP	TYPICAL
HID	HIGH INTENSITY DISCHARGE	UCB	UNIT CIRCUIT BREAKER
HOA	HAND-OFF AUTOMATIC	UG	UNDERGROUND
HP	HEAT PUMP, HORSEPOWER	UH	UNIT HEATER
HPS	HIGH PRESSURE SODIUM	UON	UNLESS OTHERWISE NOTED
HTR	HEATER	UV	UNIT VENTILATOR
HV	HIGH VOLTAGE		
HZ	HERTZ	V	VOLTS
		VFC	VARIABLE FREQUENCY CONTROLLER
IG	ISOLATED GROUND	VFD	VARIABLE FREQUENCY DRIVE
JB	JUNCTION BOX	W	WATTS, WIRE
		W/	WITH
KCMIL	THOUSAND CIRCULAR MILS	WP	WEATHER-PROOF
KV	KILOVOLTS		
KVA	KILOVOLT AMPERES	XP	EXPLOSION PROOF
KVAR	KILOVOLT AMPERES REACTIVE		
KW	KILOWATTS		

EQUIPMENT DESIGNATIONS

SYMBOL	DESCRIPTION
SWGR	SWITCHGEAR
SWBD	SWITCHBOARD
PNL	PANELBOARD
MCC	MOTOR CONTROL CENTER
XFMR	TRANSFORMER

ELECTRICAL DRAWING PRESENTATION

SYMBOL	DESCRIPTION
1	REVISION NUMBER
1	DRAWING NOTE NUMBER
XX / XX XX	SECTION/ELEVATION IDENTIFICATION
XX / XX	PART PLAN AND DETAIL IDENTIFICATION
	EXISTING LINE TYPE
	NEW ELECTRICAL WORK LINE TYPE
	FUTURE ELECTRICAL WORK LINE TYPE
	DEMOLITION LINE TYPE ON DEMOLITION DRAWINGS

Order Plans @ WWW.LDRline.com

CD	100% CD SET	01/31/2020

SHADOW ROCK ELEMENTARY SCHOOL
GYM HVAC DESIGN
1040 Kingway Drive
Lithonia, Georgia 30058

STANLEY LOVE STANLEY P.C.
ARCHITECTURE
INTERIORS PLANNING
PROGRAM MANAGEMENT
1096 SPRING STREET, N.W.
ATLANTA, GEORGIA 30309-3910
404-876-0556
404-876-8641 fax
www.stanleylove-stanley.com

DRAWING TITLE
Electrical Notes, Symbols and Abbreviations

PROFESSIONAL SEAL
GEORGIA REGISTERED No. PE030780 PROFESSIONAL ENGINEER
Expires 12/31/2020
BRIAN CRUTCHFIELD

CONSULTANT
rmr Engineering
910 HAMMOND DRIVE SUITE 725
ATLANTA, GA 30328 678.918.9329

SCALES AS STATED HEREON ARE VALID ON THE ORIGINAL DRAWING. THE DIMENSIONS OF WHICH ARE 30X40 INCHES. THE SCALES NOTED HEREIN ARE HEREBY CHANGE BY THE RATIO OF THE OVERALL SHEET DIMENSIONS OF THE PRINT TO CORRESPONDING DIMENSIONS OF THE ORIGINAL DRAWING.

THE DRAWING IS THE PROPERTY OF STANLEY, LOVE-STANLEY, P.C. AND IS NOT TO BE REPRODUCED OR COPIED IN WHOLE OR IN PART. IT IS ONLY TO BE USED FOR THE PROJECT AND SITE SPECIFICALLY ENTITLED HEREIN AND IS NOT TO BE USED ON ANY OTHER PROJECT. IT IS TO BE RETURNED UPON REQUEST.

COPYRIGHT © 2019 - ALL RIGHTS RESERVED
STANLEY, LOVE-STANLEY, P.C.

DRAWING NO.

DATE
01/31/2020

PROJECT NO.
6919.5

DRAWING NO.
E-001

RELEASED FOR CONSTRUCTION 01/31/2020