GRAPHICAL ELECTRICAL SYMBOLS

BRANCH CIRCUIT SYMBOLS					
	BRANCH CIRCUIT	HOMERUN TO 20A, 1POLE CIRCUIT BREAKER IN PANELBOARD OR DEWICE NOTED. WIRE SIZE IS 2#12&1#12GRD-3/4°C.			
	BRANCH CIRCUIT	CONCEALED IN CEILING OR WALL.			
BRANCH CIRCUIT CONCEALED IN FLOOR. EXISTING CONDUIT BARS DENOTE NEW CONDUCTORS					
				BRANCH CIRCUIT EXPOSED.	
0	BRANCH CIRCUIT RISER UP.				
BRANCH CIRCUIT RISER DOWN.		RISER DOWN.			
	BRANCH CIRCUIT NOTES				
_	BRANCH CIRCUIT	3#12&1#12GRD-3/4"C			
BRANCH CIRCUIT 4#12&1#12GRD-3/4"C		4#12&1#12GRD-3/4"C			
		2#10&1#10GRD-3/4°C			
,10一州 BRANCH CIRCUIT 3#10&1#10GRD-3/4"C					

SIZE CONDUIT PER NEC FOR GREATER NUMBER OF CONDUCTORS OR AS NOTED. THE NUMBER IN THE CIRCUIT INDICATES AWG WIRE SIZE AND THE HASHMARKS INDICATE THE NUMBER OF WIRES REQUIRED. EQUIPMENT GROUND CONDUCTOR SHALL BE SIZED IN ACCORDANCE WITH NEC TABLE 250—122. THE NUMBER OF HASH MARKS DO NOT INCLUDE EQUIPMENT GROUNDING CONDUCTOR.

GENERAL SYMBOLS			
(JUNCTION BOX.		
Θ	WALL MOUNTED JUNCTION BOX.		
√ Ø-	WALL MOUNTED JUNCTION BOX WITH FLEXIBLE CONNECTION TO EQUIPMENT.		
0 ≻	TWO GANG BOX WITH 3/4°C. STUB UP ABOVE ACCESSIBLE CEILING WITH COAXIAL CABLE AND TV JACKS. HOMERUN COAXIAL CABLE TO TBB.		
\$ _T	MANUAL MOTOR STARTER WITH THERMAL PROTECTION.		
~	SAFETY SWITCH, NON-FUSED.		
Ď	SAFETY SWITCH, FUSED.		
-	CIRCUIT BREAKER MOUNTED IN NEMA 1 ENCLOSURE UNLESS NOTED OTHERWISE		
	LIGHTING PANEL AND/OR RECEPTACLE PANEL.		
	POWER PANEL.		
TR	TRANSFORMER.		
чE	GROUND.		

GENERAL ABBREVIATIONS						
ᆂᆃᆍᇎᄟᆃᇫᄥᆠᆔᅹᇰᇝᇝᄯᇎᇎᇸᆇᅑᆇᇎᇎ	MOUNTING HEIGHT ABOVE FINISHED FLOOR. ABOVE FINISHED FLOOR. WEATHER PROOF — NEMA 3R RAIN TIGHT — NEMA 4. EXPLOSION PROOF. MOUNT ABOVE COUNTER. MOUNT BELOW COUNTER. FLUSH MOUNTED. SEE SINGLE LINE DIAGRAM. GROUND FAULT INTERRUPTING. CONDUIT. EMPTY CONDUIT FLEXIBLE CONDUIT. SEALTITE FLEXIBLE CONDUIT. ELECTRICAL METALLIC TUBING, INTERMEDIATE METALLIC TUBING, INTERMEDIATE METALLIC RONDUIT. RIGID CONDUIT. RIGID CONDUIT. RIGID CONDUIT. RIGID CONDUIT. RIGID CONDUIT. RISITING TO BE REMOVED EXISTING TO BE REMOVED EXISTING TO BE REMOVED EXISTING TO BE REMOVED					
RQ RR RL'D EM	EXISTING TO BE REMOVED. EXTEND CIRCUIT CONDUCTORS AS REQUIRED AND INSTALL FINISHED BLANK COVER. EXISTING TO BE REMOVED AND REPLACED WITH NEW. RELOCATED POSITION. EMERGENCY BATTERY PACK					

		LIGHTING F	FIXTURE & CONTROL SYMBOLS		
	¹ (A)	CEILING OUTLET	FIXTURE TYPE "A" CIRCUIT #1.		
	\otimes	CEILING OUTLET EXISTING.			
CEILING OUTLET FLUORESCENT FIXTURE, SINGLE OR CONTINUIL LENGTHS AS SHOWN.					
	\bar{Q}	CEILING OUTLET	FLUORESCENT STRIP.		
	Q	WALL OUTLET	BRACKET TYPE FIXTURE.		
	Ą	WALL OUTLET	FLUORESCENT BRACKET TYPE FIXTURE.		
\$ WALL OUTLET A.C. TYPE, SINGLE POLE, 20A, 125/277V.					
	\$ ₃	WALL OUTLET	A.C. TYPE, THREE WAY, 20A, 125/277V. A.C. TYPE, FOUR WAY, 20A, 125/277V.		
	\$4	WALL OUTLET			
	\$os	WALL OUTLET	180° DUAL TECH SENSOR LIGHTING MOTION DETECTOR, WALL MOUNTED.		
CEILING OUTLET LIGHTING MOTION DETECTOR POWER PACK. INSTAL ABOVE ACCESSIBLE CEILING.			LIGHTING MOTION DETECTOR POWER PACK. INSTALL ABOVE ACCESSIBLE CEILING.		
	D-	SWITCH OUTLET	0-10V DIMMER UNLESS OTHERWISE NOTED.		
		s	WITCH OUTLET NOTES		


	EXIT LIGHT SYMPOLS
⊗	WALL OR CEILING MOUNTED, SINGLE FACE NO ARROW.
1(0)	CEILING MOUNTED, DOUBLE PACE, LEFT OR WEST AREWS.
180	WALL OR CEILING NITED, UNGLE FACE, LE OR RIGHT ARROW.
₩	WALL OR CELLIC MOUNTS SINGLE FACE, LEFT AND RIGHT ARROWS.
1(0)	CEILING MOUNTED, POURLE FACE, LEFT AND RIGHT ARROWS.

FIXTURE CORRESPONDS TO A SWITCH DENOTED WITH THE SAME LETTER.

RECEPTACLE OUTLET SYMBOLS				
₩ALL OUTLET		DUPLEX RECEPTACLE, 20A, 125V, 3WRE, NEMA 5-20R.		
₩ALL OUTLET		DOUBLE DUPLEX RECEPTACLE, 20A, 125V, 3WRE, NEMA 5-20R, SINGLE PLATE.		
Φ= WALL OUTLET		DUPLEX RECEPTACLE, 20A, 125V, NEMA 5-20R, GFCI, WEATHER-RESISTANT, WITH EXTRA DUTY IN-USE WEATHERPROOF COVER.		
←	WALL OUTLET	SINGLE RECEPTACLE, 20A, 250V, 3WIRE, NEMA 6-20R.		
FLOOR OUTLE		FLUSH MOUNTED IN-GRADE WITH DOUBLE DUPLEX RECEPTACLE, 20A, 125V, 3WRFE LAW 20R, FOUR SPACES FOR KEYSTONE COMPETEDS. AND BRUSHED BRASS COVER.		
RECEPTACLE OUT ET NES				
"G"	GROUND FAULT INTE	RRUPTER		
"GA"	GROUND FAULT INTERRUPTES MOUNTED ABOVE COUNTER.			
"A"	MOUNTED ABOMINGUNTER.			
"BC"	MOUNTED BE ON COUNTER			
" (%)	FOR DRING POLIN	N.		
M.	THE THE PARTY NAMED IN COLUMN			

VOICE/DATA OUTLET & CONDUIT SYMBOLS				
	VOICE/DATA OUTLET	WALL MOUNTED, WITH 3/4" CONDUIT HOMERUN TO NEAREST TELEPHONE CABINET OR BACKBOARD UNLESS NOTED OTHERWISE.		
	VOICE/DATA OUTLET	TELEPHONE BACKBOARD — 3/4" PLYWOOD PAINTED WITH TWO COATS OF FIRE RETARDANT PAINT, 48"x96" HIGH, UNLESS SHOWN OTHERWISE.		
VOICE/DATA OUTLET NOTES				
"A"	"A" MOUNTED ABOVE COUNTER.			
"BC"	MOUNTED BELOW CO	UNTER.		





Express Oil Change & Tire Engineers Service Building (Hurricane)

	FINAL				
-	No.	Description	Date		
	140.	Description	Date		
	1				
	-				
	\vdash				
		2020 Aho Archite	cte II		

© 2020 Aho Architects, LLC. All Rights Reserved.


Symbol Legends and Details

Project number	20025
Date	08/27/2020
Drawn by	TH
Checked by	NB
21/ [=101

FISHER ARNOLD 2 A - E 1 O I 1907 Alex Drive, Suito 101 | Birmingham, AL 35210 205.833.7033 | Pax: 205.314.0180 | fisheramoid.com NO SCALE

REMOVED AND REPLACED WITH ITION. TERY PACK	NEW.			
	The state of the s			
)1	NOTES;	

- INDICATED MOUNTING HEIGHTS ARE FROM FINISHED FLOOR TO CENTERLINE OF OUTLET BOX, UNLESS OTHERWISE NOTED.
- REFER TO ARCHITECTURAL DETAILS FOR ADDITIONAL REQUIREMENTS.
- INSTALL OUTLETS THAT ARE IN CLOSE PROXIMITY ON THE SAME CENTERLINE.
- MOUNTING HEIGHTS SHOWN HERE ARE TYPICAL UNLESS NOTED OTHERWISE ON DRAWINGS.



Order Dians