ELECTRICAL SYMBOLS & ABBREVIATIONS

[SOME SYMBOLS MAY NOT BE USED ON THIS PROJECT]

GENERAL

SYMBOL	DESCRIPTION
	MOTOR, HP AS INDICATED
	DISCONNECT SWITCH
	MOTOR CONTROLLER
	COMBINATION MOTOR CONTROLLER/DISCONNECT UNIT
VFD	VARIABLE FREQUENCY DRIVE
C	CONTACTOR
IC	INTERCOM J BOX WALL MOUNTED AT HEIGHT INDICATED ON DRAWINGS
J	JUNCTION BOX, CEILING MOUNTED
J	JUNCTION BOX, WALL MOUNTED
PC	PHOTOCELL
R	RELAY
S	SPEAKER, CEILING MOUNTED
S	SPEAKER, WALL MOUNTED
TC	TIME CLOCK
VC	VOLUME CONTROL
	BELL
	BUZZER
	PUSHBUTTON
	CEILING MOUNTED CLOCK
	WALL MOUNTED CLOCK – SINGLE OR DOUBLE FACE
	HORN
	TRANSFORMER
ATS	AUTOMATIC TRANSFER SWITCH
	EQUIPMENT CONNECTION, HARD WIRED
D	DURESS ALARM BUTTON
CR	CARD READER
N	DOOR INTERLOCK SWITCH
NC	NURSE CALL, COORDINATE REQUIREMENTS WITH L.V. DESIGNER
C	CODE BUTTON, COORDINATE REQUIREMENTS WITH L.V. DESIGNER
AN	NURSE CALL ABOVE DOOR ANNUNCIATOR COORDINATE REQUIREMENTS WITH L.V DESIGNER
UPS	UNINTERRUPTIBLE POWER SUPPLY (BY OWNER)

LIGHTING

SYMBOL	DESCRIPTION
	INCANDESCENT OR HID FIXTURE, CEILING MOUNTED
	INCANDESCENT OR HID FIXTURE, WALL MOUNTED
	INCANDESCENT OR HID WALL WASH FIXTURE, CEILING MOUNTED CLEAR SIDE INDICATES DIRECTION OF WASH
a	FLUORESCENT FIXTURE, CEILING OR WALL MOUNTED, SUBSCRIPT INDICATES ASSOCIATED SWITCHING
	FIXTURE CONNECTED TO EMERGENCY SYSTEM
	FIXTURE WITH BATTERY PACK
	EXIT LIGHT, SINGLE/DOUBLE FACE CEILING MOUNTED WITH ARROWS AS INDICATED IN DRAWINGS
	EXIT LIGHT, WALL MOUNTED , SINGLE/DOUBLE FACE WITH ARROWS AS INDICATED IN DRAWINGS
	EMERGENCY LIGHT, BATTERY TYPE WITH CHARGER
A	SYMBOL IDENTIFYING FIXTURE TYPE. ALL FIXTURES THIS ROOM ARE FIXTURE TYPE INDICATED UNLESS INDIVIDUALLY MARKED
	POLE MOUNTED LUMINAIRE, QUANTITY AS INDICATED
	EXTERIOR FLOOD LIGHT
	TRACK LIGHT – TYPE, LENGTH AND QUANTITY OF FIXTURES AS SCHEDULED.
OS OS	OCCUPANCY SENSOR – WALL AND CEILING MOUNT RESPECTIVELY
W	'EQUIPMENT IN USE' WARNING LIGHT

PANELS AND RELATED ITEMS

SYMBOL	DESCRIPTION
	PANELBOARD (SEE SCHEDULE)
SWBD	SWITCHBOARD OR DISTRIBUTION BOARD
MCC	MOTOR CONTROL CENTER
PB	PULL BOX
TB	PLYWOOD TELEPHONE BACKBOARD

RACEWAYS

SYMBOL	DESCRIPTION
	CONDUIT CONCEALED IN WALL OR CEILING WITH ONE PHASE, NEUTRAL AND GROUND CONDUCTOR UNLESS OTHERWISE NOTED
	CONDUIT UNDER FLOOR OR CAST IN STRUCTURE WITH ONE PHASE, NEUTRAL AND GROUND CONDUCTOR UNLESS OTHERWISE NOTED
	CONDUIT EXPOSED WITH ONE PHASE, NEUTRAL AND GROUND CONDUCTOR UNLESS OTHERWISE NOTED
	SWITCH LEG
PIA–2,4,6	BRANCH CIRCUIT HOMERUN SUBSCRIPT INDICATES PANEL AND BREAKER POSITION
	MULTI–OUTLET ASSEMBLY
T	TELEPHONE
	BUS DUCT WITH TAKE OFF DEVICE

OUTLET DEVICES

SYMBOL	DESCRIPTION
L	SIMPLEX TWIST–LOCK RECEPTACLE NEMA L5–20
	SIMPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20
	DUPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20
	DUPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20 INSTALLED AT 48" AFF OR 4" ABOVE COUNTER TOP
	ISOLATED GROUND, DUPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20
GFI WP	DUPLEX RECEPTACLE GFI=GROUND FAULT INTERRUPTING 20A 125V 3 W NEMA 5–20 WP = NEMA 3R WHILE IN USE
	QUADRAPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20
	QUADRAPLEX RECEPTACLE – 20A, 120V 3W NEMA 5–20 INSTALLED AT 48" AFF OR 4" ABOVE COUNTER TOP
E	DUPLEX RECEPTACLE, HOSPITAL GRADE, RED, WITH RED PLATE CONNECTED TO ESSENTIAL ELECTRICAL SYSTEM.
X	FLOOR OUTLET DEVICE, SINGLE SERVICE , POWER . SUBSCRIPT INDICATES TYPE. SEE SCHEDULES AND SPECIFICATIONS.
X	FLOOR OUTLET DEVICE, MULITPLE SERVICE, POWER AND INFORMATION SYSTEM. SUBSCRIPT INDICATES TYPE. SEE SCHEDULES AND SPECIFICATIONS.
X	FLOOR OUTLET DEVICE, INFORMATION SYSTEM SUBSCRIPT INDICATES TYPE. SEE SCHEDULES AND SPECIFICATIONS.
	TELEPHONE OUTLET 15" AFF (SUBSCRIPT W=WALL PHONE AT 54" AFF)
	INFORMATION SYSTEM OUTLET/BACKBOX. SEE SPECIFICATIONS
	COMBINATION TELEPHONE AND DATA OUTLET – 15" AFF UON
	CABLE TELEVISION OUTLET – 15" AFF UON
AV	A/V OUTLET FOR AUDIO/VIDEO DEVICES
TV	TV OUTLET

SWITCH DEVICES

SYMBOL	DESCRIPTION
S	SINGLE POLE SWITCH
$S_{(2)\ (3)\ (4)}$	SWITCH – DOUBLE POLE, 3–WAY OR 4 WAY
$S_{(K)\ (P)\ (WP)}$	KEY OPERATED SWITCH
S_P	SWITCH WITH PILOT LIGHT IN HANDLE (ON LIGHTED UNLESS OTHERWISE NOTED)
S_{WP}	WEATHERPROOF SWITCH
S_M	MANUAL MOTOR STARTER W/ THERMAL OVERLOAD SIZED FOR MOTOR
$S_{D(\ )}$	INCANDESCENT DIMMER SWITCH WATTAGE RATING AS SHOWN IN ( ) [illegible] 1=1000, 5=1500, 2–2000
$S_{F(\ )}$	FLUORESCENT DIMMER SWITCH, NUMBER OF LAMPS AS SHOWN IN ( )
	COMBINATION SWITCH AND OCCUPANCY SENSOR
	EXPLOSION PROOF SWITCH
S_D	DOOR SWITCH
S_T	TIMER SWITCH
S_{OS}	OCC SENSOR WALL SWITCH
	DIMMING OCC SENSOR WALL SWITCH
	DIMMING WALL SWITCH

FIRE ALARM

SYMBOL	DESCRIPTION
FACP	FIRE ALARM CONTROL PANEL
RCC	REMOTE COMMAND CENTER
F	MANUAL PULL STATION 48" AFF
SD	SMOKE DETECTOR
SD	SMOKE DETECTOR, DUCT MOUNTED
TA	TEST SWITCH/REMOTE INDICATOR
PS	FIRE SPRINKLER PRESSURE SWITCH

FIRE ALARM (CON'T)

SYMBOL	DESCRIPTION
H	HEAT DETECTOR
FS	FLOW SWITCH
TS	TAMPER SWITCH
AV 30 / AV 30	AUDIO/VISUAL NOTIFICATION APPLIANCE WALL/CEILING MOUNT. SUBSCRIPT INDICATES CANDELA RATING
V 30 / V 30	VISUAL NOTIFICATION APPLIANCE WALL/CEILING MOUNT. SUBSCRIPT INDICATES CANDELA RATING
DH	MAGNETIC DOOR HOLDER
R	RELAY
PJ	FIRE FIGHTERS PHONE JACK
FF	FIRE FIGHTERS TELEPHONE
DC	DOOR CONTACT

ABBREVIATION DESCRIPTION

ABBREVIATION	DESCRIPTION
A	AMPERE(S)
ABV	ABOVE
AC	ABOVE COUNTER
A/C	AIR CONDITIONING
AIC	AMPERE INTERRUPTING CAPACITY
AFF	ABOVE FINISHED FLOOR
AFG	ABOVE FINISHED GRADE
AHU	AIR HANDLING UNIT
ATS	AUTOMATIC TRANSFER SWITCH
BFF	BELOW FINISHED FLOOR
BFG	BELOW FINISHED GRADE
BLDG	BUILDING
C	CONDUIT
CB	CIRCUIT BREAKER
CCTV	CLOSE CIRCUIT TELEVISION
CKT	CIRCUIT
COND	CONDUCTOR
CPU	CENTRAL PROCESSING UNIT
DIA	DIAMETER
DIST	DISTRIBUTION
DN	DOWN
DWGS	DRAWINGS
EC	EMPTY CONDUIT
EDF	ELECTRIC DRINKING FOUNTAIN
EF	EXHAUST FAN
EMT	ELEC. METALLIC TUBING
EQMT	EQUIPMENT
EWC	ELECTRIC WATER COOLER
EXH	EXHAUST
EXP	EXPLOSION PROOF
EXTG	EXISTING
F/A	FIRE ALARM
FC	FOOTCANDLES
FCU	FAN COIL UNIT
FLEX	FLEXIBLE METAL CONDUIT
FLUOR	FLUORESCENT
FN	FULL NEUTRAL
FT	FEET, FOOT
GALV	GALVANIZED
GFCI	GROUND FAULT CIRCUIT INTERRUPTER
GFI	GROUND FAULT INTERRUPTER
GND	GROUND
HID	HIGH INTENSITY DISCHARGE
HP	HORSEPOWER
HOA	HAND OFF AUTOMATIC
HPS	HIGH PRESSURE SODIUM
HVAC	HEATING/VENTILATING/AIR CONDITIONING
HZ	HERTZ

ABBREVIATION DESCRIPTION

ABBREVIATION	DESCRIPTION
IC	INTERCOM
ID	INSIDE DIAMETER
IMC	INTERMEDIATE STEEL CONDUIT
IN	INCHES
INC	INCANDESCENT
IG	ISOLATED GROUND
JB	JUNCTION BOX
KV	KILOVOLT
KVA	KILOVOLT AMPERE
KVAC	KILOVOLT AMPERE CAPACITIVE
KVAR	KILOVOLT AMPERE REACTIVE
KW	KILOWATT
KWH	KILOWATT HOUR
LB	POUND
LPS	LOW PRESSURE SODIUM
M	MANHOLE
MAX	MAXIMUM
MCC	MOTOR CONTROL CENTER
MECH	MECHANICAL
MH	MOUNTING HEIGHT
MIN	MINIMUM
MLO	MAIN LUGS ONLY
MTG	MOUNTING
MV	MERCURY VAPOR
NA	NOT APPLICABLE
NC	NORMALLY CLOSED
NF	NON FUSED
NO	NORMALLY OPEN
OC	ON CENTER
OFCI	OWNER FURNISHED CONTRACTOR INSTALLED
OH	OVERHEAD
P	POLE
PA	PUBLIC ADDRESS
PB	PUSHBUTTON
PBX	PRIVATE BUILDING EXCHANGE
PC	PULL CHAIN
PEC	PHOTO CELL
PNL	PANELBOARD
PSI	POUNDS PER SQUARE INCH
PVC	POLY VINYL CHLORIDE CONDUIT
PWR	POWER
RMC	RIGID METAL CONDUIT
SC	SPLIT CIRCUIT
SN	SOLID NEUTRAL
SQFT, Ø	SQUARE FOOT
SW	SWITCH
SWBD	SWITCHBOARD
TC	TIME CLOCK
TELE	TELEPHONE
TSTAT	THERMOSTAT
TV	TELEVISION
UH	UNIT HEATER
UON	UNLESS OTHERWISE NOTED
V	VOLT(S)
VP	VAPOR PROOF
W	WIRE
WP	WEATHERPROOF
XFMR	TRANSFORMER
XPD	TRANSPONDER
Z	IMPEDANCE
1P	ONE POLE
2P	TWO POLE
3P	THREE POLE
Ø	PHASE

GENERAL NOTES – ELECTRICAL

1. AS PART OF THIS CONTRACT, THE CONTRACTOR SHALL BE RESPONSIBLE FOR THE EXAMINATION AND ACCEPTANCE OF THESE DETAILED NOTES. SUCH OMISSIONS WHICH THE CONTRACTOR HAS FAILED TO SATISFY, SHALL NOT RELIEVE HIM FROM CARRYING OUT SUCH PORTIONS AS INDICATED BY THE CONSTRUCTION DOCUMENTS AND SPECIFICATIONS.
2. PRIOR TO BIDDING THE CONTRACT, REVIEW ALL PERTINENT DRAWINGS AND SPECIFICATIONS. WHERE DISCREPANCIES OCCUR BETWEEN DRAWINGS AND SPECIFICATIONS, THE HIGH[illegible]DES. WHERE ITEMS ARE SHOWN ONLY ON THE CONSTRUCTION DOCUMENTS OR SPECIFICATIONS, THE CONTRACTOR SHALL INTERPRET ITEMS TO BE ON BOTH. IN ALL CASES THE CONTRACTOR SHALL BE RESPONSIBLE FOR IMMEDIATELY NOTIFYING THE ENGINEER FOR INTERPRETATIONS AND CLARIFICATIONS.
3. STUDY AND REVIEW ALL SUPPLEMENT DRAWINGS. THE CONTRACTOR SHALL FURNISH AND INSTALL LABOR, EQUIPMENT AND MATERIALS AS SPECIFIED ON ALL RELATED DOCUMENTS.
4. IT SHALL BE THE RESPONSIBILITY OF THE CONTRACTOR TO COORDINATE THE SCOPE OF WORK WITH THE OWNER'S REPRESENTATIVE REGARDING THE PROVISIONS AND INSTALLATION OF ALL SPECIAL SYSTEMS INCLUDING, BUT NOT LIMITED TO: FIRE ALARM, SECURITY AND DATA SYSTEMS ETC. IT SHALL BE PERTINENT TO COORDINATE WITH ALL DISCIPLINES.
5. WORK SHALL COMPLY WITH THE APPLICABLE RULES OF THE NATIONAL ELECTRICAL CODES, ELECTRICAL SAFETY CODE, THE NATIONAL FIRE CODES (PUBLISHED BY THE NATIONAL FIRE PROTECTION [illegible]), THE LOCAL ELECTRICAL CODE AND ORDINANCES, AND THE TERMS AND CONDITIONS OF SERVICES OF THE ELECTRIC UTILITY, AS WELL AS ALL AUTHORITIES HAVING LAWFUL JURISDICTION. NONE OF THE TERMS OR PROVISIONS OF THIS SPECIFICATIONS OR CONSTRUCTION DOCUMENTS SHALL BE CONSTRUED AS WAVING ANY OF THE RULES, REGULATIONS, OR REQUIREMENTS OF THESE AUTHORITIES.
6. IT SHALL BE REQUIRED BY THE CONTRACTOR TO VISIT THE PROJECT SITE TO FAMILIARIZE HIMSELF WITH THE CONDITIONS AS THEY EXIST, AND TO CONFIRM LOCATIONS, SIZES AND QUANTITIES OF MATERIALS AND ITEMS TO BE REMOVED OR INSTALLED AS REQUIRED BY THESE CONSTRUCTION DOCUMENTS AND SPECIFICATIONS. ENTERING HIS BID IS A CLEAR INDICATION THAT HE HAS VISITED THE SITE AND PROJECT AREA AND ACCEPTS THE EXISTING CONDITIONS AND HIS WILLINGNESS TO COMPLY WITH THE DESIGN INTENT. ANY ADJUSTMENTS TO THE PROJECT DURING CONSTRUCTION DUE TO SITE OR PROJECT AREA CONDITIONS WILL BE AT NO CHARGE TO THIS CONTRACT.
7. THE CONTRACTOR SHALL BE RESPONSIBLE FOR KEEPING THE AREA WHERE HE IS WORKING, THE EQUIPMENT STORAGE FREE OF TRASH, CUTTINGS, STRIPPINGS, AND DISCARDED ITEMS OF THIS NATURE.
8. IN ALL AREAS COORDINATE BETWEEN THE ELECTRICAL, MECHANICAL AND PLUMBING TRADES. PROVIDE CLEARANCES IN CEILING SPACES, BETWEEN RECESSED LIGHTING FIXTURES AND THERMAL INSULATION OR COMBUSTIBLE MATERIALS; PIPING, ETC. REFERENCE N.E.C. 410–65 & 66.
9. MECHANICAL AND PLUMBING EQUIPMENT SHOWN ON THE ELECTRICAL PLANS ARE SIZED AS DESIGNED. BREAKERS, DISCONNECT SWITCHES, STARTERS, DEVICES, CONDUIT, CONDUCTORS, BRANCH CIRCUITRY, SHALL BE MODIFIED AS SUBMITTED AND APPROVED FOR INSTALLATION BY THE MECHANICAL ENGINEER. PROVIDE BRANCH CIRCUITRY AS REQUIRED BY THE EQUIPMENT'S NAMEPLATE DATA.
10. LIGHTING IN MECHANICAL OR EQUIPMENT ROOMS SHALL BE INSTALLED AND ADJUSTED IN THE FIELD FOLLOWING THE INSTALLATION OF ELECTRICAL, PLUMBING AND MECHANICAL EQUIPMENT. PROVIDE UNIFORM LIGHTING DISTRIBUTION WITHIN THE ROOM AS GENERALLY OUTLINED ON THE DRAWINGS.
11. CONFIRM COMPATIBILITY BETWEEN CEILING TYPES AS DEFINED ON THE ARCHITECTURAL ROOM FINISH SCHEDULE AND LIGHT FIXTURE TRIM AS SPECIFIED ON THE LIGHTING FIXTURE SCHEDULE. COORDINATE PRIOR TO SUBMITTING. LIST CONFLICTS WHICH OCCUR, NO CHANGE OR DEVIATION SHALL BE ACCEPTED UNLESS APPROVED OTHERWISE BY THE ENGINEER OR THE ARCHITECT.
12. REFERENCE THE ARCHITECTURAL REFLECTED CEILING PLAN FOR EXACT LOCATIONS OF LIGHT FIXTURES, OR ANY OTHER CEILING MOUNTED DEVICES.
13. RELOCATE TO THE PROPER SIDE OF THE DOOR ANY SWITCH, RECEPTACLE OR DEVICE BEING AFFECTED BY THE CHANGE IN DIRECTION OF ANY DOOR SWINGS AS SHOWN ON THE ARCHITECTURAL FLOOR PLANS, OR AS IT OCCURS DURING CONSTRUCTION.
14. ALL LIGHT CONTROL SWITCHES SHALL BE INSTALLED 6" CENTERED FROM THE DOOR JAM TO THE FIRST SWITCH.
15. VERIFY THE LIGHTING FIXTURE SCHEDULE FOR CONFLICTS WITHIN MANUFACTURERS CATALOGUE NUMBERS AND DESCRIPTIONS, VOLTAGES ETC. WHICH ARE NOTED. NOTIFY THE ENGINEER WHERE CONFLICTS OCCUR AND ASK FOR CLARIFICATION.
16. CONTRACTOR SHALL INSTALL RECESSED LIGHT FIXTURES SUCH THAT FIRE RATING VALUES ARE MAINTAINED ACCORDING TO AHJ IN AREAS WHERE FIRE RATED CEILINGS EXIST.
17. DOWNLIGHTS SHALL BE INSTALLED CENTERED ON THE CEILING GRIDS OR AS DIMENSIONED ON THE LIGHTING FLOOR PLANS. LIGHT LEAKS ENCOMPASSING FIXTURE TRIMS SHALL NOT BE ACCEPTED.
18. ALL EXIT LIGHTS SHALL BE UNSWITCHED AND CONNECTED TO THE NEAREST LIFE SAFETY CIRCUIT AS SHOWN, UNLESS NOTED OTHERWISE.
19. ALL BRANCH CIRCUITS SHALL CONTAIN A GROUND CONDUCTOR PER ARTICLE 250 OF THE 2014 NATIONAL ELECTRICAL CODE.
20. EACH REMOTE MOUNTED FRACTIONAL MOTOR SHALL BE PROVIDED WITH A RECEPTACLE AND PLUG, OR MANUAL MOTOR STARTER/DISCONNECT SWITCH SIZED AND INSTALLED ACCORDING TO THE FLA. EACH MOTOR SHALL BE COMPATIBLE WITH TYPE CONSTRUCTION AND N.E.C.
21. PROVIDE AND INSTALL STARTERS FOR EACH MOTOR AND SIZE AS REQUIRED BY N.E.C. COORDINATE WITH THE MECHANICAL CONTRACTOR AND PROVIDE ALL CONTROL STARTERS AND CONTROL SWITCHES PRIOR TO ROUGH–IN. THE MECHANICAL SCHEDULE INDICATES THE CONTROLS WHICH THE DIVISION 15 WILL PROVIDE.
22. WIRING MEANS AND METHODS ABOVE INACCESSIBLE CEILINGS OR IN AREAS WHERE ACCESS IS LIMITED SHALL CONFORM TO ALL APPLICABLE CODES AND THE AHJ. LOCATION OF JUNCTION BOXES ABOVE INACCESSIBLE CEILINGS SHALL NOT BE APPROVED. THE CONTRACTOR SHALL CONFIRM CEILING TYPES IN ALL AREAS PRIOR TO INSTALLATION.
23. ALL DUPLEX RECEPTACLES LOCATED WITHIN 4'–0" OF ANY WET AREAS, OR SUBJECT TO MOISTURE SHALL BE GROUND FAULT CIRCUIT INTERRUPT (GFCI).
24. ALL DUPLEX RECEPTACLES LOCATED INSIDE A MECHANICAL, ELECTRICAL AND STORAGE ROOM SHALL BE MOUNTED 18" ABOVE FINISH FLOOR.
25. ALL SPECIAL PURPOSE OUTLETS, DUPLEX RECEPTACLES OR DEVICES LOCATED ON THE EXTERIOR OF THE BUILDING SHALL BE GFI TYPE, AND INSTALLED IN A WEATHERPROOF TYPE FS BOX WITH WEATHERPROOF COVER.
26. DUPLEX RECEPTACLES ABOVE COUNTERS, OR CASE WORK SHALL BE MOUNTED 6" (HORIZONTALLY) ABOVE THE TOP OF THE BACK SPLASH, UNLESS OTHERWISE NOTED. SHOULD BACKSPLASH EXIST VERIFY HEIGHT AS REQUIRED. OUTLETS SHALL NOT BE MOUNTED ON TO THE BACKSPLASH.
27. SCOPE OF FIRE ALARM WORK INCLUDES INSTALLATION OF FIRE ALARM DEVICES THROUGHOUT TENANT SPACE. ALL DESIGN AND INSTALLATION WORK SHALL BE PERFORMED BY A LICENSED FIRE ALARM CONTRACTOR.
28. MINIMUM WIRE GAUGE ON ALL POWER AND LIGHTING BRANCH CIRCUITS SHALL BE #12 AWG COPPER.
29. BRANCH CIRCUIT WIRING SERVED FROM THE EMERGENCY ELECTRICAL SYSTEM SHALL BE IN METALLIC RACEWAYS AS REQUIRED BY 2014 NEC ART. 517.12.
30. ELECTRICAL RECEPTACLES AND LIGHT SWITCH PLATES SHALL BE LABELED WITH THE PANELBOARD AND CIRCUIT NUMBER SERVING THEM.

STATE OF LOUISIANA
CHARLES CULBERTSON, JR
License No. 40493
PROFESSIONAL ENGINEER
11/22/17

HOFFPAUIR STUDIO
HOFFPAUIR STUDIO
16[illegible] LOBDELL AVENUE, SUITE H1
BATON ROUGE, LOUISIANA 70809
[illegible].7406

IMEG
12710 RESEARCH BLVD
SUITE 355
AUSTIN, TX
78759
PH: 512.416.1654
FAX: 512.416.7547
www.imegcorp.com
IMEG PROJECT #: 00161308

Prairiville General Hospital
37358 Market Place Dr.
Prairieville, LA 70769

Shawn Kaarlsen and Associates
in association with
Robert C. Murray AIA
Architecture & Construction Services
13438 Bandera Rd., Ste. 202
Helotes, TX. 78023
Ph: 210.695.5716
Fx: 210.695.5714
Email: SKA@skaarch.com
SKA Inc.

Project No.	1607050
Drawn:	TB
Checked:	-
Date:	November 22, 2017

No.	Description	Date

CONSTRUCTION REISSUE SET

E000
ELECTRICAL SYMBOLS

Order Plans @ www.LDIline.com