



REMODEL STORE

OLD NAVY

CAP INC.
STORE DEVELOPMENT
FOLSOM STREET
FRANCO, CA 94105

REPS. I.D. 0000131847
STORE NUMBER: 5724
STORE LOCATION: BUCKHEAD STATION
1 BUCKHEAD LOOP NE
ATLANTA, GA 30326

DESIGN TYPE: P3
GENERATION: 18012
PROTOTYPE DATE: 08/31/17
OPENING: 2018

CONSULTANT INFO.
M-Engineering
750 Brookside Blvd.
Westerville, Ohio 43081
phone: 614-939-4039
fax: 614-939-2222
www.m-engineering.us.com

PROFESSIONAL STAMP:
brr
ARCHITECT OF RECORD:
BOYD W. BAU
6700 ANTIOCH PLAZA
SUITE 300
MEMPHIS, TN 38124
www.brrarch.com
TEL: 913-263-9095
FAX: 913-262-9044

ISSUE TYPE:
BID/PERMIT 01/05/18

REVISIONS:

DRAWN BY: AMH
AVE JOB NUMBER: 65013029/1742070

TITLE SHEET:
POWER PLAN

SHEET NUMBER:

E1-0

POWER CODED NOTES SCHEDULE							
CODED NOTE	MARK	TYPE	MANUFACTURER/MODEL	COLOR	MOUNTING HEIGHT	USE	NOTES
200	SF	Duplex	See Specifications	White	12" above glass	General	Install vertically on vertical face of storefront
202	W	Duplex - UNO	Steel box 52151 SVI	White	18" AFF UNO	General	
203		J-Box	4" sq X 1-1/2" deep	Grey	+ 40" See Arch drawings	Hand Dryer	
209		Duplex	See Specifications	White	6" above boothset	Marketing	
210		J-Box	4" sq X 1-1/2" deep	Grey	44" AFF	ADT keypad	
215		Duplex	See Specifications	White	+27" See Arch dwgs 8/A7-0	Fitting room mirrors	From ceiling route 3/4" conduit directly to back side of fitting room mirror. Then flexible conduit (hidden) to each following mirror. Install one duplex outlet per mirror. Refer to architectural details.
217		J-Box	Provide J-box for manufacturer provided USB outlets in furniture. Coordinate connection requirements prior to rough-in.				
225		DUPLEX	Hubbell #B2414 with #SA3825 cover	Aluminum	Floorbox	Cooler	Route conduit to receptacle in back left hand corner of adjacent cabinet. Provide access through toe kick.
226			Power pole provided by cashwrap vendor. Route conduit to new beverage cooler located as shown. Minimize size of trench as required to only fit the required conduit size and back fill requirements.				
229		Duplex	See Specifications	White	at deck	LP monitor	
230		J-Box	4" sq X 1-1/2" deep	Grey	see Arch drawings	Panic hardware; EM door	
306		GFI	See Specifications	White	6" below ceiling	Water heater	
308			Fire alarm devices by fire alarm contractor at GC expense. Connect to landlord fire alarm panel. Coordinate requirements with landlord prior to bid.				
310			Dedicated fire alarm phone line located at the telephone board. Connect to fire alarm control panel.				

POWER PLAN

SCALE:
1/8" = 1'-0"

Order Plans @