GENERAL LIGHTING DEMOLITION NOTES:

1. THIS DRAWING INDICATES INTENT ONLY. LOCATION OF ELECTRICAL EQUIPMENT WAS TAKEN FROM RECORD DOCUMENTS AND MAY NOT BE ACCURATE. COORDINATE WITH KROGER PROJECT MANAGER TO CONFIRM LOCATIONS OF ALL EQUIPMENT BEING REMOVED OR RELOCATED. CONTRACTOR SHALL FIELD VERIFY ALL ELECTRICAL EQUIPMENT LOCATIONS.

2. COORDINATE DEMOLITION PHASING WITH KROGER PROJECT MANAGER TO AVOID CONFLICTS WITH STORE OPERATIONS.

3. MAINTAIN OPERATION OF ALL EXISTING ELECTRICAL SYSTEMS AND SUBSYSTEMS TO REMAIN.

4. COORDINATE STORAGE, REUSE, OR DISPOSAL OF ALL REMOVED LIGHTING FIXTURES WITH KROGER PROJECT MANAGER.

5. ELECTRICAL CONTRACTOR SHALL COORDINATE ALL TEMPORARY POWER WITH CONSTRUCTION PHASING.

6. ALL LIGHTING FIXTURES BEING DEMOLISHED AND NOT REUSED SHALL BE RETURNED TO KROGER R&S.

7. ALL LIGHTING FIXTURES NOT SHOWN ARE EXISTING TO REMAIN. REFER TO NEW LIGHTING PLAN FOR ADDITIONAL INFORMATION.

GENERAL LIGHTING NOTES:

1. ALL FLUORESCENT LAMPS TO BE 3500° K UNLESS NOTED OTHERWISE.

2. MULTIWIRE BRANCH CIRCUIT SYMBOLS ARE SHOWN WITH MAXIMUM OF THREE CIRCUITS PER INDIVIDUAL HOMERUN. CONTRACTOR SHALL PROVIDE AN INDIVIDUAL NEUTRAL PER CIRCUIT OR FURNISH AND INSTALL CIRCUIT BREAKER HANDLE TIES AS REQUIRED BY NEC ARTICLE 210, PARAGRAPH 210.4(B).

3. REUSE EXISTING CONDUITS AND WIRING IF POSSIBLE. ELECTRICAL CONTRACTOR SHALL PERFORM MAINTENANCE ON ALL EXISTING ELECTRICAL ITEMS TO RESTORE THEM BACK TO THEIR PROPER OPERATING CONDITION AND REPLACE IF NECESSARY. CLEAN AND RELAMP ALL EXISTING LIGHT FIXTURES. REPLACE ALL DAMAGED FIXTURES OR PARTS OF THE FIXTURES WITH NEW TO MATCH EXISTING.

4. CONTRACTOR SHALL BE RESPONSIBLE FOR REMOVING ALL ABANDONED ELECTRICAL CONDUIT, WIRE, ETC. AFTER COMPLETE INSTALLATION OF NEW EQUIPMENT.

5. CONTRACTOR SHALL MAINTAIN ILLUMINATION OF STORE DURING REMODEL. COORDINATE PHASING OF LIGHTING REMOVAL IN SALES AREA WITH KROGER PROJECT MANAGER.

6. ALL ELECTRICAL EQUIPMENT SHOWN AS EXISTING IS BASED ON AVAILABLE RECORD DOCUMENTS AND MAY NOT BE ACCURATE. CONTRACTOR SHALL VERIFY THIS INFORMATION PRIOR TO BEGINNING WORK.

7. CONTRACTOR SHALL PERFORM A WALK-THRU OF THE SITE TO DETERMINE EXISTING ELECTRICAL CONDITIONS AND INCLUDE THE PRICE OF ANY REPAIRS NEEDED IN BASE BID.

8. REUSE EXISTING CIRCUITS & CONDUITS MADE AVAILABLE DURING CONSTRUCTION WHERE APPLICABLE. LABEL ALL CIRCUITS NOT REUSED AS SPARE IN PANELBOARD SCHEDULE.

9. ALL LIGHTING FIXTURES THAT ARE NOT LABELED AS EXISTING TO REMAIN, ELECTRICAL CONTRACTOR SHALL PERFORM MAINTENANCE ON ALL EXISTING ELECTRICAL ITEMS WITHIN PROJECT SCOPE, AS COORDINATED WITH KROGER PROJECT MANAGER, AND RESTORE THEM BACK TO THEIR PROPER OPERATING CONDITION AND REPLACE IF NECESSARY. CLEAN AND RELAMP ALL EXISTING LIGHT FIXTURES. REPLACE ALL DAMAGED FIXTURES OR PARTS OF THE FIXTURES WITH NEW TO MATCH EXISTING.

10. ALL ELECTRICAL CONDUITS IN THE SALES AREA DESCENDING FROM ROOF FRAMING TO EITHER LOW WALLS OR EQUIPMENT SHOULD BE COORDINATED AND GROUPED TOGETHER WITH OTHER MECHANICAL PIPES.

GENERAL POWER DEMOLITION NOTES:

1. THIS DRAWING INDICATES INTENT ONLY. LOCATION OF ELECTRICAL EQUIPMENT WAS TAKEN FROM RECORD DOCUMENTS AND MAY NOT BE ACCURATE. COORDINATE WITH KROGER PROJECT MANAGER TO CONFIRM LOCATIONS OF ALL EQUIPMENT BEING REMOVED OR RELOCATED. CONTRACTOR SHALL BE RESPONSIBLE FOR ANY AND ALL DAMAGES THAT MAY OCCUR DUE TO THE CONTRACTORS FAILURE TO LOCATE AND PRESERVE EXISTING ELECTRICAL SYSTEMS.

2. COORDINATE DEMOLITION PHASING WITH KROGER PROJECT MANAGER TO AVOID CONFLICTS WITH STORE OPERATIONS.

3. MAINTAIN OPERATION OF ALL EXISTING ELECTRICAL SYSTEMS AND SUBSYSTEMS TO REMAIN. RESTORE ANY ELECTRICAL SYSTEMS TO REMAIN DISRUPTED BY DEMOLITION TO PROPER WORKING ORDER.

4. THE ELECTRICAL CONTRACTOR SHALL REMOVE ALL ELECTRICAL WORK AS REQUIRED TO CLEAR AREAS OF NEW CONSTRUCTION. ANY ELECTRICAL CONDUIT, JUNCTION BOXES, WIRING, ETC. NOT TO BE REUSED MAY BE ABANDONED WHERE CONCEALED AND MUST BE REMOVED WHERE EXPOSED. PROVIDE BLANK COVERS FOR OUTLETS. ANY ABANDONED CONDUIT STUB-UPS SHALL BE CUT INTO SURFACE AND PATCHED.

5. IF AN EXISTING RACEWAY NOT TO BE REUSED INTERFERES WITH NEW WORK, REMOVE BACK TO NEAREST JUNCTION BOX AND SHALL BE INCLUDED IN BOTH UNITS.

6. MAINTAIN CONTINUITY OF BRANCH CIRCUITS SERVING MULTIPLE ITEMS WHERE ONE OR MORE ITEMS IS REMOVED. REMOVE CONDUITS AND WIRING FOR REMOVED ITEMS AS POSSIBLE.

7. CONTRACTOR SHALL REMOVE ALL EQUIPMENT NOT BEING REUSED OR NOT NECESSARY FOR PROJECT COMPLETION FOLLOWING PROPER LEGAL PROCEDURES.

8. IF BRANCH CIRCUIT WIRING THAT IS TO REMAIN IS DAMAGED DURING DEMOLITION OR INSTALLATION OF NEW OR RELOCATED EQUIPMENT, THE CONTRACTOR SHALL REPLACE THE WIRING WITH NEW WIRING OF THE SAME SIZE AND TYPE AT NO COST TO THE OWNER.

9. REPLACE ALL EXISTING COVER PLATES AND WIRING DEVICES WITHIN THE CONSTRUCTION AREA WITH NEW MATERIALS MEETING THE REQUIREMENTS OF THE CONTRACT.

10. PROVIDE NEW, TYPED PANELBOARD SCHEDULES INDICATING SPARES MADE AVAILABLE AND NEW LOADS.

11. ELECTRICAL CONTRACTOR SHALL COORDINATE ALL TEMPORARY POWER WITH CONSTRUCTION PHASING.

GENERAL POWER NOTES:

1.IN GENERAL, ELECTRIC PANELS SHALL CONTAIN 20 AMP CIRCUIT BREAKERS, WITH A MINIMUM OF THREE SPARE BREAKERS PER PANEL. THE ELECTRICAL LOAD ON A 120-VOLT, 20AMP. CIRCUITS SHALL NOT EXCEED 1800 WATTS.

2.WHERE MORE THAN ONE (1) ELECTRICAL LOAD IS DESIGNATED AT ANY OUTLET, PROVIDE A SEPARATE CIRCUIT FROM THE ELECTRIC PANEL FOR EACH LOAD. CIRCUIT LOADING LIMITED TO 1800 WATTS, UNLESS OTHERWISE NOTED. LOAD INDICATED FOR CONVENIENCE OUTLETS, SHELVING UNIT/APPLIANCE/DISPLAYS MAY BE COMBINED INTO ONE CIRCUIT PROVIDED THE 1800 WATT LOAD LIMITATION IS HONORED.

3.THE ELECTRICAL CONTRACTOR SHALL REVIEW THE UNDERSLAB CONDUIT AND RACEWAY LAYOUT WITH THE KROGER PROJECT MANAGER FOR FINAL APPROVAL PRIOR TO SLAB PLACEMENT.

4.ALL OUTLETS IN MEAT PREPARATION ROOM, PRODUCE PREP, SALAD BAR PREP ROOM, AND SEAFOOD DEPARTMENT SHALL BE GF.C.I. WITH WEATHERPROOF COVER. SEE ELR-ED-1 FOR FLOOR OUTLET DETAIL.

5.RECEPTACLES IN DELI BAKERY AND FLORAL DEPARTMENTS SHALL BE G.F.C.I. WITHOUT COVERS. SEE ELR-ED-1 FOR FLOOR OUTLET DETAIL.

6.ALL BRANCH CIRCUIT WIRING SHALL BE MINIMUM #12AWG/THWN. FOR RUNS EXCEEDING 50 FEET, WIRING SHALL BE MINIMUM #10AWG/THWN. CONTRACTOR SHALL SIZE WIRING IN ACCORDANCE WITH NEC ART. 210-19, 215-2, 310-15, & 410 FOR VOLTAGE DROP, AND NEC TABLE 8310-11 FOR DERATING FACTORS. WIRE SIZES SHOWN ON PLANS ARE MINIMUM. CONDUIT SIZE SHALL BE MINIMUM 3/4". CONTRACTOR SHALL SIZE ALL CONDUIT AND JUNCTION BOXES BASED ON THW CONDUCTOR INSULATION IN ACCORDANCE WITH NEC. ALSO REFER TO SECTION 26 05 19 OF THE SPECIFICATIONS AND NOTE #19 BELOW.

7.BRANCH CIRCUITS ARE INDICATED AS ONE CIRCUIT HOME RUNS WITH INDIVIDUAL NEUTRALS. CONTRACTOR MAY GROUP SINGLE POLE BRANCH CIRCUITS IN MULTIPLE CIRCUIT HOME RUNS WITH A SHARED NEUTRAL (3 CIRCUITS MAXIMUM). SUCH GROUPED CIRCUITS ARE THEN MULTIWIRE BRANCH CIRCUITS. INSTALLATION OF MULTIWIRE BRANCH CIRCUITS SHALL COMPLY WITH ALL 2014 N.E.C. MULTIWIRE BRANCH CIRCUIT REQUIREMENTS PER N.E.C. ARTICLE 210, PARAGRAPH 210.4(B).

8.ALL ELECTRICAL CONDUITS IN THE SALES AREA DESCENDING FROM ROOF FRAMING TO EITHER LOW WALLS OR EQUIPMENT SHOULD BE COORDINATED AND GROUPED TOGETHER WITH OTHER MECHANICAL PIPES.

9.ALL ELECTRICAL EQUIPMENT SHOWN AS EXISTING IS BASED ON AVAILABLE RECORD DOCUMENTS AND MANY NOT BE ACCURATE. CONTRACTOR SHALL VERIFY THIS INFORMATION PRIOR TO BEGINNING WORK.

10. CONTRACTOR SHALL PERFORM A WALK-THRU OF THE SITE TO DETERMINE EXISTING CONDITIONS AND INCLUDE THE PRICE OF ANY REPAIRS NEEDED IN BASE BID.

11. CIRCUIT DESIGNATIONS ARE SHOWN FOR INTENT ONLY. CONTRACTOR SHALL VERIFY CIRCUITS ARE AVAILABLE PRIOR TO BEGINNING WORK.

12. REUSE EXISTING CIRCUITS & CONDUITS MADE AVAILABLE DURING CONSTRUCTION WHERE APPLICABLE. LABEL ALL CIRCUITS NOT REUSED AS SPARE IN PANELBOARD SCHEDULE.

13. ELECTRICAL OUTLETS FOR REFRIGERATED ISLAND CASES MUST BE INSTALLED IN A STRAIGHT LINE ALIGNED WITH THE HUB DRAIN. COORDINATE WITH PLUMBING DIMENSIONED PLAN.

14. PROVIDE 10 FEET OF FLEXIBLE CONDUIT WITH STRANDED CONDUCTORS FOR REFRIGERATED CASES SERVED FROM WALL JUNCTION BOXES AND 6 FEET FOR ISLAND AND SERVICE REFRIGERATED CASES FOR CONNECTION TO CASES BY ELECTRICAL FIXTURING INSTALLATION CONTRACTOR.

15. FOR ELECTRICAL FEEDS AT SHELVING LOCATIONS, UNLESS OTHERWISE NOTED, INSTALL RIGID STEEL CONDUIT FROM JUNCTION BOX LOCATED IN THE STRUCTURAL STEEL ABOVE. LOCATE CONDUIT IN CENTER OF SHELVING RUN; PAINT CONDUIT TO MATCH COLUMNS. SEE E1SD-1 ON SHEET E5.1.

16. ALL WALL OUTLETS IN FOOD PREP AREAS SHALL BE FLUSH MOUNTED. OUTLETS LOCATED ABOVE STAINLESS STEEL TABLES SHALL BE A MINIMUM OF 46" ABOVE FLOOR. NO SURFACE MOUNTED CONDUITS ALLOWED IN MEAT AND PRODUCE PREP ROOMS.

17. PROVIDE A LOCK ON DEVICE ON THE BREAKER PROTECTING CIRCUITS THAT ARE DEDICATED WITH AN ASTERISK (*).

18. TELE POWER POLES FOR CHECK LANES SHALL BE FURNISHED BY [illegible] AND INSTALLED BY THE CONTRACTORS ELECTRICAL SUBCONTRACTOR. TERMINATE AND LABEL CONDUCTORS IN OUTLET BOX IN JOIST. SEE ESD-62, ESD-62A AND ESD-62B FOR MORE INFORMATION. CONTRACTOR SHALL PROVIDE ANY OTHER TELE-POWER POLE INDICATED ON THE DRAWINGS. SEE KROGER SPECIFICATION SECTION 26 05 33 FOR ADDITIONAL INFORMATION.

ELECTRICAL SYMBOL LEGEND

GENERAL SYMBOL EXPLANATION

	WALL OUTLET - HEIGHT AS INDICATED ON PLAN
	OUTLET INSTALLED IN JOIST SPACE, UNLESS NOTED OTHERWISE
	SURFACE MOUNTED OUTLET
JB	JUNCTION BOX
WP	WEATHERPROOF
CM	CEILING MOUNTED

	ON THE GROUND FLOOR, USE HUBBELL FLUSH FLOOR BOX #PTE1FPDBA'S WITH #CRS50GY 20A DUPLEX RECEPTACLE, FLUSH COVER #S3082/S3925 AND FITTINGS SHALL BE BRASS. ON THE MEZZANINE, USE HUBBELL FIRE-RATED POKE-THROUGH ONE-PIECE UNIT #S1PT4X6BRSJ. POWER AND DATA SHALL BE INCLUDED IN BOTH UNITS.
	120V., SINGLE RECEPTACLE GROUNDED TYPE, 2'-0" ABOVE FLOOR UNLESS NOTED OTHERWISE.
	120V., DUPLEX RECEPTACLE GROUNDED TYPE, 2'-0" ABOVE FLOOR UNLESS NOTED OTHERWISE.
	120V., DUPLEX RECEPTACLE ISOLATED GROUNDED TYPE, 2'-0" ABOVE FLOOR UNLESS NOTED OTHERWISE.
	120V., DUPLEX RECEPTACLE GFCI TYPE, 2'-0" ABOVE FLOOR UNLESS NOTED OTHERWISE.
	120V. JUNCTION BOX
	JUNCTION BOX AS NOTED ON PLAN
	208V., 3-PHASE JUNCTION BOX. RECEPTACLE #HBL5420 FOR 20A / HBL5430 FOR 30A) WHERE REQUIRED. VERIFY EXACT RECEPTACLE REQUIREMENTS WITH EQUIPMENT.
	120/208V., 3-PHASE JUNCTION BOX. RECEPTACLE (HBL7250 FOR 20A / HBL8330 FOR 30A) WHERE REQUIRED. VERIFY EXACT RECEPTACLE REQUIREMENTS WITH EQUIPMENT.
	208V., 1-PHASE JUNCTION BOX. RECEPTACLE #HBL5462 FOR 20A / HBL9330 FOR 30A) WHERE REQUIRED. VERIFY EXACT RECEPTACLE REQUIREMENTS WITH EQUIPMENT.
	120/208V., 1-PHASE JUNCTION BOX. RECEPTACLE (HBL5410 FOR 20A / HBL9430 FOR 30A) WHERE REQUIRED. VERIFY EXACT RECEPTACLE REQUIREMENTS WITH EQUIPMENT.
	120V., CEILING MOUNTED DUPLEX RECEPTACLE, GROUNDED TYPE. PROVIDE GROUND FAULT PROTECTION WHEN THE CORD TO BE CONNECTED (SERVING THE EQUIPMENT) DOES NOT CONTAIN A GROUND CONDUCTOR.
	120V., QUAD RECEPTACLE GROUNDED TYPE, 2'-0" ABOVE FLOOR UNLESS NOTED OTHERWISE.
	DISCONNECT SWITCH
	COMBINATION SWITCH AND STARTER
[ILS]	MOUNT LIGHT SENSOR INSTALLED ON ROOF FACING NORTH ENSURING SUNLIGHT CANNOT SHINE DIRECTLY INTO THE SENSOR. SENSOR SUPPLIED BY KROGER AND CONNECTED TO EMS SYSTEM BY CONTRACTOR. (Reference ESD-53)
	TELEPHONE/DATA OUTLET. FLUSH MOUNTED IN FINISHED AREAS. COORDINATE COVER CONFIGURATION WITH KROGER PROJECT MANAGER
	SINGLE POLE LIGHT SWITCH (303-WAY, (4/4-WAY, (P)-PILOT LIGHT, (I)MMOTOR RATED
	TIMER SWITCH WITH WARNING FLICKER FEATURE TO SIGNAL END OF "ON" TIME. FIELD ADJUST TO 20 MINUTE OPERATION. COOPER (GREENGATE) TSW-MV.
	3-WAY TIMER SWITCH WARNING FLICKER FEATURE TO SIGNAL END OF "ON" TIME. FIELD ADJUST TO 20 MINUTE OPERATION. COOPER (GREENGATE) TSW-MV.
	OCCUPANCY SWITCH, SINGLE LOAD. WATTSTOPPER CBP-PW-100
	OCCUPANCY SWITCH, DUAL LOAD. WATTSTOPPER CBP-DW-200
	MOMENTARY OVERRIDE SWITCH, COOPER (GREENGATE) MML SWITCH WITH NO LED. AML 1 ONE GANG, 1 SWITCH STAINLESS STEEL SWITCHPLATE AML 116.
	MOTOR CONNECTION BY CONTRACTOR
	CONDUIT CONCEALED UNDER FLOOR SLAB
	CONDUIT EXPOSED
	CONDUIT CONCEALED IN WALL OR CEILING
	CONDUIT EXPOSED
	EXIT LIGHT FIXTURE
	LEVEL SENSOR INSTALLED IN SKYLIGHT AND CONNECTED TO EMS SYSTEM FOR LIGHT DIMMING. MOUNT VERTICAL LOOKING UP INTO SKYLIGHT 12" FROM TWO ADJACENT SIDES OF SKYLIGHT AT SAME LEVEL WITH ROOF DECK. SUPPLIED BY KROGER.
	ONE WAY LIGHTING SENSOR MOUNTED LIGHTING SENSOR WITH SWITCHPACK ABOVE CEILING. CONNECT SENSOR TO SWITCHPACK WITH #16 AWG CLASS 2 CONDUCTORS. WATTSTOPPER DSP-PW WT-1100.
	ONE WAY LIGHTING SENSOR SUSPENDED 12'-6" A.F.F. OR AT CEILING WITH SWITCHPACK MOUNTED AT BAR JOIST. CONNECT SENSOR TO SWITCHPACK WITH #16 CLASS 2 CONDUCTORS. WATTSTOPPER DSP-PW WT-2200.
	TWO WAY LIGHTING SENSOR SUSPENDED 12'-6" A.F.F. OR AT CEILING WITH SWITCHPACK MOUNTED AT BAR JOIST. CONNECT SENSOR TO SWITCHPACK WITH #16 CLASS 2 CONDUCTORS. WATTSTOPPER DSP-PW WT-1100.
	TWO WAY LIGHTING SENSOR SUSPENDED 15'-6" A.F.F. OR AT CEILING WITH SWITCHPACK MOUNTED AT BAR JOIST. CONNECT SENSOR TO SWITCHPACK WITH #16 CLASS 2 CONDUCTORS. WATTSTOPPER DSP-PW WT-2250.
	ONE WAY WIDE ANGLE OCCUPANCY SENSOR. WATTSTOPPER OS P/N FS-705.
	MOTION SENSOR - WET LOCATION OCCUPANCY SENSOR. WATTSTOPPER HB356W HB62W (MODULE WITH LENS).
	MOTION SENSOR - PASSIVE INFRARED OCCUPANCY SENSOR. WATTSTOPPER HB350B-L3 (MODULE WITH LENS).
TS	TEMPERATURE SENSOR FOR REFRIGERATED CASE. SEE REFRIGERATION PLANS FOR MORE INFORMATION.
DT	DEFROST TERMINATION SENSOR FOR REFRIGERATED CASE. SEE REFRIGERATION PLANS FOR MORE INFORMATION.
SS	SUCTION STOP SOLENOID VALVE FOR REFRIGERATED CASE. SEE REFRIGERATION PLANS FOR MORE INFORMATION.

RELOCATED ELECTRICAL EQUIPMENT REQUIREMENTS

NAME	ELECTRICAL REQUIREMENTS
AL.DS650SB(R)	LH CUST. UNLOAD (95" FRONT BELT/65" REAR BE
B27(R)	2-ROLL WRAPPER (NO WINGS)
B447(R)	SERVICE SCALE/UPC PRINTER (TOLEDO)
BS6CD(R)	CAKE DECORATOR W/CDROM IMAGE DISC
B1.00(R)	AIR BRUSH W/COMPRESSOR
C39-4(R)	4' BEAUTY CARE LIGHT VALANCE
C39-4S(R)	4' BEAUTY CARE LIGHT VALANCE (STARTER)
D237(R)	SERVICE SCALE/UPC PRINTER (TOLEDO)
D26(R)	MANUAL SLICER
D11(R)	WRAPPER (TABLE TOP)
DAGD1-HX(R)	12' FIVE-DECK DAIRY CASE
DMHF-4AM(R)	4' MOBILE HOT FOOD
E4(R)	WIFI (AX PRINTER, SCALE, SCANNER)
E150(R)	OFFICE WORK PACKAGE
E17S(R)	CPU WITH ALARM
E387(R)	[illegible]
E387S(R)	[illegible]
E1.00(R)	THINCLIENT MONITOR
G2(R)	[illegible] DOOR REACH-IN [illegible] FOR [illegible] (SELF CONT.)
G2-TBSCF(R)	[illegible] DOOR FROZEN FOOD MERCH. (SELF CONT.)
G3(R)	[illegible] FEE GRINDER
G4(R)	[illegible] BOTTLED BEVERAGE MERCHANDISER
G5(R)	[illegible] CASE - 4' INLINE "SPECIALTY" SECTION
G56(R)	[illegible] CASE - 4' INLINE "READY TO DRINK" SECTION
G95(R)	[illegible] CASES - 4' INLINE "BULK" SECTION
GF38(R)	POS TERMINAL
GE150(R)	FREESTANDING WORKSTATION
GE156(R)	EFT PIN PAD & CREDIT CARD READER
GE5(R)	MICROWAVE
GGDNC6PH(R)	6' NARROW GLASS DOOR GROCERY PROMO (2 DOORS)
GGDNC8H(R)	8' NARROW GLASS DOOR ICE CREAM TEMP GROCERY (3 DOORS)
GGDNC10-H(R)	10' NARROW GLASS DOOR ICE CREAM TEMP GROCERY (4 DOORS)
GGDNC12-H(R)	12' NARROW GLASS DOOR ICE CREAM TEMP GROCERY (5 DOORS)
GM7-4(R)	4' OTC LIGHT VALANCE
GM7-4S(R)	4' OTC LIGHT VALANCE (STARTER)
GM17(R)	4' POWERED MERCHANDISE SECTION (CONTRACTOR SUPPLY)
M11T(R)	SERVICE SCALE/UPC PRINTER (TOLEDO)
MWLTEHX(R)	LOW TEMP WIDE ISLAND MEAT END CASE
MWMTEHX(R)	88W FOR FANS & A.S. HTRS, 1360W (208V, 1PH) FOR ELEC DEF (ROUTE CONDUIT TO MECH CENTER OR PROTOCOL UNIT FOR CONTROL CKT & DEF/ROST WIRING) ON WIDE ISLAND GROCERY CASE END
P21(R)	PRODUCE WRAPPER (3-ROLL) (FLOOR MODEL)
P31(R)	SERVICE SCALE/UPC PRINTER
P31T(R)	120V 1PH / 75AMPS FOR SERVICE SCALE/UPC PRINTER (TOLEDO), MOUNT RCPT 4'-0" AB FL. PROVIDE A 3/4" CONDUIT TO ECR ROOM
PMSC4S(R)	4' MOBILE SELF CONTAINED PRODUCE CASE
R16(R)	PHARMACY LASER PRINTER
R37B(R)	UNDERCOUNTER REFRIGERATOR (BIOMEDICAL)
R42(R)	UPRIGHT REFRIGERATOR/FREEZER
R88V(R)	44 GALLON SHREDDING CONTAINER
RI5(R)	RX IMAGE SCANNER
RPC(R)	
RTP(R)	RX THERMAL PRINTER (BACKTAGS & VIAL LABELS)
S200R3(R)	3 DOOR SEAFOOD STORAGE REFRIGERATOR (REMOTE)
SWLTEHX(R)	88W FOR FANS & A.S. HTRS, 1360W (208V, 1PH) FOR ELEC DEF (ROUTE CONDUIT TO MECH CENTER OR PROTOCOL UNIT FOR CONTROL CKT & DEF/ROST WIRING) ON WIDE ISLAND GROCERY CASE END
T2S(R)	2' OPEN TABLE W/UNDERSHELF
T4S(R)	4' OPEN TABLE W/UNDERSHELF
T6S(R)	6' OPEN TABLE W/UNDERSHELF
T8S(R)	8' OPEN TABLE W/UNDERSHELF

ELECTRICAL EQUIPMENT REQUIREMENTS

NAME	ELECTRICAL REQUIREMENTS
ACLR1-T	120V, 1PH, 720W DEDICATED CIRCUIT W/ ISOLATED GROUND RECEPTACLE FOR USCAN 1 BAG CHECKOUT LANE. ADDITIONAL QUAD OUTLET (85W TOTAL) ON A SEPARATE CIRCUIT FOR EAS DEACTIVATOR.
ACLR4C-T	120V, 1PH, 720W DEDICATED CIRCUIT W/ ISOLATED GROUND RECEPTACLE FOR USCAN CHECKOUT LANE. ADDITIONAL QUAD OUTLET (85W TOTAL) ON A SEPARATE CIRCUIT FOR EAS DEACTIVATOR.
ACLR4C-T	120V, 1PH, 720W DEDICATED CIRCUIT W/ ISOLATED GROUND RECEPTACLE FOR USCAN CHECKOUT LANE. ADDITIONAL QUAD OUTLET (85W TOTAL) ON A SEPARATE CIRCUIT FOR EAS DEACTIVATOR.
ALE69-4	120V, 7.2W, FOR 4 FT LED LIGHT FOR SHELVING SECTION
AUAS	120V, 10A MIN. DEDICATED CIRCUIT FOR ENTERPRISE SELF-CHECKOUT ATTENDANT STATION
B55C	LOCAL
B55SS-2	120V, 720W, 1PH, FOR SELF SERVICE BREAD SLICER
BMDLSHP	72W FOR FANS, 117W FOR LIGHTS ON 6' MIDUP BAKERY CASE
BV6D6NX	60W FOR FANS, 177W FOR LIGHTS ON 6' V.S. BEV. CASE. MOUNT J.B. 1'-6" AB FL
BV9DDNX-HE	120V, 96W FOR FANS, 65W FOR LIGHTS ON 8FT NARROW GLASS DOOR BEVERAGE CASE. MOUNT J.B. 1'-6" AB FL.
BV9DDNX13HE	120V, 144W FOR FANS, 96W FOR LIGHTS ON 13FT NARROW GLASS DOOR BEVERAGE CASE. MOUNT J.B. 1'-6" AB FL.
CH1D6HP	72W FOR FANS, 39W FOR LIGHTS ON 6' SINGLE DECK CHEESE CASE
CH1D12HP	144W FOR FANS, 60W FOR LIGHTS ON 12' SINGLE DECK CHEESE CASE
CH1D9WHP	72W FOR FANS, 24W FOR LIGHTS ON 90 DEGREE OUTSIDE SINGLE DECK CHEESE WEDGE
CID5C2HP-2	120V, 15AMP, 1PH FOR 5' SINGLE DECK MOBILE DELI CASE (SELF-CONTAINED)
D237	120V 1PH 75AMPS FOR SERVICE SCALE/UPC PRINTER (TOLEDO), PROVIDE A 3/4" COND. TO ECR ROOM
D26S	500W, 120V, 1PH, FOR DELI AUTOMATIC SLICER STACKER
E39	120V 1PH 13.0A CKT., 1750W 3'-5" AB FL FOR MICROWAVE OVEN
E41	SEE KROGER A&E STANDARDS FOR WHERE PLUMOLD IS REQUIRED
E45CP	120V, 1 PH, 2400W FOR DISPENSER, 120V, 1 PH, 1800W FOR WATER BOOSTER
E61F	1495W FOR ICE MACHINE FOR FREESTYLE (RI.GO). LOCATED ON DEVICE @ PANEL).
E66B	1750W FOR COFFEE BREWER FOR INSULATED SERVER
E77B	1150W FOR RICE COOKER
E11.5E	2400W (NON-CONTINUOUS) DEDICATED 20A CIRCUIT FOR ENERGY EFFICIENT WRAPPER (TABLE TOP) MOUNT RCPT. 4'-0" AB. FL
E116M	725W FOR MINI WRAPPER (TABLE TOP)
E17-6SC6	1115'F 6 AMPS FOR 6" SELF-CONTAINED PIZZA MAKE-UP TABLE. MOUNT RCPT. 2'-0" AB. FL. (RECEPTACLE TO BE LOCATED ON DEVICE @ PANEL)
E17-6SC8	1115V 10 AMPS FOR 8 C. PIZZA MAKE-UP TABLE. MOUNT RCPT. 2'-0" AB. FL. (RECEPTACLE TO BE LOCATED ON DEVICE @ PANEL)
E182	115V 12/1HP 8.5A FOR CHEESE SHREDDER, MOUNT RCPT 4'-0" AB. FL.
E183	120V 1PH 14AMPS FOR SALES AREA MICROWAVE, MOUNT RCPT 4'-0" AB. FL.
E265D	1700W FOR ICED TEA BREWER (DUAL DILUTION)
E270SC1-2	120V, 240W, 1PH, FOR UNDERCOUNTER REFRIGERATOR
E27.03	1 DUPLEX CONVENIENCE OUTLET AT BASE FOR EVERY 4 LIN. (BEN
E287	208V, 12A (NEMA 6-20) FOR TORTILLA WARMER
E299TV-48	120V, 180W, 1PH, FOR 48" DIGITAL MONITOR FOR DELI MENU BOARD
E33-4R-2	470W, 208V, 1PH, FOR RECESSED ELECTRICAL LOAD PANEL (ROUTE CONDUIT TO MECH CENTER OR PROTOCOL UNIT FOR CONTROL CKT & DEF/ROST WIRING) ON 6' WIDE ISLAND GROCERY CASE (SALAD WITH SOUP 2 NOTE)
E3ADSHE	120V, 70W FOR FANS & A.S. HTRS, 120W FOR LIGHTS ON 6FT GLASS DOOR PRODUCE CASE. MOUNT J.B. 1'-6" AB FL
E3AD312HE	120V, 132W FOR FANS, 144W FOR LIGHTS ON 12FT GLASS DOOR PRODUCE CASE. MOUNT J.B. 1'-6" AB FL
E4WMTEHX	300W FANS & A.S. HTRS, 3200W (208V, 1PH) FOR ELEC. DEF. (ROUTE CONDUIT TO MECH CENTER OR PROTOCOL UNIT FOR CONTROL CKT & DEF/ROST WIRING) ON 8' WIDE ISLAND GROCERY CASE (ICE CREAM TEMP)
E4WMTEHX	300W FANS & A.S. HTRS, 3200W (208V, 1PH) FOR ELEC. DEF. (ROUTE CONDUIT TO MECH CENTER OR PROTOCOL UNIT FOR CONTROL CKT & DEF/ROST WIRING) ON 8' WIDE ISLAND GROCERY CASE (ICE CREAM TEMP)
E5MCS6SS	120V, 330/9W, 1PH FOR 6' MOBILE SELF CONTAINED DELI CASE.
EP8WST6AT	208V, 1PH, 1103W OVERHEAD WARMER, 208V, 1PH, 396W FOR WARMER DRAWER, 208V, 1PH, 1498W FOR DROP-IN WARMER, 120V, 1PH, 1WW FOR CONTROLLER
EPZ5O8AT	208V, 1PH, 1504.5W FOR [illegible] LAMP, 208V, 1PH, 1914W FOR DROP-IN WARMER, 208V, 1PH, 1914W FOR DROP-IN WARMER, 208V, 1PH, 1914W FOR [illegible]
ES12HE	120V, 1PH, 1300W FOR LIGHTS, 1200W AMB FANS, 1200W A/S HTRS, 250W FOR LIGHTS
ES17-4T	18" [illegible] FEET PEDESTALS
ES17V-47	120V, 1PH, 1.5A FOR LED WIDESCREEN (47")
F	12[illegible]0W DEDICATED CIRCUIT FOR POS EQUIPMENT FOR SCO ATTENDANT STATION
F	[illegible]68W, 1PH
F	60W FOR FANS, 177W FOR LIGHTS ON 8' S-DECK NARROW FLORAL CASE
F4[illegible]	75W FOR FANS, 255W FOR LIGHTS ON 12' S-DECK NARROW FLORAL CASE
F41	SEE KROGER A&E STANDARDS FOR WHERE PLUMOLD IS REQUIRED
F47S	2[illegible]0V, 20A DUPLEX OUTLETS & 112W FOR LIGHTS ON FLORAL WORKSTATION
GM[illegible]SC	344W FOR CHECKSTAND REFRIGERATED MERCHANDISER
G101	150W FOR NCM SAMPLING AREA. PROVIDE OUTLET ON SEPARATE CIRCUIT AT BASE OF ADJACENT CASE, FIXTURE, OR COLUMN.
GE1H	115V 30W, 5'-6" AB FL, FOR FLY TRAPPER
GE3HS	120V 4kW FOR BATTERY CHARGER MOUNT OUTLET 2'-0" AB FL FOR ELECTRONIC SHOPPING CART (REAR DRIVE)
GE156	120V 250W ELEC FED FROM RACEWAY FOR EFT PIN PAD & CREDIT CARD READER
GGDNC6PH	130W FOR FANS, 182W FOR A.S. HTRS, 43W FOR LIGHTS, 1400W (208V 1PH) FOR ELEC DEF. (TO PANEL FOR DEF WIRING) ON 6' NARROW GLASS DOOR ICE CREAM TEMP GROCERY CASE
GGDNC8H	185W FOR FANS, 273W FOR A.S. HTRS, 65W FOR LIGHTS, 2100W (208V 1PH) FOR ELEC DEF. (TO PANEL FOR DEF WIRING) ON 8' NARROW GLASS DOOR ICE CREAM TEMP GROCERY CASE.
GGDNC10H	260W FOR FANS, 364W FOR A.S. HTRS, 86W FOR LIGHTS, 2800W (208V 1PH) FOR ELEC DEF. (TO PANEL FOR DEF WIRING) ON 10' NARROW GLASS DOOR ICE CREAM TEMP GROCERY CASE
GGDNC12H	325W FOR FANS, 455W FOR A.S. HTRS, 108W FOR LIGHTS, 3500W (208V 1PH) FOR ELEC DEF. (TO PANEL FOR DEF WIRING) ON 12' NARROW GLASS DOOR ICE CREAM TEMP GROCERY CASE.
GM7