Label	Designation	AMP	Phase		Main	Circuit	Mount.	NEMA	Voltage		STYLE	A.I.C.
H1	EXISTING MAIN PANEL - LEVEL 1	200	3		MLO	42	Surface	3R	277	480	PANELBOARD	65K
	'H1' FROM 'H1'											

Ckt. #	Circuit Description	Wire Size	Trip Amps	Brkr. Pole	Load Type	A Phase Load KW	B Phase Load KW	C Phase Load KW	Load Type	Brkr. Pole	Trip Amps	Wire Size	Circuit Description	Ckt. #
1					H	4.80	4.80		H					2
3	VAV-1.04 - 1ST FLOOR OFFICES	10	20	3	H			4.80	4.80	H	3	25	10	VAV-1.14 - 1ST FLOOR OFFICES	4
5					H					H					6
7					H	4.80	4.80			H					8
9	VAV-1.02 - 1ST FLOOR OFFICES	10	20	3	H			4.80	4.80	H	3	25	10	VAV-1.13 - 1ST FLOOR OFFICES	10
11					H				3.60	3.60	H				12
13	EXISTING - BUILDING SIGN	12	20	1	L	1.00	0.00				L	1	20	EXISTING - 1ST LEVEL	14
15	EXISTING - 1ST LEVEL	12	20	1	L			1.00	0.00		L	1	20	EXISTING - 1ST LEVEL	16
17	EXISTING - 1ST LEVEL	12	20	1	L					4.80	4.80	H	3	25	10	VAV-1.12 - 1ST FLOOR OFFICES	18
19	EXISTING - 1ST LEVEL	12	20	1	L	0.00	0.00					H					20
21	EXISTING - 1ST LEVEL	12	20	1	L			0.00						Space			22
23	Space													Space			24
25	Space													Space			26
27	Space													Space			28
29	Space													Space			30
31	Space													Space			32
33	Space													Space			34
35	Space													Space			36
37	Plaza Ept Panel (Future) 'HP'	2/0 AL	125	3	S	19.87	18.79										38
39					S			19.34	18.79		S	3	175	4/0 AL	PANEL 'LP' VIA XFMR T-LP		40
41					S					19.68	18.81	S					42

Phase KW:	92.247	95.527	89.986
Phase Demand KW:	92.895	95.687	90.110
Total KW:	277.741	Total Amps	334.08
Total Demand KW:	278.692	Dem Load Amps	335.22

LIGHTING "L":	3.805 KVA @ 1.25 DF= 4.756 KVA
RECEPT "R":	0.000 KVA, 1ST 10KVA + 50% OF REMAINDER 0.0 KVA
A/C "A":	0.000 KVA @ 1.00 DF= 0.000 KVA
KITCHEN "K":	0.000 KVA @ 65 DF= 0.000 KVA
MOTOR "M":	0.000 KVA, TOTAL + 25% OF LARGEST 8.0 KVA
HEATING "H":	62.991 KVA @ 1.00 DF= 62.991 KVA
MISC "S":	210.94 KVA @ 1.00 DF= 210.94 KVA

EXISTING 'H1' PANEL THAT FEEDS 'HP' PLAZA PANEL. LOCATED AT SURGE BUILDING'S MAIN ELECTRICAL ROOM (SEE SHEET E1.01).

Label	Designation	AMP	Phase		Main	Circuit	Mount.	NEMA	Voltage		STYLE	A.I.C.
HP	HIGH VOLTAGE PANEL	125	3		MLO	42	Surface	3R	277	480	PANELBOARD	65K
	FED FROM 'H1' (Surge Building)											

Ckt. #	Circuit Description	Wire Size	Trip Amps	Brkr. Pole	Load Type	A Phase Load KW	B Phase Load KW	C Phase Load KW	Load Type	Brkr. Pole	Trip Amps	Wire Size	Circuit Description	Ckt. #
1					M	2.11							Space	2
3	Fountain Pump	12	20	3	M		2.11						Space	4
5					M			2.11					Space	6
7	Space												Space	8
9	Space												Space	10
11	Space												Space	12
13	Space												Space	14
15	Space												Space	16
17	Space												Space	18
19	Space												Space	20
21	Space												Space	22
23	Space												Space	24
25	Space												Space	26
27	Space												Space	28
29	Space												Space	30
31	Space												Space	32
33	Space												Space	34
35	Space												Space	36
37	Space					17.23			S				Space	38
39	Space						16.71		S	3	175	4/0 AL	PANEL 'LP' VIA XFMR T-LP'	40
41	Space							17.04	S				Space	42

Phase KW:	19.343	18.815	19.153
Phase Demand KW:	19.870	19.343	19.680
Total KW:	57.310	Total Amps	68.94
Total Demand KW:	58.893	Dem Load Amps	70.84

LIGHTING "L":	0.000 KVA @ 1.25 DF= 0.000 KVA
RECEPT "R":	0.000 KVA, 1ST 10KVA + 50% OF REMAINDER 0.0 KVA
A/C "A":	0.000 KVA @ 1.00 DF= 0.000 KVA
KITCHEN "K":	0.000 KVA @ 65 DF= 0.000 KVA
MOTOR "M":	0.000 KVA, TOTAL + 25% OF LARGEST 2.8 KVA
HEATING "H":	0.000 KVA @ 1.00 DF= 0.000 KVA
MISC "S":	50.96 KVA @ 1.00 DF= 50.96 KVA

Label	Designation	AMP	Phase		Main	Circuit	Mount.	NEMA	Voltage		STYLE	A.I.C.
LP	LOW VOLTAGE PANEL	200	3			42	Surface	3R	120	208	PANELBOARD	10K
	FED FROM 'HP' VIA XFMR T-LP"											

Ckt. #	Circuit Description	Wire Size	Trip Amps	Brkr. Pole	Load Type	A Phase Load KW	B Phase Load KW	C Phase Load KW	Load Type	Brkr. Pole	Trip Amps	Wire Size	Circuit Description	Ckt. #
1	Lighting (Fountain)	12	20	1	L	0.30	0.26		L	1	20	12	Lighting	2
3	Lighting	12	20	1	L		0.30	1.20	L	1	20	12	Lighting	4
5		12	20	1	L			1.20	0.60	L	1	20	12	Lighting	6
7	Lighting	12	20	1	L	0.79	0.60			L	1	20	12	Lighting	8
9	Lighting	12	20	1	L		0.20	1.20		L	1	20	12	Lighting	10
11	Receptacles	12	20	1	R			1.44	1.37	M	2	20	12	Water Feature Pump	12
13	Receptacles	12	20	1	R	1.80	1.37			M	"	"	"	"	14
15	Space													Space	16
17	Space													Space	18
19	Space													Space	20
21	Space													Space	22
23	Space													Space	24
25	Space													Space	26
27	Space													Space	28
29	Space													Space	30
31	Space													Space	32
33	Space													Space	34
35	Space													Space	36
37					S	12.00								Space	38
39	Event Cam Lock	1 AL	125	3	S		12.00							Space	40
41					S			12.00						Space	42

Phase KW:	17.122	14.900	16.810
Phase Demand KW:	17.233	16.705	17.043
Total KW:	48.832	Total Amps	134.99
Total Demand KW:	51.323	Dem Load Amps	142.46

LIGHTING "L":	6.652 KVA @ 1.25 DF= 8.315 KVA
RECEPT "R":	3.240 KVA, 1ST 10KVA + 50% OF REMAINDER 3.2 KVA
A/C "A":	0.000 KVA @ 1.00 DF= 0.000 KVA
KITCHEN "K":	0.000 KVA @ 65 DF= 0.000 KVA
MOTOR "M":	2.740 KVA, TOTAL + 25% OF LARGEST 3.77 KVA
HEATING "H":	0.000 KVA @ 1.00 DF= 0.000 KVA
MISC "S":	36.00 KVA @ 1.00 DF= 36.00 KVA

LIGHTING CONTROLS SCHEDULE

Area/Space	Zone #	Ckt #	Panel	Crestron Module	Input	Output	Fixture Type	Load Type	Dim	Total Wattage	Qty
Bench tapelight	1	LP-6	Site Dimming Panel	DIMFLV8	1	1	SS1	0-10V	Y	300	2
Core/Plex Shades	2	LP-6	Site Dimming Panel	2DIM8-1	1	1	SF3	FWD	Y	600	24
West Side trees	3	LP-6	Site Dimming Panel	2DIM8-1	1	3	SF5	FWD	Y	300	10
North Side trees	4	LP-8	Site Dimming Panel	2DIM8-1	1	4	SF5	FWD	Y	300	10
Medjuls	5	LP-8	Site Dimming Panel	2DIM8-1	2	5	SF2	FWD	Y	300	12
ThinkStation	6	LP-7	Site Dimming Panel	DIMFLV8	1	2	SD1	0-10V	Y	200	12
Royals	7	LP-5	Site Dimming Panel	2DIM8-2	2	2	SF4	FWD	Y	1200	12
East Side trees	8	LP-3	Site Dimming Panel	2DIM8-1	2	8	SF5	FWD	Y	300	24
Planters tapelight	9	LP-9	Site Dimming Panel	DIMFLV8	2	3	SS2	0-10V	Y	300	16
Foxtails	10	LP-4	Site Dimming Panel	2DIM8-1	2	6	SF1	FWD	Y	300	14
Bollards	11	LP-2	Site Dimming Panel	DIMFLV8	2	4	SB3	0-10V	Y	300	10
Core Entry Shade	12	LP-4	Site Dimming Panel	2DIM8-1	2	7	SF3	FWD	Y	300	8
Fountain	13	LP-10	DMX Control		Pharos		SU1	DMX	Y		9
Fountain	13	LP-10	DMX Control		Pharos		SU2	DMX	Y		9

LEGEND
HP
LP

Order Plans @ WWW.DLine.com

POWER DESIGN INCORPORATED
11400 North Street Suite 4
St. Petersburg, Florida 33716
727.210.0434
Electrical Dept.
Alex Gromov
P.E. #61365
Expires: 02/28/2019
FL: EC13009941
powerdesigninc.us

Key Plan:

PDI - PLAZA
1000 118th Ave North
Saint Petersburg, FL 33716

CADD Technician:	Date Signed:
E. Cruz	
Designer:	
A. Baez	
Engineer:	
A. Zotescu	
Superintendent:	

06/29/2018
Permit Set

PANEL SCHEDULES - PLAZA

Date Issued
June 29, 2018

Sheet Number:
E6.01

Plotted By: Alex Baez Montalvo
Plot Date / Time: 6/28/2018 4:10 PM
Project Directory: S:\Projects\Management\05 Projects\Shed980 - Site Campus\Campus - Plaza\1. Engineering\Working Drawings\CADD\Electrical\E6.01 - Panel Schedules.dwg