2.16.2 Maximum working pressure 6" w.g.

2.16.3 Maximum length 50 feet.

2.16.4 Supports shall be spaced maximum 3 feet, support band min. 2 in. wide. Use Wiremold duct collars and galvanized strap clamps or equal as approved by Engineer.

2.16.5 Spin in fittings shall be Metal Masters Model MS3-6G or equivalent as approved by Engineer.

2.16.6 Approved products:

Flexmaster TL-M
Insulated Metalflex V-200-UL
Thermo-Flex Type-A-300

11. Duct Leakage Loss:

2.18.1 Each system shall meet SMACNA and ASHRAE leakage class 3. This leakage will be determined by the test and balance consultant.

2.18.2 Loss exceeding leakage class 3 requirements shall be controlled by the HVAC Contractor prior to acceptance by Public.

12. Duct Hangers:

2.19.1 Duct hangers shall be threaded rods or metal straps with metal bands or angles see details in the mechanical drawings.

2.19.2 Preferred Method for Exposed Ductwork system: Load-rated cable suspension system. The system shall have a specified manufacturer's safe working load (SWL) and supplementary safety factor of at least five times the SWL. The system shall be verified by SMACNA Testing & Research and shall be in compliance with SMACNA Duct Construction Standards guidelines.

2.19.3 Approved System: Cripple Hang-Fast.

2.19.4 Seismic bracing and design to comply with local conditions.

13. Grease Hoods: Owner furnished, contractor installed.

2.19.5 Install till, classified range hoods as indicated on the Drawings and in accordance with NFPA 96. Hoods shall be till gage (stainless steel to be specified on drawings), liquid tight welds, grease extractors, vapor proof lights and factory pre-piped fire suppression system.

2.19.6 Grade of stainless steel to be listed in the mechanical drawings.

14. Fire Suppression

2.19.7 Provide fire protection system (specified Section 15355 Automatic Fire Suppression System) for all grease hoods per removal hoods (Designated GH-). Shall conform to NFPA 17.

2.19.8 Fire dampers shall be at the supply air inlets.

15. Grease Hood Exhaust Duct

2.19.9 Fabricate kitchen hood ducts from 16 ga. galvanized steel sheets, 18 ga. stainless steel where exposed. Conform to NFPA 96. All joints and seams shall be welded liquid tight. Provide a flange for duct at top of exhaust fan curb.

2.19.10 Duct Access doors:

Access doors shall be of UL listed.

Ductmate, F2
Flame Guard
Acudor Products Inc.

16. Prefabricated Oven, Grease and Engine Exhaust Venting:

2.19.11 Approved Manufacturers

Metal- Fab
Selkirk
Captive-Aire

2.19.12 Type B Venting

2.19.12.1 Provide a complete insulated double wall gas venting system (U.L. Listed #103),1400 degrees F. rating and draft hood for the gas fired equipment and bakery ovens where indicated.

2.19.12.2 Thimbles, flashing, rain cap as required.

2.19.12.3 Air Intake: Single wall construction.

2.19.13 Grease Duct

2.19.13.1 Provide complete double wall, fiber insulated exhaust system as listed and compliant with NFPA 96

2.19.13.2 Use manufacturers sealants and support system and components for a complete system.

2.19.13.3 Exhaust piping shall terminate per local code or as required by NFPA 96.

2.19.13.4 Minimum 10 year warranty.

2.19.14 Engine Exhaust

2.19.14.1 Provide complete double wall fiber insulated exhaust system with insulation thickness as listed on the project plans.

2.19.14.2 Use manufacturers sealants and support system and components for a complete system.

2.19.14.3 Exhaust piping shall terminate per local code or as required by NFPA 37

2.19.14.4 Minimum 10 year Warranty.

17. Devices and other miscellaneous items:

2.19.15 Dampers: Opposed blade, butterfly type, or splitter, all factory made as indicated. Each shall have a locking quadrant accessible for adjustment, with extension sleeve for duct wrap insulation.

2.19.16 Turning Device for Registers: Titus model AG-45 or similar device as approved by Architect.

2.19.17 Radiation Dampers: UL listed and installed where indicated.

2.19.18 Piping System for Condensate: Schedule 40 PVC.

18. Insulation:

2.19.19 Concealed HVAC Ductwork

2.19.19.1 Insulate externally with foil scrim kraft (FSK) fiberglass blanket type insulation, ASTM C1136, thickness and R value as indicated on the Drawings.

2.19.19.2 Comply with ASHRAE 90.1 and energy code requirements of the AHJ.

2.19.19.3 Materials shall have flamespread less than 25, and smoke developed less than 50.

2.19.19.4 Approved manufacturers:

Johns Manville
CertainTeed
Owens Corning
Knauf

2.19.19.5 Neatly cut and fit insulation to the duct surface with all duct joints overlapped 2" minimum, secured with outward-clinch staples 4" on center each way.

2.19.19.6 On ducts 24" or greater in width the insulation on the underside of the duct shall be secured to the sheet metal surface with Fastor 5 #85-20, or equal, adhesive, and secured mechanically with sheet metal screws and caps, or mechanical fasteners adhered to the duct on not more than 18" centers each way.

2.19.19.7 All transverse and longitudinal seams, and penetrations of the vapor barrier facing shall be covered with SMACNA rated foil backed tape applied as and sealed with Foster #30-08 or #30-05, or equal, vapor barrier mastic.

2.19.20 Where indicated, exposed double wall HVAC duct work shall be internally insulated with fiberglass.

2.19.20.1 Insulate internally with fiberglass rigid board type insulation and retaining fabric, ASTM C1136, thickness and R value as indicated on the Drawings.

2.19.20.2 Materials shall have flamespread less than 25, and smoke developed less than 50.

2.19.20.3 Approved manufacturers:

Johns Manville
CertainTeed
Owens Corning
Knauf

2.19.20.4 Where indicated, exposed rectangular duct work shall be [illegible] lined.

2.19.20.5 Flexible duct liner shall be glass fibers free of [illegible] with a thermos-setting resin.

2.19.20.6 A corrosion surface shall be protected [illegible] surfaces mat coating.

2.19.20.7 Edges, joints and [illegible] approved coating.

2.19.20.8 All exposed [illegible] Duct Liner:

2.19.20.8.1 Provide [illegible] Duct liner resistant rigid board type insulation, Owens Corning "Fiberglas" Type [illegible] Products, Johns Manville [illegible] Corporation, or approved equal. Conform to [illegible] fire hazard, no smoke, no [illegible] guidelines.

2.19.20.8.2 Provide [illegible] surface coat for securing duct wrap, welded insulation pins, washers and sealers.

Approved Manufacturers:

Gemco
Mason Industries
Fastfinger, Thermal Ceramics FireMaster

Duct work accessories:

a. Balanced Dampers

2.19.19.1 Provide dampers with parallel blades for 2 position control, or opposed blades for modulating control.

2.19.19.2 All metal parts galvanized steel, Blades 16ga., bearings heavy duty molded nylon, axles: 1/2" dia. steel, 9" OC.

2.19.19.3 Steel Frames:

2.19.19.3.1 Up to 23 sq. ft.: 2"X1"X1/8"

2.19.19.3.2 Over 23 sq. ft.: 4"X1 1/4"X16ga.

2.19.19.4 Acceptable Manufacturers:

Greenheck
Ruskin

Section 26 00 00

Electrical
V10092017

1. General

1.1 Summary

1.1.1 Comply with requirements of Sections 01 11 00, 01 33 00, 01 50 00, 01 77 00, 01 78 39.

1.1.2 Provide all materials and equipment and perform all labor required to install electrical systems complete as indicated, as required by code, and as specified herein.

1.1.3 Obtain and pay for all permits, bonds, inspection. Coordinate inspections with work as it progresses.

1.1.3.1 Provide services necessary to coordinate work with work of others. Notify concerned parties before proceeding with work that will affect them.

1.1.3.2 Provide electric service to connect with site utilities at a point outside the building as shown on the Drawings.

1.1.3.3 Coordinate with Utilities all requirements for utility transformer and Metering, furnish and install all utility requirements for electrical service (in transformer pad, CT compartment, metering and pedestal)

1.1.3.4 Furnish and install all panel boards, and contactors at the locations shown on the Drawings and specified herein.

1.1.3.5 All spare, empty conduit and junction boxes to have pull string.

1.1.3.6 Furnish and install all conduit and conductors between the load side of the feeder breakers to the branch panels.

1.1.3.7 Furnish and install all branch circuits between the panel boards and the final terminal as shown on the Drawings and specified herein.

1.1.3.8 Furnish and install all secondary service between the power company transformer to the main switch as indicated on the Drawings.

1.1.3.9 Receive, store, install and make final electrical connections to all lighting fixtures as shown on the Drawings and specified herein.

1.1.3.10 Furnish and install conduit and boxes only for the public address system and telephone outlets.

1.1.3.11 Make all electrical connections to the electric door operators as shown on the Drawings and specified herein.

1.1.3.12 Make all electrical connections to equipment supplied by Public. Electrical Contractor to verify all manufacturer equipment requirements prior to connection. Any conflicts or deviation in design to be brought to the attention of the Engineer.

1.1.3.13 Make all electrical connections to refrigerated display cases and walk-in boxes as shown on the Drawings and specified herein.

1.1.3.14 Make all electrical connections between the main switchboard and the refrigeration compressors and condensing equipment as shown on the Drawings and specified herein.

1.1.3.15 Furnish and install all motor starters, disconnect devices, conduit and conductors for control and power wiring.

1.1.3.16 Make all electrical connections between the main switchboard and the air conditioning compressors, air handling units, pump packages and strip heaters as shown on the Drawings and specified herein.

1.1.3.17 Make all electrical connections between the in-store rooms mounted refrigeration equipment and the refrigerated display cases, walk-in freezers and coolers as shown on the Drawings and specified herein.

1.1.3.18 Furnish and install all conduit and conductors to totally electrically connect all controls as specified herein.

1.1.3.19 Furnish and install all electrical work required for the dry chemical fire extinguisher system in the grease exhaust hoods. in compliance with NFPA Bulletins 017, 096, and with local codes.

1.1.3.20 Furnish and install all electrical wiring devices as shown on the Drawings and specified herein.

1.1.3.21 Furnish and install all conduit, conductors, disconnect devices and flexible metal conduit to completely wire all supply and exhaust fans as shown on the Drawings and specified herein.

1.1.3.22 The Electrical Contractor is fully responsible and liable for damaged and lost materials furnished by Public. It shall be required that he sign for the materials supplied by Public.

1.1.3.23 Panels for A/C and refrigeration mechanical systems, as furnished pre-wired internally by others, shall be completely connected by the Electrical Contractor. Refer to Drawings and Specifications for air conditioning.

1.1.3.24 Furnish and install all electrical service and controls for fans installed by others.

1.1.3.25 Furnish and install power wiring to each HVAC unit including the safety disconnect switch and other required electrical devices to make the unit operational as shown on the Drawings and specified herein.

1.1.3.26 Install Optional Standby generator and Meggear transfer switch complete, as furnished by Public.

1.1.3.27 Install conduit/enclosure with pull string for fire alarm and burglar alarm system, as furnished by Public; per note on Drawings.

1.1.3.28 Install and connect air conditioning control panel, energy management system, supplied by Public.

1.1.3.29 Install conduit, conductors and make connections to "Public" sign, and all other facade signs and under canopy signs (signs supplied and installed by Sign Contractor).

1.1.3.30 Security and fire alarm systems or combined system: the Electrical Contractor shall supply and install conduit, boxes, and pull strings as shown on Drawings. Power supply, station controls and complete final hook up by Fire Alarm Contractor/Security Alarm Contractor as noted on Drawings (achieved as sub contract to the Electrical Contractor. The Electrical Contractor may or may not be the Fire Alarm Contractor/ Security Alarm Contractor as noted on these licenses.

1.1.4 Related Work by Other Contractors:

1.1.4.1 Setting and roofing in of all curbs and pitch pockets by Roofing Contractor. (setting of A/C curb only shall be by A/C Contractor)

1.1.4.2 Setting of water heaters, ovens, kitchen equipment, panel hoods, cash equipment, facade signs and other miscellaneous equipment by others. Final electrical connection by Electrical Contractor.

1.1.4.3 Kitchen Hood Fire Protection System by Others.

1.1.5 Public reserves the right to furnish some items of electrical equipment to the Electrical Contractor. If this is done the Electrical Contractor shall install the equipment and deduct the cost of equipment from his contract. Cost adjustment will be made by Change Order.

1.1.6 All apparatus shall be installed at exact height and locations as shown on the Drawings, or if not shown, at heights and locations determined by applicable codes and local.

1.1.7 Perform all excavation and backfill required for services, and for all conduit and work inside and outside the building. Cutting of curbs, walks, concrete and paving required for excavation shall be done by appropriate trade.

1.1.8 All masonry, cutting, and footers will be furnished and set in place by Public. Check Equipment Drawings against Drawings in order to verify exact locations.

2. Definitions: Explanation and Precedence of Documents:

2.1 For purposes of clarity and legibility, Electrical Drawings are essentially diagrammatic and, although size and location of equipment are drawn to scale wherever possible, Electrical Contractor shall make use of all Contract Documents.

2.2 The Drawings indicate size, connections, and routing of conduit and equipment. It is not intended, however, that all offsets, risers and bends are shown. Install all items as required to fit structure, avoid obstructions, and retain clearances, headroom, and passageways.

2.3 Remodels: Carefully examine all existing conditions, existing work in place and premises and compare drawings with the existing conditions. Submittal of bid indicates that the Electrical Contractor has visited the Site and the Drawings and has included all required items in his bid. No allowances will be made for any error or omission from Contractor's failure to visit the site and review Drawings/Documents.

2.4 Conflicts, discrepancies, and references to omissions from Drawings shall be brought to the attention of the Engineer for clarification prior to commencement of Work.

3. Submittals:

3.1 Submit LOI in accordance with Section 01 33 00 Submittal Procedures.

3.2 Upon Notice of Contract Commencement (Notice to Proceed), submit Engineer's approval:

3.2.1 List of materials intended for use in the Project.

3.2.2 Manufacturer's catalogue cuts of materials intended for use in the Project.

3.2.3 Submittals to include: Switchgear, breakers, panel boards, starters, disconnect, relays, switchboard, wire channel system, conduit, wire, boxes, wiring devices, receptacles, switches.

3.2.4 Copies of licenses of key personnel if requested by Public.

3.2.5 Samples of materials if requested by Public.

3.2.6 Other items required to complete the Work

3.3 Submit three identical bound copies of all items. Arrange categories in order listed above.

3.4 All cuts for the above shall have rough or dimensions, connection sizes, and any special installation requirements. In addition, furnish motor horsepower and voltage data for all equipment.

3.5 Close Out Documents:

3.5.1 Comply with applicable provisions of Section 01 78 39 Project Record Documents.

3.5.2 Provide a complete set of manufacturer's warranties and warranty certificates.

3.5.3 A copy of the final approval from the local building department.

4. Quality:

4.1 Subcontractor:

4.1.1 The Electrical Subcontractor shall be a reputable firm regularly engaged in this type of work, employing skilled workmen, and with proper equipment.

4.1.2 Upon request Subcontractor shall show evidence of at least two similar jobs, of comparable size and character, installed and operating within the previous two years prior to bid opening.

4.1.3 Public reserves the right to refuse any Subcontractor with or without cause.

4.1.2 Personnel:

4.1.2.1 Employ an experienced superintendent to oversee all operations.

4.1.2.2 Work shall not proceed without adequate supervision present at all times.

4.1.2.3 Work shall be accomplished by workers certified in their trade as masters, journeymen, and apprentices in accordance with the regulations of the governing authority or customary practice. Utilize workers with skills in proportion to complexity of tasks required.

4.1.2.4 Public reserves the right to reject personnel with or without cause.

4.1.3 Quality Standards:

4.1.3.1 Work shall be accomplished to ensure safety to all personnel during installation and after occupancy.

4.1.3.2 Work will be judged by Public in comparison to work of similar types. Substandard construction as judged by Public Representative will not be accepted.

4.1.3.3 Minimum counts: Make all joints, connections, unions, etc. with proper care to ensure that tight connections are made without excess material, well secured to supports

4.1.3.4 Install conduit with runs straight, accurately formed radiuses at bends, and adequate supports.

4.1.4 Regulations: Comply with applicable provisions of the following codes (latest version adopted by governing agencies):

National Fire Protection Association (NFPA)
National Electrical Code
Local Utility Code
Local Building Code
Safety Code for Mechanical Refrigeration
Conform to governing codes, ordinances and regulations of city, county and state having jurisdiction. Where local codes are not applicable, conform to National Electric Code/State Electric Code where Project is located.
OSHA - for construction safety

4.1.5 Test the entire system. The solid neutral wire shall be tested for through grounding and all but wiring shall be tested for shorts and grounding.

4.1.6 Participate in the Pre-Construction Conference.

4.1.7 Substitutions: Comply with Section 01 25 00 Product Options and Substitutions. In general, substitutions are not allowed.

5. Sequencing:

5.1 Notify General Contractor, or any others, of all required chases, sleeves and openings required so that the work can be accomplished without delay. Provide necessary sleeves, etc., to be installed. Otherwise, Electrical Sub-Contractor shall pay for approximate trades time for cutting and patching.

5.2 Joists, girders, beams, columns or reinforcing steel shall not be cut.

5.3 Where construction necessitates the routing of conduit through structural members, locating in under or through footings, permission to make such installation shall first be obtained from the Structural Engineer.

6. Temporary Operation:

6.1 The Owner may require operation of parts or all of the installation prior to Final Acceptance.

6.2 Cost of utilities for such operation shall be paid by the Contract. This operation does not constitute acceptance of the Contractor's Work.

6.3 All electricity used for construction shall be paid for by the General Contractor Furnish and install temporary electrical connection and meter for construction purposes. Remove temporary service when use is no longer required. Clean up and landscape as required.

6.3.2 Temporary Power: The Owner reserves the right to make emergency repairs as required to keep equipment in operation without voiding the Contractor's guarantee nor relieving the Contractor of his responsibilities during the guarantee period.

7. Operating Instructions and Service Manual:

7.1.1 Provide two (2) neatly bound copies of maintenance and instructions book, parts lists pertaining to all equipment furnished.

7.1.2 Each section shall be indexed and include parts lists, instruction books, suppliers' phone numbers and addresses, and individual equipment guarantees all in separate sections.

7.1.3 Representatives of the Owner shall be instructed by the Contractor as to complete care and operation of the electrical system. Before the Engineer is writing as to the persons who received the instructions and the date that this was done.

Products:

1. Materials

2.1.1 All materials shall be new, of the best quality.

2.1.2 All similar materials such as switches, panelboards, starters, contactors, fuses, circuit breakers, junction boxes, and other classes of equipment shall be of the same type and manufacture.

2.1.3 All equipment and materials shall be furnished in strict accordance with the equipment schedule and Specification requirements.

2. Panelboards

2.2.1 All panelboards shall be dead front, totally enclosed, with locking doors, with spare 30% ambient controlled to the panel boards or as noted on the Drawings. UL approved. The panelboards shall be 3 phase, 4 wire, solid neutral, ground bars, voltage and number of poles as noted on the Drawings. Panelboards shall have copper bussing. The circuits shall be connected to individual poles of the panel as shown on the Drawings, and the panel shall be provided with a typewritten directory.

2.2.2 All panels shall be factory assembled.

2.2.3 Ground fault circuit interrupters shall be provided in each panel as required by the NEC or where specified on the Drawings.

2.2.4 Provide all panels sized as noted on the Drawings or as required.

2.2.5 Circuit breakers supplied with handles [illegible] (HHD) shall be supplied with HID components.

2.2.6 Equipment ground bus and neutral bus to be copper.

2.2.7 All panels noted on drawings with isolated ground circuits shall have copper ground bus and neutral bus in addition to equipment ground bus.

2.2.8 Acceptable Manufacturers

[illegible]
Square D

2.3 Switchboards:

2.3.1 Switchboard maintenance shall be as indicated on the Drawings and shall be:

2.3.1.1 Square D

2.3.1.2 Coordinate with Public drawings with site electrical drawings. Conflicts are to be brought to the Engineer for clarification/resolution.

2.3.2 Verify method of service with local utility company and obtain written approval from Public Representative before commencement of work.

2.3.3 Obtain all utility requirements for commercial service installation. Electrical Contractor must provide all requirements of the utility for a complete and operational system.

2.3.4 System shall be grounded in conformance with NEC and as shown on Drawings.

2.3.5 All switchgear and panels shall be sized as noted on the Drawings or as required.

GE
Square - D
ITE Div. of Siemens-Allis,

2.4 Main Switchboard:

2.4.1 General: Furnish and install the service entrance distribution switchboard as herein specified and shown on the Drawings.

2.4.2 The switchboard shall meet Underwriters' Laboratories enclosure requirements and be furnished with an Underwriters' Laboratories label.

2.4.3 Construction: Square D Unistruck construction or approved equal.

2.4.4 Enclosure Construction

2.4.4.1 The switchboard framework shall consist of steel channels welded or bolted to the floors to rigidly support the entire shipping section for mounting on rollers and floor mounting. The frame work in to be formed, code gauge steel, rigidly welded and bolted together to support all cover plates, bussing and component devices during shipment and installation.

2.4.4.2 Each switchboard section shall have an open bottom and individual removable top plate for installation and termination of conduit. top and bottom Conduit areas are to be clearly shown and dimensioned on the Shop Drawings. Switchboards are to be front access only. The wireway front covers are to be hinged to permit access to the branch switch load side terminals without removing the covers. All enclosure plates shall be screw type with provision for easy handling by one man. The panel finish shall be gray enamel over a rust-inhibiting phosphate primer.

2.4.5 Bussing:

2.4.5.1 The switchboard bussing shall be plated and of sufficient cross-sectional area to continuously conduct amperage as indicated on Drawings with a maximum average temperature rise of 50 degrees c. above an ambient temperature of 25 degrees c.

2.4.5.2 The buss shall be aluminum with 100% neutral with an integrated equipment rating of 100,000 amps (rms) A.I.C. at 240V, 65,000 amps (rms) A.I.C. at 480V.

2.4.5.3 The buss shall extend the full length of the available feeder area

2.4.6 Withstand Rating:

2.4.6.1 The switchboard, as a complete unit, shall be given a single withstand short circuit current rating by the manufacturer. The withstand short circuit current rating shall certify that all equipment is capable of withstanding the stress of a fault equal to the corresponding rating of the least overcurrents protective device contained therein. Such rating shall be established by actual tests by the manufacturer on equipment constructed similarly to the subject switchboard. This test data shall be available and shall be furnished to the Engineer, if requested, with or before the submittal of Approval Drawings.

2.4.6.2 The complete unit shall have interrupting rating of not less than 100,000 amps rms symmetrical at 240 volts,30000 amps RMS symmetrical at 480V.

2.4.6.3 All devices in the switchboard to be fully rated. Series rating is unacceptable.

2.4.7 Main Switch (Two-step wired energy electronic trip molded case circuit breaker):

2.4.7.1 Individually fixed mounted through contact type, equipped with an electric trip device for remote shunt trip operation.

2.4.7.2 Circuit breakers shall have power terminals to accommodate either cable or bolted bus connections.

2.4.7.3 Circuit protective devices shall be two-step stored energy type circuit breaker, UL listed for 100% continuous current when applied in QED switchboards. Sensor ampere ratings shall be as shown on the drawings or as otherwise indicated.

2.4.7.4 Provide a fixed instantaneous (High Level Selective Override) circuit on breaker(s). The circuit shall have a definitive instantaneous adjustment to allow the breaker to remain closed for up to 30 cycles during overcurrents below the instantaneous pick-up (shown as withstand ratings. The circuit shall trip instantaneously when current levels exceed applicable withstand ratings.

2.4.7.5 Circuit breakers shall be factory sealed and shall have a date code on its face. Poles shall be labeled with respective phase designs

2.4.7.6 Breaker faceplate shall indicate rated ampacity, frame faceplate shall indicate UL and IEC certification standards with applicable voltage systems and corresponding AIC ratings.

2.4.7.7 Each circuit breaker shall be equipped with a push-to-trip button to operate the trip mechanism mechanically.

2.4.7.8 Provide local control push buttons to OPEN and CLOSE circuit breaker. Color-coded visual indication of contact position (OPEN or CLOSED) shall be provided on the front of the breaker. Provide for local manual charging following CLOSE operation, with color coded visual indicating of charging status. Visual indicator shall indicate CHARGED only when closing springs are completely charged.

2.4.8 The main switch shall be as manufactured by Square "D" or equal as approved by Public Engineer. 100% rated at specified amps - no substitutes.

2.4.9 Bus Duct: (Where Used)

2.4.9.1 Service entrance bus duct shall be amps as shown on Drawings, 3 phase, full neutral, suitable for 120/208 volts service, inside-outside location.

2.4.9.2 The bus duct shall be complete with all necessary elbows, transformer taps, for stops, wall flange for fittings and supports to provide a satisfactory installation as indicated on the Drawings.

2.4.9.3 The bus duct shall be of the same manufacturer as the main switchboard.

2.4.9.4 The bus duct shall have the same interrupting rating as the main switchboard.

2.4.9.5 Supports for bus duct by General Contractor.

2.4.10 Feeder Switches:

2.4.10.1 The feeder switches shall be quick-make, quick-break and suitable for use on the services described by the size shown on the associated Drawings. The units shall be listed and approved by Underwriters Laboratories for heavy duty entrance use and where applicable, shall be dual horsepower rated for both standard one-time or dual-element fuses. The flexible switches shall be group mounted in panel-type construction. Each switch shall be equipped with Class R" inspection type fuse clips per Bussman or Littelfuse 670A5., Class "R" type

2.4.10.2 Each switch is to be enclosed in a separate steel enclosure. The enclosure shall employ a hinged cover for access to the fuses which shall be interlocked with the operating handle to prevent opening the cover when the switch is in the on position. This interlock shall be constructed so that it can be released with a standard screwdriver tool for testing fuses without interrupting service. The units shall have padlock type provisions in the off position and the operating handle position shall give positive switch position indication, i.e. horizontal off, diagonal on. Switches shall pass industry standard 12T vibration standability tests and fuse rates units as described elsewhere in the Specifications.

2.4.10.3 All fuses in accompanied by Bussman or Littelfuse, dual-element and current limiting as shown on the Drawings.

3. Contactors

2.5.1 Contactors shall be manufactured by Square D, Siemens, or General Electric; or others as approved by Public in writing specifically for this Project.

2.5.2 Contactors shall be designed to carry the full rated current on a continuous basis.

2.5.3 Contactors shall be electrically operated, mechanically held, and suitable for remote operation. The mechanically held contactors shall be equipped with a hand clearing contacts which disconnect the magnet coil when operated. Coils for any AC magnetic base.

2.5.4 Contactors shall be as sized as shown on the Drawings and be installed in NEMA 1 enclosures.

4. Wire and Cable:

2.6.1 All wire shall be copper THWN/THWN-2 unless otherwise noted. No wire shall be smaller than #12 AWG except where noted. No aluminum wire shall be accepted, unless specifically noted.

2.6.2 Minimum wire size for control circuits shall be #12 AWG shall be noted. #16 AWG may be used for low voltage control circuits unless otherwise noted.

2.6.3 In the number of conductors installed in conduits exceed the maximum allowed by the NEC. Should the Electrical Contractor install more conductors than required, he shall notify the Engineer before installation. Conductors shall not be grouped on the footing equipment foundations.

2.6.4 Control wire for the [illegible] and refrigeration equipment shall be type THHN/THWN stranded and be not smaller than #14 or where indicated.

2.6.5 Pull boxes are allowed only when required by code. Wire must be in one unspliced run to all secondary panel feeders, and in one unspliced run to all air conditioning and refrigeration units.

2.6.6 Install all phase conductors, neutral conductor, and ground conductor from panel board to the equipment connection junction box. If the neutral conductor is not needed it shall be taped and identified in the J B. for future use.

5. Conductors and Raceways:

2.7.1 PVC: Schedule 40 conduit may be used under floor slab. Riser shall be heavy wall hot dipped galvanized steel.

2.7.2 No PVC shall be installed above ground floor slab.

2.7.3 GRC 90's shall be used on all runs over 50'.

2.7.4 Underfloor Duct:

2.7.4.1 Shall be "Walker-Duct" (no substitutes) as manufactured by Walker/ Textron Company, Parkersburg, West Virginia. Install complete service fittings, blanking plates, junction boxes, covers, etc., with threaded fittings. Use standard No. 2 and No. 4 duct with #2-24 x 2 x 2 or #2-32 x 2 x 2 inserts as shown on Drawings. adaptors #11266-3/4", for cable. Install Walker Duct junction boxes with brass tops recessed to receive terrazzo to fully feather edge. Verify locations of duct with Drawings.

2.7.4.2 Top of cut insert shall be 3/4" below finish floor.

2.7.5 Raceways concealed in wall or ceiling spaces shall be studded weight but shall be replaced at no cost to the Owner.

2.7.6 All "LS" used to turn up through concrete slabs shall be thick wall galvanized conduit & couplings.

6. Time Switches

2.8.1 Provide time switches as manufactured by Intermatic (no substitutes)

2.8.2 Time switches shall be DPST, 40 amperes, 120 volt, AC motor and automatic -6ad,spring-wound carry-over.

2.8.3 Time clocks shall be labeled

7. Outlet Boxes, Fittings, and Conductors

2.9.1 Unless hereinafter specifically noted or shown on the Drawings, the minimum size of branch circuit outlet boxes for concealed work shall be 4"x4"x1 1/2" for square boxes and 4"x1 1/2" for octagon boxes.

2.9.2 Boxes shall be provided with plaster covers of sufficient depth to bring the face of the outlet substantially flush with the finished wall or ceiling. The box shall not project beyond the finished wall or ceiling line.

2.9.3 Outlets in concrete block, or other hollow masonry walls:

2.9.3.1 Openings in concrete block walls for outlets shall be cut to exact size with a masonry saw.

2.9.3.2 Switch and receptacle mounting heights, as specified or noted may be adjusted so that the bottom of the outlets box may rest on the top of the wall block at the nearest mortar joint.

2.9.3.3 All exposed outlets shall be provided with blank covers.

2.9.4 Where conduits 1" or larger enter outlet boxes, the boxes shall be 4 11/16"x4 - 11/16"x2 1/4" minimum. Boxes shall be of ample size to provide conductor spaces as required by the National Electric Code.

2.9.5 "Handy", utility or sectional boxes will not be permitted in masonry walls.

2.9.6 When more than one switch or device is shown ganged at any location a one-piece box of suitable size shall be installed.

2.9.7 Outlet boxes furnished for the installation of lighting fixtures shall be equipped with 3/8" "Hex-Bolt" or equal fixture studs.

2.9.8 Unless otherwise noted, all switches, receptacles and devices shown on the exterior of building walls shall be installed in flush mounted boxes provided with weatherproof gaskets.

2.9.9 All conduit fittings (conduletes) shall be of the cast-metal threaded hub type, Crouse-Hinds, or Appleton.

2.9.10 All rigid conduits entering panels, cabinets, outlet boxes, etc., shall be provided with locknuts on both sides of each devices drawn tight so as to maintain positive electrical and mechanical continuity throughout the conduit system. Insulated bushings shall be installed on the inside of the termination

2.9.11 Threadless couplings shall not be used for right conduit.

2.9.12 All EMT couplings and box connectors shall be of the set screw or compression type. Compression type shall be used in all coolers/freezers, or in outdoor applications. Cast connectors or couplings will be allowed.

2.9.13 All flex conduit shall be steel with steel fittings, and shall extend a maximum of 10 ft. unless approved by Public.

2.9.14 All receptacles labeled GFI on drawings to be supplied as GFI receptacles Feed through series GFI circuit is unacceptable.

2.9.15 All receptacles labeled IG (isolated ground) shall be IG listed and shall get a separate (from other equipment ground) green with yellow stripe insulated ground conductor. All isolated ground circuits to include equipment ground conductor.

2.9.16 All conduits to have an equipment ground conductor in addition to conductors shown on drawings.

10. Junction Boxes: Wiring shall be neatly arranged, bundled and laced in proper groups.

11. Pull Boxes

2.11.1 Pull boxes shall be installed in conduit system where needed whether or not they are shown on the Drawings.

2.11.2 Boxes shall be constructed of code gauge galvanized steel with screw covers.

12. Safety Switches

2.12.1 The basis of design and quality standards is Square - D.

2.12.2 All units shall be of the same manufacturer.

2.12.3 Safety switches shall be fusible, solid neutral, 277 volt, quick make and quick-break with visible blades, single throw, general duty, of size and fusing as shown on the Drawings, or required for application. switches mounted out of doors shall be weatherproof, heavy duty type with protective bumper door bolt high.

2.12.4 Exterior unit shall be in rain tight enclosure. (NEMA 3R)

13. Wall Switches

2.13.1 5-a rocker shall be flush mounted, quiet number type, 250 volts, 20 amp. rated

2.13.2 Wall plates shall be smooth, 302 stainless steel, one piece as indicated on the Drawings

2.13.3 Switches shall be installed on the "strike" side of the door swing.

2.13.4 Switches shown near doors shall be not less than two inches and not more than twelve (12) inches from the trim.

14. Receptacles

2.14.1 All units shall be totally enclosed construction with side and rear connections. All units shall be equipped with ears and have a rating as listed below. All devices shall be labeled, Pass and Seymour or Leviton. See symbol schedule on construction drawings.

2.14.2 Duplex convenience outlets with ground shall be 20 amp, 125 volt parallel slot, "H" shaped grounding slot, heavy duty "T" rated.

2.14.3 120/208 volt, 3 wire receptacles with ground shall be single 3 wire polarized receptacles with grounding terminal.

2.14.4 Weatherproof receptacles shall be duplex, 20 amp, 125 volt parallel slot receptacles with "H" shaped grounding slot in flush, weatherproof box with gasketed cover and self-closing, spring door.

2.14.5 Floor outlets shall be 20 amp, 125 volts single or duplex parallel slot receptacles with "H" shaped grounding slot as called for, located as shown on the Drawings. Provide floor outlets with flush cap for use when not in use.

2.14.6 All device cover plates shall be smooth 302 stainless steel, one piece.

15. Lighting Fixtures

2.15.1 All lighting fixtures shall be furnished by [illegible] and installed by appropriate trade. In-line fuses are to shield wiring between fixtures and wiring to fixtures.

2.15.2 In areas of suspended ceilings [illegible] per fixture will be furnished and hung by the suspended ceiling Subcontractor. Electrical Subcontractor shall wire in fixtures in areas of suspended ceilings. Provide (2) #10 wire pigtails 6" long at joint per fixture.

16. Electric Door Operators: Furnished by [illegible] and installed by others. Electrical Contractor shall provide others with two (2) 1" conduits from control box at floor

17. Intercom and Paging System:

2.17.1 Intercom Contractor shall supply and install outlets, conduit and junctive boxes, and equipment as shown on Drawings (two (2) 1" conduits from architectural ceiling to station).

2.17.2 The entire system shall be furnished complete and provided with blank covers.

2.17.3 The conduit system shall not less than 1".

18. Telephone Outlets

2.18.1 Provide outlets as indicated on Drawings,

2.18.2 Supply and install 1" conduit from outlet box and junction box.

2.18.3 Provide stainless steel outlet boxes and cover plates.

2.18.4 Locate telephone control box inside telephone equipment room.

2.18.5 Provide outlets for wall phones at indicated locations.

19. Standby Electric-Emergency Generator and Transfer Switch

2.19.1 Emergency generator and automatic load transfer switch will be furnished by Public and shall be set in place and connected by the contractor.

Execution

1. General

3.1.1 Temporary Electric Service: Install at station 120/240 volt, 1 phase, 3 wire, 200 amp temporary service. power Consumption cost only paid by Contractor. Installation shall comply with OSHA, NEC, and all local requirements.

3.1.2 The locations of the outlets, switches and convenience outlets shall be approximately as shown on the drawings and as specified, but exact locations shall be as directed by Public Field Representative. The running of all circuits, switch legs and conduits is purely diagramatic. Do not scale from Drawings

3.1.3 Rigging and hoisting that is incidental to the electrical portion of the Work shall be performed by the Electrical Contractor. This shall include the hoisting of equipment supplied by both the Electrical Contractor and Public that are installed by the Electrical Contractor.

3.1.4 Coordinate this work with other trades so that interference between the trades can be avoided.

3.1.5 All channels, angles and other members for the installation and support of the electrical equipment shall be furnished and installed by the Electrical Contractor.

3.1.6 The attachments of boxes, conduit, hangers, etc. shall be by machine screws or through bolts to steel, expansion bolts in concrete and masonry, and wood screws in wood. Wood composition plugs shall not be used.

2. Excavation and Backfilling:

3.2.1 Do all excavating required to install any underground conduits and after the same are in place and tested and approved, Thoroughly tamp earth around conduits and restore earth to its original condition as existed.

3.2.2 Underground conduit must be covered by a minimum of three (3) inches of undisturbed fill.

3. Conduit, Raceways, Etc.

3.3.1 All metallic non-current carrying components and enclosures of the electrical wiring system are to be bonded and grounded.

3.3.2 Furnish all necessary fittings and supports to make the raceways or busways fit the building structure and equipment. Raceway size shown or called for are minimum. The Electrical Contractor shall verify all raceway sizes with the dimensions of the particular cable to be installed.

3.3.3 All exposed raceways and conduit shall be neatly installed perpendicular or parallel to walls and floors. No exposed conduit is allowed in salary area or work room (except where required in exposed structure areas of stores without ceilings).

3.3.4 All raceways shall be supported by approved types of galvanized wall brackets, ceiling trapeze hangers, or hangers on pipe straps. Perforated metal strap or tie wire shall not be used for any conduit or raceway.

3.3.5 All conduit located above ceilings shall be EMT or RIGC, and must be installed within the area provided for ceiling.

3.3.6 Areas for work of various trades: Conform to locations as defined in Section 01 11 00 Summary of Work.

3.3.7 All conduit located underground may be PVC Schedule 40, except service entrance which may be concrete encased PVC schedule 40 or heavy wall rigid conduit, or weather proof bare duct as shown. Underground conduit lengths greater than 50' shall include GRC 90.

3.3.8 All job cut threads shall be given a coat of rust-inhibitive paint.

3.3.9 Caulk where conduit passes through walls, providing fire-stopping system where required. Caulk where conduit passes through walls or freezers and coolers. All cutting to block work must be done with carborundum saw, no chisel or hammer work will be accepted.

4. Circuit Identification: Label all panels by approved means to identify circuits. Install equipment in cases, as per Drawings. Mark all panels, time clocks, starters, contactors,

disconnect devices and main panels on the outside with riveted or approved attached plast