ELECTRICAL SPECIFICATIONS

SECTION 16001 - GENERAL ELECTRICAL PROVISIONS

A. EACH CONTRACTOR SHALL GIVE ALL REQUISITE NOTICES, OBTAIN AND PAY FOR ALL PERMITS, DEPOSITS AND FEES NECESSARY FOR THE INSTALLATION OF WORK UNDER THESE SPECIFICATIONS. TWO (2) COPIES OF CERTIFICATES OF APPROVAL SHALL BE OBTAINED FROM ALL AUTHORITIES ISSUING SAME AND SHALL BE TURNED OVER TO OWNER PRIOR TO FINAL ACCEPTANCE OF THE WORK.

B. ALL WORK SHALL CONFORM WITH ALL APPLICABLE CODES AND ORDINANCES. IT SHALL BE EACH CONTRACTOR'S RESPONSIBILITY TO INQUIRE INTO, UNDERSTAND, AND COMPLY WITH ALL APPLICABLE ORDINANCES, LAWS, CODES AND/OR REGULATIONS.

C. SHOULD A BIDDER FIND DISCREPANCIES IN OR OMISSIONS FROM THE DRAWINGS OR SPECIFICATIONS, OR SHOULD HE BE IN DOUBT AS TO THEIR MEANING, HE SHOULD AT ONCE NOTIFY THE ARCHITECT WHO WILL SEND WRITTEN INSTRUCTIONS TO ALL BIDDERS.

D. BEFORE SUBMITTING A BID, BIDDERS WILL BE HELD RESPONSIBLE TO HAVE VISITED THE SITE OF THE WORK AND FULLY INFORM THEMSELVES AS TO ALL EXISTING CONDITIONS AND LIMITATIONS, INCLUDING RULES, FRINGE BENEFITS, TRAVEL PAY, AND OTHER EXPENSES PREVAILING IN THE LOCAL LABOR MARKET, AND NO ALLOWANCES SHALL SUBSEQUENTLY BE MADE ON BEHALF OF THE BIDDER BY REASON OF ANY ERROR ON HIS PART.

E. PROVIDE ALL LABOR AND MATERIAL FOR A COMPLETE INSTALLATION OF ALL ELECTRICAL WORK. ELECTRICAL WORK TO BE RUN IN CONDUITS AND OR RACEWAYS TO LOCATIONS INDICATED ON THE PLANS.

F. ALL WORK MUST BE DONE IN A WORKMANLIKE MANNER TO THE COMPLETE SATISFACTION OF THE OWNER. ALL MATERIALS SHALL BE NEW OF THE QUALITY SPECIFIED AND FREE FROM DEFECTS AND IN FIRST CLASS CONDITION. ALL CONDUIT SHALL BE RUN STRAIGHT, PLUMB AND TRUE TO GRADE. ALL EXPOSED VERTICAL CONDUITS SHALL BE PLUMB. EQUIPMENT SHALL BE INSTALLED IN ACCORDANCE WITH MANUFACTURER'S INSTRUCTIONS FOR EACH PIECE OF EQUIPMENT USED. ALL MATERIAL AND EQUIPMENT SHALL BE OF THE STANDARD SPECIFIED.

G. DIMENSIONS GIVEN ON THE PLANS SHALL TAKE PRECEDENCE OVER SCALED DIMENSIONS.

H. BEFORE ORDERING ANY MATERIALS OR DOING ANY WORK, EACH CONTRACTOR SHALL VERIFY ALL MEASUREMENTS AND DIMENSIONS AT THE BUILDING SITE AND SHALL BE RESPONSIBLE FOR THE CORRECTNESS OF SAME. ANY DIFFERENCES THAT MAY BE FOUND SHALL BE SUBMITTED TO THE PROJECT MANAGER AND OWNER FOR CONSIDERATION BEFORE PROCEEDING WITH WORK.

I. PROVIDE AND INSTALL A COMPLETE AND OPERATING ELECTRICAL INSTALLATION IN ACCORDANCE WITH THESE SPECIFICATIONS AND APPLICABLE LOCAL CONTRACT DRAWINGS. THIS SHALL INCLUDE ALL REQUIRED LABOR, EQUIPMENT, AND SUPERVISION.

J. WITHOUT LIMITING OR RESTRICTING THE VOLUME OF WORK AND SOLELY FOR THE CONVENIENCE OF THE ELECTRICAL CONTRACTOR, THE WORK TO BE PERFORMED SHALL, IN GENERAL, CONSIST OF THE FOLLOWING:

1. A COMPLETE ELECTRICAL DISTRIBUTION SYSTEM INCLUDING SERVICE ENTRANCE EQUIPMENT AND FEEDERS, PANELS, BRANCH CIRCUITS, BOXES, WIRING DEVICES, COVERPLATES, ETC.
2. METERING AS REQUIRED BY UTILITIES, INCLUDING C.T. CABINET, METER SOCKET, CONDUIT ETC., AS REQUIRED. ELECTRICAL CONTRACTOR SHALL CONTACT UTILITY CO. AND INCLUDE ALL COSTS INVOLVED INCLUDING TRANSFORMER PAD, EXCAVATION, ETC. AS REQUIRED. TAP FEES AND ONE-TIME UTILITIES SERVICE CHARGES WILL BE PAID BY OWNER (OR DEVELOPER WHERE APPLICABLE).
3. THE WIRING OF MECHANICAL EQUIPMENT SHOWN ON MECHANICAL DRAWINGS. WORK SHALL INCLUDE ALL POWER AND CONTROL WIRING, DISCONNECT SWITCHES, ETC. AS REQUIRED.
4. LIGHT FIXTURES AND LAMPS SHALL BE INSTALLED AS SHOWN ON THE PLANS INCLUDING ALL DEVICES, EQUIPMENT, ETC. REQUIRED FOR MOUNTING. INCLUDE ALL PAINTING AS REQUIRED.
5. A COMPLETE SOUND SYSTEM FOR TELEPHONE INCLUDING SERVICE ENTRANCE CONDUIT, CABINETS, BRANCH CONDUITS, OUTLET BOXES, CABLES, COVERPLATES, ETC. ELECTRICAL CONTRACTOR SHALL CONTACT TELEPHONE CO., AND INCLUDE ALL COSTS INVOLVED FOR THE SERVICE ENTRANCE.
6. A COMPLETE EMERGENCY LIGHTING SYSTEM AS SHOWN ON THE DRAWINGS.
7. A CONDUIT SYSTEM FOR THE CASH REGISTER AND DATA SYSTEMS INCLUDING OUTLET BOXES, ETC.
8. A COMPLETE CONDUIT SYSTEM FOR FIRE ALARM AND SECURITY SYSTEMS INCLUDING OUTLET BOXES, ETC.
9. INSTALLATION OF THE ENERGY MANAGEMENT SYSTEM (EMS) AS SHOWN ON THE DRAWINGS INCLUDING ALL WIRING, JUNCTION BOXES, OUTLET BOXES, CONDUITS, ETC. AS REQUIRED TO FORM A COMPLETE SYSTEM.
10. ALL CONDUIT FOR TELEPHONE/DATA SHALL BE RUN WITH A PULL STRING.

K. ALL ITEMS OF LABOR, MATERIAL AND EQUIPMENT NOT SPECIFIED IN DETAIL OR SHOWN ON DRAWINGS, BUT INCIDENTAL TO OR NECESSARY FOR THE COMPLETE INSTALLATION AND PROPER OPERATION OF THE WORK SHALL BE FURNISHED AS IF CALLED FOR IN DETAIL BY THE SPECIFICATIONS OR DRAWINGS.

L. BEFORE ENERGIZING ANY CIRCUITS TEST FOR GROUNDS AND SHORTS. TEST CIRCUITS WITH A "MEGGER" TESTER TO DETERMINE THAT INSULATION VALUES CONFORM TO APPLICABLE NEMA STANDARDS. CHECK MOTOR CONTROLLERS TO DETERMINE THAT PROPERLY SIZED OVERLOAD DEVICES ARE INSTALLED. CHECK MOTORS FOR PROPER ROTATION. TEST OTHER ELECTRICAL EQUIPMENT FOR PROPER OPERATION. PROVIDE REPORT OF FINDINGS.

M. THE ELECTRICAL CONTRACTOR SHALL DO ALL ELECTRIC POWER WIRING AND CONTROL WIRING INCLUDING SETTING OF ALL MOTORS NOT DIRECTLY CONNECTED TO DRIVEN EQUIPMENT AND SETTING OF ALL CONTROLS EXCEPT THOSE FACTORY MOUNTED ON EQUIPMENT OR PANELBOARDS. THE MECHANICAL CONTRACTOR SHALL INSTALL AND SET ALL CONTROLS AND APPURTENANCES INSTALLED IN PIPES AND DUCTWORK. THE MECHANICAL CONTRACTOR SHALL FIELD INSTALL ELEMENT DUCT SENSORS IN EXISTING HVAC DUCTWORK AS REQUIRED FOR CONTROL SEQUENCES FOR HVAC EQUIPMENT. SEE MECHANICAL AND ELECTRICAL DRAWINGS FOR FURTHER DETAILS AND REQUIREMENTS.

N. ALL EXPOSED CONDUIT, EQUIPMENT, HANGERS, ETC., WILL BE PAINTED BY CONTRACTOR WHEN REQUIRED.

O. OWNER SHALL PROVIDE THE FOLLOWING EQUIPMENT FOR WHICH THE CONTRACTOR SHALL PROVIDE ELECTRICAL WORK:

1. EXTERIOR SIGNS
2. POS TERMINALS (ALSO REQUIRES ISOLATED GROUND SYSTEM BY CONTRACTOR.)
3. SENSORMATIC (WHEN INDICATED ON DRAWINGS)
4. ENERGY MANAGEMENT SYSTEM COMPONENTS

P. ITEMS PURCHASED THROUGH A NATIONAL ACCOUNT (REFER TO RESPONSIBILITY MATRIX ELSEWHERE IN THE DOCUMENTS).

1. LIGHT FIXTURES (AND LAMPS WHERE INDICATED).

Q. PROVIDE TEMPORARY POWER AS NEEDED FOR CONSTRUCTION WORK. COORDINATE WITH UTILITY COMPANY.

R. ALL PAINTING OF EXPOSED ELECTRICAL COMPONENTS, INCLUDING CONDUITS, HANGERS, JUNCTION BOXES AND OTHER WORK IN FINISHED AREAS, INCLUDING ANY EQUIPMENT ROOMS, WILL BE DONE UNDER THE GENERAL CONSTRUCTION CONTRACT. EXPOSED PIPE AND EQUIPMENT ON EXTERIOR SHALL BE PAINTED.

S. PERFORM ALL REQUIRED CUTTING AND PATCHING NECESSARY TO COMPLETE THE WORK. PROVIDE LISTED FIRE STOP SYSTEM FOR ALL PENETRATIONS THROUGH RATED WALLS, FLOORS, CEILINGS, ETC.

T. CONTRACTOR SHALL GUARANTEE ALL MATERIAL, EQUIPMENT AND WORKMANSHIP FOR A PERIOD OF ONE YEAR FROM DATE OF FINAL ACCEPTANCE BY THE OWNER. REPLACE ALL DEFECTIVE MATERIAL AND WORKMANSHIP AND ALL OTHER WORK AND EQUIPMENT DAMAGED THEREBY WITHOUT COST TO OWNER IN ADDITION TO THE ONE (1) YEAR GUARANTEE, THE CONTRACTOR SHALL FURNISH ANY WARRANTIES OR GUARANTEES THAT NORMALLY COME WITH SPECIFIC PIECES OF EQUIPMENT THAT EXCEED THE ONE (1) YEAR GUARANTEE.

U. PROVIDE A COMPLETE SET OF AS-BUILT DRAWINGS ON COMPLETION OF THE PROJECT.

SECTION 16050 - ELECTRICAL MATERIALS & METHODS

A. SHOP DRAWINGS: PROVIDE ALL PHYSICAL AND PERFORMANCE CHARACTERISTICS OF ALL EQUIPMENT SPECIFIED.

1. PANELBOARDS, LIGHTING CONTACTORS, TRANSFORMERS, AND SERVICE EQUIPMENT.
2. SWITCHES, OUTLETS, AND AUTOMATIC LIGHTING CONTROLS.

B. THE CONTRACTOR SHALL REVIEW, APPROVE AND SUBMIT SEVEN (7) COPIES OF ALL SHOP DRAWINGS. IT WILL BE THE CONTRACTOR'S RESPONSIBILITY TO CHECK AND SUBMIT ALL SHOP DRAWINGS LISTED WITHIN THE SPECIFICATIONS TO THE ARCHITECT WITHIN SEVEN (7) CALENDAR DAYS OF THE PROJECT START DATE SO AS NOT TO DELAY THE PROJECT, OR DELAY THE WORKING DRAWINGS FOR ANY SEPARATE CONTRACTOR.

C. NONE OF THESE ITEMS LISTED ABOVE SHALL BE INSTALLED BY THE CONTRACTOR UNTIL REVIEW HAS BEEN MADE BY THE ARCHITECT/ENGINEER. THIS CONTRACTOR SHALL CHECK SHOP DRAWINGS OF ALL OTHER TRADES' EQUIPMENT TO ASCERTAIN PROPER LOCATION OF ELECTRICAL EQUIPMENT AND CONNECTIONS.

D. ALL WORK INCLUDING ALL EQUIPMENT AND MATERIALS SHALL BE COMPLETELY SATISFACTORY AND ACCEPTABLE IN OPERATION, APPEARANCE AND CAPACITY.

E. ANY WORK WHICH DOES NOT COMPLY WITH THE DRAWINGS AND/OR SPECIFICATIONS, OR WHICH IS DEFECTIVE OR DAMAGED WILL BE HELD TO BE DEFECTIVE AND WILL BE REMOVED AND REPLACED WITH PROPER AND ACCEPTABLE MATERIAL, EQUIPMENT AND/OR APPURTENANCES OR PUT IN SUCH REPAIR AS SHALL BE SATISFACTORY TO THE OWNER WITHOUT ADDITIONAL COST TO OWNER.

F. CONTRACTOR SHALL FURNISH ALL LABOR, MATERIALS, EQUIPMENT, HANGERS, DEVICES, HARDWARE AND SERVICES NECESSARY FOR THE INSTALLATION OF THE WORK SPECIFIED FOR THIS CONTRACT. HE SHALL ERECT ALL STRUCTURAL STEEL REQUIRED FOR PROPER SUPPORT OF EQUIPMENT REQUIRING SAME. ALL SUPPORTS, BRACKETS, OR CLAMPS AND OTHER ITEMS SHALL BE INSTALLED IN STRICT ACCORDANCE WITH THE BEST PRACTICES OF THE TRADE AND RECOGNIZED CODES.

G. METALS - ALL EQUIPMENT SHALL BE LISTED AND LABELED BY AN APPROVED TESTING AGENCY SUCH AS UL OR ETL. STRUCTURAL STEEL MEMBERS AND HANGERS SHALL ALSO CONFORM TO ASTM STANDARD SPECIFICATION A-36.

H. ALL MATERIAL TO BE PAINTED SHALL BE CLEANED AND PRIMED BEFORE FINAL PAINTING.

I. THE ELECTRICAL CONTRACTOR SHALL VERIFY DIMENSIONS AND CLEARANCES REQUIRED FOR THE FINAL LOCATION OF ALL EQUIPMENT. OUTLETS, EQUIPMENT OR WIRING IMPROPERLY PLACED BECAUSE OF THE ELECTRICAL CONTRACTOR'S FAILURE TO OBTAIN THIS INFORMATION SHALL BE RELOCATED AND REINSTALLED WITHOUT ADDITIONAL EXPENSE TO OWNER. THE ELECTRICAL CONTRACTOR SHALL DETERMINE THE ACTUAL DIRECTION OF ALL DOOR SWINGS BEFORE INSTALLING LIGHT SWITCHES. IMPROPERLY LOCATED SWITCHES SHALL BE RELOCATED WITHOUT ADDITIONAL EXPENSE TO OWNER.

J. UNLESS OTHERWISE MENTIONED OR INDICATED, MOUNTING HEIGHTS OF OUTLETS ARE SHOWN ON THE DRAWINGS OR IN THE SPECIFICATIONS. ALL DIMENSIONS GIVEN SHALL BE CONSIDERED TO BE FROM CENTER OF OUTLET OR BOTTOM OF LIGHT FIXTURE TO FINISHED FLOOR.

K. IT WILL BE THE SOLE RESPONSIBILITY OF THE ELECTRICAL CONTRACTOR TO PROPERLY ROUGH FOR THE ELECTRICAL CONDUIT, WIRING, AND EQUIPMENT UNDER THIS CONTRACT AND ANY COST INVOLVED IN THE RELOCATION OF THE ABOVE WILL BE THE ENTIRE RESPONSIBILITY OF THE CONTRACTOR. NO ADDITIONAL COST WILL BE PAID FOR ANY RELOCATION OF ROUGH-IN. FIELD VERIFY ALL GRADES, LOCATIONS, AND DIMENSIONS.

L. CONTRACTOR SHALL CARRY OUT ALL NEW WORK WITH A MINIMUM OF NOISE. ALL SITE AREAS AND NEW EQUIPMENT, FLOORS AND WALLS, SHALL BE PROTECTED FROM DUST AND DIRT CAUSED BY THE WORK. PROTECTION SHALL INCLUDE SUITABLE TEMPORARY BARRIERS OR COVERINGS. THE EXTERIOR AND INTERIOR PREMISES OF EACH BUILDING SHALL BE KEPT AS CLEAN AS POSSIBLE DURING CONSTRUCTION. ANY DAMAGED SURFACES OR EQUIPMENT AS A RESULT OF THE CONTRACTOR'S NEGLIGENCE SHALL BE REPLACED OR CORRECTED BY THIS CONTRACTOR AS REQUIRED.

M. THE CONTRACTOR SHALL MAKE FINAL CONNECTIONS BETWEEN ALL EQUIPMENT FURNISHED UNDER THIS CONTRACT. THE ELECTRICAL CONTRACTOR SHALL PROVIDE, INSTALL AND CONNECT ALL POWER WIRING OF CABLES TO ALL EQUIPMENT FURNISHED BY OTHERS.

N. DUE TO THE SCHEMATIC NATURE AND SMALL SCALE OF THE ELECTRICAL DRAWINGS, IT IS NOT POSSIBLE TO INDICATE ALL EXACT LOCATIONS, OFFSETS, FITTINGS, ACCESS PANELS, PULL BOXES, AND MISCELLANEOUS PARTS WHICH MAY BE REQUIRED TO FORM A COMPLETE SYSTEM. THE DRAWINGS ARE GENERALLY INDICATIVE OF THE WORK TO BE INSTALLED. THIS CONTRACTOR SHALL CAREFULLY INVESTIGATE THE STRUCTURAL AND FINISH CONDITIONS AFFECTING THE WORK AND ARRANGE ALL WORK ACCORDINGLY, FURNISHING NECESSARY PARTS AND EQUIPMENT AS MAY BE REQUIRED TO MEET THE VARIOUS CONDITIONS.

O. COORDINATE WORK WITH OTHER TRADES. MAKE NECESSARY, REPOSITION WORK TO AVOID INTERFERENCE AT NO ADDITIONAL COST TO OWNER. COORDINATE REVISED LOCATIONS WITH OWNER.

P. ALL OVERCURRENT DEVICES AND EQUIPMENT FURNISHED UNDER OTHER CONTRACTS, SHALL BE SET AND ADJUSTED TO SUIT THE LOAD CONDITIONS.

Q. AFTER ALL TESTS AND ADJUSTMENTS HAVE BEEN MADE, THE CONTRACTOR SHALL FULLY INSTRUCT THE OWNER'S REPRESENTATIVE IN THE PROPER METHODS OF OPERATION AND MAINTENANCE OF EQUIPMENT INSTALLED UNDER THIS CONTRACT. PROVIDE OWNER WITH TWO INSTRUCTION MANUALS ON EACH SYSTEM. INSTRUCTION MANUALS SHALL CONSIST OF REPRODUCTIONS OF THE SHOP DRAWINGS, MANUFACTURER'S INSTALLATION INSTRUCTIONS, GUARANTEES, ETC. INSTRUCTION SHALL BE FURNISHED UNTIL OWNER IS SATISFIED.

R. THE CONTRACTOR SHALL EXAMINE THE ARCHITECTURAL, STRUCTURAL, MECHANICAL, AND PLUMBING DRAWINGS. IF ANY DISCREPANCIES OCCUR BETWEEN THE DRAWINGS OR BETWEEN THE DRAWINGS AND THE SPECIFICATIONS, HE SHALL IMMEDIATELY SUBMIT THE MATTER TO THE ARCHITECT FOR CLARIFICATION AND OBTAIN WRITTEN INSTRUCTIONS AS TO THE MANNER IN WHICH TO PROCEED. NO DEPARTURES FROM THE CONTRACT DRAWINGS SHALL BE MADE WITHOUT PRIOR WRITTEN APPROVAL OF THE OWNER.

S. THE CONTRACTOR SHALL REPAIR, REPLACE AND MAINTAIN IN SERVICE ANY NEW OR EXISTING UTILITIES, FACILITIES OR SERVICES (UNDERGROUND, OVERHEAD, INTERIOR OR EXTERIOR) DAMAGED OR OTHERWISE RENDERED UNSERVICEABLE OR INOPERATIVE DURING THE COURSE OF CONSTRUCTION. THE METHOD USED BY THE CONTRACTOR IN REPAIRING, REPLACING OR MAINTAINING THE SERVICES SHALL BE APPROVED BY OWNER.

T. THE CONTRACTOR SHALL FURNISH ALL LABOR, MATERIALS, EQUIPMENT AND SERVICES NECESSARY TO REPAIR ALL PAVEMENT DISTURBED UNDER THE CONTRACT.

U. PRIOR TO THE START-UP OF ANY SYSTEMS, ELECTRICAL CONTRACTOR SHALL CAREFULLY CHECK ALL DEVICES AND MANUFACTURER'S INSTRUCTIONS FOR THE PROPER PROCEDURE OF START-UP.

V. CHECK SERVICE ENTRANCE VOLTAGES AND INFORM ELECTRIC UTILITY OF ANY OVER-VOLTAGE OR UNDER-VOLTAGE CONDITIONS. CHECK GROUND CONDITIONS AND GROUNDING RESISTANCE. CHECK SYSTEM FOR PROPER PHASING. ALL WORK IS REQUIRED BY UTILITY CO. ON CONSTRUCTION DRAWINGS.

W. BALANCE ALL SINGLE PHASE LOADS AT PANELBOARDS. THE TOTAL CONNECTED LOAD ON EACH LEG OF THE PANEL SHALL NOT VARY MORE THAN 10 PERCENT. IF NECESSARY EXCHANGE THE CIRCUIT WIRES FROM THE LEGS OF THE PANEL UNTIL THE ABOVE CONDITIONS ARE SATISFIED. RELABEL ANY CIRCUITS AND/OR RECONFIGURE ANY PANEL BOARD DIRECTORIES TO INDICATE THE NEW SCHEME.

X. REPLACE ALL BURNED OUT LAMPS PRIOR TO FINAL ACCEPTANCE.

Y. ELECTRICAL CONTRACTOR SHALL MEGGER TEST EACH MOTOR WINDING BEFORE ENERGIZING THE MOTOR. THE INSULATION RESISTANCE SHALL BE RECORDED BASED ON AMBIENT TEMPERATURE AND VOLTAGE INFORMATION FURNISHED BY OWNER. ELECTRICAL CONTRACTOR SHALL SUBMIT RECORDED INSULATION RESISTANCE AND NOTIFY OWNER OF ALL MOTORS WITH LOW INSULATION RESISTANCE. MOTOR MAY BE TURNED OVER AS REPLACED.

Z. IN ADDITION TO ANY OTHER TESTS HEREIN SPECIFIED, THE SYSTEMS, AFTER COMPLETION, SHALL BE TESTED IN OPERATION FOR AT LEAST FIFTEEN (15) DAYS AND SHOWN TO BE IN SATISFACTORY OPERATING CONDITION.

AA. SHOULD ANY OF THE EQUIPMENT OR APPARATUS FURNISHED BY THE CONTRACTOR REQUIRE THE SERVICE OF A FACTORY REPRESENTATIVE FOR INSTALLATION OR ADJUSTMENT, THE CONTRACTOR SHALL PROVIDE SAME WITHOUT ADDITIONAL COST TO THE OWNER.

BB. WHERE REQUIRED IN PENETRATIONS OF FIRE RATED WALLS, CEILINGS OR FLOORS, ELECTRICAL CONTRACTOR SHALL FURNISH AND INSTALL NELSON FLAMESEAL FIRESTOP PUTTY OR EQUAL FIRESTOP SYSTEM.

CC. SLEEVES THROUGH EXTERIOR WALLS BELOW GRADE SHALL HAVE THE SPACE BETWEEN CONDUIT AND SLEEVE CAULKED WATERTIGHT.

DD. THIS ELECTRICAL CONTRACTOR SHALL BE RESPONSIBLE FOR THE PROPER DIRECTION OF ROTATION OF ALL MOTORS AND SHALL CHANGE CONNECTIONS AS REQUIRED TO PROVIDE FOR PROPER ROTATION.

EE. ELECTRICAL CONTRACTOR SHALL PROVIDE DRAWER WIRING AND LINE VOLTAGE WIRING AND LINE VOLTAGE CONTROL WIRING INDICATED AND COVERED UNDER THE MECHANICAL AND PLUMBING SPECIFICATIONS AND DRAWINGS.

FF. REFER TO MECHANICAL AND PLUMBING DRAWINGS AND SCHEMATIC WIRING DIAGRAMS OF ALL EQUIPMENT. USE MANUFACTURER'S INSTRUCTIONS FOR ACTUAL FIELD CONSTRUCTION.

GG. ELECTRICAL CONTRACTOR SHALL REFER TO MECHANICAL AND PLUMBING DRAWINGS FOR ADDITIONAL ELECTRICAL WORK TO BE INCLUDED IN HIS BID. THIS CONTRACTOR SHALL WIRE BETWEEN PUMPS AND STARTERS. PROVIDE INTERCONNECTING WIRING BETWEEN RELAYS AND SWITCHES AS REQUIRED.

SECTION 16060 - GROUNDING & BONDING

A. FURNISH AND INSTALL A COMPLETE GROUNDING SYSTEM AS SHOWN ON THE DRAWINGS, SPECIFIED HEREIN AND AS REQUIRED BY THE NATIONAL ELECTRICAL CODE, NATIONAL SAFETY CODE AND/OR LOCAL CODES AND ORDINANCES.

B. PROVIDE CONTINUOUS GROUND CONNECTIONS TO ALL EQUIPMENT, DUCTWORK, METAL PIPING, AND STRUCTURAL STEEL. TELEPHONE, INTERCOM, ALARM SYSTEM BRANCHES AND SINGLE CIRCUIT BRANCHES MAY BE 1/2" CONDUIT. EACH ALARM SYSTEM TRUNK SHALL BE 3/4" CONDUIT MIN TO ALARM CONTROL. METAL OR PLASTIC BUSHINGS SHALL BE INSTALLED ON ALL CONNECTIONS 1 1/4" OR LARGER.

C. THE CONTRACTOR SHALL PROVIDE A GROUND ELECTRODE SYSTEM AS SHOWN ON THE DRAWINGS AND PER ELECTRICAL UTILITY REQUIREMENTS, INCLUDING TRANSFORMER PAD (IF REQUIRED), CONDUIT, CABLE, DISCONNECTION MEANS AND DEVICES. THE NUMBER OF CONDUCTORS AND DEVICES AND ACCORDING TO APPROPRIATE SECTIONS OF THE N.E.C. BOXES SHALL HAVE KNOCK OUTS FOR CONDUIT TERMINATIONS AND MOUNTING LUGS AND EARS FOR COVERS. BOXES ARE TO BE RIGIDLY SECURED IN POSITION TRUE AND SQUARE.

D. CONCEALED OUTLET BOXES SHALL NOT BE LESS THAN FOUR INCHES SQUARE OR RECTANGULAR AND PROVIDED WITH THE PROPER SIZE KNOCKOUTS FOR THE CONDUITS USED. ALL UNUSED KNOCKOUTS MUST REMAIN CLOSED. BOXES IN PLASTER CONSTRUCTION SHALL BE PROVIDED WITH APPROVED COVERS OR PLASTER RINGS.

E. ALL OUTLETS OCCURRING IN OTHER THAN PLASTER CONSTRUCTION SHALL BE PROVIDED WITH FLUSH RECTANGULAR SQUARE-CORNERED BOXES MADE FOR THE PURPOSE, WHERE DEVICES ARE GANGED, GANG-TYPE BOXES SHALL BE INSTALLED.

F. BOXES SHALL BE OF UNIT CONSTRUCTION AND OF SIZE REQUIRED BY THE N.E.C. FOR THE NUMBER OF DEVICES SHOWN. THE SHAPE OF THE BOX SHALL BE SUCH AS TO PERMIT SURFACING MATERIALS TO BE CUT IN STRAIGHT LINES AND TO FIT CLOSELY AROUND THE BOX. THE BOX SHALL BE SO PLACED THAT THE COVER PLATE WILL BE FLUSH WITH THE FINISHED WALL SURFACE.

G. ALL BOXES FOR LIGHTING OUTLETS SHALL BE ROUND OR OCTAGONAL AND PROVIDED WITH FIXTURE STUDS OF A SIZE SUITABLE FOR THE WEIGHT OF THE FIXTURE TO BE SUPPORTED. IN NO CASE SHALL THE FIXTURE STUD BE LESS THAN 3/8 INCH. THE STUD SHALL BE OF INTEGRAL CONSTRUCTION WITH THE BOX.

H. OUTLET BOXES USED FOR EXTERIOR OUTLETS OR FOR EXPOSED INTERIOR CONDUIT RUNS SHALL BE OF CAST RUST-RESISTING METAL. GASKETED "IN-USE" COVERS SHALL BE PROVIDED WHERE THE OUTLET IS EXPOSED TO WEATHER OR MOISTURE.

I. JUNCTION AND PULL BOXES SHALL BE FABRICATED FROM GALVANIZED METAL OF CODE GAUGE THICKNESS AND BE OF AMPLE SIZE TO PROPERLY ACCOMMODATE THE CONDUCTORS PASSING THROUGH OR CONTAINED THEREIN. FLUSH MOUNTED BOXES SHALL BE FITTED WITH A COVER WHICH OVERLAPS THE BOX ALL AROUND.

J. CONDUITS TERMINATING IN STEEL BOXES SHALL BE PROVIDED WITH APPROVED LOCKNUTS INSIDE AND OUTSIDE OF THE BOX WITH AN APPROVED BUSHING. ALL CONDUIT TO BE SQUARE CUT AND REAMED TO REMOVE BURRS.

K. RIGID STEEL CONDUITS IN WET, DAMP OR WEATHERPROOF (WP) AREAS SHALL HAVE ALL COUPLINGS SEALED WITH WEATHERPROOF SEALING COMPOUND.

L. CONDUITS SHALL BE SECURELY SUPPORTED FROM BUILDING STRUCTURE AT MAXIMUM 8 FT. INTERVALS FOR 3/4" AND 1" CONDUITS AND ON 10 FT. CENTERS FOR LARGER CONDUITS, BY APPROVED PIPE HANGERS ON SUPPORTING ASSEMBLIES, ALL AS PER N.E.C. REQUIREMENTS.

M. BOXES SHALL NOT BE PLACED IN LOCATIONS MADE INACCESSIBLE BY PIPING, DUCTS, CONDUITS OR OTHER EQUIPMENT. JUNCTION AND PULL BOXES SHALL HAVE ATTACHED TO THEM A MANUFACTURER'S LABEL, UNDERWRITER'S LABEL AND AN INDICATION OF THE METAL GAUGE. BOXES SHALL BE INSTALLED EVERY 100 FEET IN ALL MAJOR FEEDERS.

N. COORDINATE ALL WORK WITH OTHER TRADES.

O. ALL CONDUIT AND EQUIPMENT SHALL BE FIRMLY INSTALLED TO PREVENT SWAYING, VIBRATING, OR SAGGING BY STEEL HANGERS OR FABRICATED SUPPORTS OF APPROVED DESIGN.

SECTION 16080 - ELECTRICAL IDENTIFICATION

A. ALL SWITCHGEAR, PANELS, TIME CLOCKS, THERMAL OVERLOAD FAN SWITCHES, EQUIPMENT CONTROL SWITCHES, CIRCUIT BREAKERS, SAFETY SWITCHES, MOTOR STARTERS AND SIMILAR ITEMS SHALL BE IDENTIFIED BY NAME, FUNCTION AND/OR CONTROL.

B. NAMEPLATES SHALL BE AT LEAST 1" X 3" WITH CHARACTERS NOT LESS THAN 1/4", THEY SHALL BE MADE UP OF TWO LAMINATED BLACK PLASTIC SHEETS BONDED WITH A MIDDLE SHEET OF WHITE PLASTIC AND ENGRAVED CHARACTERS ENGRAVED IN ONE BLACK SHEET TO THE DEPTH OF THE WHITE PLASTIC. SECURELY FASTEN LABELS SO THAT THEY ARE VISIBLE AND AS INDICATED ON THE DRAWINGS.

SECTION 16120 - CONDUCTORS AND CABLE:

A. ALL WIRING SHALL BE IN CONDUIT. ROMEX AND DIRECT BURIAL WIRING SYSTEMS ARE NOT ACCEPTABLE. MC AND AC CABLE ARE ALLOWED INDOORS WHERE CONCEALED IN FINISHED DUST AND DIRT PROOF STRUCTURE WHERE NEATLY ATTACHED TO STRUCTURAL MEMBERS IN JOIST SPACE.

B. ALL CONDUCTORS SHALL BE A PURE COPPER 98% WITH INSULATION RATED AT 600 VOLTS MINIMUM. INSULATION RATING FOR BRANCH CIRCUIT #10 AND #12 AWG - TYPE "THWN" 75 DEGREES CENTIGRADE. BRANCH CIRCUIT #8 OR LARGER - TYPE "THWN" OR "THHN" 75 DEGREES CENTIGRADE. FEEDERS (MOTOR OR PANEL) - TYPE "THWN" OR "THHN" 75 DEGREES CENTIGRADE. RUNS WITHIN CONTINUOUS LIGHT FIXTURES - TYPE "THHN" 90 DEGREES CENTIGRADE.

C. MINIMUM WIRE SIZE - 20 AMP BRANCH CIRCUITS SHALL BE #12 UP TO 75 FEET AND #10 OVER 75 FEET. DISTANCE TO BE MEASURED FROM THE PANEL-BOARD CIRCUIT BREAKER TO THE FIRST OUTLET.

D. COLOR CODING (UNLESS REQUIRED OTHERWISE BY LOCAL CODE):

1. 208Y/120 VOLT CIRCUITS SHALL BE COLOR CODED AS FOLLOWS: A PHASE BLACK, B PHASE RED, C PHASE BLUE, NEUTRAL - WHITE.
2. 480Y/277 VOLT CIRCUITS SHALL BE COLOR CODED AS FOLLOWS: A PHASE BROWN, B PHASE ORANGE, C PHASE YELLOW, NEUTRAL - GRAY.

E. BRANCH WIRING SHALL BE INSTALLED ON ALL CIRCUITS IN RELAY AND CONTACTOR ENCLOSURES.

F. LOW VOLTAGE WIRING SHALL BE OF SIZE AND INSULATION RECOMMENDED BY THE MANUFACTURER OF THE EQUIPMENT BEING SERVED.

G. THE CONTRACTOR SHALL PROVIDE SERVICE ENTRANCE CONDUCTORS AS SHOWN ON THE DRAWINGS AND PER ELECTRICAL UTILITY REQUIREMENTS, INCLUDING TRANSFORMER PAD (IF REQUIRED), CONDUIT, CABLE, DISCONNECTION MEANS AND DEVICES. THE NUMBER OF CONDUCTORS AND DEVICES AND ACCORDING TO APPROPRIATE SECTIONS OF THE N.E.C. BOXES SHALL HAVE KNOCK OUTS FOR CONDUIT TERMINATIONS AND MOUNTING LUGS AND EARS FOR COVERS. BOXES ARE TO BE RIGIDLY SECURED IN POSITION TRUE AND SQUARE.

H. THE APPROXIMATE SCHEMATIC LOCATION OF CEILING, SWITCH AND OTHER OUTLETS IS GIVEN ON THE DRAWINGS. THE EXACT LOCATIONS SHALL BE DETERMINED IN THE BUILDING AS THE WORK PROGRESSES. THIS CONTRACTOR SHALL VERIFY ALL DOOR SWINGS AT JOB SITE. IN NO CASE SHALL SWITCHES BE LOCATED BEHIND DOOR SWINGS. ALL SWITCH LOCATIONS SHALL BE CHANGED AT CONTRACTOR'S EXPENSE. THE CONTRACTOR SHALL ALSO FIELD VERIFY ALL EQUIPMENT LOCATIONS AND ADJUST DEVICE AND OUTLET LOCATIONS TO AVOID INACCESSIBILITY. CONTRACTOR TO RELOCATE INACCESSIBLE OUTLETS AT NO ADDITIONAL COST TO OWNER.

I. UNLESS OTHERWISE INDICATED, OR OTHERWISE DECIDED AT THE SITE, OUTLET BOXES IN WALLS SHALL BE LOCATED WITH CENTERLINE AT ELEVATION ABOVE THE FINISHED FLOOR AS SHOWN ON TABLE:

1. WALL SWITCH OUTLETS 4'-0"
2. CONVENIENCE OUTLETS 1'-6"
3. SPECIAL OUTLETS ABOVE COUNTERTOPS
4. TELEPHONE OUTLETS 1'-6"

J. THE PROJECT MANAGER AND OWNER RESERVE THE RIGHT TO CHANGE THE LOCATION OF ANY OUTLET, BEFORE IT HAS BEEN INSTALLED, WITHOUT ADDITIONAL COST TO OWNER.

K. ALL SWITCHES MOUNTED VERTICALLY SHALL HAVE THE "ON" POSITION AT THE TOP AND ALL HORIZONTALLY MOUNTED SWITCHES SHALL HAVE THE "ON" POSITION AT THE LEFT.

SECTION 16200 - ELECTRICAL SERVICE

A. THE BUILDING SERVICE SHALL BE 208Y/120 VOLT, 3 PHASE, 4 WIRE OR AS NOTED ON THE DRAWINGS. SERVICE ENTRANCE EQUIPMENT SHALL BE LISTED BY UNDERWRITERS LABORATORIES AND METERING REQUIREMENTS OF THE LOCAL POWER COMPANY, AND INSTALL IN ACCORDANCE WITH THEIR CRITERIA.

B. SWITCHGEAR PANELS