LIGHTING CONTROL EQUIPMENT LEGEND		
ITEM	DESCRIPTION	MODEL
LCP1A	LOW VOLTAGE RELAY PANEL WITH 24 RELAYS	SOFTSWITCH 128 WITH (24) 20A/1P RELAYS AND BMS INTEGRATION (XPS24)
LCP1B	LOW VOLTAGE RELAY PANEL WITH 24 RELAYS	SOFTSWITCH 128 WITH (24) 20A/1P RELAYS AND BMS INTEGRATION (XPS24)
LCP2	LOW VOLTAGE RELAY PANEL WITH 24 RELAYS	SOFTSWITCH 128 WITH (24) 20A/1P RELAYS AND BMS INTEGRATION (XPS24)
SLV	LOW VOLTAGE 2-BUTTON ON/OFF SWITCH	TOUCH 2-BUTTON WALL STATION ON/OFF CONTROL (SO-2BN-WH)
SWITCH PE	EXTERIOR PHOTOCELL	PCO 2400
--- ----- ---	CAT 5 LOW VOLTAGE CONTROL CABLE	

NOTES:

1. A COMPLETE LIGHTING CONTROL SYSTEM SHALL BE PROVIDED AND INSTALLED BY THE ELECTRICAL CONTRACTOR AS MANUFACTURED BY LUTRON. COORDINATE ALL EQUIPMENT AND WIRING REQUIREMENTS WITH LUTRON PRIOR TO PROJECT START UP. THE LIGHTING CONTROL SYSTEM WILL PROVIDE AUTOMATED ON/OFF CONTROL OF SELECTED LIGHT FIXTURES AND EXTERIOR LIGHTS. ALL LOW VOLTAGE SWITCHES WILL ACT AS OVERRIDE SWITCHES IN THE EVENT LIGHTS NEED TO BE ON AFTER NORMAL BUSINESS HOURS. ALL EXTERIOR LIGHTING WILL BE EITHER PHOTOCELL ON/OFF OR PHOTOCELL ON/TIMECLOCK OFF CONTROLLED.

COORDINATE EXACT LUTRON EQUIPMENT AND WIRING REQUIREMENTS WITH MANUFACTURER PRIOR TO PRICING.



1 LIGHTING CONTROL WIRING DIAGRAM
DIAGRAMMATIC

LIGHTING CONTROL PANEL LCP2 RELAY SCHEDULE			
CIRCUIT NUMBER	RELAY NUMBER	AREA	CONTROL
EL2-1	1	HALL 216 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-1	2	JANITOR 207 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-1	3	MEN SHOWER 206 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-3	4	MEN TOILET 207 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-3	5	WOMEN SHOWER 204 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-3	6	WOMEN TOILET 203 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-3	7	JANITOR 208 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-5	8	STORAGE 223 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
EL2-5	9	KITCHEN 212 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
	10	SPARE	
	11	SPARE	
	12	SPARE	
	13	SPARE	
	14	SPARE	
	15	SPARE	
	16	SPARE	
	17	SPARE	
	18	SPARE	
	19	SPARE	
	20	SPARE	
	21	SPARE	
	22	SPARE	
	23	SPARE	
	24	SPARE	

ALL TIME SETTINGS SHALL BE APPROVED BY OWNER.

LIGHTING CONTROL PANEL LCP1B RELAY SCHEDULE			
CIRCUIT NUMBER	RELAY NUMBER	AREA	CONTROL
ELIB-1	1	BAG HOLD 112 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	2	LOCKER 115 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	3	CLOSET 114 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	4	OFFICE/SUP 110 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	5	WAC OFFICE 109 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	6	HALL LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-1	7	LACTATION 104 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	8	[illegible] 106 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	9	MOTHERS TOILET LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	10	MOTHERS TOILET LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	11	CATER 101 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	12	JANITOR 102 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-3	13	TOILET 103 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-7	14	SEC WAIT 133 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-7	15	HALL 138 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-9	16	SCREEN 134 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-9	17	SSCP 133 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIB-9	18	OFFICE 131 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
	19	SPARE	
	20	SPARE	
	21	SPARE	
	22	SPARE	
ELIB-7	23	HALL 149 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
	24	SPARE	

ALL TIME SETTINGS SHALL BE APPROVED BY OWNER.

LIGHTING CONTROL PANEL LCP1A RELAY SCHEDULE			
CIRCUIT NUMBER	RELAY NUMBER	AREA	CONTROL
ELIA-1	1	BAG CLAIM 166 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-1	2	WOMEN 167 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-1	3	MEN 164 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-3	4	PRIMARY 163 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	5	OFFICE 157 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	6	SUP 160 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	7	HALL 149 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	8	BREAK 152 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	9	SEIZ 151 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-5	10	FILE 150 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-7	11	MALE LOCKER 153 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-7	12	FEMALE LOCKER 154 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-7	13	LACTATION 155 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-7	14	TLT 156 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-9	15	HALL 145 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
ELIA-9	16	SECONDARY 161 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
	17	SPARE	
	18	SPARE	
	19	SPARE	
ELIA-9	20	LAB 144 LTS	LOW VOLTAGE SWITCH ON/TIMECLOCK 11:00 PM OFF
	21	SPARE	
	22	SPARE	
	23	SPARE	
	24	SPARE	

ALL TIME SETTINGS SHALL BE APPROVED BY OWNER.

DIMMING PANELBOARD SCHEDULE - "DIM-EX"

MAIN: 125A M.L.O. — VOLTAGE: 480/277 — PHASE: 3 — WIRE: 4 — MOUNTING: SURFACE — A.I.C. — NOTES:

CKT	BKR AMP	TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	NTR'L	A/C	HTG	KITC	MISC	PHASE	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT
1	20	1	1	#12	3/4"	RAMP LTS - R1	0.5							A	PEDESTRIAN LTS - F2	3/4"	#2	1	20	2
3	20	1	1	#12	3/4"	RAMP LTS - R1	0.5							B	PEDESTRIAN LTS - F3	3/4"	#2	1	20	4
5	20	1	1	#12	3/4"	SPARE								A	WEST FACADE LTS - F4	3/4"	#2	1	20	6
7	20	1	1	#12	3/4"	SPARE								B	FRONT FACADE LTS - F5	3/4"	#2	1	20	8
9	20	1	1	#12	3/4"	SPARE								A	EAST FACADE LTS - F6	3/4"	#2	1	20	10
11	20	1	1	#12	3/4"	SPARE								B	ARRIVE FACADE LTS - F7	3/4"	#2	1	20	12
13	20	1	1	#12	3/4"	SPARE								A	ARRIVE ENTRY LTS - F8	3/4"	#2	1	20	14
15	20	1	1	#12	3/4"	SPARE								B	SIDE WALK LTS - F9	3/4"	#2	1	20	16
LIGHTING (KVA):							5.8	1.6	0.5	0.0	0.0	0.0	0.0		CONNECTED LOAD (KVA):					13
RECEPTACLES (KVA):							0.0								DEMAND LOAD:					7.3
MOTORS (KVA):							0.0							PHASE A	9.4					
A/C (KVA):							0.0							PHASE B	7.8					7.8
HEATING (KVA):							0.0							PHASE C	9.2					9.2
KITCHEN (KVA):							0.0								KVA	AMPS				
MISCELLANEOUS (KVA):							0.0													

NOTES:

1. LUTRON DIMMING PANEL. SEE SHEET E-206L FOR DETAILS.

DIM-EX DEMAND CALCS							
LIGHTING		5.80	KVA X	125	%	=	7.3 KVA
RECEPTACLE	TOTAL	0.00	KVA				
	1ST	10.00	KVA X	100	%	=	0.0 KVA
	REMAIN	0.00	KVA X	50	%	=	0.0 KVA
MOTORS		0.00	KVA X	100	%	=	0.0 KVA
A/C		0.00	KVA X	100	%	=	0.0 KVA
HEATING		0.00	KVA X	100	%	=	0.0 KVA
FUTURE		-----	KVA X	100	%	=	0.0 KVA
KITCHEN		0.00	KVA X	65	%	=	0.0 KVA
MISCELLANEOUS		0.00	KVA X	100	%	=	0.0 KVA
TOTAL	=	5.8 amps				=	7.3 KVA

DIMMING PANELBOARD SCHEDULE - "DIM-IN"

MAIN: 125A M.L.O. — VOLTAGE: 480/277 — PHASE: 3 — WIRE: 4 — MOUNTING: SURFACE — A.I.C. — NOTES:

CKT	BKR AMP	TRIP	POLE	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MISC	A/C	HTG	KITC	MISC	DESCRIPTION	COND SIZE	WIRE SIZE	POLE	BKR TRIP	CKT
1	20	1	1	#12	3/4"	MAIN [illegible] & LTS	0.1							CONCESSION PEND LTS	3/4"	#12	1	20	2
3	20	1	1	#12	3/4"	MAIN SEATING & LTS	0.1							CONCESSION DN LTS	3/4"	#12	1	20	4
5	20	1	1	#12	3/4"	MAIN VESTIBULE LTS	0.1							VESTIBULE LTS	3/4"	#12	1	20	6
7	20	1	1	#12	3/4"	MAIN SEATING AREA LTS	0.1							HALL LTS	3/4"	#12	1	20	8
9	20	1	1	#12	3/4"	VESTIBULE LTS	0.1							LOBBY DN LTS	3/4"	#12	1	20	10
11	20	1	1	#12	3/4"	VESTIBULE LTS	0.1							RECEPTION DN LTS	3/4"	#12	1	20	12
13	20	1	1	#12	3/4"	SPARE	0.1							SPACE	3/4"	#12	1	20	14
15	20	1	1	#12	3/4"	SPARE	0.0							SPACE	3/4"	#12	1	20	16
17	20	1	1	#12	3/4"	HIGH CLG SUP LTS	0.2							SPACE	3/4"	#12	1	20	18
19	20	1	1	#12	3/4"	HIGH CLG SUP LTS	0.2							SPACE	3/4"	#12	1	20	20
21	20	1	1	#12	3/4"	HIGH CLG SUP LTS	0.6							SPACE	3/4"	#12	1	20	22
23	20	1	1	#12	3/4"	HIGH CLG SUP LTS	0.6							SPACE	3/4"	#12	1	20	24
LIGHTING (KVA):							5.8	1.2	0.0	0.0	0.0	0.0	0.0	CONNECTED LOAD (KVA):					5.8
RECEPTACLES (KVA):							0.0							DEMAND LOAD (KVA):					4.3
MOTORS (KVA):							0.0					PHASE A	3	23.8					
A/C (KVA):							0.0					PHASE B	2	17.5	CONNECTED LOAD (AMPS):					16.1
HEATING (KVA):							0.0					PHASE C	1	22.5	DEMAND LOAD (AMPS):					12.1
FUTURE (KVA):							0.0						KVA	AMPS						
MISCELLANEOUS (KVA):							0.0													

NOTES:

1. LUTRON DIMMING PANEL. SEE SHEET E-206L FOR DETAILS.

DIM-IN DEMAND CALCS							
LIGHTING		5.80	KVA X	125	%	=	7.3 KVA
RECEPTACLE	TOTAL	0.00	KVA				
	1ST	10.00	KVA X	100	%	=	0.0 KVA
	REMAIN	0.00	KVA X	50	%	=	0.0 KVA
MOTORS		0.00	KVA X	100	%	=	0.0 KVA
A/C		0.00	KVA X	100	%	=	0.0 KVA
HEATING		0.00	KVA X	100	%	=	0.0 KVA
FUTURE		-----	KVA X	100	%	=	0.0 KVA
KITCHEN		0.00	KVA X	65	%	=	0.0 KVA
MISCELLANEOUS		0.00	KVA X	100	%	=	0.0 KVA
TOTAL	=	28.1 amps				=	7.3 KVA

Order Plans @ WWW.Line.com

WIL-1702-ID206L.dwg, Plotted By: rwr
Dec 17, 2018 - 10:38am

SABER ENGINEERING
2923 South Tryon Street Suite 280
Charlotte, North Carolina 28203
tel 704.373.0068
MECHANICAL ELECTRICAL PLUMBING

NORTH CAROLINA PROFESSIONAL ENGINEER SEAL 032787 DAVID M. MORRISON

DEC 7, 2018
CAD NUMBER = C-2130

WILSON AIR CENTER
NORTH TERMINAL
HCD [illegible]-018
CHARLOTTE DOUGLAS INTERNATIONAL AIRPORT
5530 WRIS FIELD DRIVE
CHARLOTTE, NC 28208

ARCHITECT
THE WILSON GROUP
P O BOX 5610
CHARLOTTE, NC 28299
(704) 331-9747

CIVIL ENGINEER
TALBERT, BRIGHT & ELLINGTON
3525 WHITEHALL PARK DRIVE, SUITE 210
CHARLOTTE, NC 28273
(704) 426-6070 FIRM NO.: C-1163

STRUCTURAL ENGINEER
STEWART
101 N. TRYON ST., SUITE 1400
CHARLOTTE, NC 28202
(704) 909-3523 FIRM NO.: C-1051

MECHANICAL, ELECTRICAL, PLUMBING & FIRE PROTECTION ENGINEER
SABER ENGINEERING
2923 S. TRYON ST., SUITE 280
CHARLOTTE, NC 28203
(704) 373-0068 FIRM NO.: C-2130

LANDSCAPE ARCHITECT
URBAN DESIGN PARTNERS
1318-E6 CENTRAL AVENUE
CHARLOTTE, NC 28205
(704) 334-3303 FIRM NO. C-TBD

COMMUNICATIONS INFRASTRUCTURE
DB CONSULTING
246 LOVES FARM ROAD
BLACKSBURG, SC 29702
(704) 497-7228 FIRM NO. C-TBD

REVISIONS

DATE DECEMBER 7, 2018
PROJECT NUMBER 9197-000

SHEET TITLE
LIGHTING CONTROL DETAILS

SHEET NUMBER
E-208L