



CONSULTANT

A REMODEL FOR:
KROGER GA-214
3139 US HWY 278, N.E.
COVINGTON, GA

PROJECT: KROGER ATLANTA
DATE: 04-01-2019
CONSTRUCTION SET

ELECTRICAL SYMBOLS AND GENERAL NOTES

Table with columns: MARK, DATE, DESCRIPTION

PROJECT NO: 19085
CIV DWG FILE: GA-214.E0.1
DRAWN BY: WSM
CHK'D BY: HCK

E0.1
SHEET NO.

ELECTRICAL NOTES:

- 1. ELECTRICAL WORK SHALL BE IN ACCORDANCE WITH THE MOST RECENT ADOPTED NFPA, NATIONAL ELECTRIC CODE, AND LOCAL CODES.
2. ALL MATERIALS, DEVICES, APPLIANCES, AND EQUIPMENT SHALL BE NEW AND LABEL LISTED BY AN APPROVED THIRD PARTY TESTING AGENCY APPROVED BY THIS STATE.
3. WIRING SHALL BE COPPER SINGLE CONDUCTORS. MINIMUM WIRE SIZE IS #12 AWG. CONDUCTORS #8 AND LARGER SHALL BE TYPE THHN OR THWN STRANDED. #12 THRU #10 SHALL BE THIN SOLID. WIRE TO LIGHT FIXTURES SHALL BE AS REQUIRED BY U.L. LABEL. COLOR CODE CONDUCTORS.
4. CONDUITS SHALL BE STEEL INDOOR & OUTDOOR. SCHEDULE 40 PVC SHALL BE ALLOWED ONLY BELOW FLOOR SLAB OR GRADE. EMT SHALL BE USED FOR SIZES 1/2" THROUGH 3 1/2".
5. CONNECT ALL HVAC, PLUMBING AND OTHER CONTRACTOR OR OWNER FURNISHED EQUIPMENT. VERIFY ALL LOCATIONS OF HVAC, PLUMBING AND OTHER CONTRACTOR OR OWNER FURNISHED EQUIPMENT PRIOR TO ROUGH-IN. CHECK EQUIPMENT SHOP DRAWINGS AND COORDINATE WITH HVAC, PLUMBING, AND ALL OTHER EQUIPMENT CONTRACTORS FOR DISCONNECT SWITCH, CONDUIT, WIRING REQUIREMENTS (THIS INCLUDES VERIFYING IF A NEUTRAL CONDUCTOR IS REQUIRED), FUSE AND BREAKER SIZES, WIRING OF STARTERS, VOLTAGE REQUIREMENTS, AND LOCATIONS. PROVIDE A TIMER FOR ALL PLUMBING RECIRCULATION PUMPS. MAKE ALL NECESSARY REVISIONS TO THESE ITEMS AT NO ADDITIONAL COST TO THE OWNER.
6. THE ELECTRICAL CONTRACTOR SHALL VISIT THE JOBSITE PRIOR TO SUBMISSION OF BID TO FAMILIARIZE HIMSELF WITH THE CONDITIONS UNDER WHICH THE WORK WILL BE PERFORMED AND THE EXTENT OF WORK REQUIRED. INCLUDE ALL COST IN BID PRICE.
7. SUPPORT ALL CONDUITS WITH STRAPS AND CLAMPS. RUN ALL CONDUIT PARALLEL, OR PERPENDICULAR TO BUILDINGS.
8. ELECTRICAL DEMOLITION, RELOCATION OF EXISTING EQUIPMENT, CUTTING AND PATCHING REQUIRED FOR THE INSTALLATION OF THIS NEW WORK IS THE RESPONSIBILITY OF THE ELECTRICAL CONTRACTOR. THE EXTENT OF THE WORK REQUIRED SHALL BE DETERMINED DURING THE PRE-BID JOBSITE VISIT.
9. ALL ELECTRICAL SYSTEMS AND EQUIPMENT SHALL COMPLY WITH ARTICLE 165 OF THE INTERNATIONAL BUILDING CODE.
10. PROVIDE MIN. 24" HORIZONTAL SEPARATION BETWEEN BOXES INSTALLED IN OPPOSITE SIDES OF A SAME WALL AS INDICATED IN N.E.C. 300.21.
11. ALL DISCONNECTS SHALL BE HEAVY DUTY RATED, WITH ARC GUARD, AND SHALL HAVE A MECHANICAL INTERLOCK TO PREVENT THE DOOR FROM BEING OPENED, WITHOUT OPERATING THE INTERLOCK. THE MECHANICAL INTERLOCK SHALL ALSO PREVENT ACTIVATING THE SWITCH WHEN THE DOOR IS OPEN. THE MECHANICAL INTERLOCK SHALL BE DEFEATABLE BY A SPECIAL TOOL, AND SHALL BE U.L. LISTED AS PART OF THE DISCONNECT. EXTERNAL OPERATING HANDLE SHALL INDICATE ON AND OFF POSITION AND SHALL HAVE LOCK-OPEN PADLOCKING PROVISIONS.
12. SERVICE GROUND IMPEDANCE SHALL BE MEASURED, AND SHALL BE 5 OHMS OR LESS. IF UPON MEASUREMENT, SERVICE GROUND READING EXCEEDS 5 OHMS, THEN ADDITIONAL GROUND RODS SHALL BE DRIVEN TO REDUCE READING TO 5 OHMS OR LESS. NOTIFY ENGINEER OF FINAL SERVICE GROUND MEASUREMENT.
13. BREAKERS THAT FEED CONTACTORS AND TIME CLOCKS TO BE CURRENT LIMITING TO ALLOW A MAXIMUM LET THRU OF 22K AIC WITH 80K AIC AVAILABLE.
14. ALL TERMINATIONS ON PANELS SHALL HAVE DUAL RATED 60°C/75°C LUGS.
15. PROVIDE INTERNAL OR EXTERNAL DISCONNECTING MEANS FOR EACH FLUORESCENT LUMINAIRE THAT UTILIZES DOUBLE-ENDED LAMPS AND CONTAINS BALLASTS THAT CAN BE SERVICED IN PLACE TO COMPLY WITH N.E.C. 410.80(B).
16. ELECTRICAL CONTRACTOR TO PROVIDE SEPARATE NEUTRAL FOR EACH BRANCH CIRCUIT TO MEET NEC 200.4. MULTIWIRE BRANCH CIRCUITS, SHARED NEUTRALS WILL NOT BE ALLOWED. FOR FURNITURE BRANCH CIRCUITS, ALL FURNITURE SHALL BE WIRED PER N.E.C. 605. FURNITURE BRANCH CIRCUITS SHALL BE FED WITH SINGLE POLE BREAKERS. INSTALL U.L. APPROVED HANDLE TIES ON SINGLE POLE BREAKERS AS REQUIRED FOR TWO AND THREE CIRCUITS FEEDING FURNITURE. THE ELECTRICAL CONTRACTOR SHALL VERIFY THE FURNITURE SYSTEM IN THE FIELD PRIOR TO CONNECTION AND PROVIDE ADDITIONAL NEUTRAL AND/OR GROUND CONDUCTORS AS REQUIRED. ALL OTHER NEUTRAL CIRCUITS TO HAVE SEPARATE NEUTRAL. LEVEL OF HANDLE TIES, FOR CONDITIONS WHERE ONE OR MORE EXISTING LIGHT FIXTURES OR RECEPTACLES ARE BEING RELOCATED, THE ENTIRE CIRCUIT MUST BE RENOVATED TO MEET NEC 200.4. THIS MEANS THE ELECTRICAL CONTRACTOR MUST PROVIDE A SEPARATE NEUTRAL FOR EACH REVISED CIRCUIT, OR PROVIDE A HANDLE TIE WITH THE CIRCUITS IN WHICH THIS RENOVATED CIRCUIT SHARES A NEUTRAL. IF THE ELECTRICAL CONTRACTOR CHOOSES TO USE HANDLE TIES IN LEVEL OF SEPARATE NEUTRALS, THIS MUST BE FIELD MARKED BY SHARED NEUTRAL CIRCUITS BEING RENOVATED ARE CONTINUOUS WITHIN THE PANEL, AND ADJUST THE BREAKERS ACCORDINGLY WITHIN THE PANEL, SO THAT HANDLE TIES CAN BE INSTALLED. THIS MUST BE DONE PRIOR TO BID AND SHALL BE INCLUDED IN THE ELECTRICAL CONTRACTOR'S BID PRICE.
17. SERVICE CONDUCTORS SHALL CONFORM TO N.E.C. 230.6.
18. ALL METAL HALIDE BALLASTS SHALL BE PULSE START TYPE.
19. ALL TELECOMMUNICATIONS CONDUIT, SLEEVES, OR PATHWAYS ARE TO BE LONG KEEPING THROUGH CONDUITS (BENDING POINTS) ARE TO BE INSTALLED PER MANUFACTURERS AND TELECOM CONTRACTORS RECOMMENDATIONS.
20. THE ELECTRICAL CONTRACTOR SHALL FIELD SURVEY THE INTERIORS OF ALL PANELS AND SWITCHGEAR IN WHICH BREAKERS ARE BEING INSTALLED, AND VERIFY THAT ALL INTERIOR BUSSING AND FRAMES ARE AVAILABLE PRIOR TO SUBMISSION OF BID. ANY ADDITIONAL BUSSING REQUIRED WITHIN PANELS AND SWITCHGEAR SHALL BE INCLUDED IN BID PRICE.
21. NO OPEN FLAME DEVICES SHALL BE UTILIZED TO BEND PVC CONDUIT. ALL HEATING DEVICES SHALL BE ENCLOSED FLAME HEAT GUN OR HEAT ROLLER, NO TORCHES. ALL HEATING METHODS MUST BE APPROVED BY ELECTRICAL ENGINEER PRIOR TO INSTALLATION. ANY CONDUIT THAT HAS BEEN HEATED TO WHERE PVC IS DAMAGED OR DISCOLORED SHALL BE REMOVED AND REPLACED AT NO ADDITIONAL COST.
22. ALL BALLASTS IN FLUORESCENT LIGHT FIXTURES THAT ARE CONTROLLED BY OCCUPANCY SENSORS ARE TO BE PROGRAM START BALLASTS.
23. ALL BREAKERS THAT FEED TRANSFORMERS THAT ARE NOT LOCATED IN THE SAME ROOM AS THE TRANSFORMER ARE TO HAVE A PERMANENT BREAKER LOCK AND THE LOCATION OF THE BREAKER SHALL BE FIELD MARKED ON THE TRANSFORMER AS PER NEC 450.4.
24. AS PER N.E.C. 230.95 (C), THE PERFORMANCE TEST REPORT SHALL BE PROVIDED FOR AUTHORITY HAVING JURISDICTION, A41 AT THE TIME OF INSPECTION.

FIRE/SECURITY ALARM SYMBOL SCHEDULE

Table with columns: SYMBOL, DESCRIPTION. Includes symbols for smoke detector, fire alarm pull station, fire alarm strobe, fire alarm horn/strobe, fire alarm horn/strobe ceiling mounted, fire alarm strobe ceiling mounted, fire/security alarm connection to delay egress hardware, remote security sounder, security door contact, security/fire alarm contact/connection for specified equipment, security alarm motion sensor, security alarm control panel, fire alarm control panel, sprinkler flow switch, sprinkler tamper switch.

NOTE: NOT ALL SYMBOLS WILL BE USED FOR THIS PROJECT

ELECTRICAL SYSTEM AND EQUIPMENT

Method of Compliance: Energy Code: ASHRAE 90.1: Lighting schedule (each fixture type): Additional Prescriptive Compliance: 508.2.1 More Efficient Mechanical Equipment, 508.2.2 Reduced Lighting Power Density, 508.2.3 Energy Recovery Ventilation Systems, 508.2.4 Higher Efficiency Service Water Heating, 508.2.5 On-Site Supply of Renewable Energy, 508.2.6 Automatic Daylighting Control Systems

SYMBOL SCHEDULE

Table with columns: SYMBOL, DESCRIPTION. Includes symbols for distribution panelboard, conduit run concealed in ceiling or in wall, conduit run concealed in floor or wall, circuit run home, troffer type lighting fixture, emergency battery pack, strip lighting fixture, wall or ceiling mtd. lighting fixture, track lighting, mono point track head, photoluminescent exit sign, single pole, double pole, three way, fractional hp manually operated motor starter, duplex, ground receptacle, same as above except mounted in wp-08 weatherproof enclosure, same as above except mounted above table or counter, same as above except ground fault type, isolated ground receptacle, ceiling mounted or cord drop receptacle, flush mounted floor box with duplex receptacle, dmvdr, and trim, flush mounted floor box with quad receptacle, dmvdr, and trim, special use receptacle, voltage, phase and ampere based on load served.

NOTE: NOT ALL SYMBOLS WILL BE USED FOR THIS PROJECT

Order Plans