PANEL: 'LP1B' SEC 1 BUS AMP: 400 AMPS MAIN BREAKER: 400 A MLO
MOUNTING: SURFACE PHASE: 3 WIRE: 4 VOLTAGE: 208Y120 AIC: 65,000

CKT	CIRCUIT DESCRIPTION	BREAKER P	BREAKER AMP	WIRE NO	WIRE SIZE	GND SIZE	COND	KVA/PH A	KVA/PH B	KVA/PH C	KVA/PH A	KVA/PH B	KVA/PH C	COND	GND SIZE	WIRE SIZE	WIRE NO	BREAKER AMP	BREAKER P	CIRCUIT DESCRIPTION	CKT
1	WATER FOUNTAIN	1	20	2	12	12	3/4	1.5			0.6			3/4	12	12	2	20	1	GENERAL RECEPT.	2
3	SERVER RECEPT.	1	20	2	12	12	3/4		0.8			0.8		3/4	12	12	2	20	1	SERVER RECEPT.	4
5	ELEVATOR RECEPT.	1	20	2	12	12	3/4			0.2			0.6	3/4	12	12	2	20	1	RESTROOM RECEPT.	6
7	ELEVATOR RECEPT.	1	20	2	12	12	3/4	0.2			2.0			3/4	10	10	3	30	2	WASHER/DRYER	8
9	FITNESS RM. RECEPT.	1	20	2	12	12	3/4		0.8			2.0									10
11	FITNESS RM. RECEPT.	1	20	2	12	12	3/4			0.6			2.0	3/4	10	10	3	30	2	WASHER/DRYER	12
13	FITNESS RM. RECEPT.	1	20	2	12	12	3/4	0.6			2.0										14
15	FITNESS RM. RECEPT.	1	20	2	12	12	3/4		0.2			0.4		3/4	12	12	2	20	1	RESTROOM RECEPT.	16
17	FITNESS RM. RECEPT.	1	20	2	12	12	3/4			0.4			0.6	3/4	12	12	2	20	1	CORRIDOR RECEPT.	18
19	FITNESS RM. RECEPT.	1	20	2	12	12	3/4	0.4			1.0			3/4	12	12	2	20	1	CONF. RM. RECEPT.	20
21	FITNESS RM. RECEPT.	1	20	2	12	12	3/4		0.2			0.8		3/4	12	12	2	20	1	CONF. RM. RECEPT.	22
23	EXTERIOR RECEPT.	1	20	2	12	12	3/4			1.0			0.8	3/4	12	12	2	20	1	CONF. RM. RECEPT.	24
25	EXTERIOR RECEPT.	1	20	2	12	12	3/4	0.4			0.6			3/4	12	12	2	20	1	CONF. RM. RECEPT.	26
27	GUEST SUITE LIGHTING	1	20	2	12	12	3/4		0.7			0.7		3/4	12	12	2	20	1	GUEST SUITE LIGHTING	28
29	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			0.2	3/4	12	12	2	20	1	GUEST SUITE RECEPT.	30
31	GUEST SUITE RECEPT.	1	20	2	12	12	3/4	0.2			0.2			3/4	12	12	2	20	1	GUEST SUITE RECEPT.	32
33	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		0.8			0.8		3/4	12	12	2	20	1	GUEST SUITE RECEPT.	34
35	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.6			0.6	3/4	12	12	2	20	1	GUEST SUITE RECEPT.	36
37	GUEST SUITE RECEPT.	1	20	2	12	12	3/4	0.2			0.2			3/4	12	12	2	20	1	GUEST SUITE RECEPT.	38
39	FACP	1	20	2	12	12	3/4		0.5			1.5		3/4	12	12	2	20	2	ECH-2	40
41	EWH-1	1	20	2	12	12	3/4			1.5			1.5								42
							TOTALS	3.5	4.0	4.5	6.6	7.0	6.3								
								PANEL TOTALS			10.1	11.0	10.8								

PANEL: 'LP1B' SEC 2 BUS AMP: 400 AMPS MAIN BREAKER: 400 A MLO
MOUNTING: SURFACE PHASE: 3 WIRE: 4 VOLTAGE: 208Y120 AIC: 65,000

CKT	CIRCUIT DESCRIPTION	BREAKER P	BREAKER AMP	WIRE NO	WIRE SIZE	GND SIZE	COND	KVA/PH A	KVA/PH B	KVA/PH C	KVA/PH A	KVA/PH B	KVA/PH C	COND	GND SIZE	WIRE SIZE	WIRE NO	BREAKER AMP	BREAKER P	CIRCUIT DESCRIPTION	CKT
43	GUEST SUITE LIGHTING	1	20	2	12	12	3/4	0.7			0.7			3/4	12	12	2	20	1	GUEST SUITE LIGHTING	44
45	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		0.2			0.2		3/4	12	12	2	20	1	GUEST SUITE RECEPT.	46
47	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			0.2	3/4	12	12	2	20	1	GUEST SUITE RECEPT.	48
49	GUEST SUITE RECEPT.	1	20	2	12	12	3/4	0.8			1.0			3/4	12	12	2	20	1	GUEST SUITE RECEPT.	50
51	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		0.6			1.0		3/4	12	12	2	20	1	GUEST SUITE RECEPT.	52
53	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			0.2	3/4	12	12	2	20	1	GUEST SUITE RECEPT.	54
55	GUEST SUITE LIGHTING	1	20	2	12	12	3/4	0.7			0.2			3/4	12	12	2	20	1	ELEV. LIGHTS	56
57	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		0.2			0.2		3/4	12	12	2	20	1	ELEV. LIGHTS	58
59	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			1.0	3/4	12	12	2	20	1	EXTERIOR LIGHTS/SIGNAGE	60
61	GUEST SUITE RECEPT.	1	20	2	12	12	3/4	0.8			1.5			3/4	12	12	2	20	2	ECH-2	62
63	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		1.0			1.5									64
65	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			1.4	3/4	12	12	2	20	2	CU-2	66
67	GUEST SUITE LIGHTING	1	20	2	12	12	3/4	0.7			1.4										68
69	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		0.2			0.1		3/4	12	12	2	15	2	SS-2	70
71	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			0.1								72
73	GUEST SUITE RECEPT.	1	20	2	12	12	3/4	0.8			5.0			1	10	6	3	60	3	DUCT HEATER	74
75	GUEST SUITE RECEPT.	1	20	2	12	12	3/4		1.0			5.0									76
77	GUEST SUITE RECEPT.	1	20	2	12	12	3/4			0.2			5.0								78
79	SUMP PUMP	1	20	2	12	12	3/4	1.0										20	1	SPARE	8[illegible]
81	SPARE	1	20															20	1	SPARE	8[illegible]
83	SPARE	1	20															20	1	SPARE	84
							TOTALS	5.5	3.2	1.2	9.8	8.0	7.9								
								PANEL TOTALS			15.3	11.2	9.1								

PANEL: 'LP1B' SEC 3 BUS AMP: 400 AMPS MAIN BREAKER: 400 A MLO
MOUNTING: SURFACE PHASE: 3 WIRE: 4 VOLTAGE: 208Y120 AIC: 65,000

CKT	CIRCUIT DESCRIPTION	BREAKER P	BREAKER AMP	WIRE NO	WIRE SIZE	GND SIZE	COND	KVA/PH A	KVA/PH B	KVA/PH C	KVA/PH A	KVA/PH B	KVA/PH C	COND	GND SIZE	WIRE SIZE	WIRE NO	BREAKER AMP	BREAKER P	CIRCUIT DESCRIPTION	CKT
85	PTAC-1	2	20	3	12	12	3/4	2.0			0.5			3/4	12	12	2	15	2	OA-2	86
87									2.0			0.5									88
89	PTAC-1	2	20	3	12	12	3/4			2.0			2.5	3/4	10	10	2	30	2	EUH-1	90
91								2.0			2.5										92
93	PTAC-1	2	20	3	12	12	3/4		2.0			5.4		3/4	10	8	3	50	3	HP-4	94
95										2.0			5.4								96
97	PTAC-1	2	20	3	12	12	3/4	2.0			5.4										98
99									2.0			3.8		3/4	10	8	3	45	3	H-P-2 CONNECTION 1	100
101	PTAC-1	2	20	3	12	12	3/4			2.0			3.8								102
103								2.0			3.8										104
105	PTAC-2	2	30	3	10	10	3/4		2.9			3.8		3/4	10	8	3	45	3	H-P-2 CONNECTION 2	106
107										2.9			3.8								108
109	AC-1	2	15	3	12	12	3/4	0.5			3.8										110
111									0.5			2.5		3/4	10	10	2	30	2	EUH-1	112
113	AC-2	2	15	3	12	12	3/4			0.4			2.5								114
115								0.4			0.1			3/4	12	12	2	15	2	AC-15	116
117	AC-14	2	15	3	12	12	3/4		0.4			0.1									[illegible]
119										0.4			0.4	3/4	12	12	2	15	2	AC-16	120
121	ECH-2	2	20	3	12	12	3/4	1.5			0.4										122
123									1.5			0.2		3/4	12	12	2	15	2	AC-1[illegible]	124
125	EWH-1	1	20	2	12	12	3/4			1.5			0.2								126
							TOTALS	10.4	11.3	11.2	16.5	16.3	18.6								
								PANEL TOTALS			26.9	27.6	29.8								

PANEL: 'PP1' BUS AMP: 225 AMPS MAIN BREAKER: 2[illegible]5 A MLO
MOUNTING: SURFACE PHASE: 3 WIRE: 4 VOLTAGE: [illegible] AIC: 65,000

CKT	CIRCUIT DESCRIPTION	BREAKER P	BREAKER AMP	WIRE NO	WIRE SIZE	GND SIZE	COND	KVA/PH A	KVA/PH B	KVA/PH C	KVA/PH A	KVA/PH B	KVA/PH C	COND	GND SIZE	WIRE SIZE	WIRE NO	BREAKER AMP	BREAKER P	CIRCUIT DESCRIPTION	CKT
1	MECHANICAL RM. RECEPT.	1	20	2	12	12	3/4	[illegible]			1.0			3/4	12	12	2	20	1	SUMP PUMP	2
3	DHU PT 1	[illegible]	45	[illegible]	8	10	3/4		3.4									20	1	SPARE	4
5										3.4								20	1	SPARE	6
7								3.4										20	1	SPARE	8
9	ACC-1	2	20	3	12	12	3/4		1.3									20	1	SPARE	10
11										1.3								20	1	SPARE	12
13	GE-[illegible]	1	20	2	12	12	3/4	1.2										20	1	SPARE	14
15	SPARE	1	20															20	1	SPARE	16
17	SPARE	1	20															20	1	SPARE	18
19	SPARE	1	20															20	1	SPARE	20
21	SPARE	1	20															20	1	SPARE	22
23	SPARE	1	20															20	1	SPARE	24
25	SPARE	1	20															20	1	SPARE	26
27	SPARE	1	20															20	1	SPARE	28
29	SPARE	1	20															20	1	SPARE	30
31	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	32
33	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	34
35	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	36
37	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	38
39	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	40
41	SPACE/PROVISIONS	1																	1	SPACE/PROVISIONS	42
							TOTALS	5.0	4.7	4.7	1.0	###	###								
								PANEL TOTALS			6.0	4.7	4.7								

entegra
integrated energy engineering
262 Dickinson Drive | Reading | PA | 19605
610-750-9129 | www.entegraeng.com

Date	Description	No.

DISCLAIMER:
Meister Architects PC. is providing, by agreement with certain parties, materials stored electronically. The parties recognize that data, plans, specifications, reports, documents, or other information recorded on or transmitted as electronic media (including but not necessarily limited to "CAD documents") are subject to undetectable alteration, either intentional or unintentional, due to, among other causes, transmission, conversion, media degradation, software error, or human alteration. Accordingly, all such documents are provided to the parties for informational purposes only and not as an end product or as a record document. Any reliance thereon is deemed to be unreasonable and unenforceable. The signed and/or stamped hard copies of the Architect's Instruments of Service are the only true documents of record.

MEISTER · COX ARCHITECTS
INFO@MEISTER-COX.COM
PHONE: 610-375-1331 FAX: 610-375-4555
1522 PENN AVENUE WYOMISSING, PA 19610
WWW.MEISTER-COX.COM

SEAL:

ELECTRICAL PANEL SCHEDULES

HOLIDAY INN EXPRESS & SUITES
INTERSECTION OF HAYNES PLACE & LAMM RD.
WILSON, NC 27893

STATUS: FOR BID
PROJ. DATE: 06/06/2019
PROJ. NO. 19-116
PRINTED: 06/06/2019
DRAWN BY: jlm/brm/jpk
CHECKED BY: brm
SHEET NO. E5.3
SCALE: AS NOTED

Order Plans @ WWW.LDILine.com