



PHILLIPS

KEYPLAN

CONSULTANT



PROFICIENT ENGINEERING
6991 Peachtree Industrial Blvd Building 700
Peachtree Corners, Georgia 30092
404.330.9798
PROJECT # 119288

SEAL



ISSUE & REVISION RECORD

#	DATE	DESCRIPTION
1	08.10.2019	30% DESIGN REVIEW SET
2	08.16.2019	90% REVIEW SET
3	08.23.2019	PERMIT SET

This document is the property of Phillips Partnership, P.C. and is controlled on behalf of Phillips Partnership, P.C. and is not to be used for any other project without the prior written consent of Phillips Partnership, P.C.

PROJECT

Fairfield BY MARRIOTT INN & SUITES

DAWSONVILLE, GEORGIA

PROTOTYPE VERSION 2016
REV 7 12-21-16

4 STORY, 92 UNITS
w/ INDOOR POOL

FAIRFIELD DAWSON FOREST ROAD
DAWSONVILLE, GA
30534

CLIENT

RIMROCK COMPANIES
10000 RIVERSIDE AVE
SUITE 32001
JACKSONVILLE, FL 32204

PHILLIPS JOB NUMBER 1972101

ISSUE DATE 08/23/2019

DRAWN BY CHECKED BY ATIRK

DRAWING TITLE SCHEDULES

SHEET NUMBER

E-0.5

5901 PEACHTREE DUNWOODY RD.
BUILDING A, SUITE 450
ATLANTA, GEORGIA 30328
PHILLIPS PART.COM 770.394.1616

CALLOUT	SYMBOL	LAMP	DESCRIPTION	MODEL	VOLTS
B01		(1) 36.4W 3500K LED	RECESSED BOX	EATON - METALUX 22CZ-LD5-39-UNV-L835-CD1-U	120V 1 F 2W
B04		(1) 23.4W 3500K LED	RECESSED BOX	EATON - METALUX 22SR-LD2-29-G-UNV-L835-CD1-U	120V 1 F 2W
B06		(1) 54.2W 3500K LED	RECESSED BOX	EATON - METALUX 24GR-LD5-72-F1-UNV-L835-CD1-U	120V 1 F 2W
B07		(1) 36.4W 3500K LED	RECESSED BOX	TBD	120V 1 F 2W
B08		(1) 21W LED	LINEAR BOX	EATON NEDRAY S1 24DR-3793D830-F833F- UDD-F-W	120V 1 F 2W
B18		(1) 23.5W 3500K LED	RECESSED BOX	22CZ-LD5-29-UNV-L835-CD1-U	120V 1 F 2W
D1.32A		(1) 50W 3000K Halogen	TRACK HEAD	700TMSCA037 I -H	120V 1 F 2W
D1.88		(4) 24W 3000K FL	BACKLIT MIRROR	ELECTRIC MIRROR LLC - S1LHOUETTE 30	120V 1 F 2W
D2.28		(1) 1.3W 2700K LED	RECESSED LIGHT	CHALLENGER LIGHTING COMPANY- CAS4777 -00- SAND	120V 1 F 2W
D2.29		(1) 1.0W 2700K LED	RECESSED LIGHT	CHALLENGER LIGHTING COMPANY- CAS4777 -00- SAND	120V 1 F 2W
D2.30		(2) 30W 3000K LED	WALL MOUNTED LIGHT FIXTURE	RESTORATION HARDWARE 70030726	120V 1 F 2W
D2.31		(2) 1.7W INTEGRATED LED	ROUND VANITY MIRROR WITH FLANKING LED SCONCES	SCOTT LAMP COMPANY INC 70030726	120V 1 F 2W
D2.32		(1) 60W 3000K LED	RECESSED LIGHT	RESTORATION HARDWARE 70030726	120V 1 F 2W
D2.33		(2) 30W 3000K LED	LINEAR WALL SCONCE	PHILIPS LIGHTING INC 663A-035-F75D	120V 1 F 2W
D2.34		(2) 1.3W 2700K FL	WALL MOUNTED LIGHT FIXTURE	SCOTT LAMP COMPANY - 3623FL	120V 1 F 2W
D2.35		(2) 30W LED	EXIT SIGN	RESTORATION HARDWARE 70030733CHRTR	120V 1 F 2W
D2.36		(2) 20W 3000K LED	WALL SCONCE WITH GLASS SIDES	RESTORATION HARDWARE 70030732BGMTR	120V 1 F 2W
J04		(1) 28W 3000K LED	STRIP LIGHTING FIXTURE SURFACE MOUNTED	EATON METALUX 4WILED-LD4-2405L-FUNV-L835-CD1-U	120V 1 F 2W
J05		(1) 36W 3500K LED	STRIP LIGHTING FIXTURE SURFACE MOUNTED	EATON METALUX 4WILED-LD4-2405L-FUNV-L835-CD1-U	120V 1 F 2W
J1.8		(1) 24W 3100K LED	LIGHT STRIP FIXTURE	RICHELIEAU FLEXYLED CH TAPE LIGHTS #103197122 WARM WHITE STRIP LIGHT 1/2" PER ROLL (24W TOTAL) 30141210-45	120V 1 F 2W
J1.9		(1) 24W 3100K LED	LIGHT STRIP FIXTURE	RICHELIEAU FLEXYLED CH TAPE LIGHTS #103197122 WARM WHITE STRIP LIGHT 1/2" PER ROLL (24W TOTAL) 30141210-45	120V 1 F 2W
J20		LED	.75 LINEAR COVE FIXTURE	EATON IQO Q031-3K-90.101 .1.1.2.1.1 SA.BK.WALL	120V 1 F 2W
K01		(1) 23W 3500K LED	WALL MOUNTED FIXTURE	EATON - CORELITE JB-LL-3L35-1D-120-SU-WA-3	120V 1 F 2W
K02		(1) 3000K LED	DIVIDE SURFACE MOUNT WITH INTEGRAL OCCUPANCY SENSOR	EATON - CORELITE D91W3-3L35-UK2-1D-UNV-SU 5WPD1-JB-5	120V 1 F 2W
O01		(1) 26W 3000K CFL	JELLY JAR SCONCE	PHILIPS QUALITY EXCELINE FLW26HFLGGC-1	120V 1 F 2W

CALLOUT	SYMBOL	LAMP	DESCRIPTION	MODEL	VOLTS
O05		(1) 40W 4000K LED	ILLUMINATOR RECESSED WALL SCONCE	INSIGHT LIGHTING MLEDWLED-60-40K-WM-INT-1-W-NAT	120V 1 F 2W
R72		(1) 15.7W 5000K LED	RECESSED LIGHT FIXTURE	EATON - HALO PDG20 ED010-FDM6A-930-G1VH	120V 1 F 2W
R73		(1) 14W 3000K LED	RECESSED LIGHTING FIXTURE	EATON - HALO PDG20 ED010-FDM6A-930-G1VWVCF	120V 1 F 2W
R75		(1) 23.5W 3500K LED	RECESSED LIGHTING FIXTURE	EATON - PORTFOLIO LD64-15-D010TE-ERMG415-930 -6LM121H-HB26	120V 1 F 2W
R76		(1) 1.3W 2700K LED	RECESSED LIGHT FIXTURE	EATON - HALO H457TATED10 -ELG406930WH	120V 1 F 2W
R77		(1) 1.3W 3000K LED	RECESSED LIGHTING FIXTURE	EATON - HALO H2750CAT-ML5606830-691WB	120V 1 F 2W
R82		(1) 18W 3000K LED	G DOWNLIGHT	EATON - SHAPER 340-GB15-D010-0.340-EU6B-1020-903-6LBWLI-CC	120V 1 F 2W
R83		(1) 1.3W 3000K LED	G DOWNLIGHT	TBD	120V 1 F 2W
R84		(1) 1.2.1W 3000K LED	RECESSED LIGHTING FIXTURE	EATON - HALO M4D09NPL930E-TL43R2GMWMB H245ICAT	120V 1 F 2W
R87		(1) 1.5.3W 3000K LED	G DOWNLIGHT	PHILIPS - LIGHTTOUER PGRD15N210UVB / PGRD930VB / PGRDCCF	120V 1 F 2W
R99		(1) 1.2.1W 3000K LED	PENDANT LIGHT	EATON - HALO M4D09NPL930E-TIR50AQ225-TL41R-MB-H995ICAT	120V 1 F 2W
R100		(1) 1.2.1W 3000K LED	PENDANT LIGHT	EATON - HALO M4D09NPL930E-TIR50AQ225-TL41RMB-H995ICAT	120V 1 F 2W
T04		(1) LED	14" ROUND CEILING MOUNT	LSI POC93/618219	120V 1 F 2W
T06		(1) LED	G CEILING MOUNTED LED/EXHAUST FAN COMBO	TBD	120V 1 F 2W
X01		(1) 1W LED	EXIT SIGN WITH BACKUP BATTERY	EATON - SURELITES CX7	120V 1 F 2W
X03		(2) 2.4W LED	EMERGENCY LIGHTING UNIT	EATON - SURELITES 5EL255D	120V 1 F 2W
XR		(1) INCLUDED	REMOTE LAMP HEAD	LITHONIA ELA-OMP-L0309-5D	120V 1 F 2W
Z28		(1) 10.2W 5000K LED	RECESSED LIGHTING FIXTURE	PHILIPS - LIGHTTOUER PGRD10N210UVBEM / PGRD840VB / PGRDCLP	120V 1 F 2W
Z38		(2) 30W 3000K LED	WALL MOUNTED LIGHT FIXTURE	ASHLEY LIGHTING INC 71269A-035-F75D	120V 1 F 2W
Z64		(4) LED	GALLEON AREA AND ROADWAY LUMINAIRE(3) 70 CRI, 4000K, 1050MA LIGHTSQUARES WITH 16 LEDs EACH AND TYPE V MEDIUM OPTICS	EATON - MGRRAW-EDISON (FORMER COOPER LIGHTING), GLEON-AF-03-LED-E1-5M2	120V 1 F 2W
Z71		(1) 9.9W 4000K LED	RECESSED LIGHTING FIXTURE	EATON - HALO PDG10ED010-FDM6A840-61VC	120V 1 F 2W
Z78		(1) 19.9W 4000K LED	RECESSED LIGHTING FIXTURE	PDG20ED010-FDM6A840-61VC	120V 1 F 2W
Z99		(1) LED	EXTERIOR BOLLARD	TO BE SELECTED BY OWNER/ARCHITECT	120V 1 F 2W

CALLOUT	SYMBOL	VOLTS	KVA	BREAKER	CIRCUIT	WIRE CALLOUT	DISCONNECT DESCRIPTION
CU-1		208V 20V 2F 3W	5.72	40/2	H4-17,19	3/4"C,2#8,#8N,#10G	60A/2P/NEMA 3R
CU-2		208V 20V 2F 3W	2.93	20/2	H4-21,23	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
CU-3		208V 20V 2F 3W	3.76	30/2	H4-9,11	1/2"C,2#10,#10N,#10G	30A/2P/NEMA 3R
CU-4		208V 20V 2F 3W	2.93	20/2	H4-14,16	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
CU-5		208V 20V 2F 3W	5.72	40/2	H4-13,15	3/4"C,2#8,#8N,#10G	60A/2P/NEMA 3R
EF-1		120V 1 F 2W	0.53	20/1	H1C-13	1/2"C,1#12,#12N,#12G	LOCKABLE BREAKER
EF-1		120V 1 F 2W	0.53	20/1	H1C-9	1/2"C,1#12,#12N,#12G	LOCKABLE BREAKER
EF-2		120V 1 F 2W	0.53	20/1	H1C-11	1/2"C,1#12,#12N,#12G	LOCKABLE BREAKER
EF-2		120V 1 F 2W	0.53	20/1	H1C-7	1/2"C,1#12,#12N,#12G	LOCKABLE BREAKER
EF-3		120V 1 F 2W	0.53	20/1	H1C-15	1/2"C,1#12,#12N,#12G	LOCKABLE BREAKER
EF-B		120V 1 F 2W	0.1	20/1	H1A-40	1/2"C,1#10,#10N,#10G	SWITCHED WITH LIGHTS
EF-B		120V 1 F 2W	0.1	20/1	H1A-40	1/2"C,1#10,#10N,#10G	SWITCHED WITH LIGHTS
ERU-1		208V 3F 4W	30.23	100/3	H4-26,28,30	1-1/4"C,3#2,#2N,#8G	100A/3P/NEMA 3R
ERU-2		208V 3F 4W	23.24	80/3	H4-36,38,40	1-1/4"C,3#2,#2N,#8G	100A/3P/NEMA 3R
EWB-A		208V 20V 2F 3W	2	20/2	H1B-1,3	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
EWB-A		208V 20V 2F 3W	2	20/2	H1B-13,15	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
FCU-1		208V 20V 2F 3W	3.31	20/2	R2E-6,8	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
FCU-2		208V 20V 2F 3W	3.31	20/2	R2E-14,16	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
FCU-3		208V 20V 2F 3W	3.31	20/2	H1B-9,11	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
FCU-4		208V 20V 2F 3W	3.31	20/2	H1B-25,27	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
FCU-5		208V 20V 2F 3W	3.31	20/2	R2E-10,12	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-1		208V 20V 2F 3W	0.42	20/2	H1B-5,7	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-2		208V 20V 2F 3W	0.42	20/2	H1B-21,23	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-3		208V 20V 2F 3W	0.21	20/2	H1B-17,19	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-A		208V 20V 2F 3W	0.21	20/2	R2E-2,4	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-A		208V 20V 2F 3W	0.21	20/2	R3E-2,4	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MFCU-A		208V 20V 2F 3W	0.21	20/2	R4E-2,4	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MHP-1		208V 20V 2F 3W	0.21	20/2	R4E-6,8	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 1
MHP-1		208V 20V 2F 3W	2.7	20/2	H4-18,20	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-2		208V 20V 2F 3W	2.7	20/2	H4-32,34	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-3		208V 20V 2F 3W	2.7	20/2	H4-5,7	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-A		208V 20V 2F 3W	2.7	20/2	H4-2,4	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-A		208V 20V 2F 3W	2.7	20/2	H4-6,8	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-A		208V 20V 2F 3W	2.7	20/2	H4-10,12	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MHP-A		208V 20V 2F 3W	2.7	20/2	H4-22,24	1/2"C,2#12,#12N,#12G	30A/2P/NEMA 3R
MFCU-1		208V 3F 4W	0.2	20/3	H4-29,31,33	1/2"C,3#12,#12N,#12G	30A/3P/NEMA 1
FDU-1		208V 3F 4W	8.14	40/3	H1C-2,4,6	3/4"C,3#8,#8N,#10G	60A/3P/NEMA 1
FLA		120V 1 F 2W	0.2	20/1	H4-25	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 3R
FLA		120V 1 F 2W	0.2	20/1	H4-27	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 3R
RF-1		120V 1 F 2W	0.6	20/1	H1C-16	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 1
RF-2		120V 1 F 2W	0.6	20/1	H1C-18	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 1
WH-1		120V 1 F 2W	0.6	20/1	H1C-10	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 1
WH-2		120V 1 F 2W	0.6	20/1	H1C-8	1/2"C,1#12,#12N,#12G	30A/1P/NEMA 1