PANELBOARD SCHEDULE - 'A'

MAIN: 400A MCB | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | AIC: 22K | NOTES:

CKT #	BKR TRIP	POLE #	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	PHASE	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	DESCRIPTION	LOAD SIZE	WIRE SIZE	POLE #	BKR TRIP	CKT #
1	20	1	10	3/4"	LTG AT ENT HANGAR (CLP)	0.9								1.0												2
2	20	1	10	3/4"	LTG AT EGRESS HANGAR (CLP)	0.9								1.0							HANGAR CEILING FAN	3/4"	12	1	20	4
3	20	1	10	3/4"	LTG HANGAR (LDP) & EMLTG	1.6								1.0												6
5	20	1	10	3/4"	LTG HANGAR (LDP) & EMLTG	1.6								1.0												8
7	20	1	10	3/4"	LTG HANGAR (LDP) & EMLTG	1.6								1.0							HANGAR CEILING FAN	3/4"	12	1	20	10
9	20	1	10	3/4"	LTG HANGAR (LDP) & EMLTG	1.6								1.0												12
11	20	1	12	3/4"	RECEPT - EXT		0.9														EPO POWER	1 1/4"	2	3	100	14
13	20	1	12	3/4"	ELECTRICAL PANEL/SIGNAGE		0.1																			16
15	60	2	8	3/4"	WATER HEATER #8-1									7.0												18
17														7.0							RECEPTACLES	3/4"	12	1	20	20
19														7.0							RECEPTACLES	3/4"	12	1	20	22
21	100	3	3	1 1/4"	EPO POWER									7.0							RECEPTACLES	1"	6	2	30	24
23														7.0												26
25	20	1	10	3/4"	RECEPTACLES	0.9								1.0							RECEPTACLES	1"	6	2	30	28
27	20	1	12	3/4"	LTG - EXTERIOR (LCP)	0.8								1.0												30
29	30	1	12	3/4"	LTG - EXTERIOR (LCP)	1.8								0.0							RECEPT - TYP	3/4"	12	1	20	32
31	20	1	12	3/4"	SPARE					0.0				0.4							RECEPT - TYP	3/4"	12	1	20	34
33	20	1	12	3/4"	SPARE					0.0				0.0							RECEPT - TYP	3/4"	12	1	20	36
35	20	3	10	3/4"	SPARE		0.9							0.0												38
37							0.9							0.0												40
39							0.9							0.0												42
SECTION 2																					SECTION 2					
41	15	2	12	3/4"	SPARE				1.0					1.0							OFFICE RECEPTACLES	3/4"	12	1	20	44
43									1.0					0.0							RECEPT -	3/4"	12	1	20	46
45	60	2	8	3/4"	WATER HEATER #8-2					8.3				0.0												48
47										8.3				0.0												50
49	15	2	12	3/4"	SPARE									0.0												52
51											0.9	0.0									TOILET FAN & EMD RECEPTS	3/4"	12	1	20	54
53																				2.3	WATER HEATER	3/4"	10	2	30	56
55	15	2	12	3/4"	SPARE															2.3						58
57																				6.9	CRI SEP 20 ABM	3/4"	12	1	20	60
59	15	2	12	3/4"	SPARE																SPARE	3/4"	12	1	20	62
61														2.3							SPARE SPACE/VIA	3/4"	8	2	30	64
63	30	1	12	3/4"	LTG - OFFICE	1.8								2.3							CTRL PANEL					66
65	20	1	12	3/4"	LTG - WOMEN/TOILET & EMLTG	1.0								7.3												68
67	20	1	12	3/4"	LTG - EXT CANOPY & EXT EMLTG	0.5								0.9							SPARE	3/4"	12	1	20	70
69	20	1	12	3/4"										0.9												72
71	20	1	12	3/4"										0.9												74
LIGHTING (KVA):						12.7	12.7	0.0	7.7	0.0	0.0	0.0	26.3	0.0	8.7	21.3	0.0	0.0	0.0	0.0	CONNECTED LOAD (KVA):					168.3
RECEPTACLES (KVA):						6.2															DEMAND LOAD (KVA):					120.1
MOTORS (KVA):						23.8							PHASE A	52	389.7											
A/C (KVA):						7.0							PHASE B	35	262.0						CONNECTED LOAD (AMPS):					700.5
HEATING (KVA):						1.0							PHASE C	13	102.3						DEMAND LOAD (AMPS):					500.4
KITCHEN (KVA):						0.0									504	AMPS										
MISCELLANEOUS (KVA):						72.2																				

NOTES:
1. PANEL SHALL BE EQUAL TO SQUARE D NQOD, SE LISTED.
2. PROVIDE SWD/HID RATED BREAKERS FOR LIGHTING CIRCUITS.
3. PROVIDE HACR BREAKERS FOR HVAC EQUIPMENT.
4. LCR - LIGHTING CONTRACTOR CONTROLLED BY LIGHTING CONTROL PANEL. PC/TC FOR PHOTOCELL ON, TIMECLOCK OFF CONTROL. CONTROL PANEL TO BE EQUAL TO WATTSTOPPER LP8 SERIES WITH EXTERIOR PHOTOCELL. LOCATE CONTROL PANEL ADJACENT TO PANEL AND LOCATE PHOTOCELL ON NORTH SIDE OF BUILDING. PROVIDE AUTO/OFF/ON OVERRIDE SWITCH. PROGRAM CONTROL PANEL TO PROVIDE SEPARATE SET POINTS FOR LCR1, LCR2 AND LCR3.
5. LCP - CIRCUIT VIA LIGHTING CONTROL PANEL FOR MANUAL ON / SCHEDULE OFF CONTROL. COORDINATE CONTROL STATION LOCATIONS WITH OWNER.
6. BREAKERS SERVING EMERGENCY/EGRESS LIGHTING TO SO LABELED.

PANELBOARD SCHEDULE - 'D'

MAIN: 400A MLO | VOLTAGE: 208/120 | PHASE: 3 | WIRE: 4 | MOUNTING: SURFACE | AIC: 22K | NOTES:

CKT #	BKR TRIP	POLE #	WIRE SIZE	COND SIZE	DESCRIPTION	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	PHASE	LOAD (KVA) LTG	REC	MTR	A/C	HTG	KIT	MISC	DESCRIPTION	COND SIZE	WIRE SIZE	POLE #	BKR TRIP	CKT #
1	60	3	10	3/4"	DOOR OPERATOR				1.0								1.0				DOOR OPERATOR	3/4"	10	3	60	2
3									1.0								1.0									4
5									1.0								1.0									6
7	50	3			SPARE																SPARE					8
9																					SPACE					10
11																					SPACE					12
13					SPACE																SPACE					14
15					SPACE																SPACE					16
17					SPACE																SPACE					18
19					SPACE																SPACE					20
21					SPACE																SPACE					22
23					SPACE																SPACE					24
LIGHTING (KVA):						0.0	0.0	0.0	0.0	0.0	0.0	0.0		0.0	0.0	0.0	0.0	0.0	0.0	0.0	CONNECTED LOAD (KVA):					0.0
RECEPTACLES (KVA):						0.0															DEMAND LOAD (KVA):					0.0
MOTORS (KVA):						0.0							PHASE A	0	0.0											
A/C (KVA):						0.0							PHASE B	0	0.0						CONNECTED LOAD (AMPS):					0.0
HEATING (KVA):						0.0							PHASE C	0	0.0						DEMAND LOAD (AMPS):					0.0
KITCHEN (KVA):						0.0									0.0	AMPS										
MISCELLANEOUS (KVA):						0.0																				

NOTES:
1. PANEL SHALL BE EQUAL TO SQUARE D NQOD, SE LISTED.
2. PROVIDE SWD/HID RATED BREAKERS FOR LIGHTING CIRCUITS.
3. PROVIDE HACR BREAKERS FOR HVAC EQUIPMENT.

PNL D DEMAND CALCS

LIGHTING	0.0	KVA X	1.25	%	=	0.0 KVA
RECEPTACLE TOTAL	0.0	KVA				
1ST	10.0	KVA X	100	%	=	0.0 KVA
REMAIN	0.0	KVA X	50	%	=	0.0 KVA
MOTORS	0.0	KVA X	100	%	=	0.0 KVA
A/C	0.0	KVA X	100	%	=	0.0 KVA
HEATING	0.0	KVA X	100	%	=	0.0 KVA
FUTURE		KVA X	100	%	=	0.0 KVA
KITCHEN	0.0	KVA X	65	%	=	0.0 KVA
MISCELLANEOUS	0.0	KVA X	100	%	=	0.0 KVA
TOTAL =	16.7	amps		=		6.8 KVA

PNL A DEMAND CALCS

LIGHTING	10.76	KVA X	125	%	=	13.5 KVA
RECEPTACLE TOTAL	6.22	KVA				
1ST	10.00	KVA X	100	%	=	6.2 KVA
REMAIN	0.00	KVA X	50	%	=	0.0 KVA
MOTORS	22.75	KVA X	100	%	=	22.8 KVA
A/C	7.00	KVA X	100	%	=	7.0 KVA
HEATING	1.00	KVA X	100	%	=	1.0 KVA
FUTURE		KVA X	100	%	=	0.0 KVA
KITCHEN	0.00	KVA X	65	%	=	0.0 KVA
MISCELLANEOUS	72.20	KVA X	100	%	=	72.2 KVA
TOTAL =	333.9	amps		=		322.1 KVA

SERVICE DEMAND CALCS

LIGHTING	10.76	KVA X	125	%	=	13.5 KVA
RECEPTACLE TOTAL	6.22	KVA				
1ST	10.00	KVA X	100	%	=	6.2 KVA
REMAIN	0.00	KVA X	50	%	=	0.0 KVA
MOTORS	25.75	KVA X	100	%	=	25.8 KVA
A/C	2.00	KVA X	100	%	=	2.0 KVA
HEATING	1.00	KVA X	100	%	=	1.0 KVA
FUTURE		KVA X	100	%	=	0.0 KVA
KITCHEN	0.00	KVA X	65	%	=	0.0 KVA
MISCELLANEOUS	73.20	KVA X	100	%	=	73.2 KVA
TOTAL =	355.5	amps		=		125.1 KVA

FEEDER SCHEDULE - CU

STD. FUSE OR C/B TRIP SIZE	# OF SETS	BUILDING WIRE QUANTITY & SIZE. TYPE THWN - DRY TYPE THWN - WET	MINIMUM CONDUIT SIZE
30	1	4 #10, #10 G	1/2"
35	1	4 #8, #10 G	3/4"
40	1	4 #8, #10 G	3/4"
45	1	4 #6, #10 G	1"
50	1	4 #6, #10 G	1"
60	1	4 #6, #10 G	1"
70	1	4 #4, #8 G	1 1/4"
80	1	4 #3, #8 G	1 1/4"
90	1	4 #2, #8 G	1 1/4"
100	1	4 #2, #8 G	1 1/4"
110	1	4 #2, #6 G	1 1/2"
125	1	4 #1, #6 G	1 1/2"
150	1	4 #1/0, #6 G	2"
175	1	4 #2/0, #6 G	2"
200	1	4 #3/0, #6 G	2"
225	1	4 #4/0, #4 G	2 1/2"
250	1	4 - 250MCM, #4 G	2 1/2"
300	1	4 - 350MCM, #4 G	2 1/2"
350	2	4 #2/0, #3 G	2"
400	1	4 - 600MCM, #3 G	3"
450	2	4 #4/0, #2 G	1 1/2"
500	2	4 - 350MCM, #2 G	1 1/2"
600	2	4 - 500MCM, #1 G	3"

NOTES:
1. ALL FEEDER SIZES LISTED MAY NOT BE USED IN PROJECT RISER DIAGRAM.
2. ELECTRICAL CONTRACTOR TO VERIFY CONDUIT SIZE REQUIRED FOR WIRE TYPES OTHER THAN THOSE LISTED ABOVE ARE USED.
3. REFER TO LATEST EDITION OF NEC FOR CONDUIT TYPES REGARDLESS OF THEIR LOCATION. IF CONDUIT OTHER THAN 'EMT' IS REQUIRED USE SIZE PER MAXIMUM FILL TABLES.
4. FEEDER SIZES SHOWN IN PROJECT RISER WITH A DELTA SYMBOL 'Δ' ARE 3Φ, 3 WIRE FEEDERS, A NEUTRAL WIRE IS NOT REQUIRED.
5. FEEDER SIZES SHOWN IN PROJECT RISER WITH A DELTA SYMBOL 'Y' ARE 1Φ, 3 WIRE FEEDERS.
6. IG - PROVIDE ISOLATED GROUND CONDUCTOR FOR ISOLATED GROUND BUS IN PANEL.
7. FEEDERS ARE SIZED FOR NEC DEMAND ONLY. EC TO ADJUST FEEDER SIZES AS REQUIRED TO MAINTAIN 3% MAX VOLTAGE DROP FROM SERVICE ENTRANCE



NOTES:
1. COORDINATE ALL ELECTRICAL SERVICE WORK WITH LOCAL UTILITY PRIOR TO PROJECT START UP. ALL WORK MUST CONFORM TO LOCAL UTILITY RULES AND REGULATIONS.
2. ALL ELECTRICAL EQUIPMENT SIZES ARE BASED ON SQUARE D. IF OTHER MANUFACTURER IS SELECTED IT IS THE CONTRACTOR'S RESPONSIBILITY TO ENSURE ALL EQUIPMENT FITS IN SPACE PROVIDED.

1 POWER RISER DIAGRAM
DIAGRAMMATIC ONLY



2 GROUNDING DETAIL
NTS

GROUNDING ELECTRODES SHALL BE PROVIDED IN ACCORDANCE WITH NEC SECTION 250. ALL GROUNDING ELECTRODE CONDUCTORS SIZED AS INDICATED ON POWER RISER DIAGRAM. **ALL METHODS OF CREATING THE GROUNDING SYSTEM MAY NOT BE REQUIRED OR AVAILABLE.**



4 EMERGENCY FIXTURE WIRING
DIAGRAMMATIC ONLY



3 TELEPHONE/DATA RISER
NTS

NOTES:
1. COORDINATE EXACT TELEPHONE AND DATA WIRING REQUIREMENTS WITH OWNER PRIOR TO PROJECT START UP.
2. COORDINATE ALL DATA/TELEPHONE SERVICE WORK WITH LOCAL UTILITY PRIOR TO PROJECT START UP.

Order Plans @ WWW.LDILine.com

SABER ENGINEERING
2923 South Tryon Street Suite 280
Charlotte, North Carolina 28203
tel 704.373.0068
MECHANICAL ELECTRICAL PLUMBING
FIRM NUMBER = C-2130

CAPE FEAR REGIONAL JETPORT
HOWIE FRANKLIN FIELD

NEW CORPORATE HANGAR
4005 AIRPORT ROAD
SOUTHPORT, NC 28461

ARCHITECT
THE WILSON GROUP
P O BOX 5510
CHARLOTTE, NC 28299
(704) 331-9747

PROJECT MANAGER I CIVIL ENGINEER
TALBERT & BRIGHT
4810 SHELLEY DRIVE
WILMINGTON, NC 28405
(910) 763-5350

STRUCTURAL ENGINEER
STEWART
101 N. TRYON ST., SUITE 1400
CHARLOTTE, NC 28202
(704) 906-3523

MECHANICAL, ELECTRICAL, PLUMBING & FIRE PROTECTION ENGINEER
SABER ENGINEERING
2923 S. TRYON ST., SUITE 280
CHARLOTTE, NC 28203
(704) 373-0068

REVISIONS

DATE AUGUST 2, 2019
PROJECT NUMBER 9217-000

SHEET TITLE
PANELS, DETAILS AND RISER DIAGRAM

SHEET NUMBER
E4

ML-1960-04-Dwg, Plotted By: JustinC
Aug 01, 2019 - 4:04pm