

GENERAL SCHEDULE

CALLOUT	SYMBOL	VOLTS	KVA	CIRCUIT	WIRE CALLOUT	DISCONNECT DESCRIPTION
CRIU-1	☐	208V 3P 4W	8.93	E2-12,14,16	3/4"C.3#8.#8N.#10G	60A/3P/NEMA 1
CRIU-2	☐	208V 3P 4W	8.93	E2-16,20,22	3/4"C.3#8.#8N.#10G	60A/3P/NEMA 1
CRIU-3	☐	208V 3P 4W	4.97	E2-24,26,28	1/2"C.3#12.#12N.#12G	30A/3P/NEMA 3R
CROU-1	☐	208V 3P 4W	29.43	EMDP-2,4,6	1-1/2"C.3#1.#1N.#6G	200A/3P/NEMA 3R
CROU-2	☐	208V 3P 4W	45.25	EMDP-8,10,12	2"C.3#2/0.#2/0N.#6G	200A/3P/NEMA 3R
CROU-3	☐	208V 3P 4W	13.65	EMDP-14,16,18	1"C.3#6.#6N.#10G	60A/3P/NEMA 3R
CU-1	☐	208/120V 2P 3W	2.43	M-5,7	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 3R
CU-2	☐	208/120V 2P 3W	4.64	E2-8,10	3/4"C.2#8.#8N.#10G	60A/2P/NEMA 3R
CU-3	☐	208/120V 2P 3W	3.49	M-15,17	1/2"C.2#10.#10N.#10G	30A/2P/NEMA 3R
CU-4	☐	208/120V 2P 3W	2.43	M-23,25	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 3R
EDH-1	☐	208V 3P 4W	30	EMDP-1,3,5	1-1/2"C.3#1.#1N.#6G	100A/3P/NEMA 1
EDH-2	☐	208V 3P 4W	65	EMDP-7,9,11	2-1/2"C.3#250kcmil.#250kcmil N.#4G	200A/3P/NEMA 1
EDH-3	☐	208V 3P 4W	20	EMDP-13,15,17	1-1/4"C.3#4.#4N.#8G	60A/3P/NEMA 1
EF-1	☐	120V 1P 2W	0.1	1A-28	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-2	☐	120V 1P 2W	0.1	1A-28	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-3	☐	120V 1P 2W	0.24	1A-28	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-4	☐	120V 1P 2W	0.53	2A-30	1/2"C.1#12.#12N.#12G	30A/1P/NEMA 3R
EF-5	☐	208V 3P 4W	11.64	2A-20,22,24	1"C.3#6.#6N.#10G	60A/3P/NEMA 3R
EF-6	☐	120V 1P 2W	0.15	2A-14	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-A	☐	120V 1P 2W	0.1	2A-14	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-A	☐	120V 1P 2W	0.1	2A-16	1/2"C.1#10.#10N.#10G	SWITCHED WITH LIGHTS
EF-A	☐	120V 1P 2W	0.1	2A-18	1/2"C.1#12.#12N.#12G	SWITCHED WITH LIGHTS
EWH-1	☐	208/120V 2P 3W	1.5	M-2,4	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FCU-1	☐	208/120V 2P 3W	9.3	M-1,3	3/4"C.2#6.#6N.#10G	60A/2P/NEMA 1
FCU-2	☐	208V 3P 4W	19.99	E2-2,4,6	1"C.3#6.#6N.#10G	60A/3P/NEMA 1
FCU-3	☐	208V 3P 4W	17.18	M-9,11,13	1"C.3#6.#6N.#10G	60A/3P/NEMA 1
FCU-4	☐	208/120V 2P 3W	9.3	M-19,21	3/4"C.2#6.#6N.#10G	60A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-1,3	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-5,7	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-9,11	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-21,23	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-17,19	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-10,12	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-10	☐	208/120V 2P 3W	0.31	EM-6,8	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-33,35	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-29,31	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-25,27	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-37,39	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-2,4	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-14,16	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-18,20	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-22,24	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-34,36	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-30,32	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-12	☐	208/120V 2P 3W	0.31	EM-13,15	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-2410	☐	208/120V 2P 3W	0.31	EM-38,40	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
FFU-2410	☐	208/120V 2P 3W	0.31	EM-26,28	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-1	☐	208/120V 2P 3W	0.48	M-27,29	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-2	☐	208/120V 2P 3W	0.48	M-31,33	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-3	☐	208/120V 2P 3W	0.48	M-35,37	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-4	☐	208/120V 2P 3W	0.48	M-39,41	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-5	☐	208/120V 2P 3W	0.48	E2-30,32	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-6	☐	208/120V 2P 3W	0.48	M-6,8	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 1
MFCU-7	☐	208/120V 2P 3W	0.1	2A-26,28	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 3R
MHP-1	☐	208/120V 2P 3W	6.05	M-10,12	3/4"C.2#8.#8N.#10G	60A/2P/NEMA 3R
MHP-2	☐	208/120V 2P 3W	6.05	M-14,16	3/4"C.2#8.#8N.#10G	60A/2P/NEMA 3R
MHP-3	☐	208/120V 2P 3W	6.05	M-18,20	3/4"C.2#8.#8N.#10G	60A/2P/NEMA 3R
MHP-4	☐	208/120V 2P 3W	3.43	M-22,24	1/2"C.2#10.#10N.#10G	30A/2P/NEMA 3R
MHP-5	☐	208/120V 2P 3W	3.35	E2-34,36	1/2"C.2#10.#10N.#10G	30A/2P/NEMA 3R
MHP-6	☐	208/120V 2P 3W	6.05	M-26,28	3/4"C.2#8.#8N.#10G	60A/2P/NEMA 3R
MHP-7	☐	208/120V 2P 3W	2.77	M-30,32	1/2"C.2#12.#12N.#12G	30A/2P/NEMA 3R
RP-1	☐	120V 1P 2W	0.3	1A-7	1/2"C.1#12.#12N.#12G	BREAKER
WH-1	☐	208V 3P 4W	24	MDP-8,10,12	1-1/4"C.3#2.#2N.#8G	BREAKER

LUMINAIRE SCHEDULE

CALLOUT	SYMBOL	LAMP	DESCRIPTION	MODEL	VOLTS
EX-1	⊗	(1) 5W LED	THERMOPLASTIC EXIT SIGN	SURELITES EUX6R	120V 1P 2W
L-1	○	(1) 18W LED	6" LED RECESSED DOWNLIGHT	TECH LIGHTING EN3S-LH-9-40-A-A65-EN3S-L-F-O-W-149MR16GL	120V 1P 2W
L-1E	●	(1) 18W LED	6" LED RECESSED DOWNLIGHT ON GENERATOR	TECH LIGHTING EN3S-LH-9-40-A-A65-EN3S-L-F-O-W-149MR16GL	120V 1P 2W
L-2	○	(1) 18W LED	6" LED RECESSED DOWNLIGHT W/ BEAM FOCUS ON WALL	TECH LIGHTING EN3S-LH-9-40-A-A65-EN3S-L-F-O-W-149MR16GL	120V 1P 2W
L-3	☐	(1) 19.2W LED	2x2 LED RECESSED TROFFER	METALUX 22CZ-32-UNV-L840-CD1	120V 1P 2W
L-3E	☐	(1) 19.2W LED	2x2 LED RECESSED TROFFER ON GENERATOR	METALUX 22CZ-32-UNV-L840-CD1	120V 1P 2W
L-4	☐	(1) 30.1W LED	2x4 LED RECESSED TROFFER	METALUX 24CZ-32-UNV-L840-CD1	120V 1P 2W
L-4E	☐	(1) 30.1W LED	2x4 LED RECESSED TROFFER ON GENERATOR	METALUX 24CZ-32-UNV-L840-CD1	120V 1P 2W
L-5	☐	(1) 90W LED	2x4 LED CLEANROOM RECESSED TROFFER	KENALL CSEDI-24-90L-50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-5A	☐	(1) 67W LED	2x4 LED CLEANROOM RECESSED TROFFER	KENALL CSEDI-24-67L50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-5AE	☐	(1) 67W LED	2x4 LED CLEANROOM RECESSED TROFFER ON GENERATOR	KENALL CSEDI-24-67L50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-5B	☐	(1) 45W LED	2x4 LED CLEANROOM RECESSED TROFFER	KENALL CSEDI-24-45L50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-5BE	☐	(1) 45W LED	2x4 LED CLEANROOM RECESSED TROFFER ON GENERATOR	KENALL CSEDI-24-45L50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-5E	☐	(1) 90W LED	2x4 LED CLEANROOM RECESSED TROFFER ON GENERATOR	KENALL CSEDI-24-90L-50K-DIM1-DV-2F-2H-SYM	120V 1P 2W
L-6	— —	(1) 24W LED	LINEAR RECESSED LED	EATON S121-DR-LO-40-GYP-0072-1-U-DD-1-B	120V 1P 2W
L-6E	— —	(1) 24W LED	LINEAR RECESSED LED ON GENERATOR	EATON S121-DR-LO-40-GYP-0072-1-U-DD-1-B	120V 1P 2W
L-7	— —	(1) 41W LED	4' LINEAR LED STRIP	EATON 4SNLED-LD5-33SL-LW-UNV-L840-C	120V 1P 2W
L-7A	— —	(1) 41W LED	4' LINEAR LED STRIP	EATON 8SNLED-LD5-74SL-LW-UNV-L840-C	120V 1P 2W
L-7AE	— —	(1) 41W LED	4' LINEAR LED STRIP ON GENERATOR	EATON 8SNLED-LD5-74SL-LW-UNV-L840-C	120V 1P 2W
L-7E	— —	(1) 41W LED	4' LINEAR LED STRIP ON GENERATOR	EATON 4SNLED-LD5-33SL-LW-UNV-L840-C	120V 1P 2W
L-9	☐	(1) 30W LED	2x4 LED RECESSED TROFFER	LITHONIA 2ESL4-40L-MVOLT-EZ1-LP840-N100	120V 1P 2W
L-9E	☐	(1) 30W LED	2x4 LED RECESSED TROFFER ON GENERATOR	LITHONIA 2ESL4-40L-MVOLT-EZ1-LP840-N100	120V 1P 2W
L-10	— —	(1) 38W LED	8' LED STRIP	FOCAL POINT FNRS-FL40-625LF-40K-1C-UNV-L11-G-CLV24-PS-8'-C8	120V 1P 2W
L-11	○	(1) 17W LED	VANITY LIGHT	TECH LIGHTING 700BCTR33S-LED930	120V 1P 2W
L-12	⊕	(3) 20W LED	DECORATIVE PENDANT	TECH LIGHTING 700LSESN3S-LED930	120V 1P 2W
L-13	⊕	(1) 20W LED	DECORATIVE PENDANT	BELLACORE 2133146	120V 1P 2W
L-14	⊕	(1) 35W LED	DECORATIVE PENDANT	TECH LIGHTING 700FJRIRUS-24	120V 1P 2W
L-15	— —	(1) 20W LED	DOWNLIGHT	FWSL-FL-450LF-40K-1C-UNV-LD1-U-WH-6FT	120V 1P 2W
L-16	○	(1) 3W LED	CABINET LIGHTING	HAFELE LOOX COLLECTION 833.78.151	120V 1P 2W
L-17	— —	(1) 21.4W LED	UNDER CABINET LIGHT	EATON HALO HU30	120V 1P 2W
L-18	— —	(1) 8W LED	LED STRIP LIGHT	LUMINI LineLED LLDW36-27-41K-SL-SL-XX-PSV010WD96-24	MULTIPLE
L-19	○	(1) 26W 3000K CFL	JELLY JAR SCONCE	PHILIPS QUALITY EXCELINE RLW26HFLCGC-1	120V 1P 2W
XR	☐	(1) INCLUDED	REMOTE LAMP HEAD	LITHONIA ELA-QWP-L0309-SD	120V 1P 2W

ELEVATOR EQUIPMENT SCHEDULE

CALLOUT	SYMBOL	VOLTS	KVA	BREAKER	CIRCUIT	WIRE CALLOUT	DISCONNECT DESCRIPTION
E-CAB	☐	120V 1P 2W	1.2	20/1	E2-27	1/2"C.1#12.#12N.#12G	30A/1P/NEMA 1
ELEV-A	☐	208V 3P 4W	22.45	80/3	EMDP-19,21,23	1-1/4"C.3#2.#2N.#8G	100/3/NEMA 1/80A
ESP-1	☐	120V 1P 2W	1.92	20/1	E2-29	1/2"C.1#12.#12N.#12G	30A/1P/NEMA 1



CROSSFIELDS
CHIROPRACTIC OFFICE DESIGN



THIS DRAWING IS THE PROPERTY OF CROSSFIELDS, INC. AND ANY REPRODUCTION OR COPYING OF THIS DRAWING, IN WHOLE OR PART IS PROHIBITED WITHOUT WRITTEN PERMISSION.

INNOVATION COMPOUNDING
DR. SHAWN HODGES
6095 PINE MOUNTAIN RD, SUITE 104
KENNESAW, GA 30152

REVISIONS:		
NO.	DATE	DESCRIPTION

DRAWN BY: **AT** CHECKED BY: **BA**
DATE: **09.24.19**
PROJECT NUMBER: **17125-IC**
SHEET NO: **E0.4**

ISSUED FOR PERMITTING