NEW PANEL: MDP

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 800 AMP | MAIN CIRCUIT BREAKER | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	FRAME (NON-T)	CKT NO	A	B	C	CKT NO	FRAME (NON-T)	TRIP	WIRE	LOAD SERVED	LOAD KVA
27.00		3R			1				2					0.00
25.29	PANEL "R"	3R	250		3				4	225		3R	SPD	0.00
20.52		3R			5				6				(NOTE 7)	0.00
13.54		3R												0.00
33.19	PANEL "M"	3R	400		7				8	225		3R	SPARE	0.00
12.25		3R											SPUTURE/EXPANSION	0.00
0.00					9				10	225		3R	SPARE	0.00
0.00	SPACE ONLY													0.00
0.00					11				12				SPACE ONLY	0.00
0.00	SPACE ONLY													0.00
0.00					13				14				SPACE ONLY	0.00
0.00	SPACE ONLY													0.00
180.7							SUB-TOTALS							0.0

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	9.1	CONNECTED
HEATING	19.6	A= 59.6 KVA / 451.2 A
COOLING	61.2	B= 56.9 KVA / 466.8 A
VENTILATION	5.3	C= 58.2 KVA / 462.9 A
MOTORS	1.9	DEMAND
KITCHEN	0.5	A= 54.9 KVA / 450.0 A
RECEPTACLES	58.6	B= 51.5 KVA / 428.0 A
WATER HEATER	1.4	C= 51.4 KVA / 427.7 A
MISC	13.7	DEMAND @ 125%
SPARE	0.7	A= 67.8 KVA / 562.5 A
TOTAL (CONNECTED)	180.2	B= 64.4 KVA / 530.2 A
TOTAL (DEMAND)	158.5	C= 64.2 KVA / 534.8 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE "ALL MOTOR" SPD (ASM / MODE 4WAY / PHASE).

NEW PANEL: M — SECTION 1

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 400 AMP | MAIN LUGS ONLY | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	POLES	CKT NO	A	B	C	CKT NO	POLES	TRIP	WIRE	LOAD SERVED	LOAD KVA
2.20	CU-1	12	20	1	1				2	1	20	12	(EWH-1) (GARAGE/ROOM 151)	1.65
2.20		12			3				4			12		0.00
3.03	CU-2	8	40	3	5				6			12	(EWH-2 MECHANICAL 154)	1.00
3.09		6			7				8			12		1.00
2.20	CU-3	10	30	1	9				10	1	15	12	(EWH-3 MECHANICAL 146)	1.00
2.20		10			11				12			12		1.00
2.20	CU-4	10	30	1	13				14	2	20	10	(ERV-1 MEZZANINE)	1.65
2.20		10			15				16			12		1.65
4.03	CU-5	4	60	1	17				18	1	20	12	(DU-1 LOBBY 101)	1.00
4.03		4			19				20			12	(ANC-1 VT 126)	1.35
4.03	CU-6	4	60	1	21				22	1	20	12	(EWH-4 (EXTERIOR STORAGE 2)	1.00
4.03		4			23				24			12		1.00
2.20	CU-7	4	60	2	25				26	1	15	12	(EWH-5 (MEZZANINE)	1.00
4.09		4			27				28			12		1.00
3.63	CU-8	8	40	2	29				30	2	30	10	(DU-2 (LOBBY) & AC-2	1.14
3.63		8			31				32			10		1.14
4.00	CU-9	4	60	2	33				34	1	15	12	(EFH-2 (GARAGE 138)	0.32
4.62		4			35				36				SPACE ONLY	0.00
2.20	CU-10	10	30	1	37				38				SPACE ONLY	0.00
2.20		10			39				40				SPACE ONLY	0.00
2.32	(EWH-1 (GSELLY 139)	12	15	1	41				42				SPACE ONLY	0.00
92.3							SUB-TOTALS							19.0

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	0.0	CONNECTED
HEATING	0.0	A= 18.5 KVA / 154.1 A
COOLING	0.0	B= 19.3 KVA / 152.7 A
VENTILATION	0.0	C= 19.1 KVA / 155.2 A
MOTORS	0.0	DEMAND
KITCHEN	0.0	A= 18.5 KVA / 154.1 A
RECEPTACLES	56.6	B= 19.3 KVA / 152.7 A
WATER HEATER	0.0	C= 19.1 KVA / 155.2 A
MISC	12.5	DEMAND @ 125%
SPARE	0.7	A= 23.1 KVA / 192.6 A
TOTAL (CONNECTED)	79.3	B= 22.8 KVA / 190.8 A
TOTAL (DEMAND)	55.9	C= 23.9 KVA / 198.9 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE SQUARE-A SPD (ASM / MODE 4WAY / PHASE) 200 MIN.
8. PROVIDE BREAKER WITH HANDLE LOCK-ON DEVICE.

NEW PANEL: M — SECTION 2

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 400 AMP | MAIN LUGS ONLY | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	POLES	NOTES	CKT NO	A	B	C	CKT NO	NOTES	POLES	TRIP	WIRE	LOAD SERVED	LOAD KVA
1.65	(DU-1 (MEZZANINE)	12	15	1		43				44		1	20	12	(FAN) F-1,2	0.45
1.65	(DU-2 (MEZZANINE)	12	15	1		45				46		1	20	12	(FAN) F-3,4,5,6,7,8	0.24
1.07	(DU-3 (MEZZANINE)	12	15	1		47				48		1	15	12	(WH1 / RCP1 (MECHANICAL 154)	0.70
1.07	(DU-4 (MEZZANINE)	12	15	1		49				50		1	15	12	(WH2 / RCP2 (EXT STORAGE 1/2)	0.75
1.65	(DU-5 (MECHANICAL 154)	12	20	1		51				52		2	20	12	GARAGE ROLLUP DOOR	0.50
1.65	(DU-6 (JANITOR 122)	12	20	1		53				54		2	20	12	GARAGE ROLLUP DOOR	0.50
1.88	(DU-7 (JANITOR 122)	12	20	1		55				56		2	20	12	WHEELCHAIR LIFT	0.59
1.65	(DU-8 (CASH STORAGE 135)	12	20	1		57				58		2	20	12	MECHANICAL LAB DRYER	0.40
1.88	(DU-9 (CASH STORAGE 135)	12	20	1		59				60		2	20	12	MECHANICAL CONTROLS	0.50
1.07	(DU-10 (CASH STORAGE 135)	12	15	1		61				62			20		SPARE	0.00
3.00	SPARE	12	15	1		63				64			20		SPARE	0.00
0.00	SPARE	12	15	1		65				66			20		SPARE	0.00
0.00	SPARE	12	15	1		67				68			20		SPARE	0.00
0.00	SPARE	12	15	1		69				70			20		SPARE	0.00
0.00	SPARE	12	15	1		71				72			20		SPARE	0.00
0.00	SPARE	12	20	1		73				74			20		SPARE	0.00
0.00	SPARE	12	20	1		75				76			20		SPARE	0.00
0.00	SPARE	12	20	1		77				78			20		SPARE	0.00
0.00	SPACE ONLY					79				80					SPACE ONLY	0.00
0.00	SPACE ONLY					81				82					SPACE ONLY	0.00
0.00	SPACE ONLY					83				84					SPACE ONLY	0.00
14.2							SUB-TOTALS									5.4

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	0.0	CONNECTED
HEATING	0.0	A= 7.5 KVA / 62.2 A
COOLING	0.0	B= 8.1 KVA / 67.0 A
VENTILATION	1.8	C= 8.1 KVA / 66.7 A
MOTORS	1.9	DEMAND
KITCHEN	0.5	A= 7.5 KVA / 62.2 A
RECEPTACLES	0.0	B= 8.2 KVA / 67.6 A
WATER HEATER	1.4	C= 8.1 KVA / 66.7 A
MISC	0.9	DEMAND @ 125%
SPARE	0.0	A= 9.3 KVA / 77.8 A
TOTAL (CONNECTED)	19.7	B= 7.7 KVA / 63.7 A
TOTAL (DEMAND)	19.7	C= 7.6 KVA / 63.4 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE FEED THRU LUGS.
8. REFER TO MECHANICAL CONNECTION SCHEDULES FOR DETAILS.
9. 9A - DENOTES SEE PLANS FOR WIRE SIZE

NEW PANEL: R — SECTION 1

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 250 AMP | MAIN LUGS ONLY | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	POLES	CKT NO	A	B	C	CKT NO	POLES	TRIP	WIRE	LOAD SERVED	LOAD KVA
0.90	REC - WEST 101 - LOBBY 101	12	20		1				2		20	12	REC - RECORDS/DISPATCH 103	0.72
0.09	REC - TOILET 106, 107	12	20		3				4		20	12	REC - RECORDS/DISPATCH 103	1.08
1.08	REC - FUTURE OFFICE 102	12	20		5				6		20	12	REC - RECORDS/DISPATCH 103	1.08
1.08	REC - DEPUTY CHIEF 110	12	20		7				8		20	12	REC - CHIEF 113	1.08
0.50	EWC - LOBBY 101	12	20	3	9				10		20	12	REC - MEN 126, WOM 125, JAN122	0.90
1.20	REC - COPIER - WORK/BRK 120	12	20		11				12		20	12	REC - CONF 119	0.90
0.18	REC - WORK/BRK 120 - COFFEE	12	20		13				14		20	12	REC - CONF 119	1.26
0.50	REC - WORK/BRK 120	12	20		15				16		20	12	REC - PATROL 118, CONF 119	0.72
1.00	FRIDGE - WORK/BRK 120	12	20	9	17				18		20	12	REC - INVEST CAPTAIN 115	1.66
1.68	REC - SARGUET BULL PEN 126	12	20		19				20		20	12	REC - PATROL BULL PEN 127	1.08
1.68	REC - SARGUET BULL PEN 126	12	20		21				22		20	12	REC - PATROL BULL PEN 127	1.08
1.68	REC - SARGUET BULL PEN 126	12	20		23				24		20	12	REC - PATROL BULL PEN 127	0.72
1.68	REC - SARGUET BULL PEN 126	12	20		25				26		20	12	REC - PATROL BULL PEN 127	1.08
1.00	REC - IT 125	12	20	10	27				28		20	12	REC - DETECTIVES BULL PEN 129	1.08
1.00	REC - IT 125	12	20	10	29				30		20	12	REC - DETECTIVES BULL PEN 129	1.08
1.00	REC - IT 125	12	20	10	31				32		20	12	REC - DETECTIVES BULL PEN 129	1.08
1.00	REC - IT 125	12	20	10	33				34		20	12	REC - GARAGE 138, SALLY 139	0.72
1.00	REC - CORRIDOR 125, 145,149	12	20		35				36		20	12	REC - EVIDENCE LAB 135	0.72
0.36	REC - MECH 146, ELEC 147	12	20		37				38		20	12	REC - 135, 136, 137, 132	0.90
0.72	REC - 140, 141, 142, 143	12	20		39				40		20	12	REC - EXTERIOR GFI	0.72
1.80	REC - COPIER - (NEXT) 141	12	20		41				42		20	12	REC - ROOFTOP GFI	0.54
16.5							SUB-TOTALS							20.6

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	9.1	CONNECTED
HEATING	0.0	A= 37.1 KVA / 275.2 A
COOLING	0.0	B= 25.5 KVA / 210.5 A
VENTILATION	0.0	C= 26.8 KVA / 224.2 A
MOTORS	0.0	DEMAND
KITCHEN	0.0	A= 18.5 KVA / 154.1 A
RECEPTACLES	56.6	B= 19.3 KVA / 152.7 A
WATER HEATER	0.0	C= 19.1 KVA / 155.2 A
MISC	12.5	DEMAND @ 125%
SPARE	0.7	A= 23.1 KVA / 192.6 A
TOTAL (CONNECTED)	79.3	B= 22.8 KVA / 190.8 A
TOTAL (DEMAND)	55.9	C= 23.9 KVA / 198.9 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE SQUARE-A SPD (ASM / MODE 4WAY / PHASE) 200 MIN.
8. PROVIDE BREAKER WITH HANDLE LOCK-ON DEVICE.

NEW PANEL: R — SECTION 2

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 250 AMP | MAIN LUGS ONLY | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	POLES	NOTES	CKT NO	A	B	C	CKT NO	NOTES	POLES	TRIP	WIRE	LOAD SERVED	LOAD KVA
1.44	REC - WALL - TRAINING 102	12	20			43				44			20	12	REC - FLOOR - TRAINING 102	1.08
1.08	REC - WALL - TRAINING 102	12	20			45				46			20	12	REC - FLOOR - TRAINING 102	1.08
1.44	REC - WALL - TRAINING 102	12	20			47				48			20	12	REC - FLOOR - TRAINING 102	1.08
1.08	PROJECTOR - TRAINING 102	12	20			49				50			20	12	REC - FLOOR - TRAINING 102	1.08
0.54	REC - MECH 154 SPRINKLER 157	12	20			51				52			20	12	REC - FLOOR - TRAINING 102	1.08
0.54	REC - VIDEO WORKSTATION 59	12	20			53				54			20	12	REC - WEST FLAG DRIVE 100	0.72
1.69	REC - CORR 11 JAN 31 STOR 38	12	20			55				56		3	10		GENERATOR BLOCK HEATER	1.00
1.08	REC - TOILET/CORR 21,27,29,34	12	20			57				58						1.80
0.54	REC - ARMORY 20, PASSAGE 30	12	20			59				60		2	10		GENERATOR BATT CHARGER	1.00
0.50	REC - CORR 12 BRK13, STOR 14,26	12	20			61				62		2	10		GENERATOR RECEPTACLE	0.18
0.50	REC - VENDING 18	12	20	9		63				64		2	10		GENERATOR 12	0.50
0.50	REC - VENDING 16	12	20	9		65				66		2	10		REC - FITNESS 11, CORR 12 BRK 13	1.08
0.50	REC - VENDING 17	12	20	9		67				68		2	10		REC - PATROL 11	0.72
0.50	REC - ICE 19	12	20	9		69				70		2	10		REC - FITNESS 11	0.90
0.50	REC - FRIDGE - BRK RM 13	12	20	9		71				72		2	10		EXTERIOR LIGHTS	0.90
0.50	REC - DISHWASHER - BRK RM 13	12	20	9		73				74		2	10		REC - MEZZANINE	0.36
0.50	REC - COFFEE - BRK RM 13	12	20	9		75				76		2	10		GATE MOTOR (9524)	0.50
0.50	REC - BRK RM 13	12	20	9		77				78		2	10		GATE MOTOR (9624)	0.50
0.30	FIRE ALARM CIRCUIT	12	20	10,11		79				80		2	10		GENERATOR LIGHTS	0.30
0.72	LIGHTING CONTACTOR	12	20			81				82		2	10		REC - EXTERIOR GFI	0.72
1.80	GATE MOTOR (9524)	10	20			83				84		2	10		GATE MOTOR (9624)	0.50
15.1							SUB-TOTALS									18.1

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	0.3	CONNECTED
HEATING	0.0	A= 10.4 KVA / 86.9 A
COOLING	0.0	B= 10.0 KVA / 82.9 A
VENTILATION	0.0	C= 9.8 KVA / 81.4 A
MOTORS	0.9	DEMAND
KITCHEN	0.0	A= 8.2 KVA / 67.9 A
RECEPTACLES	22.2	B= 8.0 KVA / 66.4 A
WATER HEATER	0.0	C= 8.1 KVA / 67.2 A
MISC	1.0	DEMAND @ 125%
SPARE	0.0	A= 10.2 KVA / 84.6 A
TOTAL (CONNECTED)	24.5	B= 10.0 KVA / 82.8 A
TOTAL (DEMAND)	24.2	C= 10.1 KVA / 84.0 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE FEED THRU LUGS.
8. LOAD TOTAL INCLUDES FEED THRU SECTIONS.
9. PROVIDE SQUARE-A SPD (ASM / MODE 4WAY / PHASE) 200 MIN.
10. PROVIDE BREAKER WITH HANDLE LOCK-ON DEVICE.

NEW PANEL: R — SECTION 3

SQD MFGR

VOLTAGE: 120 / 208 | 3 PHASE | 4 WIRE | NQOD TYPE
MOUNTING: SURFACE | 250 AMP | MAIN LUGS ONLY | 22,000 AIC

LOAD KVA	LOAD SERVED	WIRE	TRIP	POLES	NOTES	CKT NO	A	B	C	CKT NO	NOTES	POLES	TRIP	WIRE	LOAD SERVED	LOAD KVA
0.18	LIGHTS	12	20			85				86			20		SPARE	0.00
0.09	LIGHTS	12	20			87				88			20		SPARE	0.00
0.40	LIGHTS	12	20			89				90			20		SPARE	0.00
0.64	LIGHTS	12	20			91				92			20		SPARE	0.00
0.04	LIGHTS	12	20			93				94			20		SPARE	0.00
1.27	LIGHTS	12	20			95				96			20		SPARE	0.00
0.55	LIGHTS	12	20			97				98			20		SPARE	0.00
0.76	LIGHTS	12	20			99				100			20		SPARE	0.00
0.82	LIGHTS	12	20			101				102			20		SPARE	0.00
0.50	LIGHTS	12	20			103				104			20		SPARE	0.00
0.50	LIGHTS	12	20			105				106			20		SPARE	0.00
0.70	EXTERIOR LIGHTS	12	20			107				108			20		SPARE	0.00
0.18	EXTERIOR LIGHTS	12	20			109				110			20		SPARE	0.00
0.30	MEZZANINE LIGHTS	12	20			111				112			20		SPARE	0.00
0.50	PWR. SERVAGE BACKFLOW	12	20			113				114			20		SPARE	0.00
0.90	DOMESTIC BACKFLOW	12	20			115				116			20		SPARE	0.00
0.00	SPARE		20			117				118			20		SPARE	0.00
0.00	SPARE		20			119				120			20		SPARE	0.00
0.00	SPARE		20			121				122			20		SPARE	0.00
0.00	SPARE		20			123				124			20		SPARE	0.00
0.00	SPARE		20			125				126			20		SPARE	0.00
9.4							SUB-TOTALS									4.8

LOAD	KVA	TOTAL LOAD PER PHASE
LIGHTS	6.5	CONNECTED
HEATING	0.0	A= 3.3 KVA / 27.5 A
COOLING	0.0	B= 5.1 KVA / 42.5 A
VENTILATION	0.0	C= 5.5 KVA / 45.8 A
MOTORS	0.9	DEMAND
KITCHEN	0.0	A= 3.2 KVA / 26.8 A
RECEPTACLES	0.0	B= 5.1 KVA / 42.5 A
WATER HEATER	0.0	C= 5.5 KVA / 45.8 A
MISC	1.0	DEMAND @ 125%
SPARE	0.0	A= 4.0 KVA / 33.3 A
TOTAL (CONNECTED)	8.5	B= 6.4 KVA / 53.1 A
TOTAL (DEMAND)	8.4	C= 6.9 KVA / 57.3 A

NOTES:
1. BREAKER FRAME SHALL BE AS REQD PER PANEL AIC RATING
2. SHALL BE FULLY RATED - SERIES RATINGS NOT ALLOWED.
3. ALL BUSSING, INCL GND AND NEUTRAL, SHALL BE COPPER.
4. ALL MOUNTED PANEL & BRKR LUGS SHALL MATCH CONDTRS.
5. PROVIDE HINGED DOOR-IN-DOOR WITH LOCK OUTER DOOR LOCK.
6. PROVIDE METAL DIRECTORY FRAME.
7. PROVIDE FEED THRU LUGS.
8. LOAD TOTAL INCLUDES FEED THRU SECTIONS.
9. PROVIDE SQUARE-A SPD (ASM / MODE 4WAY / PHASE) 200 MIN.
10. PROVIDE BREAKER WITH HANDLE LOCK-ON DEVICE.

WATER HEATER SCHEDULE - GAS FIRED

SYMBOL	DESCRIPTION	DISCONNECT	FEEDER
WH-1	GAS FIRED WATER HEATER	MANUAL MOTOR STARTER	2#12,1#12G,3/4"C.
WH-2	GAS FIRED WATER HEATER	MANUAL MOTOR STARTER	2#12,1#12G,3/4"C.

HW CIRCULATION PUMP SCHEDULE

SYMBOL	ELECTRICAL DATA				DISCONNECT	FEEDER
	HP	VOLTS	PH	HZ		
RCP1	1/24	120	1	60	MANUAL MOTOR STARTER	2#12,1#12G,3/4"C.
RCP2	1/24	120	1	60	MANUAL MOTOR STARTER	2#12,1#12G,3/4"C.

VARIABLE SPEED CONDENSING FURNACE SCHEDULE

SYMBOL	FAN MOTOR	ELECTRICAL DATA				DISCONNECT	FEEDER
	H.P.	FLA	MCA	FUSE	VOLTAGE		
DU-1	1/2	7.7	8.9	15	120V~1Ø	30/F15~1P	2#12,1#12G,3/4"C.
DU-2	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-3	1/2	7.7	8.9	15	120V~1Ø	30/F15~1P	
DU-4	1/2	7.7	8.9	15	120V~1Ø	30/F15~1P	
DU-5	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-6	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-7	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-8	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-9	1	12.8	13.8	20	120V~1Ø	30/F20~1P	
DU-10	1/2	7.7	8.9	15	120V~1Ø	30/F15~1P	

FAN SCHEDULE

SYMBOL	LOCATION	ELECTRICAL DATA			DISCONNECT	FEEDER
		WATTS	H.P.	VOLTAGE		
F-1	SALLYPORT		1/4	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	2#12,1#12G,3/4"C.
F-2	SALLYPORT		1/4	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-3	WOMEN 126	83	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-4	TOILET 143	17	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-5	DRUG STOR 131	17	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-6	MEN 124	83	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-7	TOILET 107	17	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	
F-8	TOILET 106	17	–	120V~1Ø	MANUAL MOTOR STARTER (BY M.C.)	

2-SPEED CONDENSING UNIT SCHEDULE (AIR COOLED)

SYMBOL	COMPRESSOR		FAN	ELECTRICAL DATA			DISCONNECT	FEEDER
	LRA	RLA	FLA	MCA	FUSE	VOLTAGE		
CU-1	83.0	15.3	2.1	21.1	30	208V~1Ø	30/F30~2P	2#10,1#10G,3/4"C.
CU-2	104.0	21.2	2.7	29.2	40	208V~1Ø	60/F40~2P	2#8,1#10G,3/4"C.
CU-3	83.0	15.3	2.1	21.1	30	208V~1Ø	30/F30~2P	2#10,1#10G,3/4"C.
CU-4	83.0	15.3	2.1	21.1	30	208V~1Ø	30/F30~2P	2#10,1#10G,3/4"C.
CU-5	152.9	28.8	2.7	38.7	60	208V~1Ø	60/F60~2P~3R	2#4,1#10G,3/4"C.
CU-6	152.9	28.8	2.7	38.7	60	208V~1Ø	60/F60~2P~3R	2#4,1#10G,3/4"C.
CU-7	152.9	28.8	2.7	38.7	60	208V~1Ø	60/F60~2P~3R	2#4,1#10G,3/4"C.
CU-8	104.0	21.2	2.7	29.2	40	208V~1Ø	60/F40~2P~3R	2#8,1#10G,3/4"C.
CU-9	152.9	28.8	2.7	38.7	60	208V~1Ø	60/F60~2P~3R	2#4,1#10G,3/4"C.
CU-10		15.3	2.0	21.1	30	208V~1Ø	30/F30~2P~3R	2#10,1#10G,3/4"C.

ENERGY RECOVERY VENTILATOR SCHEDULE

SYMBOL	LOCATION	POWER			DISCONNECT	FEEDER
		MCA	MOCP	VOLTAGE		
ERV-1	MEZZANINE	17.7	25.0	208V~1Ø	30/F25~2P