SECTION 16010
ELECTRICAL GENERAL

1.0 GENERAL

1.01 SCOPE

A. Division 16 includes all Specifications in the 16000 series and the accompanying Electrical Drawings. Provide all labor, materials and equipment, and all necessary operations to provide the complete scope of the electrical systems intended under this Division. Division 16 is not a stand alone document, but a part of the complete Project Documents.

B. Attention is called to the fact that there are many interfaces between the work required in this Division and the work required in other Divisions. Provide the necessary interface and coordination with other Divisions to provide a complete project.

1.02 EXISTING CONDITIONS

A. Attention is called to the fact that the work is to be performed within an existing, operational facility. Prior to the submission of bids, each bidder shall visit the project site, thoroughly investigate and be familiar with all existing conditions which will affect their work; especially the work to be performed above the existing ceilings.

B. When this project is finished, the work under this Division shall be complete in every respect, completely integrated with all the existing systems, and left in perfect operating condition. The electrical service to the building shall not be interrupted at any time without written coordination of the building's Owner. All existing electrical equipment removed during the project shall be removed from the site after inspection of the building's Owner. All existing electrical systems required to be operating at the project's completion or required to remain in use during the project shall be reconnected, replaced, rerouted or otherwise made to fit with proper workmanship techniques and left in safe working order.

C. Connect new work to existing work in a neat and workmanlike manner. Where an existing structure must be cut or existing utilities interfere, such obstructions shall be bypassed, removed, replaced or relocated, patched and repaired. Work disturbed or damaged shall be replaced or repaired to its prior condition.

D. Prior to the start of any demolition or construction, secure the services of a qualified, EPA Certified asbestos abatement agency to check the existing insulation, etc. for asbestos. Should asbestos be found, do not proceed with demolition or construction; notify the Architect in any case in writing of the agency's findings.

1.03 CODES AND REGULATIONS

A. All work under this Division shall comply with all local building codes, laws, regulations, ordinances and the requirements of the 2017 National Electrical Code with Georgia Amendments.

B. Where conflicts of installation requirements occur between the aforementioned codes, regulations or the Contract Documents, the most restrictive shall govern.

C. Obtain all permits and licenses and pay all fees required by local authorities. Arrange for all necessary inspections required by the authorities having jurisdiction and provide written certificates of approval to the project Owner or his designated representative.

1.04 DEFINITIONS

A. Contract Documents: The complete set of project Drawings and Specifications.

B. Provide: Furnish, install and connect.

C. Work: All materials installed, including all labor to provide complete system.

D. Wiring or Wired: All wire or cable installed in conduit from panelboard to equipment and connected at both ends with all required boxes, connectors, couplings, etc.

E. Conduit: Rigid steel conduit; intermediate metal conduit (I.M.C.); electrical metallic tubing (EMT) plastic conduit (PVC), electrical non-metal tubing (ENT), or flexible steel conduit.

1.05 DRAWINGS AND SPECIFICATIONS

A. The Drawings and Specifications together are to be considered as the Contract Documents. Any work shown in one and not shown in the other, or implied by either, shall be provided to give a complete project.

B. Should any conflicts exist between the Drawings and Specifications or there is an item shown/called for which is not clearly defined, immediately submit a request for clarification. No additional monies will be granted later when a conflict is resolved or an item is more clearly defined.

C. The Drawings are schematic and are not intended to show the exact location outlets, etc. or the routing of conduit.

D. The exact location of equipment requiring electrical connections (mechanical equipment, elevators, lights, etc.) shall be as located by other Divisions of the Contract Documents. Refer to the Architectural, Structural and Mechanical Documents for dimensions and details of building construction and provide work described in this Division so that it conforms to the details of the project. The right is reserved to relocate any receptacle, switch or other outlet a maximum of 10'-0" before it is permanently installed without incurring additions to the Contract amount.

1.06 SITE VISIT

A. Visit the site and become familiar with all aspects of the site and existing conditions before submitting Contract price.

B. No allowance will be made for lack of knowledge of existing conditions.

1.07 DEVIATIONS

A. No deviations from the Contract Documents shall be made without the full knowledge and written consent of the Architect.

B. If the existing conditions make it desirable to modify the Contract Documents in regard to this work, provide a written request to the Architect.

2.0 PRODUCTS

2.01 STANDARDS FOR MATERIALS AND WORKMANSHIP

A. All materials used shall be new and shall be stamped with the label of Underwriters Laboratories, Inc. (UL).

B. All materials shall meet the standards of the following associations and institutes where applicable:

1. National Fire Protection Association (NFPA)
2. American Society of Testing Materials (ASTM)
3. American National Standards Institute (ANSI)
4. National Electrical Manufacturer's Association (NEMA)
5. Institute of Electrical and Electronic Engineers (IEEE)

C. Manufacturers names and catalog numbers specified herein are intended to describe the material and set the standard of quality. All bids shall be based on material specified. Requests for approval of material not specified shall be considered if the request is in written form and submitted to the Architect no later than fourteen (14) days before bid date. All requests shall conform with the provisions of the general and supplementary conditions.

D. Samples of materials requested to be substituted shall be furnished upon the request of the Architect.

2.02 SHOP DRAWINGS AND SUBMITTAL

A. The Engineer's review of shop drawings or submittals is a cursory review to check for general compliances of submittals with the design intent of the Contract Documents. The Engineer's review does not relieve the Contractor of his responsibility of complying with the Contract Documents. All coordination of the work in strict compliance with the Contract Documents is the sole responsibility of the Contractor.

B. The following items shall be submitted for review:

1. Conduit and wire
2. Devices
3. Coverplates
4. Fuses
5. Overcurrent devices
6. Disconnect switches
7. Lighting fixtures
8. Panelboards
9. Transformers

C. All shop drawings and submittals shall be submitted in compliance with the requirements of the general and supplementary conditions. No more than four (4) copies of submittal data will be reviewed. Any additional copies will be returned unmarked. The responsibility of copying review comments on any additional copies will rest solely with the contractor.

D. All submittals shall bear the name of the manufacturer to be used.

E. All shop drawings and submittals shall include a stamped indication signifying that the submittal has been reviewed for compliance with the Contract Documents by the Contractor. This stamped indication also represents the fact that the Contractor has checked this submittal for its interaction with all other Divisions and certifies by his signature or initials that all coordination has taken place. The stamp shall include the date, name of the Contracting Firm, the signature of the Contractor, certification of compliance and approval. This stamp shall be on the submittal before the Engineer will review it.

F. The engineer will review an individual submittal not more than twice. If the submittal is rejected again on the second review, the contractor will bare all responsibility for paying for the engineer's time for additional reviews. Such payments to the engineer shall be withheld from the next monthly pay application.

2.03 RECORD (AS-BUILT) DRAWINGS AND MAINTENANCE MANUALS

A. At job completion, submit to the Architect, a set of Construction Documents showing all deviations from the Contract Documents. The Drawings shall also have dimensions locating all underground conduits.

B. At job completion, submit to the Architect, three (3) sets of maintenance and instruction manuals for all equipment furnished on the project.

3.0 EXECUTION

3.01 COORDINATION

A. Coordinate all space requirements with all other Divisions before installing any work. Install work such that adequate space will be allotted for all other work from other Divisions to be installed and also will allow room for future access for repair and maintenance.

B. Any work installed without proper coordination shall be relocated at the Architect's direction without increasing the Contract price.

C. During the bidding process or the pricing for a guaranteed maximum price, coordinate with all other Divisions for the total amount of work required in Division 16. Any work shown or implied in another Division requiring work in Division 16 shall be included in the Contract price regardless of whether or not it is addressed in Division 16.

3.02 PROTECTION OF MATERIALS

A. All equipment shall have the original finish when the building is turned over to the Owner.

B. Protect equipment during construction from dirt, water, chemical, mechanical damage, etc. Protect all conduit openings so that no foreign material will enter the conduit.

3.03 TESTS, DEMONSTRATION AND INSTRUCTIONS

A. Test all systems described in this Division in the presence of the Owner or designated representative upon completion of the work. Demonstrate that the installation is in accordance with Contract Documents.

B. Any work found not to be in compliance with the Contract Documents shall be repaired or replaced without incurring any additions to the Contract price.

C. Provide to the Owner during construction on maintenance and operation of all systems and equipment provided under this Division. Provide all necessary labor and personnel to thoroughly present these instructions.

3.04 GUARANTEE

A. All system, equipment, components, work, etc. provided under this Division shall be covered by a one year guarantee starting at the time of final acceptance of the work by the Owner. Any defects in the work, systems, equipment or components found during this year shall be corrected at no charge. The guarantee shall include providing all necessary cutting, patchwork, repainting, etc. to make the work complete and new.

B. Present this guarantee and any additional warranties or guarantees on furnished equipment or systems to the Architect. All equipment or system guarantees are in addition to the general guarantee.

SECTION 16100
ELECTRICAL BASIC MATERIALS & METHODS

1.0 GENERAL

1.01 DESCRIPTION

A. All work specified in this Section shall comply with the provisions of Section 16010.

B. This Section describes the basic electrical materials and installation methods that are acceptable and applicable to Division 16.

2.0 PRODUCTS

2.01 CONDUIT

A. Galvanized rigid steel conduit shall be low carbon, hot-dipped galvanized both inside and out with threaded joints.

B. Intermediate metal conduit (IMC) shall be steel, galvanized both inside and out with threaded joints.

C. Electrical metallic tubing (EMT) shall be steel, galvanized both inside and out.

D. Plastic conduit (PVC) shall be schedule 40 PVC heavy wall type. A grounding conductor shall be provided.

E. Flexible metal conduit shall be flexible steel conduit, tubing and shall meet Underwriters Laboratories Standard for Flexible Steel Conduit.

F. Liquid-tight flexible metal conduit and liquid-tight non-metallic conduits shall be liquid-tight and sunlight resistant.

G. Steel conduit approved manufacturers are Allied, Triangle and Republic.

H. PVC and ENT conduit approved manufacturers are Carlon and Triangle.

2.02 CONDUIT FITTINGS

A. Rigid conduit and IMC conduit fittings shall be zinc-coated, ferrous metal and taper threaded type.

B. EMT fittings shall be zinc-coated steel and hexnut compression or set-screw type. EMT connectors shall have insulated throats.

C. PVC fittings, elbows and cement shall be produced by the same manufacturer. All joints shall be solvent welded in accordance with the manufacturer's recommendations.

D. Conduit connections to switchboards, motor control centers, transformers, panel cabinets, and pull boxes shall have grounding wedge lugs between the bushing and the box or locknuts designed to bite into the metal.

E. Each conduit end shall be provided with either an insulated throat connector or separate locknut and insulated bushing. Bushing shall be installed before any wire is pulled.

F. Conduit fittings approved manufacturers are Raco, Steel City, O.Z. Gedney, Thomas & Betts and Appleton.

G. Expansion fittings shall be provided in all conduit which crosses and expansion joint.

2.03 CONDUCTORS

A. Conductors shall be copper of 98% conductivity, 600 volt insulation. Sizes specified are AWG gauge for No. 4/0 and smaller and circular mils (MCM) for all sizes larger than no. 4/0. Conductors No. 10 and smaller shall be solid and type "THHN" or "THWN" insulation. No. 8 and larger shall be stranded and type "THW" or "XHHW" insulation.

2.04 OUTLETS

A. Outlet boxes and covers shall be of such form and dimensions as to be adapted to their specified usage, locations, size and quantity of conduit, and size and quantity of conductors entering the boxes. In special "Fire Rated" partitions, outlets shall comply with ASTM No. E119.

B. Flush ceiling outlets for surface or pendant mounted lighting fixtures shall be one-piece 4" square or octagonal pressed steel boxes. Boxes for devices in unfinished masonry walls or stud walls shall be pressed steel, square corner, sectional switch boxes, or shall be 4" square box with a square cornered tile wall cover, set flush with masonry construction. Boxes in concrete ceiling slab shall be octagonal, shallow concrete boxes. Welded boxes are not acceptable.

C. All outlet boxes in plaster or masonry walls or ceiling shall be provided with plaster rings.

D. Junction boxes and all outlets not indicated as containing wiring devices or lighting fixtures shall have covers. Covers for outlets in walls shall be as specified for wall switches and receptacles.

E. Outlet boxes exposed to the weather and outlet boxes for vaportight lighting fixtures and devices shall be of cast iron corrosion resistant type.

F. Outlet box approved manufacturers are Appleton, Raco, Steel City or Crouse-Hinds.

2.05 DISCONNECT SWITCHES

A. Disconnect switches shall be heavy-duty type, enclosed switches of quick-make, quick-break construction. Switches shall be horsepower rated for 600 volts AC and shall be Class R. Lugs shall be listed for copper and aluminum.

B. Fusible disconnect switches shall have provision for padlocking in the "off" position.

C. Switches shall be enclosed in NEMA 1 General purpose enclosure unless noted otherwise. Switches located on the exterior of the building or in "wet" locations shall have NEMA 3R enclosures.

D. Fusible disconnect switches shall have rejection type fuse clips with dual element, current limiting types of rating shown.

E. Disconnect switches shall be mounted to structure. Disconnect switches shall not be mounted to mechanical equipment or ductwork.

2.06 NAMEPLATES

A. Nameplates shall have 3/8" high engraved letters.

B. 120 or 208 volts: white core laminated bakelite with black finish.

C. 277 or 480 volts: white core laminated bakelite with red finish.

2.07 WALL SWITCHES

A. Wall switches shall be plastic, totally enclosed, quiet type, self-grounding, 120 volts and 20A rating and shall match existing if possible and equal the following:

Single Pole: Hubbell No. CS1221, or equal by Leviton, P&S or Cooper.

Double Pole: Hubbell No. CS1222, or equal by Leviton, P&S or Cooper.

Three-Way: Hubbell No. CS1223, or equal by Leviton, P&S or Cooper.

Four-Way: Hubbell No. CS1224, or equal by Leviton, P&S or Cooper.

B. Color shall be as selected by architect.

C. Flush motor switches with red pilot light and with overload protection for fractional horsepower motors shall be Hubbell No. HBL1221PL.

D. Key switches shall be Hubbell No. HBL1221L 20A Series or approved equal by P&S or Leviton.

2.08 RECEPTACLES

A. Duplex receptacles shall be plastic, two-pole, three wire, self-grounding, side wired, 125 volts and 15A rating and shall match existing if possible and be equal to the following: Duplex receptacles shall be Hubbell No. CR5262 Series, or equal by Leviton, P&S or Cooper, isolated ground type shall be Hubbell No. CR52526 Series, or equal by Leviton, P&S or Cooper.

B. Single receptacles shall be two-pole, three wire, self-grounding, side wired, 125 volts and 20A rating and shall be equal to the following: Single receptacles shall be Hubbell No. HBL5361 Series, or equal by Leviton, P&S or Cooper. Isolated ground type to be Hubbell No. IG-5361 Series, or equal by Leviton, P&S or Cooper.

C. Ground fault circuit interrupt (GFI) receptacles shall be Hubbell GFR5352, or equal by P&S, Leviton or Cooper.

D. Color shall be as selected by the Architect.

2.09 COVERPLATES

A. Coverplates for flush mounted devices shall be brushed finished stainless steel standard size, Hubbell "P" Series or equal by Leviton, P&S or Cooper.

B. Telephone outlet coverplates shall have same finish as above and have a bushed hole in the center.

C. Coverplates for exterior devices shall be self closing, die cast aluminum Hubbell WP8M or equal by Leviton, P&S or Cooper.

2.10 SMOKE AND FIRE STOP FITTINGS

A. Smoke and Fire Stop Fittings shall be UL listed for that purpose. The fittings used to seal conduit either on the outside of the conduit, busway or cable or internally shall have heat activated intumescent material which expands to fill all voids. Smoke and fire stop fittings shall be O.Z./Gedney "FIRE-SEAL" or Dow Corning silicone RTV foam with an hourly fire-rating equal to or higher than the rating of the floor, ceiling or wall through which the cable or conduit passes. The seals for conduit shall be of the flanged type.

2.12 FUSES

A. Provide all fuses. All fuses shall be of the same manufacturer. All fuses shall be of the high interrupting rating (200,000 Amps), current limiting type and manufactured by Bussmann. Fuses shall be provided for each fuse cutout and the specified quantity of fuses shall be furnished for spares.

B. Circuits 0 to 600 ampere shall be protected by rejection type, current limiting BUSSMANN LOWPEAK Dual Element Fuses LPN-RK (250 volts) or LPS-RK (600 volts). All dual-element fuses shall have separate overload and short-circuit clearing characteristics. The fuse must hold 500% of rated current for a minimum of 10 seconds and be listed by Underwriter's Laboratories, Inc., with an interrupting rating of 200,000 amperes RMS symmetrical. The fuses shall be UL Class RK-1.

C. Circuits 601 to 6000 ampere shall be protected by current limiting BUSSMANN HI-CAP time-Delay Fuses KRP-C. Fuses shall employ "O" rings as positive seals between the end bells and the glass melamine fuse barrel. The terminals shall be opened. Fuses shall be time-delay and must hold 500% of rated current for a minimum of 4 seconds, clear 200% rated current in 0.1 seconds or less and be listed by Underwriter's Laboratories, Inc., with an interrupting rating of 200,000 amperes RMS symmetrical. The fuses shall be UL Class RK-1.

D. Furnish and turn over to the Owner a minimum one (1) set of spare fuses (set consisting of three fuses) for each size and rating of fuse used. Where the number of fuses of the same type and rating actually installed exceeds five (5) sets, furnish an additional one set of spares for each five (5) or fraction thereof.

E. Provide a cabinet or rack to store the spare fuses, Bussman Cat. No. SFC

F. Acceptable manufacturers are Bussman or equal by Littlefuse.

3.0 EXECUTION

3.01 CONDUIT

A. Rigid steel (or IMC) shall be used for service entrance and all feeders and branch circuits where exposed to damage.

B. EMT shall be used for branch circuits, fire alarm and telephone when not underground or in concrete in contact with the earth.

C. Schedule 40 PVC may be used for all underground feeders, service entrance conductors when encased in 4" of concrete on all sides, or under the lowest floor slab.

D. Conduit shall be continuous from outlet to outlet, from outlet to cabinet, junction box and pull box. Conduit shall enter and be secured to all boxes, etc., in such a manner that each system will be electrically continuous from service to all outlets such that a good ground is provided. All conduit from cabinets and junction boxes shall terminate in approved outlet boxes or conduit fittings. Conduit connections to any box which has no threaded hub shall be double locknutted.

E. Provide junction boxes or pull boxes where shown and where necessary to avoid excessive runs or too many bends between outlets. The conduit sizes shown may increase if desired to facilitate the pulling of cables.

F. All conduit shall be concealed unless indicated otherwise. Install exposed conduit parallel with or at right angles to the building walls and support from walls or ceilings at intervals required by Code with approved galvanized iron clamps or hangers. Concealed conduit above the ceiling shall be supported independent of ceiling construction. Where ceilings of lay-in type are used, conduit must be installed high enough to permit removal of ceiling panels and lighting fixtures. Use threaded rods and hangers for supporting single conduit. Use trapeze hangers consisting of double-nutted threaded rods and "Unistrut" channels or angles of 12 gauge minimum steel for supporting multiple conduit.

G. Minimum size conduit for branch circuits shall not be smaller than 1/2". Home runs shall extend from outlets shown to panel designated. Home runs shown shall not be combined. Home run conduit shall not be smaller than 3/4".

H. At couplings, conduit ends shall be threaded so that they meet in the coupling. Right and left hand couplings shall not be used; conduit couplings of the Erikson type shall be used at locations requiring such joints.

I. All conduit for future use, for telephone wire, or for data communication cable, shall be left with No. 16 gauge wire pulled in them or a pull line as manufactured by Ideal, and the ends securely corked or capped.

J. Expansion fittings shall be installed in all conduit which pass through the cross-sectional area of expansion joints.

K. Provide non-hardening elastic type duct seal compound, Neer No. DC, 3M Co. "Scotchfil", or Gardner Bender duct seal, for each conduit entering the building from outside and for each conduit passing from one space into another which is normally at a lower temperature.

L. Provide watertight conduit hubs on conduit terminating in a box or cabinet exposed to the weather.

M. Space in sleeves or around conduit that pass through fire resistive or fire rated walls, partitions, floors or ceilings shall be closed by packing with an unlabelled fire resistive material that will maintain the rating of the barrier penetrated.

3.02 FLEXIBLE CONDUIT

A. PVC extruded cover flexible conduit shall be used in making short flexible connections to rotating or vibrating machinery or equipment. The flexible conduit at these locations shall be as short as possible, but shall have a minimum length of 12".

B. A green stranded bonding jumper shall be installed outside of all flexible conduit that extends directly from a non-flex conduit to a rotating or vibrating machine. Where a junction box is used, the green stranded bonding jumper shall be installed inside the flexible conduit and attached to the junction box and to the machine. When the bonding jumper is installed outside of the flexible conduit, plastic wire straps shall be used 6" o.c. to secure the jumper to the flexible conduit.

C. Flexible metal (MC) conduit system may be utilized where concealed in walls and/or millwork only. MC cables shall run from point of exist from wall or millwork to nearest structurally suppr junction box. MC cable will not be permitted to be installed in the above ceiling space and shall not pass through a fire rated partition. Conductor colors of the MC cables shall comply with 16100 3.04 D.

1. MC cable shall be constructed to have an insulated, copper grounding conductor. Sheathing with a bare aluminum conductor shall not be used as a ground.

3.04 WIRING

A. All conductors shall be installed in conduit. No conductors shall be pulled into the conduit until the conduit system is complete and plaster had dried. Wire pulling lubricants shall be Gardner-Bender "Wirelade" or Ideal "Yellow 77".

B. Conductors shall be continuous from outlet to outlet and from outlet to junction box or pull box. All splices and joints shall be carefully and securely made to be mechanically and electrically solid with approved wire type splicers, Gardner Bender "Wingard" or Ideal "Wingnut". Tape shall be "Scotch" No. 33 for indoor and No. 88 for outdoor or Gardner Bender No. 93-881. Where connection is made to any terminals of more than 30 amperes capacity and where conductors larger than No. 8 are connected to any terminal, copper terminal lugs shall be bolted to the conductors. Where multiple connections are made to the same terminal, individual lugs for each conductor shall be used.

C. Each conduit shall have a minimum of two (2) conductors pulled in, unless that particular conduit is specified as being for systems other than electrical or for spare or future use or unless noted otherwise.

D. Conductors for lighting and receptacle circuits shall have color coded jackets. The wiring shall be installed with the same color used with its respective phase throughout the entire job as follows:

208/120 Volt System	480/277 Volt System
Phase A – Black	Phase A – Brown
Phase B – Red	Phase B – Orange
Phase C – Blue	Phase C – Yellow
Neutral – White	Neutral – Gray
Ground – Green	Ground – Green

E. The feeder and service entrance conductors shall be color coded by the use of colored plastic tape applied within 6" of each conductor end.

F. Branch circuit conductors shall not be smaller than No. 12 and where the home run from center of load exceeds 100'-0", the conductors from home run outlet to panel shall be No. 10 minimum.

G. For branch circuits terminating in outlet without device, leave minimum of 12" of slack wire coiled for connection of equipment. All conductors shall be identified with proper circuit numbers at terminals, junction boxes at panelboards within 6" of conductor ends.

3.05 OUTLETS

A. Provide galvanized steel or cast type boxes for all outlets.

B. Where outlet boxes are used to support lighting fixtures, the outlet box shall be anchored to the structural members of the building per NEC 370-13.

C. Outlet boxes shall be flush mounted unless they are specifically shown as being used with exposed conduit or are located above a ceiling.

D. Where outlets are supplied from conduit run in or below floor slabs, the conduit shall be stubbed up at the location shown and the wall built up around the conduit.

E. Cuts for outlet boxes in masonry walls shall be made so that the coverplate will completely cover the cut. The mounting height of switch, receptacle and other outlets may be varied slightly, with the Architects approvals, so that the outlet box, top or bottom, will occur at a masonry joint.

F. The edge of all outlet boxes shall be flush with the surface in which they are recessed. The devices that fit into the outlet boxes shall be screwed tight before the coverplate is installed and the coverplate shall not be used as a means of tightening the devices in place.

G. Where outlets are shown as being adjacent and different mounting heights are specified for each, they shall be mounted one directly over the other, on the centerline of the group.

3.06 NAMEPLATES

A. Provide specified nameplates on the distribution panels, feeder switches, feeder breakers, panelboards, disconnect switches, contactors, starters, transformers, start-stop push buttons and motor switches.

B. Provide nameplates on every device in the main switchboard, distribution panels and motor control centers.

C. Nameplates for surface mounted equipment shall be installed on the exterior of equipment with sheetmetal screws. Nameplates for flush or recessed mounted equipment shall be installed on the inside of the panel door or cover with epoxy cement.

3.07 WALL SWITCHES AND RECEPTACLES

A. Where more than one device is indicated at a location, the devices shall be gang-mounted in combined multi-gang boxes and covered jointly by a common coverplate. Provide barriers as required by the devices and voltages being used.

3.08 COVERPLATES

A. All junction boxes, outlet boxes, multi-gang switch boxes, utility boxes, etc., shall be covered with a coverplate. The coverplate shall be a finished plate as specified unless designated otherwise.

B. Coverplates shall be mounted vertically unless designated otherwise.

3.09 GROUNDING

A. Ground connections shall be in accordance with the 2017 National Electrical Code.

B. Provide an insulated green bonding jumper from the grounding lug of all receptacles to a Steel City "GET" clip or a sheet metal screw in the outlet box. The ground wire installed behind the device mounting screws will not be acceptable.

C. Provide 1 #6-3/4" conduit from the system ground to the telephone company main distribution frame or service cabinet and to each telephone backboard.

3.10 TELEPHONE CONDUIT SYSTEM

A. Telephone service shall include wood backboards and equipment cabinets with service entrance conduit as shown.

B. Telephone service entrance cable, all branch cabling and telephone instruments shall be provided by the telephone equipment vendor.

C. Provide an outlet and conduit system for the telephones as shown and leave the same in readiness for wiring by others. Provide pull line in all telephone conduit. Terminate all conduit at a uniform height with smooth insulated bushings at the telephone wood backboards.

D. Telephone wall outlets shall be pressed steel sectional switch boxes, wall mounted at the locations indicated. Coverplates shall have a bushed hole.

E. Telephone floor outlets shall be floor boxes as specified at the locations indicated.

3.11 CONNECTION TO EQUIPMENT

A. Equipment furnished by the Owner or other Sections, such as mechanical equipment, sprinkler equipment, etc., will be installed by others. Provide electrical service and make the electrical circuit connection to the equipment.

B. Provide 6'-0" insulated flexible cord set with grounding cord plug for connection to building appliances and equipment. Cords shall be furnished in accordance with electrical characteristics indicated. Multiple conductor cords shall be rubber with PVC jacket and green insulated ground conductor.

3.12 CORING, SLEEVING AND PATCHING

A. Cast sleeves for conduit accurately before the concrete floors are poured, or set boxes on the forms so as to leave openings in the floors in which the required conduits can be subsequently located. Fill in the voids around the sleeves with concrete.

B. Should the performance of this preliminary work be neglected and should cutting be required in order to install conduit, then the expense of the cutting and restoring of surfaces to their original conditions shall be accomplished without incurring additions to the Contract.

3.13 EQUIPMENT ANCHORING

A. All items of electrical equipment, such as switchboards, motor control centers, transformers, standby generator, etc., shall be securely anchored to the building structure. The anchoring shall be accomplished by utilizing a minimum size of 3/8" steel anchor bolts in the structure and to the item of equipment. A minimum of two (2) anchor bolts shall be provided on each side of each item of equipment with the following exceptions:

SECTION 16200
SERVICE AND DISTRIBUTION

1.0 GENERAL

N/A

2.0 PRODUCTS

2.01 BRANCH CIRCUIT PANELBOARDS

A. Panelboards (panels) shall be general purpose enclosures and shall be surface or flush mounted as indicated. Panels shall be of the automatic circuit breaker type, factory assembled by the manufacturer of the circuit breakers. Panels shall be for the voltage indicated with the quantity of poles and ampacity of circuit breakers shown.

B. Bus bars for the mains shall be of copper sized in accordance with U.L. standards. Full size bars shall be included. Bus bar taps for panels with single pole branches shall be arranged for sequence phasing of the branch circuit devices.

C. All circuit breakers shall be manually operated, thermal-magnetic, automatic, of the ampacity and poles as indicated. They shall be quick-make, quick-break, both on manual and automatic operation. Breakers shall be over-the-center toggle operating type, with the handle going to a position between ON and OFF to indicate automatic tripping. All multi-pole breakers shall have internal common trip. Breakers shall have a minimum of 10,000 RMS symmetrical amperes interrupting capacity unless designated otherwise. The breakers furnished shall be determined by the specifications and by the minimum U.L. labeled RMS symmetrical amperes interrupting capacity at circuit voltage. All circuit breakers shall be bolted on and rigidly braced.

D. Each panel as a complete unit shall have a short-circuit current rating equal to or greater than the available fault current.

E. Panels shall be as manufactured to match base building.

3.0 EXECUTION

3.01 INSTALLATION

A. Provide a typewritten directory under plastic for all panelboards with spares marked in pencil.

B. Provide all necessary hardware to level and secure the switchgear as required by the manufacturer's instructions. Make all electrical connections for supply and load circuits and leave in operating condition.

C. Clean enclosure of all switchgear of all foreign matter, including dust.

D. Remove all rust marks and repaint to leave switchgear in new condition.

3.02 STUDIES

A. Provide a complete short circuit and coordination study for the actual switchgear manufacturer provided from the service entrance to all end devices.

SECTION 16300
LIGHTING

1.0 GENERAL

2.0 PRODUCTS

2.01 LIGHTING FIXTURES

A. Each lighting fixture shall be as specified in the Lighting Fixture Schedule corresponding with its respective designation (letter).

2.02 LAMPS

A. The type lamps shall be as specified for each lighting fixture in the lighting fixture schedule.

B. Lamps specified is the catalog number for General Electric and is given as a standard of the quality and performance required. Equivalent by Sylvania or Westinghouse will be acceptable. When a lamp manufacturer's name is used along with the catalog number in the lighting fixture schedule, it is considered required by any other lamp and shall not be substituted for. The lamp performance with energy conserving ballasts furnished under this Section shall be certified by a nationally recognized independent testing laboratory.

3.0 EXECUTION

3.01 SUPPORT OF LIGHTING FIXTURES

A. All lighting shall be supported from the building structure. The fixtures shall be supported in a manner that will insure the fixture weight being equally distributed from each support and the fixture remaining in a level position.

SECTION 16920
MOTOR CONTROLS AND WIRING

1.0 GENERAL

1.01 SCOPE

A. All motors shall be provided under Division 15.

B. A motor starter shall be provided under this Section for each motor except for those specified in Division 15 to be furnished with integral starters. Motor starters shall be installed either in a Motor Control Center or separately mounted adjacent to the motor served.

C. Motor power wiring is defined as those conductors between the energy source and the motor. This power wiring shall be terminated at the motor terminals.

2.0 PRODUCTS

2.01 MOTOR STARTERS

A. Starters for motors 1/3 horsepower or smaller shall be manual unless remote or automatic starting is required, in which case the starters shall be magnetic, full voltage, non-reversing, single-speed, unless otherwise indicated. All other starters shall be magnetic.

B. Each starter for a three-phase motor shall be furnished with three (3) overload relays sized for the full load running current of the motor actually provided. Provide an external "HAND-OFF-AUTO" selector switch with green "RUNNING" light. Provide a red pilot light to indicate motor "STOPPED". Each pilot light shall have a legend plate indicating reason for signal.

C. Each overload relay shall have a normally open alarm contact which will close only when actuated by an overload (not to be confused with N.O. or N.C. auxiliary contacts). These contacts shall be properly wired to their respective pilot light provided on the starter front cover and having a "TRIPPED" legend plate.

D. Individually mounted motor starters shall be in a NEMA Type 1 general purpose enclosure in unfinished areas and shall be flush mounted in all finished areas. All starters mounted in exterior areas shall have a NEMA 3R enclosure. Each starter shall have a laminated nameplate to indicate Division 15 unit number, function and circuit number.

E. A control power transformer shall be provided at each motor starter for connection to the to the controls provided under Division 15. The control power transformer shall be mounted inside the motor starter enclosure. All control transformers at 50 VA or greater shall have primary fusing. Coordinate all control equipments with Division 15 and equipment manufacturers.

F. All motor starters, push buttons and pilot lights shall be of the same manufacturer as the switchboard and shall be General Electric, Square D, Joslyn Clark Controls or Westinghouse.

Order Plans @ BW-Online.com

Hendrick

1201 Peachtree Street, NE
400 Colony Square
Suite 1900
Atlanta, GA 30361

T: 404.261.9383
F: 404.240.9398
www.hendrickinc.com

No.	Date	Description
	01/08/2020	ISSUED/RELEASED FOR CONSTRUCTION

Project Name

FranklinStreet

FRANKLIN STREET
3384 PEACHTREE ROAD
NE, SUITE 650
ATLANTA, GA 30326

ISSUE
ISSUED/RELEASED FOR CONSTRUCTION

ELECTRICAL SPECIFICATIONS

GEORGIA REGISTERED ENGINEERS KEVIN W. PRINCE

PROJECT NORTH

BW&A Barrett, Woodyard & Associates, Inc.
3495 Holcomb Bridge Road
Norcross, GA 30092
Phone (770) 810-8800

©This drawing is copyrighted. It may not be reproduced nor used in any other form on any other project.
BW&A No.# 2019-2477

RS	This drawing and all reproductions are the property of Hendrick, Inc. and may be used or reproduced only with the written permission of Hendrick, Inc.
Drawn	
KP	
Checked	
As indicated	
Scale	
01/08/2020	
Date	
142-001-01	E-0.1
Project No.	Drawing Number