



- ### GENERAL DEMOLITION NOTES
1. CONTRACTOR SHALL VISIT THE SITE TO VERIFY EXISTING CONDITIONS PRIOR TO SUBMISSION OF BID. NO ADDITIONAL COMPENSATION SHALL BE CONSIDERED FOR FAILURE TO OBSERVE THIS REQUIREMENT.
 2. CONTRACTOR SHALL DISCONNECT AND REMOVE ALL ELECTRICAL WIRING AND EQUIPMENT AS REQUIRES WITHIN ALL AREAS TO BE RENOVATED. THIS SHALL INCLUDE BUT NOT BE LIMITED TO FIXTURES, DEVICES, OUTLETS, SWITCHED, RECEPTACLES, STARTERS, DISCONNECTS, PANELS, FEEDERS, ETC.
 3. CONTRACTOR SHALL DISCONNECT AND REMOVE ALL EXISTING CIRCUITS TO MECHANICAL EQUIPMENT BEING REMOVED. REFER TO ALL MECHANICAL DEMOLITION DRAWINGS OR NOTES.
 4. WHERE ELECTRICAL ITEMS ARE REMOVED, ALL BRANCH DEVICES WIRING SHALL BE REMOVED BACK TO PANEL SERVING THE EQUIPMENT. WHERE CIRCUITS SERVE ADDITIONAL DEVICES OR EQUIPMENT REMAINING, WIRING SHALL BE REMOVED BACK TO THE NEAREST ACTIVE JUNCTION BOX.
 5. CONTRACTOR SHALL MAINTAIN CONTINUITY OF EXISTING CIRCUITS THAT ARE TO REMAIN IN OPERATION AND SCHEDULE FOR REFERENCE FROM MAIN PANELS. FORWARD FINDINGS TO ENGINEER FOR REVIEW AND COORDINATION.
 6. ALL UNUSED CIRCUITS REMAINING AFTER REMOVAL SHALL BECOME SPARE IN PANELS, LABELED AS SPARE, AND REMOVED TO THE OFF-POSITION.
 7. CONTRACTOR SHALL REFER TO ARCHITECTURAL DEMOLITION DRAWING FOR ADDITIONAL INFORMATION AND SCOPE OF DEMOLITION.
 8. ALL MATERIALS AND EQUIPMENT REMOVED SHALL BE DISPOSED OF AS DIRECTED BY THE OWNER OR THE ARCHITECT.
 9. ALL ELECTRICAL CONDUITS MUST BE PULLWIRES AND BE TAGGED PROPERLY.
 10. ELECTRICAL CONTRACTOR SHALL TIE BACK ALL LOOSE WIRING (INCLUDING LOW VOLTAGE) IN AN ORDERLY FASHION.
 11. CONTRACTOR TO VERIFY ALL EXISTING CIRCUITS AND RELABEL PANEL SCHEDULES IN FIELD AS REQUIRED.
 12. CONTRACTOR TO VERIFY ALL EXISTING PANEL LOADING IN FIELD AS REQUIRED PRIOR ANY NEW WORK.

- ### ELECTRICAL LEGEND NOTES
- D1 ALL ELECTRICAL EQUIPMENT IN THIS AREA IS EXISTING TO REMAIN, UNLESS NOTED OTHERWISE.
 - D2 EXISTING PHOTOLAB AND CHECKOUT EQUIPMENT/CASEWORK TO BE REMOVED. CONTRACTOR SHALL DISCONNECT EXISTING POWER AND TELECOMMUNICATIONS CIRCUITS/CABLING SERVING EXISTING CASEWORK/EQUIPMENT, AS NEEDED, TO ALLOW FOR REMOVAL OF CASEWORK/EQUIPMENT, AND RE-CONNECT TO NEW CASEWORK/EQUIPMENT ONCE IT HAS BEEN INSTALLED.
 - D3 EXISTING ROOM/AREA TO REMAIN AS-IS. NO WORK, UNLESS NOTED OTHERWISE.
 - D4 ALL MERCHANDISE FIXTURES TO BE DEMOLISHED. DISCONNECT EXISTING POWER (I.E. POWER POLES) AND TELECOMMUNICATIONS CIRCUITS/CABLING SERVING EXISTING MERCHANDISE FIXTURES/EQUIPMENT, AS NEEDED, TO ALLOW FOR REMOVAL OF CASEWORK/EQUIPMENT. NEW MERCHANDISE FIXTURES TO BE INSTALLED. RE-CONNECT EXISTING CIRCUITS TO NEW FIXTURES.
 - D5 DISCONNECT AND REMOVE ALL EXISTING WALL RECEPTACLES HIGHER THAN 18" AFF IN RETAIL AREA EXCEPT EXISTING RECEPTACLES FOR DIGITAL SCREENS, FREEZERS, COOLERS, CHECKOUT, PHOTOLAB AND PHARMACY AREA.
 - D6 EXISTING BLOOD PRESSURE MACHINE TO BE REMOVED.
 - D7 EXISTING PHARMACY CASEWORK TO BE MODIFIED OR REPLACED WITH NEW CASEWORK. CONTRACTOR SHALL DISCONNECT EXISTING POWER AND TELECOMMUNICATIONS CIRCUITS/CABLING SERVING EXISTING CASEWORK/EQUIPMENT, AS NEEDED, TO ALLOW FOR REMOVAL OF CASEWORK/EQUIPMENT, AND RE-CONNECT TO NEW CASEWORK/EQUIPMENT ONCE IT HAS BEEN INSTALLED. COORDINATE EXACT REQUIREMENTS PRIOR TO WORK.
 - D8 EXISTING ACC(S), FLM(S), ATM, POSTER PRINTER, DUPLEX PRINTER, APEX PROCESSOR, AND KODAK PRINTER TO BE RELOCATED TO NEW LOCATION. SEE E4 FOR NEW LOCATION AND NOTES.
 - D9 EXISTING SIGN-IN TABLE EQUIPMENT/CASEWORK TO BE RELOCATED. CONTRACTOR SHALL DISCONNECT EXISTING POWER AND TELECOMMUNICATIONS CIRCUITS/CABLING SERVING EXISTING CASEWORK/EQUIPMENT, AS NEEDED, TO ALLOW FOR REMOVAL OF CASEWORK/EQUIPMENT, AND RE-CONNECT TO NEW CASEWORK/EQUIPMENT ONCE IT HAS BEEN INSTALLED.
 - D10 EXISTING RECEIVING ACCESS TO BE RELOCATED TO NEW LOCATION. DISCONNECT EXISTING POWER AND COMMUNICATIONS CIRCUITS/CABLING SERVING EXISTING ACCESS ALARM EQUIPMENT. EXTEND TO NEW DOOR LOCATION AND RE-CONNECT EXISTING CIRCUITS TO NEW ACCESS ALARM EQUIPMENT.
 - D11 EXISTING HAND DRYER TO BE REPLACED. CONTRACTOR SHALL DISCONNECT POWER TO EXISTING DRYER AND CONNECT CIRCUIT TO NEW DRYER ONCE ITS INSTALLED.



HEALTH HUB/Rx CONSULTATION
STORE NUMBER: 4176

11 RIVER RIDGE DRIVE, OAKLEY PLAZA
ASHEVILLE, NC 28803

CAP CODE: 90

CS PROJECT NUMBER: 146740

ARCHITECT OF RECORD:

118 S. College St. Ste. 400 Asheville, NC 28802
T: 704.626.6394 F: 704.641.8729
www.littleonline.com

This drawing and the design shown are the property of Little Architectural Consulting. The reproduction, copying or other use of this drawing without their written consent is prohibited and any infringement will be subject to legal action.

222 N. McDowell St. Suite 204
Charlotte, NC 28204
(704) 344-7881 | (704) 347-2095
www.shultzeng.com | 505-20-296
NC FIRM LICENSE NUMBER: C-0898
M-D-M E-W-C P-D-M

DEVELOPER:



SEAL:

REVISIONS:

DRAWING BY:	WC
CVS PROJECT MANAGER:	RJ
DATE:	11-02-2020
JOB NUMBER:	121-14217-08
TITLE:	POWER PLAN - DEMOLITION
SHEET NUMBER:	ED2
COMMENTS:	

1 OVERALL POWER DEMOLITION PLAN
ED2 SCALE: 1/8" = 1'-0"