

ARM AND BASE PLATE											
Arm ID Ax-ArmLength S-SingleArm D-DoubleArm H-HeavyDuty	Total Arm Length (ft)	Arm			Arm Extension			Base Plate			
		FA/SA (ft)	FC/SC (in)	FD/SD (in)	FE/SE (ft)	FG/SG (in)	FH/SH (in)	HT (in)	FJ/SJ (in)	FK/SK (in)	
A30/S	30	30	11	0.250				22	25	3	
A30/S/H		30	12	0.250							
A30/D		30	11	0.250				30	36		
A30/D/H		30	12	0.250							
A40/S	40	40	13	0.250				22	27	3	
A40/S/H		40	14	0.250							
A40/D		40	13	0.250				30	36		
A40/D/H		40	14	0.250							
A50/S	50	32.5	12	0.250	20.5	14	0.313	22	29	3	
A50/S/H		32.5	13	0.250	20.5	15					
A50/D		32.5	12	0.250	20.5	14			30		36
A50/D/H		32.5	13	0.250	20.5	15					
A60/S		60	35.5	12	0.250	27.5		15	0.375		30
A60/S/H	35.5		13	0.250	27.5	15					
A60/D	35.5		12	0.250	27.5	15					
A60/D/H	35.5		13	0.250	27.5	16					
A70/S	70	38	13	0.250	35	17	0.375	30	36	3	
A70/S/H		38	14	0.250	35	18					
A70/D		38	13	0.250	35	17					
A70/D/H		38	14	0.250	35	18					
A78/S	78	39	13	0.250	42	18	0.375	30	36	3	
A78/S/H		39	15	0.250	42	20					
A78/D		39	13	0.250	42	18					
A78/D/H		39	15	0.250	42	20					

POLE, BASE PLATE AND ARM CONNECTION																					
Pole ID Px-PoleNo S-SingleArm D-DoubleArm L-Luminaire	Upright				Base Plate					Arm-Upright Connection											
	UA (ft)	UD (in)	UE (in)	UG (ft)	No. Bolts	BA (in)	BB (in)	BC (in)	BF (in)	HT (in)	FJ/SJ (in)	FL/SL (in)	FN/SN (in)	FO/SO (in)	FP/SP (in)	FR/SR (in)	FS/SS (in)	FT/ST (in)			
P1/S	25									22	25			14		2	8				
P1/S/L	39	16	0.375	37.5	6	32	2.5	2	40	30	36	0.75	0.438	23	1.25	2.75	12.5	0.438	0.438	0.438	
P1/D	25																				
P1/D/L	39																				
P2/S	25	18	0.375	37.5	6	34	2.5	2	40	22	27	0.75	0.438	15	1.25	2.75	12.5	0.438	0.438	0.438	
P2/S/L	39																				
P2/D	25																				
P2/D/L	39									30	36			23		2.75	12.5				
P3/S	25	20	0.375	37.5	6	36	2.5	2	40	22	29	0.75	0.438	16	1.25	2.75	12.5	0.438	0.438	0.438	
P3/S/L	39																				
P3/D	25																				
P3/D/L	39									30	36			23		2.75	12.5				
P4/S	25	22	0.375	37.5	8	38	2.5	2	40	30	36	0.75	0.438	17	1.25	2.5	12.5	0.438	0.438	0.438	
P4/S/L	39																				
P4/D	25																				
P4/D/L	39													23							
P5/S	25	24	0.375	37.5	8	40	2.5	2	40	30	36	0.75	0.5	18	1.25	2.5	12.5	0.5	0.5	0.5	
P5/S/L	39																				
P5/D	25																				
P5/D/L	39													23							
P6/S	25	24	0.5	37.5	8	42	2.5	2.25	45	30	36	0.75	0.625	18	1.5	2.5	12	0.625	0.625	0.625	
P6/S/L	39																				
P6/D	25																				
P6/D/L	39													23							
P7/S	25	26	0.5	37.5	8	44	2.5	2.25	45	30	36	0.75	0.625	19	1.5	2.5	12	0.625	0.625	0.625	
P7/S/L	39																				
P7/D	25																				
P7/D/L	39													23							

NOTE:  
1. Work this Index with Index 649-031.

Order Plans @

DRILLED SHAFT								
Drilled Shaft ID	DA (ft)	DB (ft)	RA	RB	RC	RD (in)	RE	RF (in)
DS/12/4.0	12	4.0	11	14	8	12		
DS/12/4.5	12	4.5	11	16	8	12		
DS/14/4.5	14	4.5	11	16	10	8		
DS/14/5.0	14	5.0	11	18	10	8		
DS/16/4.5	16	4.5	11	16	10	8		
DS/16/5.0	16	5.0	11	18	10	8		
DS/18/5.0	18	5.0	11	18	10	8		
DS/20/5.0	20	5.0	11	18	10	6	10	9
DS/25/5.0	25	5.0	11	18	10	6	10	9



**FleischmanGarcia**  
ARCHITECTURE • PLANNING • INTERIOR DESIGN  
1500 SOUTH AVENUE, SUITE 300  
PORT RICHEY, FLORIDA 34673  
PHONE (813) 721-4800  
FAX (813) 721-9900  
REGISTRATION NUMBER: SA 000217

**Pasco County  
Fire & Rescue Station  
No. 17  
New Port Richey, Florida**

THIS DESIGN AND DRAWING IS THE PROPERTY OF FLEISCHMAN-GARCIA, INC. NO PART OF THIS DRAWING IS TO BE REPRODUCED, COPIED, OR TRANSMITTED IN ANY FORM OR BY ANY MEANS, WITHOUT THE WRITTEN PERMISSION OF FLEISCHMAN-GARCIA, INC.

FGA PROJECT NUMBER

ISSUE DATE  
05-25-20

STANDARD  
MAST ARM  
ASSEMBLIES

SHEET NUMBER  
T3.0